

Avaya Solution & Interoperability Test Lab

Application Notes to Integrate Avaya Aura® Communication Manager 6.0.1, Avaya Aura® Application Enablement Services 6.1 and Avaya Contact Recorder 10.1 using Single Step Conferencing – Issue 1.0

Abstract

These Application Notes describe the configuration steps required to successfully integrate Avaya Aura® Communication Manager 6.0.1, Avaya Aura® Application Enablement Services 6.1 and Avaya Contact Recorder 10.1. Avaya Contact Recorder is a call recording solution capable of capturing audio from Avaya Aura® Communication Manager using a variety of integration mechanisms. The integration mechanism used in this test is Single Step Conferencing. Avaya Contact Recorder uses the TSAPI interface of Avaya Aura® Application Enablement Services to extract agent and call state information and the DMCC interface of Avaya Aura® Application Enablement Services Server to capture the media.

Information in these Application Notes has been obtained through Full Stack Test conducted at the Avaya Solution and Interoperability Test Lab.

©2011 Avaya Inc. All Rights Reserved.

Table of Contents:

1. Introduction 4
1.1. Full Stack Testing and Results 4
1.2. Assumptions 5
1.3. Acronyms 6
1.4. Lab Configuration 7
1.5. Equipment and Software Validated 8
2. Configure Avaya Aura® Communication Manager 9
2.1. Verify Avaya Aura® Communication Manager License 9
2.2. Administer System Parameters Features 10
2.3. Administer Class of Restriction 11
2.4. Administer Agent Stations 12
2.5. Administer Codec Set 13
2.6. Administer Network Region 14
2.7. Administer Virtual IP Softphones 15
2.8. Administer AE Services 17
2.9. Administer CTI Link for DMCC and TSAPI 17
2.10. Assign AES Server to Network Region 18
3. Configure Avaya Aura® Application Enablement Services 19
3.1. Launch Avaya Aura® Application Enablement Services 19
3.2. Verify DMCC and TSAPI Licenses 21
3.3. Create Switch Connection 21
3.4. Administer TSAPI Link 25
3.5. Obtain Tlink Name 26
3.6. Disable Security Database 27
3.7. Restart TSAPI Service 28
3.8. Administer Avaya Contact Recorder User for DMCC 29
3.9. Administer Avaya Contact Recorder User for TSAPI 30
4. Configure Avaya Contact Recorder 31
4.1. Launch Avaya Contact Recorder 31
4.2. Administer Communication Manager Information 32
4.3. Administer Recorder Information 33
4.4. Administer Conferenced Mode 34
5. Verification Steps 35

©2011 Avaya Inc. All Rights Reserved.

5.1. Verify Avaya Aura® Communication Manager 35
5.2. Verify Avaya Aura® Application Enablement Services 35
5.3. Verify Avaya Contact Recorder 37
5.4. Verify Avaya Contact Recorder Recording Playback 38
6. Additional References 39

©2011 Avaya Inc. All Rights Reserved.

1. Introduction

These Application Notes describe the configuration steps required to successfully integrate Avaya Aura® Communication Manager 6.0.1, Avaya Aura® Application Enablement Services 6.1 and Avaya Contact Recorder 10.1. Avaya Contact Recorder is a call recording solution capable of capturing audio from Avaya Aura® Communication Manager using a variety of integration mechanisms. The integration mechanism used in this test is Single Step Conferencing.

Avaya Contact Recorder uses the TSAPI interface of Avaya Aura® Application Enablement Services to extract agent and call state information and the Device, Media and Call Control (DMCC) interface of Avaya Aura® Application Enablement Services Server to capture the media associated with the target stations on Avaya Aura® Communication Manager. Target stations are the stations Avaya Contact Recorder monitors for call recording. Any calls that occur on the stations will be recorded by Avaya Contact Recorder.

In the test configuration agents are configured to support both outbound calls and inbound calls in an active call center environment. Both outbound calls and inbound calls are recorded by the Avaya Contact Recorder.

To implement the call recording solution, a number of DMCC virtual IP softphones are configured within the Avaya Contact Recorder. At the time when Avaya Contact Recorder is launched, the Avaya Contact Recorder registers the virtual IP softphones with Avaya Aura® Communication Manager. When outbound calls are initiated by those target stations, Avaya Contact Recorder will receive call events and TSAPI events to trigger recording of the calls. It will send a Single Step Conference request via TSAPI to conference in one of its virtual IP softphones for capturing the media. When inbound calls are received by the target stations, Avaya Contact Recorder will use TSAPI events to trigger the Single Step Conferencing request for capturing the media.

1.1. Full Stack Testing and Results

The Full Stack Testing included feature, serviceability and reliability testing of Avaya Contact Recorder as integrated in a complex customer Intelligent Routing configuration.

The testing focused on verifying the following Avaya Contact Recorder capabilities as applicable to agent activity in a highly customized Call Center environment:

- Handling of real-time agent states and call events from complex Intelligent Routing solution.
- Use of Avaya AES DMCC registration services to register and un-register the virtual IP softphones.
- Use of Single Step Conference to connect virtual IP softphones to calls participated by target stations.
- Use of Avaya AES DMCC monitoring services and media control events to obtain the media from the virtual IP softphones.

©2011 Avaya Inc. All Rights Reserved.

- Proper recording, logging, and playback of calls for scenarios involving inbound, outbound, agent drop, customer drop, hold, reconnect, transfer, conference, simultaneous calls, agent blending, and managed jobs.
- Ability to record very long calls.

The Full Stack Testing focused on verifying the ability of the Avaya Contact Recorder to recover from adverse conditions, such as network outage, server reboot, Enterprise Survivable Server failovers, etc.

Full Stack test cases were executed manually. During the test, inbound calls were placed by simulating customer calls into the Intelligent Routing solution and then routed to agents in varying agent/phone states. The agent accepted the call and the conversation between the customer and the agent was recorded. The recordings were reviewed using the Avaya Contact Recorder Replay function. Agent outbound calls were placed manually to observe direct Agent Dialing, VDN, transfer, conference, etc.

An important focus of the test was to make sure that calls were recorded from the beginning to the end. In addition, for calls that have multiple segments (e.g. transfer and conference calls) attention was paid on whether all the segments were recorded.

All test cases were executed and passed. Avaya Contact Recorder successfully recorded, stored and played back the calls between the agents and the customers. For serviceability testing, Avaya Contact Recorder was able to resume call recording after network disconnect/re-connect and after reboot of Avaya Contact Recorder along with Enterprise Survivable Server failovers.

1.2. Assumptions

These Application Notes do not provide any configuration details for the following list of assumptions:

- The front end, highly customized and complex customer Intelligent Routing configuration has been installed, configured and is operational
- Avaya Aura® Communication Manager has been installed and is operational. Additionally, the “procr” interface has been administered and is operational.
- The Enterprise Survivable Server has been installed and is operational. Additionally, the “procr” interface has been administered and is operational.
- Avaya Aura® Application Enablement Services has been installed and is operational
- Avaya Contact Recorder has been installed and is operational

©2011 Avaya Inc. All Rights Reserved.

1.3. Acronyms

ARS	Automatic Route Selection (Routing on Avaya Aura® Communication Manager)
CM-ES	Communication Manager – Evolution Server
CM-FS	Communication Manager – Feature Server
DCP	Digital Communications Protocol
DNIS	Dialed Number Identification Service
DNS	Domain Naming System
DTMF	Dual Tone Multi Frequency
ESS	Enterprise Survivable Server
FQDN	Fully Qualified Domain Name (hostname for Domain Naming Resolution)
IP	Internet Protocol
IPSI	IP-services interface (Control Card in Communication Manager)
LAN	Local Area Network
PSTN	Public Switched Telephone Network
RTP	Real Time Protocol
SAT	System Access Terminal (Avaya Aura® Communication Manager Administration Interface)
SIL	Solution Interoperability Lab
SIP	Session Initiation Protocol
SM	Avaya Aura® Session Manager
SMGR	Avaya Aura® System Manager
SNMP	Simple Network Management Protocol
SRE	SIP Routing Element
SSH	Secure Shell
SSL	Secure Socket Layer
TAC	Trunk Access Code (Avaya Aura® Communication Manager Trunk Access)
TCP	Transmission Control Protocol
TCP/IP	Transmission Control Protocol/Internet Protocol
TLS	Transport Layer Security
URL	Uniform Resource Locator
VDN	Vector Directory Number
WAN	Wide Area Network
XML	eXtensible Markup Language

©2011 Avaya Inc. All Rights Reserved.

1.4. Lab Configuration

The following is the Lab configuration used for testing.




Figure 1. Avaya Contact Recorder Configuration Overview

©2011 Avaya Inc. All Rights Reserved.

1.5. Equipment and Software Validated

The following equipment and software were used for the sample configuration.

Equipment/Software	Software Version
Avaya Aura® Communication Manager • Avaya S8800 Media Server	6.0.1 (R016x.00.1.510.1, patch 18777)
Avaya G450 Media gateway	FW: g450_sw_31_18_1
Avaya IP (H.323) Deskphones: • 9650 • 9630 • 9620 • 9608 • 9641	 ha96xxua3_0_02 ha96xxua3_0_02 ha96xxua3_0_02 S9608_11HALBR6_1r31_V4r52 S9608_11HALBR6_1r31_V4r52
Avaya IP-Agent	7.0.28.184
Avaya Aura® Application Enablement Services • Dell 1950	6.1 (r6-1-0-16-0)
Avaya Contact Recorder	10.1

©2011 Avaya Inc. All Rights Reserved.

2. Configure Avaya Aura® Communication Manager

This section provides the procedures for configuring Avaya Aura® Communication Manager. The procedures include the following areas:

- Verify Communication Manager License
- Administer System Parameters Features
- Administer Class of Restriction
- Administer Agent Stations
- Administer Codec Set
- Administer Network Region
- Administer Virtual IP Softphones
- Administer AE Services
- Administer CTI link for DMCC
- Assign AES to Network Region

2.1. Verify Avaya Aura® Communication Manager License

Log in to the System Access Terminal (SAT) to verify that the Communication Manager license has proper permissions for features illustrated in these Application Notes. Use the "**display system-parameters customer-options**" command to verify that the **Computer Telephony Adjunct Links** customer option is set to "**y**" on **Page 3**.

```
display system-parameters customer-options                      Page   3 of  11
                              OPTIONAL FEATURES

    Abbreviated Dialing Enhanced List? y          Audible Message Waiting? y
        Access Security Gateway (ASG)? n              Authorization Codes? y
        Analog Trunk Incoming Call ID? y                      CAS Branch? n
 A/D Grp/Sys List Dialing Start at 01? y                        CAS Main? n
Answer Supervision by Call Classifier? y                 Change COR by FAC? n
                                ARS? y  Computer Telephony Adjunct Links? y
                ARS/AAR Partitioning? y   Cvg Of Calls Redirected Off-net? y
          ARS/AAR Dialing without FAC? y                       DCS (Basic)? y
          ASAI Link Core Capabilities? y                DCS Call Coverage? y
          ASAI Link Plus Capabilities? y               DCS with Rerouting? n
       Async. Transfer Mode (ATM) PNC? n
  Async. Transfer Mode (ATM) Trunking? n    Digital Loss Plan Modification? n
              ATM WAN Spare Processor? n                            DS1 MSP? n
                                ATMS? n             DS1 Echo Cancellation? n
                  Attendant Vectoring? n
```


©2011 Avaya Inc. All Rights Reserved.

Navigate to **Page 4.** Verify that the **Enhanced Conferencing** and **Media Encryption over IP** customer options are set to "**y**" on **Page 4**.

```
change system-parameters customer-options                      Page   4 of  11
                              OPTIONAL FEATURES

   Emergency Access to Attendant? y                               IP Stations? y
            Enable 'dadmin' Login? y
            Enhanced Conferencing? y                         ISDN Feature Plus? y
                   Enhanced EC500? y          ISDN/SIP Network Call Redirection? n
    Enterprise Survivable Server? n                            ISDN-BRI Trunks? n
       Enterprise Wide Licensing? n                                   ISDN-PRI? y
              ESS Administration? n                 Local Survivable Processor? n
          Extended Cvg/Fwd Admin? y                       Malicious Call Trace? y
     External Device Alarm Admin? n                    Media Encryption Over IP? y
  Five Port Networks Max Per MCC? n       Mode Code for Centralized Voice Mail? n
                Flexible Billing? n
   Forced Entry of Account Codes? y                    Multifrequency Signaling? y
      Global Call Classification? y           Multimedia Call Handling (Basic)? y
             Hospitality (Basic)? y        Multimedia Call Handling (Enhanced)? y
 Hospitality (G3V3 Enhancements)? y                  Multimedia IP SIP Trunking? n
                       IP Trunks? y

           IP Attendant Consoles? n
```

If any option specified in this section does not have a proper value, contact the Avaya sales team or business partner for a proper license file.

2.2. Administer System Parameters Features

Use the "**change system-parameters features**" command to enable **Create Universal Call ID (UCID)**, which is located on **Page 5**. For **UCID Network Node ID**, enter an available node ID.

```
change system-parameters features                              Page   5 of  18
                        FEATURE-RELATED SYSTEM PARAMETERS

SYSTEM PRINTER PARAMETERS
  Endpoint:               Lines Per Page: 60

SYSTEM-WIDE PARAMETERS
                                    Switch Name: SIL-devcon27
            Emergency Extension Forwarding (min): 10
          Enable Inter-Gateway Alternate Routing? n
Enable Dial Plan Transparency in Survivable Mode? n
                              COR to Use for DPT: station

MALICIOUS CALL TRACE PARAMETERS
               Apply MCT Warning Tone? n   MCT Voice Recorder Trunk Group:
      Delay Sending RELease (seconds)? 0
SEND ALL CALLS OPTIONS
     Send All Calls Applies to: station    Auto Inspect on Send All Calls? n
              Preserve previous AUX Work button states after deactivation? n
UNIVERSAL CALL ID
     Create Universal Call ID (UCID)? y    UCID Network Node ID: 555
```


©2011 Avaya Inc. All Rights Reserved.

Navigate to **Page 13**, and enable **Send UCID to ASAI**. This parameter allows for the universal call ID to be sent to Avaya Contact Recorder.

```
change system-parameters features                              Page  13 of  18
                     FEATURE-RELATED SYSTEM PARAMETERS
 CALL CENTER MISCELLANEOUS
          Callr-info Display Timer (sec): 10
                       Clear Callr-info: next-call
       Allow Ringer-off with Auto-Answer? n

   Reporting for PC Non-Predictive Calls? n


         Interruptible Aux Notification Timer (sec): 3
       Interruptible Aux Deactivation Threshold (%): 95

  ASAI
           Copy ASAI UUI During Conference/Transfer? y
       Call Classification After Answer Supervision? y
                                  Send UCID to ASAI? y
```

2.3. Administer Class of Restriction

Use the "**change cor n**" command, where "**n**" is the class of restriction (COR) number to be assigned to the target stations and virtual IP softphones. Set the **Calling Party Restriction** field to "**none**", as shown below.

```
change cor 5                                                   Page   1 of  23
                              CLASS OF RESTRICTION

               COR Number: 5
         COR Description:

                      FRL: 0                                  APLT? y
  Can Be Service Observed? y           Calling Party Restriction: none
Can Be A Service Observer? y            Called Party Restriction: none
        Time of Day Chart: 1       Forced Entry of Account Codes? n
         Priority Queuing? n                 Direct Agent Calling? n
     Restriction Override: none        Facility Access Trunk Test? n
     Restricted Call List? n                  Can Change Coverage? n

            Access to MCT? y             Fully Restricted Service? n
Group II Category For MFC: 7             Hear VDN of Origin Annc.? n
         Send ANI for MFE? n              Add/Remove Agent Skills? n
            MF ANI Prefix:               Automatic Charge Display? n
Hear System Music on Hold? y   PASTE (Display PBX Data on Phone)? n
                         Can Be Picked Up By Directed Call Pickup? n
                                      Can Use Directed Call Pickup? n
                                      Group Controlled Restriction: inactive
```


©2011 Avaya Inc. All Rights Reserved.

2.4. Administer Agent Stations

Modify each physical station used by agents to allow the station to be service-observed and involved in inbound calls. Use the "**change station n**" command, where "**n**" is the station extension, to change the **COR** field to "**5**" which is defined in **Section 2.3**.

```
change station 4150000                                      Page   1 of   5
                                    STATION

Extension: 415-0000                    Lock Messages? n               BCC: 0
     Type: 9650                        Security Code: 123456           TN: 1
     Port: S00000                    Coverage Path 1:                 COR: 5
     Name: stat 4150000              Coverage Path 2:                 COS: 1
                                     Hunt-to Station:
STATION OPTIONS
                                          Time of Day Lock Table:
             Loss Group: 19          Personalized Ringing Pattern: 1
                                               Message Lamp Ext: 415-0000
           Speakerphone: 2-way              Mute Button Enabled? y
        Display Language: english                Button Modules: 0
 Survivable GK Node Name:
          Survivable COR: internal             Media Complex Ext:
   Survivable Trunk Dest? y                         IP SoftPhone? n
```

Repeat this section for all agent stations. In this Full Stack Test effort, four physical agent stations "4150000 - 4150003" were modified.

©2011 Avaya Inc. All Rights Reserved.

2.5. Administer Codec Set

Enter the "**change ip-codec-set n**" command where "**n**" is the codec set to be used by the network region for the virtual IP softphones. Enter "**G.729A**" and "**G.711MU**" to the **Audio Codec** field and "**6**" to the **Frames Per Pkt** field. Retain the values of other fields. Add "**aes**" to the **Media Encryption** table in row 2.

***Note:** G.729A is an audio data compression algorithm which preserves network bandwidth.

```
change ip-codec-set 5                                          Page   1 of   2

                         IP Codec Set

   Codec Set: 5

   Audio        Silence      Frames   Packet
   Codec        Suppression  Per Pkt  Size(ms)
 1: G.729A            n         6        60
 2: G.711MU           n         6        60
 3:
 4:
 5:
 6:
 7:


    Media Encryption
 1: none
 2: aes
```


©2011 Avaya Inc. All Rights Reserved.

2.6. Administer Network Region

Enter the "**change ip-network-region n**" command where "**n**" is the network region for the virtual IP softphones. Set the **Codec Set** field to the codec set value administered in **Section** Error! Reference source not found..

```
change ip-network-region 5                                    Page   1 of  20
                            IP NETWORK REGION
  Region: 5
Location:         Authoritative Domain:
    Name: ACR CoR
MEDIA PARAMETERS                Intra-region IP-IP Direct Audio: no
      Codec Set: 5              Inter-region IP-IP Direct Audio: no
   UDP Port Min: 2048                     IP Audio Hairpinning? n
   UDP Port Max: 3329
DIFFSERV/TOS PARAMETERS
 Call Control PHB Value: 46
        Audio PHB Value: 46
        Video PHB Value: 26
802.1P/Q PARAMETERS
 Call Control 802.1p Priority: 6
        Audio 802.1p Priority: 6
        Video 802.1p Priority: 5      AUDIO RESOURCE RESERVATION PARAMETERS
H.323 IP ENDPOINTS                                     RSVP Enabled? n
  H.323 Link Bounce Recovery? y
 Idle Traffic Interval (sec): 20
   Keep-Alive Interval (sec): 5
            Keep-Alive Count: 5
```


©2011 Avaya Inc. All Rights Reserved.

2.7. Administer Virtual IP Softphones

Virtual IP Softphones are used by Avaya Contact Recorder to conference into calls involving target stations and to capture media. Add a virtual IP softphone using the "add station n" command, where "n" is an available extension number. Enter the following values for the specified fields, and retain the default values for the remaining fields.

- **Type:** "4624"
- **Name:** A descriptive name.
- **Security Code:** A desired value.
- **COR** "5" which is defined in **Section 2.3**.
- **IP SoftPhone:** "y"

```
add station 22991                                          Page   1 of   6
                                  STATION

Extension: 22991                      Lock Messages? n              BCC: 0
     Type: 4624                       Security Code: 123456          TN: 1
     Port: S00026                   Coverage Path 1:                COR: 5
     Name: ACR DMCC 22991           Coverage Path 2:                COS: 1
                                    Hunt-to Station:
STATION OPTIONS
                                         Time of Day Lock Table:
             Loss Group: 19         Personalized Ringing Pattern: 1
                                              Message Lamp Ext: 22991
           Speakerphone: 2-way             Mute Button Enabled? y
        Display Language: english
 Survivable GK Node Name:
          Survivable COR: internal            Media Complex Ext:
   Survivable Trunk Dest? y                        IP SoftPhone? y

                                           IP Video Softphone? n
```


©2011 Avaya Inc. All Rights Reserved.

Navigate to **Page 4**. Enter button type "**conf-dsp**" to the **Button 4** field and. Empty the value in the **Button 3** field.

***Note:** These button assignments are used by the Contact Recorder. The **conf-disp** button is used to retrieve information about each party of a conference call

```
add station 22991                                          Page   4 of   6
                                    STATION
 SITE DATA
       Room:                                            Headset? n
       Jack:                                            Speaker? n
      Cable:                                           Mounting: d
      Floor:                                        Cord Length: 0
   Building:                                          Set Color:

ABBREVIATED DIALING
     List1:                     List2:                     List3:


BUTTON ASSIGNMENTS
 1: call-appr                            7:
 2: call-appr                            8:
 3:                                      9:
 4: conf-dsp                            10:
 5:                                     11:
 6:                                     12:
```

Repeat this section to administer the desired number of virtual IP softphones, using sequential extension numbers and the same security code for all virtual IP softphones. In the test environment, several virtual IP softphones have been administered as shown below. However, only four virtual IP softphones (4151000 through 4151003) are used for this test.

```
list station                                                        Page   1

                                  STATIONS

Ext/          Port/   Name/                        Room/       Cv1/ COR/   Cable/
 Hunt-to       Type      Surv GK NN        Move     Data Ext    Cv2  COS TN Jack

415-1000      S00009  CR 4151000                                  5
               4624                        no                     1   1
415-1001      S00012  CR 4151001                                  5
               4624                        no                     1   1
415-1002      S00015  CR 4151002                                  5
               4624                        no                     1   1
415-1003      S00018  CR 4151003                                  5
               4624                        no                     1   1
415-1004      S00021  CR 4151004                                  5
               4624                        no                     1   1
415-1005      S00029  CR 4151005                                  5
               4624                        no                     1   1
415-1006      S00032  CR 4151006                                  5
               4624                        no                     1   1
```


©2011 Avaya Inc. All Rights Reserved.

2.8. Administer AE Services

Add the AES Server **Name** and **IP Address** to the **IP Node-Names** table using the "**change node-names ip name**" where "**name**" is a unique entry in the IP Node Names table.

```
change node-names ip tranio                                    Page   1 of   2
                                IP NODE NAMES
    Name                 IP Address
procr                  135.9.228.62
tranio                 135.9.228.40
```

Use the "**change ip-services**" command to add **AESVCS** to the **IP Services** table. On Page **1**, enter **AESVCS** under **Service Type**, set **Enabled** to "**y**", enter "**procr**" under **Local Node** and set **Local Port** to "**8765**".

```
change ip-services                                             Page   1 of   3

                                IP SERVICES
 Service     Enabled     Local       Local       Remote      Remote
  Type                   Node        Port        Node        Port
AESVCS         y        procr         8765
```

On Page **3**, enter the IP Node Name previously assigned to the AES server under **AE Services Server**, set the **Password** and ensure **Enabled** is set to "**y**".

```
change ip-services                                             Page   3 of   3
                          AE Services Administration

   Server ID    AE Services       Password          Enabled    Status
                   Server
      1:        tranio            aespassword1        y        in use
```

2.9. Administer CTI Link for DMCC and TSAPI

Add a CTI link using the "**add cti-link n**" command, where "**n**" is an available CTI link number. Enter an available extension number in the **Extension** field. Note that the CTI link number and extension number may vary. Enter "**ADJ-IP**" in the **Type** field, and a descriptive name in the **Name** field. Default values may be used in the remaining fields.

```
add cti-link 5                                                 Page   1 of   3
                                CTI LINK
Extension: 415-5000
     Type: ADJ-IP
                                                                      COR: 1
     Name: tranio
```


©2011 Avaya Inc. All Rights Reserved.

2.10. Assign AES Server to Network Region

Use the "**change ip-network-map**" command to add the IP address of the AES server "**135.9.228.40**" to network region "**5**" administered in **Section 2.6**. As all the virtual IP softphones register via the AES sever, they will automatically be assigned to that network region.

```
change ip-network-map                                        Page   1 of  63
                              IP ADDRESS MAPPING

                                                 Subnet Network     Emergency
 IP Address                                      Bits   Region VLAN Location Ext
 ----------------------------------------------- ------ ------ ---- -------------
FROM: 135.9.228.40                              /      5      n
  TO: 135.9.228.40
```


©2011 Avaya Inc. All Rights Reserved.

3. Configure Avaya Aura® Application Enablement Services


This section provides the procedures for configuring Avaya Aura® Application Enablement Services. The procedures include the following areas:

- Launch AES
- Verify DMCC and TSAPI Licenses
- Create Switch Connection
- Administer TSAPI link
- Obtain Tlink Name
- Disable Security Database
- Restart TSAPI service
- Administer Avaya Contact Recorder User for DMCC
- Administer Avaya Contact Recorder User for TSAPI

3.1. Launch Avaya Aura® Application Enablement Services


Access the Application Enablement Services (AES) web-based interface by using the URL "**https://ip-address:8443**" in an Internet browser window, where "**ip-address**" is the IP address of the AES server.

The **Welcome to Avaya Application Enablement Service** screen is displayed. Click **Continue to Login**.




©2011 Avaya Inc. All Rights Reserved.

The **Please login here** screen is displayed. Log in using the appropriate credentials.



The **Welcome to OAM** screen is displayed.




©2011 Avaya Inc. All Rights Reserved.

3.2. Verify DMCC and TSAPI Licenses


Avaya Contact Recorder has been granted unrestricted access to the DMCC and TSAPI interfaces. No additional **Device Media and Call Control** and **TSAPI Simultaneous Users** licenses are required for DMCC and TSAPI access.

3.3. Create Switch Connection

Select **Communication Manager Interface → Switch Connections** from the left pane. The **Switch Connections** screen shows a listing of the existing switch connections. Enter **Connection Name** and click **Add Connection**.




The **Connection Details – silcm5** page is displayed. Enter the AES password, defined in **Section 2.8**, for the **Switch Password** and **Confirm Switch Password** fields. Click the checkbox for both **SSL** and **Processor Ethernet**. Click **Apply**.



©2011 Avaya Inc. All Rights Reserved.


Locate the **Connection Name** that was just added, in this case "**silcm5**", and select the corresponding radio button. Click **Edit PE/CLAN IPs**.



The **Edit Processor Ethernet IP** screen is displayed. Enter the IP Address for the Communication Manager procr and click **Add/Edit Name or IP** button. Click **Back**.




Click the **Edit H.323 Gatekeeper** button to add the IP Address for the gatekeeper.




©2011 Avaya Inc. All Rights Reserved.


The **Edit H.323 Gatekeeper** screen is displayed. Note the IP address as this value will be used later to configure the Avaya Contact Recorder. Click **Back** when finished.



Click the **Survivability Hierarchy** button to add the IP Address for the Enterprise Survivable Server.




The **Survivability Hierarchy** screen is displayed. Enter the **Cluster ID/MID** for the Enterprise Survivable Server. For these Application Notes the Cluster ID is "3". Click **Insert**.




©2011 Avaya Inc. All Rights Reserved.

The Cluster ID is added to the table. Select the radio button for this Cluster ID and click the **Edit PE IP** button.




Enter the IP Address for the Processor Ethernet assigned to the ESS and click **Add/Edit Name or IP** button. The IP Address is added to the table. Click **Back**.



©2011 Avaya Inc. All Rights Reserved.

3.4. Administer TSAPI Link


To administer a TSAPI link, select **AE Services → TSAPI → TSAPI Links** from the left pane. The **TSAPI Links** screen is displayed, as shown below. Click **Add Link**. Note that the TSAPI link used for this test is Link 1 which is already configured. The screen below is for illustration purposes only.



The **Add TSAPI Links** screen is displayed next.

The **Link** field is only local to the Application Enablement Services server, and may be set to any available number. For **Switch Connection**, select the relevant switch connection from the drop-down list. For **Switch CTI Link Number**, select the CTI link number from **Section 2.9**. Retain the default values in the remaining fields, and click **Apply Changes**.

***Note:** The TSAPI link used for this test is Link 1 and is already configured. The screen below is for illustration purpose only.




©2011 Avaya Inc. All Rights Reserved.

3.5. Obtain Tlink Name

Select **Security → Security Database → Tlinks** from the left pane. The **Tlinks** screen shows a listing of the Tlink names. A new Tlink name is automatically generated for the TSAPI service. Locate the Tlink name associated with the relevant switch connection, which would use the name of the switch connection as part of the Tlink name. Make a note of the associated Tlink name, to be used later for configuring the Avaya Contact Recorder.


In this case, the associated Tlink name is "AVAYA#**SILCM5**#CSTA#TRANIO" where the switch connection "SILCM5" from **Section 3.3** is used as part of the Tlink name.



©2011 Avaya Inc. All Rights Reserved.

3.6. Disable Security Database


Select **Security → Security Database → Control** from the left pane, to display the **SDB Control for DMCC, TSAPI, JTAPI and Telephony Web Services** screen in the right pane. Uncheck **Enable SDB for DMCC Service** field and **Enable SDB TSAPI Service, JTAPI and Telephony Web Services** field. Click **Apply Changes**.



©2011 Avaya Inc. All Rights Reserved.

3.7. Restart TSAPI Service

Select **Maintenance → Service Controller** from the left pane, to display the **Service Controller** screen in the right pane. Check the **TSAPI Service**, and click **Restart Service**.




©2011 Avaya Inc. All Rights Reserved.

3.8. Administer Avaya Contact Recorder User for DMCC

Select **User Management → User Admin → Add User** from the left pane, to display the **Add User** screen in the right pane.


Enter desired values for **User Id**, **Common Name**, **Surname**, **User Password**, and **Confirm Password**. For **CT User**, select "**Yes**" from the drop-down list. Retain the default value in the remaining fields. Click **Apply** at the bottom of the screen (not shown).



©2011 Avaya Inc. All Rights Reserved.

3.9. Administer Avaya Contact Recorder User for TSAPI

Use the same procedure specified in **Section 3.8** to configure a user for TSAPI service access.



©2011 Avaya Inc. All Rights Reserved.


4. Configure Avaya Contact Recorder

This section provides the procedures for configuring Avaya Contact Recorder. The procedures include the following areas:


- Launch Avaya Contact Recorder
- Administer Contact Center Information
- Administer Recorder Information
- Administer Conferenced Mode

4.1. Launch Avaya Contact Recorder

Launch a web browser and enter "http://<IP address of Avaya Contact Recorder>:8080" in the URL field. Log in using proper credentials.



The following screen is displayed.




©2011 Avaya Inc. All Rights Reserved.

4.2. Administer Communication Manager Information

Navigate to **General Setup → Contact Center Interface** tab and set the following fields:

- **Switch Type:** select **Communication Manager**
- **Avaya Communication Manager Name**: Switch name defined in **Section 3.3**
- **AE Server Address(es):** IP address of the Avaya AES server
- **DMCC Username**: **User Id** configured in **Section 3.8**
- **DMCC Password**: **User Password** configured in **Section 3.8**
- **Encrypt Media Streams** Set to "**Yes**"
- **IP Station Security Code**: **Security Code** configured in **Section 2.7**
- **AES TSAPI Server(s)**: IP address of the Avaya AES server
- **AES TSAPI Service Identifier(s)**: **Tlink Name** configured in **Section 3.5**
- **AES TSAPI Service Login ID**: **User Id** configured in **Section 3.9**
- **AES TSAPI Service password**: **User Password** configured in **Section 3.9**
- **Extensions assigned to recorder**: Use "Add Port(s)" to add the virtual IP softphone extensions configured in **Section 2.7**


*Note: The **Service Observe Feature Access Code** is set to "***79**" which is used for another test and is outside the scope of this Application Notes.



©2011 Avaya Inc. All Rights Reserved.

4.3. Administer Recorder Information

Navigate to **General Setup → Recorder** tab and set the **IP address on this server to use for recordings (RTP, screen content etc.)** field to the IP Address of the Contact Recorder. Retain default values for the remaining fields.




©2011 Avaya Inc. All Rights Reserved.

4.4. Administer Conferenced Mode

Navigate to **Operations → Conferenced** tab and set the following fields:

- **Audio format**: Use default value **G.729A (8kbps)**
- **Maximum Concurrent Recordings (on this recorder)**: Number of recording ports allocated to the Conferenced Mode
- **Record calls to or from**: Use "Add address(s)" to add the target stations.

Retain the default values for other fields.



©2011 Avaya Inc. All Rights Reserved.

5. Verification Steps

This section provides the steps that can be performed to verify proper configuration of Avaya Aura® Communication Manager, Avaya Proactive Contact, Avaya Contact Recorder, and Avaya Aura® Application Enablement Services.

5.1. Verify Avaya Aura® Communication Manager

On Communication Manager, verify the status of the administered CTI link by using the "**status aesvcs cti-link**" command. Verify that the **Service State** is "established" for the CTI link number administered in **Section 2.9**, as shown below.

```
status aesvcs cti-link

                         AE SERVICES CTI LINK STATUS

CTI   Version  Mnt   AE Services      Service       Msgs     Msgs
Link           Busy  Server           State         Sent     Rcvd

5     4        no    tranio           established   15       15
```

Verify the registration status of the virtual IP softphones by using the "**list registered-ip-stations**" command. Verify that extensions used by this test from **Section 2.7** are displayed, as shown below.

```
list registered-ip-stations                                    Page   1


                            REGISTERED IP STATIONS

Station Ext   Set Type/ Prod ID/   TCP Station IP Address/
or Orig Port  Net Rgn   Release    Skt Gatekeeper IP Address
------------- --------- ---------- --- ---------------------------------------
415-1000      4624      IP_API_A    y  135.9.228.40
              5         3.2040         135.9.228.62
415-1001      4624      IP_API_A    y  135.9.228.40
              5         3.2040         135.9.228.62
415-1002      4624      IP_API_A    y  135.9.228.40
              5         3.2040         135.9.228.62
415-1003      4624      IP_API_A    y  135.9.228.40
              5         3.2040         135.9.228.62
```


5.2. Verify Avaya Aura® Application Enablement Services

Verify the **Switch Connection** status by selecting **Status → Status and Control → Switch Conn Summary** from the left pane. Verify "**Conn State**" is "**Talking**".

©2011 Avaya Inc. All Rights Reserved.




Verify the status of the DMCC link by selecting **Status → Status and Control → DMCC Service Summary** from the left pane. The **DMCC Service Summary – Session Summary** screen is displayed. In the lower portion of the screen, verify that the **User** column shows an active session with the user name from **Section 3.8**, and that the **# of Associated Devices** column reflects the number of virtual IP softphones being used by Avaya Contact Recorder (4 of them are for **Conferenced** recording and the rest are allocated for a separate test).




Verify the status of the TSAPI link by selecting **Status → Status and Control → TSAPI Service Summary** from the left pane. The **TSAPI Link Details** screen is displayed. Verify the **Status** is "Talking" for the TSAPI link administered in **Section 3.4**, as shown below.

©2011 Avaya Inc. All Rights Reserved.




5.3. Verify Avaya Contact Recorder

From the Avaya Contact Recorder screen, navigate to **Recorder Status → Server**. The following screen is displayed. Verify that the **Link to DMCC at 135.9.228.40** field shows "**ACTIVE**", the **Link to TSAPI at AVAYA#SILCM5#CSTA-S#TRANIO** field shows "**UP**".




Navigate to **Recorder Status → Ports**. The following screen is displayed. Verify the number of ports allocated to the **Conferenced Mode** is consistent with the number configured in **Section 4.4**. The other ports shown are assigned to **Quality** Mode which is used for another test and is outside the scope of this application notes.




©2011 Avaya Inc. All Rights Reserved.

5.4. Verify Avaya Contact Recorder Recording Playback

Select **Replay** from the Avaya Contact Recorder menu bar. The following screen is displayed.



Specify the search criteria in the left pane. Click **SEARCH** to update the screen with call recordings. Verify that the recording entries reflect the calls supposed to be recorded and displayed. Click the radio button to select an entry and click the play button (green triangle) to listen to the playback. Verify that the content of the recording matches the content of the call.



©2011 Avaya Inc. All Rights Reserved.

6. Additional References

Avaya references, available at http://support.avaya.com.

1. Installing and Configuring Avaya Aura® Communication Manager document http://support.avaya.com/css/P8/documents/100089133
2. Avaya Aura® Application Enablement Services Administration and Maintenance Guide, Release 6.1, Issue 2, February 2011 http://support.avaya.com/css/P8/documents/100127029
3. Avaya Contact Recorder 10.1 Planning, Installation and Administration Guide. Available on product media.

©2011 Avaya Inc. All Rights Reserved.

©2011 Avaya Inc. All Rights Reserved.
Avaya and the Avaya Logo are trademarks of Avaya Inc. All trademarks identified by ® and ™ are registered trademarks or trademarks, respectively, of Avaya Inc. All other trademarks are the property of their respective owners. The information provided in these Application Notes is subject to change without notice. The configurations, technical data, and recommendations provided in these Application Notes are believed to be accurate and dependable, but are presented without express or implied warranty. Users are responsible for their application of any products specified in these Application Notes.

Please e-mail any questions or comments pertaining to these Application Notes along with the full title name and filename, located in the lower right corner, directly to the Avaya Solution & Interoperability Test Lab at interoplabnotes@list.avaya.com.