



Avaya one-X[®] Deskphone H.323 9608, 9611G, 9621G, and 9641G Call Center User Guide

Release 6.2
16-603613
Issue 2
February 2012

Notice

While reasonable efforts have been made to ensure that the information in this document is complete and accurate at the time of printing, Avaya assumes no liability for any errors. Avaya reserves the right to make changes and corrections to the information in this document without the obligation to notify any person or organization of such changes.

Note

Using a cell, mobile, or GSM phone, or a two-way radio in close proximity to an Avaya IP telephone might cause interference.

Documentation disclaimer

"Documentation" means information published by Avaya in varying mediums which may include product information, operating instructions and performance specifications that Avaya generally makes available to users of its products. Documentation does not include marketing materials. Avaya shall not be responsible for any modifications, additions, or deletions to the original published version of documentation unless such modifications, additions, or deletions were performed by Avaya. End User agrees to indemnify and hold harmless Avaya, Avaya's agents, servants and employees against all claims, lawsuits, demands and judgments arising out of, or in connection with, subsequent modifications, additions or deletions to this documentation, to the extent made by End User.

Link disclaimer

Avaya is not responsible for the contents or reliability of any linked Web sites referenced within this site or documentation provided by Avaya. Avaya is not responsible for the accuracy of any information, statement or content provided on these sites and does not necessarily endorse the products, services, or information described or offered within them. Avaya does not guarantee that these links will work all the time and has no control over the availability of the linked pages.

Warranty

Avaya provides a limited warranty on its Hardware and Software ("Product(s)"). Refer to your sales agreement to establish the terms of the limited warranty. In addition, Avaya's standard warranty language, as well as information regarding support for this Product while under warranty is available to Avaya customers and other parties through the Avaya Support Web site: <http://support.avaya.com>. Please note that if you acquired the Product(s) from an authorized Avaya reseller outside of the United States and Canada, the warranty is provided to you by said Avaya reseller and not by Avaya.

Licenses

THE SOFTWARE LICENSE TERMS AVAILABLE ON THE AVAYA WEBSITE, [HTTP://SUPPORT.AVAYA.COM/LICENSEINFO/](http://support.avaya.com/licenseinfo/) ARE APPLICABLE TO ANYONE WHO DOWNLOADS, USES AND/OR INSTALLS AVAYA SOFTWARE, PURCHASED FROM AVAYA INC., ANY AVAYA AFFILIATE, OR AN AUTHORIZED AVAYA RESELLER (AS APPLICABLE) UNDER A COMMERCIAL AGREEMENT WITH AVAYA OR AN AUTHORIZED AVAYA RESELLER. UNLESS OTHERWISE AGREED TO BY AVAYA IN WRITING, AVAYA DOES NOT EXTEND THIS LICENSE IF THE SOFTWARE WAS OBTAINED FROM ANYONE OTHER THAN AVAYA, AN AVAYA AFFILIATE OR AN AVAYA AUTHORIZED RESELLER; AVAYA RESERVES THE RIGHT TO TAKE LEGAL ACTION AGAINST YOU AND ANYONE ELSE USING OR SELLING THE SOFTWARE WITHOUT A LICENSE. BY INSTALLING, DOWNLOADING OR USING THE SOFTWARE, OR AUTHORIZING OTHERS TO DO SO, YOU, ON BEHALF OF YOURSELF AND THE ENTITY FOR WHOM YOU ARE INSTALLING, DOWNLOADING OR USING THE SOFTWARE (HEREINAFTER REFERRED TO INTERCHANGEABLY AS "YOU" AND "END USER"), AGREE TO THESE TERMS AND CONDITIONS AND CREATE A

BINDING CONTRACT BETWEEN YOU AND AVAYA INC. OR THE APPLICABLE AVAYA AFFILIATE ("AVAYA").

Avaya grants End User a license within the scope of the license types described below. The applicable number of licenses and units of capacity for which the license is granted will be one (1), unless a different number of licenses or units of capacity is specified in the Documentation or other materials available to End User. "Designated Processor" means a single stand-alone computing device. "Server" means a Designated Processor that hosts a software application to be accessed by multiple users. "Software" means the computer programs in object code, originally licensed by Avaya and ultimately utilized by End User, whether as stand-alone Products or pre-installed on Hardware. "Hardware" means the standard hardware originally sold by Avaya and ultimately utilized by End User.

License types

Designated System(s) License (DS). End User may install and use each copy of the Software on only one Designated Processor, unless a different number of Designated Processors is indicated in the Documentation or other materials available to End User. Avaya may require the Designated Processor(s) to be identified by type, serial number, feature key, location or other specific designation, or to be provided by End User to Avaya through electronic means established by Avaya specifically for this purpose.

Shrinkwrap License (SR). Customer may install and use the Software in accordance with the terms and conditions of the applicable license agreements, such as "shrinkwrap" or "clickthrough" license accompanying or applicable to the Software ("Shrinkwrap License"). (see "Third-party Components" for more information).

Copyright

Except where expressly stated otherwise, no use should be made of materials on this site, the Documentation, Software, or Hardware provided by Avaya. All content on this site, the documentation and the Product provided by Avaya including the selection, arrangement and design of the content is owned either by Avaya or its licensors and is protected by copyright and other intellectual property laws including the sui generis rights relating to the protection of databases. You may not modify, copy, reproduce, republish, upload, post, transmit or distribute in any way any content, in whole or in part, including any code and software unless expressly authorized by Avaya. Unauthorized reproduction, transmission, dissemination, storage, and or use without the express written consent of Avaya can be a criminal, as well as a civil offense under the applicable law.

Third-party components

Certain software programs or portions thereof included in the Product may contain software distributed under third party agreements ("Third Party Components"), which may contain terms that expand or limit rights to use certain portions of the Product ("Third Party Terms"). Information regarding distributed Linux OS source code (for those Products that have distributed the Linux OS source code), and identifying the copyright holders of the Third Party Components and the Third Party Terms that apply to them is available on the Avaya Support Web site: <http://support.avaya.com/Copyright>.

Preventing Toll Fraud

"Toll fraud" is the unauthorized use of your telecommunications system by an unauthorized party (for example, a person who is not a corporate employee, agent, subcontractor, or is not working on your company's behalf). Be aware that there can be a risk of Toll Fraud associated with your system and that, if Toll Fraud occurs, it can result in substantial additional charges for your telecommunications services.

Avaya Toll Fraud Intervention

If you suspect that you are being victimized by Toll Fraud and you need technical assistance or support, call Technical Service Center Toll Fraud Intervention Hotline at +1-800-643-2353 for the United States and Canada. For additional support telephone numbers, see the Avaya Support Web site: <http://support.avaya.com>. Suspected security

vulnerabilities with Avaya products should be reported to Avaya by sending mail to: securityalerts@avaya.com.

Trademarks

All non-Avaya trademarks are the property of their respective owners, and "Linux" is a registered trademark of Linus Torvalds.

Downloading Documentation

For the most current versions of Documentation, see the Avaya Support Web site: <http://support.avaya.com>.

Contact Avaya Support

Avaya provides a telephone number for you to use to report problems or to ask questions about your Product. The support telephone number is 1-800-242-2121 in the United States. For additional support telephone numbers, see the Avaya Web site: <http://support.avaya.com>.

Federal Communications Commission (FCC) Interference Statement

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

FCC Caution: Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate this equipment.

FCC/Industry Canada Radiation Exposure Statement

This device complies with the FCC's and Industry Canada's RF radiation exposure limits set forth for the general population (uncontrolled environment) and must not be co-located or operated in conjunction with any other antenna or transmitter.

Warning

The handset receiver contains magnetic devices that can attract small metallic objects. Care should be taken to avoid personal injury.

Power over Ethernet (PoE) warning

This equipment must be connected to PoE networks without routing to the outside plant.

Contents

Chapter 1: Introduction to the Avaya Call Center agent deskphones.....	7
9621G and 9641G buttons and features.....	7
Scrolling and navigation using touch-based deskphone models.....	11
9608 and 9611G buttons and features.....	11
Scrolling and navigation using button-based deskphone models.....	15
Call Center work icons.....	15
Status alerting.....	17
Using the on-screen keyboard.....	18
Setting the Phone screen width.....	19
Setting the Quick Touch panel.....	20
Adjustable telephone stand.....	21
Chapter 2: About logging in and out and signing in and out as an agent.....	23
Logging in to your telephone extension.....	23
Logging out of your telephone extension.....	24
Signing in as an agent.....	24
Signing off as an agent.....	25
Chapter 3: About the Home screen and Avaya menu options.....	27
Home screen and Avaya menu.....	27
The Home screen on touch-based phones.....	27
Avaya menu on button-based phones.....	28
Accessing the Features menu.....	29
Chapter 4: Setting up and using recorded agent greetings.....	31
About Agent Greetings.....	31
About call center greeting types.....	32
Adding an agent greeting using a touch-based deskphone.....	33
Changing the greeting type using a touch-based deskphone.....	34
Adding an agent greeting using a button-based deskphone.....	35
Changing existing greetings.....	37
Chapter 5: About Call Center deskphone functionality.....	39
Using agent deskphones in the Call Center.....	39
About status line information and icons.....	39
About the agent information line.....	40
About agent work modes and states.....	40
Changing agent work mode or status.....	41
Chapter 6: Answering a Call.....	43
Answering a call if you are signed in as an agent.....	43
Chapter 7: About Features.....	45
Accessing the Features menu.....	45
Accessing features using a button module.....	46
Index.....	47

Chapter 1: Introduction to the Avaya Call Center agent deskphones

The 9608, 9611G, 9621G, and 9641G are multiline deskphones that you can use in a standard office environment or with Avaya Call Center 3.0 or later releases. The 9621G and 9641G deskphones are touch-based phones with a color display. The 9611G and 9608 are button-based phones. The 9611G has a color display, while the 9608 has a monochrome display.

You can connect a dual headset adapter to the 9641, 9608, and 9611G models so that two persons can listen in on calls. You can attach up to three button modules to these models to extend call appearances or features or both.


Additionally, the 9641G has an optional faceplate designed specifically for using this model in a call center. With these deskphones you can obtain convenient features and capabilities at your fingertips, including a Phone Screen to view and manage your calls, and icons indicating agent status, call states, feature status, queued calls, and missed calls. Using the designated feature buttons, you can change your agent work mode or status with one touch.

Not all functions and features described in this user guide may be available on your deskphone or applicable to the way your call center operates. If you find that a function or feature is not available, contact your supervisor or system administrator.

Important:

Specific user guides address standard office deskphone operation and features such as placing calls, reviewing call history, conference calling, and modifying deskphone options and settings for your personal preferences. Depending on which deskphone model you are using, see *Avaya one-X™ Deskphone H.323 9608 and 9611G User Guide (Document Number 16–603593)* or the *Avaya one-X™ Deskphone H.323 9621G and 9641G User Guide (Document Number 16–603594)*, available on the Avaya Support Site: <http://avaya.support.com>.

9621G and 9641G buttons and features



*** Note:**

The 9641G model includes a call center faceplate and a dual headset adapter replacing the handset as the only voice option.

Callout No.	Name	Description
1	USB Port	If administered, you can insert a USB device, thumb drive, or flash drive to transfer contacts between your phone and an external data source. You can also recharge some battery-powered devices by using a USB cable to connect the device to USB port of your deskphone. Note: The 9621G does not have a USB port.
2	Message Waiting Indicator	An illuminated red light in the upper-right corner of your phone indicates you have messages waiting. This light flashes when you receive an incoming call. If Visual Alerting is enabled, this light flashes when you receive an incoming call. In addition to the Message Waiting Indicator, the Message button is also illuminated when you have voice mail messages waiting.

Callout No.	Name	Description
3	Phone Display: Top Line	When the phone is idle, the top line shows the missed call icon with the number of calls missed, your primary extension, and the time and date. System messages also display on the top line.
4	Phone Display: Agent Status Line	When you are logged in as an agent, the Status line shows your current work status. For more information, see About status line information and icons on page 39 for information. Touch Features on the right side of the Status line to move from the Phone screen to the Features list. Touch Calls on the right side of the Status line to move from the Features list to the Phone screen.
5	Phone Display: Agent Information Line	The Agent Information line below the Status line shows information about a call state; see About the agent information line on page 40 for information.
6	Call Appearance/ Feature lines	When the Phone screen is active, the lines below the Status line show call appearances. For example, information about an active call, an idle line, or which line has a held or conference call. Touch a call/line appearance to make or answer a call. When the Features list is active, the lines show the call center features you use to do your job, such as VU Stats, After Call work and other features.  Note: By default, the feature labels and call/bridge appearances appear on separate screens. However, you can request the administrator to configure a consolidated screen for feature labels and call/bridge appearances. Touch a labeled feature button to enable or disable that feature. The feature buttons provide access to the Avaya call center system features that have been administered for your extension. The green LED next to each feature button indicates if the feature is currently on or off. If the green light is on, the feature is on. The feature buttons provide the same features that are available in the features menu. If you have the Quick Touch panel activated at the bottom of the display (see Setting the Quick Touch on page 20 panel), only two or three call appearance lines show on the display, depending on how many lines you indicate for the Quick Touch panel.
7	Softkeys	The bottom line of the display shows the softkeys applicable to the information displayed on the screen. Softkey labels appear directly on the softkeys, which you touch to take the indicated action. The labels and the actions vary depending on the current context.

Callout No.	Name	Description
8	Quick Touch Panel	If administered, the Quick Touch panel provides additional buttons for features and work modes. Note that when displayed, the Quick Touch panel might overlay some of your call appearance lines. For more information, see Setting the Quick Touch Panel on page 20.
9	Contacts	Press the Contacts button to view the entries in your contact list.
10	Home	Press the Home button to access the Home screen. The Home screen provides options to customize phone settings, configure call logging, select the display language, view network information, and log out the telephone extension.
11	History	Press the History button to view a list of your outgoing, incoming, and missed calls. The icon on the History button is illuminated when you have missed calls. Direct agent calls (DAC) will show on your log but call center calls will not.
12	Phone Button	Press the Phone button to return to the Phone screen from the Features list or another application.
13	Message	Press the Message button to connect directly to your voicemail system.
14	Volume	Press + or - on the Volume button while active on the headset to adjust the volume. To adjust the volume of the ringer, press + or - on the volume button while the headset is inactive.
15	Mute	Press the Mute button to mute a call in progress. To take a call off mute, press Mute again.
16	Dual Headset Adapter	When attached, two people with headsets can listen to the same call with this adjunct device.
17	Release	Press the Release button to end a call. Note: This button appears only if the Contact Center (CC) face plate is attached to the 9641G model.

 Note:

A **Release** button is displayed instead of the **FORWARD** and **HEADSET** buttons on the deskphone, when the deskphone is attached with a CC face plate. The face plate can be attached to the 9641G phone only.

Scrolling and navigation using touch-based deskphone models


If you have a 9621G or 9641G deskphone model, use the on-screen up and down arrow buttons on the upper right corner of the screen to scroll up or down through a list.

To switch between call appearances and features, touch **Features** or **Calls** in the upper right of the display, depending on the screen that is currently on display.

On touch-based phones, a list item has a **Details** button with a blue right-facing arrow. Touch the button to see more information about the item.

You can act on objects such as a line or softkey, by touching the object or by touching the on-screen softkey labels. Softkey labels change according to the context.

9608 and 9611G buttons and features



	Name	Description
1	USB Port	Available on 9611G deskphones only. If administered, you can insert a USB device such as a memory stick, thumb drive, or flash drive to transfer contacts between your phone and an external data source. You can also recharge some battery-powered devices by using a USB cable to connect the device to USB port of your deskphone. Note: The 9608 deskphone does not have a USB port.
2	Message Waiting Indicator	An illuminated red light in the upper-right corner of your phone indicates you have messages waiting. This light flashes when you receive an incoming call.
3	Phone Display: Top Line	When the phone is idle, the top line shows the missed call icon with the number of calls missed, your primary

	Name	Description
		extension, and the time and date. System messages also display on the top line. * Note: After successful agent log in, the primary extension on the top line is replaced by Agent ID.
4	Phone Display: Agent Status line	When you are logged in as an agent, the Status line (below the top line) shows your current work status; see About status line information and icons on page 39 for information.
5	Phone Display: Agent Information line	The Agent Information line displays all agent related information such as caller information, user-user information, and agent status information depending on the VU-stat configuration. For more information, see About the agent information line on page 40.
6	Phone Display: Call Appearances/ Feature Lines	When the Phone screen is active, the Call Appearance lines show call information, for example, information about an active call, an idle line, or a line that has a held, or a conference call. When the Features list is active, the display area shows the call center features you use to do your job, such as VU Stats, After Call work and other features. * Note: You can change the screen width from Full width mode where each call appearance or feature occupies the entire width of a line to Half width mode where each call appearance or feature occupies half the width of a line, effectively splitting the screen in half. For more information on changing the screen width, see Setting the Phone screen width on page 19.
6	Call/Line Appearance Buttons or Feature Buttons	The right and left sides of the display screen have up to 8 buttons that you can program as either call appearance, line buttons or feature buttons. Press a call appearance, or line button to make or answer a call or to resume a call on hold. Press a labeled feature button to activate or deactivate that feature. The feature buttons provide access to the Avaya call center system features that have been administered for your extension. The green LED next to each feature button indicates if the feature is currently on or off. If the green light is on, the feature is on. The feature buttons provide the same features that are available in the Features menu. For more information about the features menu, see the Features Menu on page 29.
7	Phone Display: Softkey Labels	The bottom line of the display shows the softkey labels applicable to the information displayed on the screen.

	Name	Description
8	Softkeys	Press the softkeys to select the actions indicated by the softkey labels above them. The labels and the actions vary depending on the current context.
9	Message	Press the Message button to connect directly to your voicemail system.
10	Navigation Arrows	A scroll bar appears on the right side of the display area when there is more information than can be displayed. Press the up or down navigation arrows to scroll through lists in that direction. Press the right or left navigation arrows to navigate between different views of an application, to move between the Calls screen and the Features menu, to move the cursor during text input, or to move between options.
10	OK	Press the OK button for a shortcut to an action. For example, when you select a call log entry, pressing OK dials the number.
11	Calls/Features	Press Calls to move from the Features list to the Phone screen. Press Features to move from the Phone screen to the Features list. Pressing the Phone button on the phone also displays the Phone screen.
12	Contacts	Press the Contacts button to view the entries in your contact list.
13	History	Press the History button to view a list of your outgoing, incoming, and missed calls. The icon on the History button is illuminated when you have missed calls. Direct Agent Calls (DAC)s will show on your log but call center calls will not.
14	Home	Press the Home button to access the Avaya menu. The Avaya menu screen provides options that allow you to customize phone settings, configure call history logging, select the display language, view network information, and log out the telephone extension.
15	Volume	Press + or - on the Volume button while active on the headset to adjust the volume. To adjust the volume of the ringer, press + or - on the volume button while the headset is inactive.
16	Mute	Press the Mute button to mute a call in progress. To take a call off mute, press Mute again.
17	Dual Headset Adapter	Attach an adjunct device with which more than one person can listen in on a call. This feature is available on the 9608 deskphone.
18	Speaker On/Off	Illuminates when the Speakerphone is active.

	Name	Description
19	Headset On/Off	Illuminates when a Headset is active.

Scrolling and navigation using button-based deskphone models

On a 9608 and 9611G model deskphone, a navigation icon in the phone indicates that you can scroll to more options or information. When navigating through the options and features on your telephone display, use the navigation arrows to scroll and the line buttons or the **OK** button to select lines or options. The navigation arrows are located on the phone itself surrounding the **OK** button.

When you scroll to a line on the display, that line is selected, as indicated by highlighting. The softkey labels change according to the options available for the selected line. The **OK** button is a shortcut for the default action. You can also select a line or feature without scrolling by pressing the corresponding line button.

Call Center work icons

The icons in the following table indicate the state of a call, navigation choices, or the status of a call center feature or activity. Depending on the action they depict, these icons can appear on the agent status line, the Information line, a call appearance line, or in the general application area of the display screen. If you have a 9608 monochrome deskphone, the icons show in black and white. If you have a color display deskphone such as the 9611G, 9621G, or 9641G, the icons display in color or gray shades or both.

 Note:

For information about the agent work status icons, see [About status line information and icons](#) on page 39.

Icon	Description
	Missed calls. A call was not answered or was forwarded to voice mail. The total number of missed calls displays next to this icon.
	This call appearance line is idle and not in use.
	An incoming call is alerting on this call appearance line.

Icon	Description
	A call is active on this line.
	A call is on Hold on this line.
	Your calls are being forwarded.
	A Conference is active on this line.
	A Conference is on hold on this line.
	A Bridged Call is in progress on this line.
	On the Phone screen display, use the right arrowhead icon to access the Features screen. On the Features screen display, use the right arrowhead icon to access your calls on the Phone screen.
	Scroll up or down when there is more information than can display in the application area.
 (9608)  (9611G)  (9621G, 9641G))	Indicates a Forced Logout Override is in effect. Depending on how your call center system is administered, a system-generated forced logout might occur. For example, based on the time of day. This icon indicates an override is active.
 (9608)  (9611G, 9621G, 9641G)	Notifies you that your Agent Greeting has been recorded and is available.
 (9608)  (9611G, 9621G, 9641G)	Notifies you that your Agent Greeting is being played.
 (9608, 9611G)  (9621G, 9641G)	Indicates the Queued Calls feature is active and you have calls in the queue.
 (9608)  (9611G)  (9621G, 9641G)	Indicates that the VU Stats feature is active.

Icon	Description
 (9608, 9611G)  (9621G, 9641G)	Use the feature arrows to move left or right between feature settings, for example, to select a Greeting type when establishing an Agent Greeting.

*** Note:**

Some screens, for example, the Contacts main screen, do not display these icons to make room for other controls and indicators that apply to that specific screen.

Status alerting

For button-based agent deskphone models, such as 9608 and 9611G, each call, each call appearance button and feature button has two LEDs, one green and one red, to indicate the status of the call appearance or feature. For touch-based agent deskphones such as the 9621G and 9641G, the entire line is shown in a color to indicate call status, and for the Feature list. A colored square icon indicates the status of the Features list. The status is identified by whether the LED or color highlight is on, off, or blinking LEDs only as described in the following tables.

Table 1: Call appearance button LEDs/line colors

LED or line color	Description
Steady green LED	Call appearance or Feature is active. Applicable to the 9608 and 9611G deskphones only.
Steady yellow highlight on line	Call appearance is active. Applicable to the 9611G deskphones only.
Slow blinking green LED	Call appearance is ringing. Applicable to the 9608 and 9611G deskphones only.
Steady green highlight on line	Call appearance is ringing. Applicable to the 9621G and 9641G deskphones only.
Steady red LED	Call appearance is selected and will be used when you go off-hook. It remains steady red while you use the call appearance. Applicable to the 9608 and 9611G deskphones only.
Flashing line LED	Call put on hold using the hold soft key
Fluttering or unsteadily flashing line LED	Call put on hold as part of conference or transfer procedure state.
Off	Call appearance is available.

Table 2: Feature button LEDs

LED/Square Icon	Description
Steady green	Feature is active.
Off	Feature is not active.

Using the on-screen keyboard

If you have a touch-based deskphone such as a 9621G or 9641G, an on-screen keyboard appears when you add or edit any text. You can switch between alphabetic and numeric keyboards, and you can use the keyboard to enter symbols and accented letters.

Use the following diagrams to add or change text or numbers. Touching and holding down the right or left buttons of the Backspace or cursor produces an automatic repeat action that stops when you lift your finger or stylus. Remember to touch the **Done** check mark when you finish

editing. Use the **Cancel X** to discard any edits and return to the previous screen, retaining the original information.

Figure 1: Text Entry Keyboard





Figure 2: Numeric Entry Keyboard



Setting the Phone screen width

Procedure

1. Press **Home**.
2. Select **Options & Settings** or **Phone Settings**.
3. Press **Select** or **OK**.
4. Select **Screen & Sound Options**.
5. Press **Select** or **OK**.

6. Select **Phone Screen Width**.
 7. Press **Change** or **OK** to change the screen width from Full where each call appearance or feature occupies the entire width of a line to Half mode each call appearance or feature occupies half the width of a line, effectively splitting the screen in half or Half to Full.

If your screen width is set to Half and you set the [Large Text](#) option to “On” (to display a larger font), the screen width will automatically change from Half to Full, to allow the larger text size to display properly. In this case, if you prefer a split screen, you must turn off large text.
 8. Press **Save**.
-

Setting the Quick Touch panel

About this task

When you use the Quick Touch panel, the Calls screen provides access to more of your work states and features, at a glance. When a feature is on or active, the associated button is highlighted in green. You can set the Quick Touch Panel to display one (the default) or two lines, or set it not to display at all. Note that displaying the Quick Touch panel can limit your call appearances display to two or three lines at a time.

 Note:

The QTP feature is available only on the 9621G and the 9641G deskphones.

Procedure

1. Press **Home**.
2. Touch **Settings**.
3. Touch **Options & Settings**.
4. Touch **Screen and Sound Options**.
5. On the **Screen and Sounds** menu, touch **Show Quick Touch Panel** to change the setting from 1 Line to 2 Lines, from 2 Lines to No, or from No to 1 Line.

 Note:

When you are signed in as an agent, the default number of lines on the Quick Touch panel is two lines. When you are not signed in as an agent, the default number of lines is one.

6. Touch **Save** to save the setting or **Cancel** to return to the menu without saving.
-

Adjustable telephone stand

The deskphone stand attaches to the phone in one of two ways so that you can place the phone in a relatively flat position or at an angle. Before you attach the stand, take note of the Model Number label on your deskphone, attached to the deskphone's underside.

You can adjust the display screen of the 9621G and 9641G models to different angles for optimal viewing. To move the display screen, gently pull the top of the display screen towards you. As you pull the screen towards you, you may hear a clicking sound. Each of these four clicks is a locking position for the display screen. Gently push on the display screen to adjust the screen to a previous position. Gently pull the display screen all the way towards you and push to return it to the original flat position.

Chapter 2: About logging in and out and signing in and out as an agent

Call center agents have two types of logins:

- one for the telephone extension itself called login.
- one that identifies you as a call center agent called sign in.

To sign in as an agent, you must first log in to the deskphone itself unless the deskphone is already logged in. To log out from your telephone extension, you must first sign off as an agent. If you share a deskphone with another agent, you may be instructed to just sign in and sign off as an agent, leaving the deskphone logged in at all times to preserve call center information. You can sign in and out as an agent using one of the following ways, depending on how your call center system is administered:

- Using a Feature access code (FAC) provided by your supervisor.
- Using a Feature button labeled Sign In or Sign Out.
- Using a Feature button labeled Login or Logout.
- Using another Feature Button, softkey, autodial button, or abbreviated dial button designated by the system administrator for agent sign in and sign out.
- Using Computer Telephony Interface (CTI) agent login.

Note:

The following conditions must be met for Agent Login Detection to properly detect the Agent ID by use of a Abrv-dial or Autodial button:

- Abrv-dial/Autodial button must contain the Agent Login FAC followed by a complete Agent ID (password cannot be administered as part of the button)
- Abrv-dial/Autodial button can contain the Agent Login FAC only AND the Agent Login Detection via VuStat feature must be fully implemented.

Your supervisor will explain the proper agent sign in and sign out procedures for your call center environment, which may not be the same as the procedures provided in this chapter. In all cases, follow the Agent sign in and sign out procedures your supervisor provides.

Logging in to your telephone extension

About this task

Before you can sign in as an agent, you must log in to your telephone extension if you have not already done so. Log in from the initial screen at the system prompt for your extension.

Procedure

1. Enter your extension in the text box on the phone display.
 2. If you have a touch-based deskphone, touch **Enter**. If you have a button-based deskphone, press **Enter** or **OK**.
 3. Enter your password.
 4. If you have a touch-based deskphone, touch **Enter**. If you have a button-based deskphone, press **Enter** or **OK**.
-

Logging out of your telephone extension

Procedure

1. Press **Home**.
 2. If you have a touch-based deskphone, select **Settings**. If you have a button-based deskphone, proceed to step 3.
 3. If you have a touch-based deskphone, touch **Log Out**. If you have a button-based deskphone, scroll down and select **Log Out**.
 4. If you have a touch-based deskphone, touch **Log Out** to confirm. If you have a button-based deskphone, press **Log Out** or **OK**, then press **Log Out** to confirm.
- After you have logged off, the status line displays *Logged out*.
-

Signing in as an agent

About this task

If the telephone prompts you for your Extension, you must first log in to the deskphone before you enter your call center agent identification.

Important:

The agent sign in procedure uses a Feature access code (FAC). Depending on how your call center operation is administered, this particular sign in procedure may not apply. For example, some call center systems may be administered for Agent sign in using a Feature Button or softkey. In this case, sign in to the Call Center as you have been trained to do by your supervisor.

 Note:

When signing in using mode other than Feature Access Code (FAC), the agent greetings that are recorded will not be backed up and the Agent ID will not display on the top line. To get the Agent Greetings backed up and the Agent ID to display on the top line, contact your administrator. In all cases, follow the Agent sign in and sign out procedures your supervisor provides.

Procedure

1. Enter your Sign In Feature Access Code using the dialpad.
2. Enter your Agent ID using the dialpad.
3. Enter your Agent Password, if applicable.

Result

The top display line now shows your Agent ID and the Agent Status line shows your current status such as Aux Work. The headset LED is illuminated and the Aux Work feature button is shown as active or on.

Signing off as an agent

About this task

Depending on how your call center system is administered and how busy the call center is, the system may override your attempt to sign out. In this case, follow the procedures specified by your supervisor. The sign-out operation can be carried out using the Agent Logout Feature Access Code.

- Press the **Agent-logout** softkey to sign off as an agent.

Result

The top display line no longer displays the Agent ID. The Agent Status line displays the current status as **Logged Out**.

About logging in and out and signing in and out as an agent

Chapter 3: About the Home screen and Avaya menu options

Home screen and Avaya menu

If you have a 9621G or 9641G deskphone, the Home screen contains icons that provide access to adjust and customize options and settings for your deskphone, record and update your Greetings, get information about your phone and network settings, and log out. But if you have a 9608 or 9611G deskphone, the Avaya Menu provides access to those features instead.

 Note:

The options, settings, and sub-menus that appear on the Home screen and Avaya menu depend on how your extension was administered. Some items described here may not be available. Other options, settings, and submenus might be available which are not specifically related to a call center. For those standard features, see *Avaya one-X™ Deskphone H.323 9608 and 9611G User Guide (Document Number 16–603593)* and *Avaya one-X™ Deskphone H.323 9621G and 9641G User Guide (Document Number 16–603594)*, available on the Avaya Support Site: <http://avaya.support.com>.

The Home screen on touch-based phones

Press the **Home** button on the display screen to gain access to the Home screen. The Home screen has a black background with icons. With the icons, you can gain access to telephone options and settings and adjust or customize the options and settings or view the phone and network settings. From the Home screen, you can also set up and update your Agent Greetings, access Web-based applications to get information about the time and weather in different parts of the world, display a calculator, and use the Favorite speed dial buttons. Using **My Pictures** option on the Home screen, you can load a picture from a USB device as a phone screensaver. The exact content of your Home screen depends on how your administrator has set up your system but the screen normally includes the following standard Avaya features:

- **Greetings:** You can add up to six Agent Greetings, edit those greetings, and remove greetings you no longer need.
- **Settings:** You can use change your call settings, the language in which information displays on the screen, the way your screen looks and sounds, log into a phone as a guest, clean your screen, log out your phone.

- **World Clock:** You can see the time and weather in different parts of the world. This Avaya application might not be available on Call Center deskphones.
- **Weather:** You can see the current weather conditions in an area you choose and a short-term weather forecast. This Avaya application might not be available on Call Center deskphones.
- **Calculator:** You can use the simple, four-function calculator. This Avaya application might not be available on Call Center deskphones.
- **My Pictures:** You can use pictures from a USB device as your telephone screensaver.

Your administrator may make other Web-based applications available to you, for example, a corporate directory or support page. To start any application you see on the Home screen, touch the icon. Depending on how many Avaya applications, contact favorites, and Web-based applications are administered, you may have a second page for your Home screen. Touch the scroll bar on the right side of the Home screen to view the next page.

*** Note:**

The Settings options depend on how your extension was administered. Some options described in this guide may not be available to you. This guide describes the Greetings option only. For other features and applications that may be on your touch-based deskphone, see *Avaya one-X Deskphone H.323 9621G and 9641G User Guide (16–603594)*.

Avaya menu on button-based phones

You can use the Avaya menu to adjust and customize options and settings for your telephone, add or update Agent Greetings, access additional Web-based applications, get information about your phone and network settings, and log out. For details, see [Agent Greetings](#) on page 31. The other menu choices are explained in detail in *Avaya one-X™ Deskphone H.323 9608 and 9611G User Guide*. When you press the **Home** button, you see the following menu, depending on how your administrator has set up your system and on the applications available to you:

*** Note:**

The menus and submenus that you can see depend on how your extension was administered. Some options or sub-menus may not be available. Contact your System Administrator if you have any questions.

Sample Menu — if no WML Applications administered	Sample Menu — with WML Applications administered
> Greetings > Phone Settings > Guest Login > Log Out > About Avaya one-X	> Greetings > Options & Settings > Browser > Network Information > VPN Settings

Sample Menu — if no WML Applications administered	Sample Menu — with WML Applications administered
> My Pictures	> Log Out > About Avaya one-X > My Pictures

*** Note:**

On menus without WML applications, select **Phone Settings** to access the standard telephone Options & Settings menu.

- Greetings: You can add an Agent Greeting, change an existing Agent Greeting, or remove an Agent Greeting you no longer need.
- Options & Settings: If your menu is customized, you can change your call settings, personalize button labels, adjust brightness and contrast, select your ringing pattern, and more.
- The Browser menu contains additional web-based applications. (If no web applications are available for your phone, the Browser menu is not shown.)
- Network Information: You can see a summary of network-related parameters for your phone and provides diagnostic information. If your administrator has set up Web applications, this option appears under the Phone Settings menu instead.
- About Avaya one-X provides the release number of your telephone software; our administrator may ask you to check the release number to troubleshoot problems.
- Guest Login: You can log in to a phone to which you are not normally assigned, to access your own contacts and features.
- Log Out: You can sign off the phone, to protect your settings or to allow another user to log in. Log out does not display unless your phone (and any associated button module) is in an idle state.
- My Pictures: You can use pictures from a USB device as your telephone screensaver, but is only available on those deskphones with a USB interface.

Accessing the Features menu

Procedure

1. From the Phone screen, use the navigation button and scroll to the right side to access the **Features** menu.
For models with LEDs, the LED next to the feature name indicates if the feature is currently on or off. If the light is on, the feature is on.
To return to the main Phone screen, press **Phone** or scroll to the left.
2. Scroll down to see the features that have been administered for your extension.

The green LED next to the Feature button indicates if the feature is currently on or off. If the light is on, the feature is on. The red LED next to the Feature button blinks while the feature label is displayed on the screen.

Chapter 4: Setting up and using recorded agent greetings

About Agent Greetings

Agents can record their own *greetings* which can then be played back to callers. For example, *Thanks for calling Informaxx. My name is Sally. How can I help you?*. Up to six greetings can be set up, each ten seconds in length. Recorded greetings consist of a Label or a greeting name, the recorded greeting itself, and an optional type.

The agent initiates Manual type greetings while VDN greeting types play automatically by recognizing the number the caller has dialed and playing the corresponding greeting. This feature is important when the agent handles incoming calls for different departments or companies. When you set up a VDN greeting, you must specify the numbers that the system must look for to play the correct VDN greeting. You can also specify where in the phone number the system should look. The pattern of numbers the system looks for is called a “match string” and the place to look is called a “match criterion.”

For more information, see [About call center greeting types](#) on page 32. To set up a greeting, see [Adding an agent greeting using a touch-based deskphone](#) on page 33 if you have a 9641G or 9621G model or [Adding an agent greeting using a button-based deskphone](#) on page 35 if you have a 9608 or 9611G model.

 Note:

Supervisors or administrators can prevent agents from setting up their own greetings. If you cannot see a Greetings option on the Avaya menu of 9608 and 9611G or the Home screen of 9621G and 9641G, your administrator has denied you permission to establish and modify your own greetings.

 Important:

You cannot create, edit, or delete a Greeting while you are in Available status, or when there is any call in progress whether active, or held, regardless of your status as an agent. You must change your status from *Available* to *Aux* or *ACW* for Agent Greetings icon to appear.

 Note:

To create, edit, delete, or play a greeting on your telephone, provide the telephone your agent ID. If you have logged into the call center using the CTI login, and your agent ID is not displayed in the center of the Top Line, then you can only modify the greetings. The greeting would not be backed up after modifying the greeting label. In this situation, contact

your administrator who may have created a special vu-display feature button that you should press at this point, to populate the Agent ID at the top of the display.

About call center greeting types

When you add a greeting, a default type of “Auto Answer” is automatically assigned and will play that greeting for all incoming calls. Other types of greeting may apply to your operation depending on how the call center is set up and the number of customers are assigned to an agent. Your supervisor will assist you in setting up your greetings or might set the greetings for you. Because different greeting types have different match criteria options and associated text strings, use the following chart to determine with your supervisor the type of greeting and associated information best suited to each type of greeting you record.

Table 3: Greeting Types and Match Criteria

Greeting type	Description	Match criteria options
Manual	Agent must select the Greetings softkey to play the message for each incoming call.	None
Auto answer (default)	The greeting plays automatically for an incoming call or for any incoming call that does not fully match the other options.	All calls: The default is to play for all incoming calls. In ready Mode: Play for incoming calls when agent status is Available.
VDN	Vector Directory Number. Call vectors are commands that route incoming calls to the call center and determine how these calls are processed. The VDN permits each call to be treated uniquely according to a number of factors, including the number the caller dials, the number the caller calls from, the number of calls in queue, and the time of day or day of the week or both.	Anywhere (default): The data matches any set of characters in the incoming call-associated display message. On left: The data matches the characters on the left end of the incoming call-associated display message. On right: The data matches the characters on the right end of the incoming call-associated display message. Exact match: The data matches exactly the entire incoming call-associated display message .
ANI	Automatic Number Identification. This type makes vector routing decisions	Anywhere (default): The data matches any set of characters in the incoming

Greeting type	Description	Match criteria options
	based on the caller identity and the number of the originating line.	call-associated display message. On left: The data matches the characters on the left end of the incoming call-associated display message. On right: The data matches the characters on the right end of the incoming call-associated display message. Exact match: The data matches exactly the entire incoming call-associated display message.
Prompted Digits	Used in call centers with automatic recordings that <i>prompt</i> the caller to enter <i>digits</i> to reach a specific area of assistance in the call center. For example, a caller might be prompted to press <i>1</i> to reach Sales or <i>2</i> for Billing inquiries.	Anywhere (default): The data matches any set of characters in the incoming call-associated display message. On left: The data matches the characters on the left end of the incoming call-associated display message. On right: The data matches the characters on the right end of the incoming call-associated display message. Exact match: The data matches exactly the entire incoming call-associated display message.

Adding an agent greeting using a touch-based deskphone

About this task

You can add up to six different greetings and set them to play automatically or manually when you have an incoming call.

*** Note:**

Use this procedure if you have a touch-based deskphone such as the 9621G or 9641G. If you have a button-based deskphone such as the 9608 or 9611G, see [Adding an agent greeting using a button-based deskphone](#) on page 35.

Procedure

1. Press **Home**.
2. Touch **Greetings**.
3. Touch **New** or any numbered blank greeting line.
The phone displays the on-screen keyboard displays so that you can enter the new greeting label.
4. Use the on-screen keyboard to enter a label that distinguishes this greeting from other greetings you may already have or will be adding. The Greeting Label can be up to 15 characters. For details on entering text using the keyboard [Using the on-screen keyboard](#) on page 18 .
5. Touch the **Next** keyboard button.
6. Touch **Record**.
7. Speak your greeting (up to ten seconds) into the headset, and then press **Stop**.
8. Choose one of the following options:
 - To listen to the greeting, touch **Play**.
 - To replace the greeting, touch **Restart** and repeat the previous step.
 - To save the recording, touch **Done** and proceed to the next step.
 - To delete the recording you just made, touch **Cancel**.

Next steps

If the default greeting type shown is correct, touch **Save** to save the Greeting, its label, and the Greeting type.

If the default greeting type is not the one you want, proceed to [Changing the greeting type using a touch-based deskphone](#) on page 34 before saving the greeting.

Related topics:

[Changing the greeting type using a touch-based deskphone](#) on page 34

Changing the greeting type using a touch-based deskphone

About this task

When adding a new greeting, the telephone displays the **Greetings Type Selection** screen after you indicate that you have completed recording your greeting. New greetings are automatically assigned a default type of *Auto Answer* with a Match Criterion of *All Calls* and you use the **Greetings Type Selection** screen to change that default type, if required. When changing an existing greeting, the **Greeting Type Selection** screen displays when you select the greeting you want to change, and touch the **Type Details** icon.

The default greeting type *Auto Answer* with a Match Criterion of *All Calls* means that this greeting plays automatically when you answer an incoming call. The other greeting types are

Manual, VDN, ANI and Prompted Digits. Other than Manual, all types require that you also select match criteria, such as when to invoke this greeting, or where to find the data to trigger the greeting. You must also select additional data, such as a telephone number sequence or string with which the system can match the display message to a specific greeting. This feature is useful when you deal with different groups of customers and want a customer-specific greeting to play based, for example, on the number the caller has dialed. For more information about Greeting Types and their applicable match criteria, see [About call center greeting types](#) on page 32.

Procedure

1. Ensure that the telephone displays the greeting whose type you want to change. Touch the **Details** icon on the right side of the Type line.
2. Use the **Right Arrow** on the Type line to cycle consecutively through the available types or the **Left Arrow** to cycle back through the types. Notice that the Match Criteria value below the type may change to correspond with the type currently displayed.
3. To change the match criterion for the greeting type, use the **Right Arrow** on the Match Criterion line to cycle consecutively through the available criteria or the **Left Arrow** to cycle back through the choices.
4. If the telephone displays the **String to Match** label, you must indicate what string of digits the telephone should look for. Touch the **String to Match** line and use the dialpad to enter the number sequence that should be matched for this greeting. For example, if you serve two customers with the telephone numbers 732-42-111 and 732-842-2222, you can enter just the last four digits of those numbers as the strings to match for their respective greetings. After entering the string, press **Done** to return to the **Type Selection** screen.
5. Touch **Done** again, then touch **Save** on the **Greetings Summary** screen.

Adding an agent greeting using a button-based deskphone

About this task

You can add up to six different greetings and set them to play automatically or manually when you have an incoming call. The default greeting type *Auto Answer* with a Match Criterion of *All Calls* means that this greeting plays automatically when you answer an incoming call. Other types are Manual, VDN, ANI and Prompted Digits. Other than Manual, all types require that you also select match criteria such as when to invoke this greeting, or where to find the data to trigger the greeting. You must also select additional data such as a telephone number sequence or string, with which the system can match the display message to a specific greeting. This feature is useful when you deal with different groups of customers and want a

customer-specific greeting to play based, for example, on the number the caller has dialed. For more information about Greeting Types and their applicable match criteria, see [About call center greetings type](#) on page 32.

*** Note:**

Use this procedure if you have a button-based deskphone such as the 9608 or 9611G. If you have a touch-based deskphone such as the 9621G or 9641G, see [Adding an agent greeting using a touch-based deskphone](#) on page 33.

Procedure

1. Press **Home**.
2. Select **Greetings**.
3. Press **New** or press the line button for any numbered blank greeting line.
4. Use the dialpad to enter a label that distinguishes this greeting from other greetings you may already have or will be adding. The Greeting Label can be up to 15 characters.
5. Press **Record**.
6. Speak your greeting for up to ten seconds into the headset or speaker, whichever device is active, and then press **Stop**.
7. Choose one of the following options:
 - To listen to the greeting, press **Play**.
 - To replace the greeting, press **Restart** and repeat the previous step.
 - To save the greeting, press **Done** and proceed to the next step.
 - To delete the greeting without saving the greeting, press **Cancel**.
8. If the default greeting type shown is Auto Answer with a *Match Criterion* of *All Calls* is correct, proceed to the step 12. To change the greeting type, press the line button for the line on which Type appears to display the **Greetings Type Selection** screen and proceed to the step 9.
9. Use the **Right Arrow** to cycle consecutively through the available types or the **Left Arrow** to cycle back through the types. Notice that the Match Criteria value below the type may change to correspond with the type currently displayed.
10. To change the match criteria for the greeting type, press the line button on which Match Criteria appears, then use the **Right Arrow** to cycle consecutively through the available criteria or the **Left Arrow** to cycle back through the types.
11. Press the line button on which **String to match** appears and then, press **More**. Use the dialpad to enter a number sequence that should be matched. For example, if you serve two customers with the telephone numbers 732-842-1111 and 732-842-2222, you can enter just the last four digits of those numbers as the string to match for their respective greetings. After entering the string, press **More** again to return to the **Type Selection** screen.

12. Press **Done**, and then press **Save** on the **Greetings Summary** screen.

Changing existing greetings

You can change an existing greeting in any or all of the following ways:

- You can edit the label of a greeting.
- You can re-record a greeting without changing any other part.
- You can edit the greeting Type, Match Criteria, or String to Match or both.
- You can delete the entire greeting and any associated data.

To change any part of a greeting, press **Home**, select **Greetings**, and then, select the greeting you want to change or remove.

For more information on the 9641G and 9621G models, see [Adding an agent greeting using a touch-based deskphone](#) on page 33 and [Changing the greeting type using a touch-based deskphone](#) on page 34.

For information on the 9608 and 9611G models, see [Adding an agent greeting using a button-based deskphone](#) on page 35.

You can then make a change as indicated in those procedures, and select **Save** to store the changes.

Chapter 5: About Call Center deskphone functionality

Using agent deskphones in the Call Center

Your duties as an agent involve understanding how the deskphone presents work-related information, including work modes and agent status, call information, and greetings.

About status line information and icons

What you see on the status line of the display screen depends on what you are doing at the time. Special icons indicate your status. At times, the telephone might display more than one icon.

Icon and text	Indicated Status
 for monochrome displays, or  for color displays, and the word Available	Signed in, in Available mode, and with no Aux Work pending.
 for monochrome displays, or  for color displays and the word Pending	Signed in, in Available mode, and with Aux Work or After Call Work pending.
 for monochrome displays, or  for color displays, and the words Aux Work	Signed in and in Aux Work mode.
 for monochrome displays, or  for color displays, and the words After Call	Signed in and in After Call Work mode.
 for monochrome displays, or  for color displays, and the words Logged Out	Signed out as an agent.

Icon and text	Indicated Status
 for monochrome displays, or  for the 9611G color display, or  for the 9621G and 9641G color displays.	The VU Stats feature is active.
 for monochrome displays or  for the 9611G color display or  for the 9621G and 9641G color displays.	Incoming calls are queued up and waiting.
 for monochrome displays, or  for the 9611G color display, or  for the 9621G and 9641G color displays.	Forced logout override is in effect.

For more information on other status indicators and icons for call center activities, see [Other call center action icons](#) on page 15.

About the agent information line

The Phone screen displays the Agent Information line directly below the Status line. This line provides information such as the company or group for which you are assigned to receive calls or caller information based on the number the caller dialed.

About agent work modes and states

When you are logged in as an agent, icons on the top two display lines and the Feature buttons show your current work mode and state. Agent work modes are Auto-In and Manual-In. An agent will usually have only one work mode which is either Auto-In or Manual-In as administered for the agent. Agent states are:

- Pending** You are in the Available state, but have pressed an Aux or ACW button. The Pending state reminds you that when the call is completed, you will be placed in the Aux or ACW state as applicable.
- Aux** You are placed in the Auxiliary state after agent login. You must change to Auto-In or Manual-In work mode to become available to receive incoming call center calls. You can change back to Aux to indicate you are not available to receive call center calls, for example, when you want to take a break. You must enter a

Reason Code when changing to Aux. This feature might be optional or compulsory depending on how your system is administered.

ACW	The deskphone may automatically put you into an After Call Work (ACW) state after you complete each call. If you were in Manual-In mode before the call, you must re-enter a Manual-In mode to accept another call. Switch to ACW to perform after call work, such as completing a call-related form.
Available	You have to move to Available state through Auto-In and Manual-in feature button when you want to handle calls.
Logged Out	This state is automatically assigned when the deskphone is administered as a call center phone but no agent sign-in has occurred. If you sign out as an agent but do not log off the deskphone, this status is also assigned.

To learn how to interpret upper line displays, see [About status line information and icons](#) on page 39 and [About the agent information line](#) on page 40. For information on the icons and button LEDs you might see while signed in as an agent, see [Call center work icons](#) on page 15 and [Status alerting](#) on page 17.

Changing agent work mode or status

- Press or touch the line or feature button assigned to the work mode or work state to which you want to change. Alternately, access the Features menu screen and select the desired work mode/state. The associated LED flashes to indicate you are transitioning into the work mode or state you chose, and then remains lit steadily when the selected work mode or status is active.

Chapter 6: Answering a Call

Procedure

To answer a call to the Call Center, you must be signed in as an agent. When you receive an incoming call on a touch-based deskphone, the incoming line is highlighted. When you receive an incoming call on a button-based deskphone, the green LED associated with the call flashes. The incoming call is usually selected automatically. However, if you are already on a call or if you receive more than one incoming call at a time, you may need to select the call you want to answer manually. Receiving incoming call center calls also depends on your current work mode and status, as described in [About agent work modes and states](#) on page 40.

Answering a call if you are signed in as an agent

About this task

Several variables such as your call center system configuration, call delivery mode, agent status, the number of greetings recorded determine how you answer a call.

For more information, see [About agent work modes and states](#) on page 40 and [About status line information and icons](#) on page 39.

In all cases, you are alerted to incoming calls by a special tone, the call appearance line button flashing green in case of button-based models, or the call appearance line itself highlighted in green for touch-based phones, and the ringing icon displayed on the incoming call's line.

* Note:

If you have a touch-based deskphone (9621G or 9641G), touch the desired softkey. If you have a button-based deskphone (9608 or 9611G), press the desired softkey. Alternate ways to using the **Answer** softkey to answer a call are to press the flashing line button for the incoming call (button-based models) or touching the call appearance line itself (for touch-based models). Your supervisor will advise you as to how incoming calls to the call center appear and provide any details not covered below.

Procedure

1. If you are in either Manual-In or Auto-In mode, you must always wait for an alerting signal such as a ring or tone. Then touch or press the **Answer** softkey. If Auto-Answer is enabled, the phone generates a zip tone to alert you, and then activates the call. In either case, the table below identifies how to answer the call depending on the type of greetings you recorded:

Recorded greeting	Response to the greeting
No greeting is recorded.	Start speaking to the caller.
A non-Manual greeting is recorded that matches the Type, Match Criterion, and String to Match for the incoming call.	Listen to the greeting, and then start speaking to the caller.
No non-Manual greeting is recorded that matches the Type, Match Criterion, and String to Match for the incoming call, but one Manual greeting has been recorded.	Touch or press the Greeting softkey, listen to the greeting, and then start speaking to the caller.
No non-Manual greeting is recorded that matches the Type, Match Criterion, and String to Match for the incoming call, but more than one Manual greeting has been recorded.	Touch or press the Greeting softkey, select the appropriate greeting to return to the Phone screen, listen to the greeting, and then start speaking to the caller.
No non-Manual greeting is recorded that matches the Type, Match Criterion, and String to Match for the incoming call, and no Manual greeting has been recorded.	Start speaking to the caller.

2. Press or touch **Release** to end a call, unless you are instructed otherwise by your supervisor.

Chapter 7: About Features

Your administrator might have set up your telephone so that it presents the Features as described in this chapter together on one screen with your call appearances. If yes, the features do not appear on a separate Features menu. However, for most agent deskphones, the Features menu gives you access to agent work modes, Speed Dial buttons, or advanced telephony features like Directory, Abbreviated Dial, and Call Forwarding. With the Directory, you can dial other users on your system by name. If your administrator sets up Abbreviated dialing, you can dial certain numbers by touching one number on the dialpad. You can use Send All Calls and Call Forward to have your incoming calls sent to other numbers. Note that if you have a touch-based phone, any features assigned to an attached Button Module will not display on the Features menu. If you have a button-based phone, features assigned to the Button Module will display on the Features menu. The particular features available to you depend on what your administrator has assigned to your phone.

In addition to the Features menu, your administrator may also place selected features on softkeys on the call appearance (Calls) screen. For touch-based phones, frequently used features can also be set up on the Quick Touch panel, if the panel is activated. For more information about what features and options are available for your extension, contact your system administrator.

Accessing the Features menu

Procedure

1. If you have a touch-based deskphone model such as 9621G or 9641G, from the Calls screen, touch the **Features** button in the upper right corner to view the Features menu. If you have a button-based deskphone model such as the 9608 or the 9611G, use the **Right** navigation arrow from the Phone screen to access the Features menu.

On a touch-based model, the ☐ icon next to a feature indicates the feature status; for a button-based model, the feature line button indicates its status. If shown in green on color phone models, the feature is active; if the icon is gray-shaded the feature is available but not active. For models with LEDs such as 9608 and, 9611G, the LED next to the feature name indicates if the feature is currently on or off. If the light is on, the feature is on.

2. Scroll down to see the features that have been administered for your extension.
-

Accessing features using a button module

About this task

If you have a button module attached to your agent deskphone, the button module might have feature buttons for call center features, additional call appearances, and standard deskphone features like Call Forwarding, Call Pickup, Go to Coverage, or Auto Callback.

 Note:

The 9621G deskphone does not support button modules.

Procedure

To use a feature button on a button module, press the button next to the feature you want to activate. Depending on your button module model, the LED associated with the feature you select lights up to indicate that the feature is active.

Index

A

Adding a greeting [33](#), [35](#)
Adjustable display [21](#)
Agent greeting [34](#)
 greeting type entry [34](#)
Agent greetings [31](#)
agent information [40](#)
Agent information line [40](#)
Agent sign in [23](#), [24](#)
agent sign off [25](#)
Agent sign off [23](#)
Agent work information [39](#)
Agent work mode/state [40](#)
Answering a call [43](#)
 if you are logged in as an agent [43](#)
Avaya menu [27](#)
 about [27](#)
Avaya Menu [19](#), [28](#)
 about [28](#)
 screen width [19](#)

B

Button module [46](#)
 accessing features using [46](#)

C

changing agent work mode or status [41](#)

D

Deskphone stand [21](#)
 about [21](#)

E

entering using touch-based phone [34](#)

F

Features [29](#), [45](#)
 about [45](#)
 accessing [29](#), [45](#)

G

Greeting Type [34](#)
Greeting types [32](#)
 explanation of [32](#)
Greetings [33](#), [35](#), [37](#)
 changing [37](#)
 setting up [33](#), [35](#)
Greetings, about [31](#)

H

Home screen [27](#)
 about [27](#)
Home Screen [27](#)
 about [27](#)

I

Icons [39](#)
Icons in telephone display [15](#)
 about [15](#)
Incoming Calls [43](#)
 answering [43](#)
Information line [40](#)

K

Keyboard [18](#)
 using [18](#)

L

LEDs [17](#)
 alerting [17](#)
legal notices [2](#)
Logging in to your telephone [23](#)
logging in to your telephone extension [23](#)
Logging out of your telephone extension [23](#)
Logout [27](#)

N

Navigation Arrows [11](#), [15](#)

page control	11 , 15
right	11 , 15
up & down	11 , 15
Network Information	27

O

on status line	39
On-screen keyboard	18
about	18
Options & Settings	20 , 27
setting the Quick Touch panel	20

Q

Quick Touch panel	20
configuring	20

S

screen width	19
setting	19

Scrolling and Navigation	11 , 15
about	11 , 15
Signing in	24
as agent	24
Status line information	39

T

Telephone display icons	15
about	15

U

Using deskphones in the call center	39
about	39

W

Work mode	40
Work state	40