



Administering Avaya Aura[®] Experience Portal

Release 7.1
Issue 1
May 2016

Notice

While reasonable efforts have been made to ensure that the information in this document is complete and accurate at the time of printing, Avaya assumes no liability for any errors. Avaya reserves the right to make changes and corrections to the information in this document without the obligation to notify any person or organization of such changes.

Documentation disclaimer

"Documentation" means information published in varying mediums which may include product information, operating instructions and performance specifications that are generally made available to users of products. Documentation does not include marketing materials. Avaya shall not be responsible for any modifications, additions, or deletions to the original published version of Documentation unless such modifications, additions, or deletions were performed by or on the express behalf of Avaya. End User agrees to indemnify and hold harmless Avaya, Avaya's agents, servants and employees against all claims, lawsuits, demands and judgments arising out of, or in connection with, subsequent modifications, additions or deletions to this documentation, to the extent made by End User.

Link disclaimer

Avaya is not responsible for the contents or reliability of any linked websites referenced within this site or Documentation provided by Avaya. Avaya is not responsible for the accuracy of any information, statement or content provided on these sites and does not necessarily endorse the products, services, or information described or offered within them. Avaya does not guarantee that these links will work all the time and has no control over the availability of the linked pages.

Warranty

Avaya provides a limited warranty on Avaya hardware and software. Refer to your sales agreement to establish the terms of the limited warranty. In addition, Avaya's standard warranty language, as well as information regarding support for this product while under warranty is available to Avaya customers and other parties through the Avaya Support website: <https://support.avaya.com/helpcenter/getGenericDetails?detailId=C20091120112456651010> under the link "Warranty & Product Lifecycle" or such successor site as designated by Avaya. Please note that if You acquired the product(s) from an authorized Avaya Channel Partner outside of the United States and Canada, the warranty is provided to You by said Avaya Channel Partner and not by Avaya.

Licenses

THE SOFTWARE LICENSE TERMS AVAILABLE ON THE AVAYA WEBSITE, <https://support.avaya.com/licenseinfo>, UNDER THE LINK "AVAYA SOFTWARE LICENSE TERMS (Avaya Products)" OR SUCH SUCCESSOR SITE AS DESIGNATED BY AVAYA, ARE APPLICABLE TO ANYONE WHO DOWNLOADS, USES AND/OR INSTALLS AVAYA SOFTWARE, PURCHASED FROM AVAYA INC., ANY AVAYA AFFILIATE, OR AN AVAYA CHANNEL PARTNER (AS APPLICABLE) UNDER A COMMERCIAL AGREEMENT WITH AVAYA OR AN AVAYA CHANNEL PARTNER. UNLESS OTHERWISE AGREED TO BY AVAYA IN WRITING, AVAYA DOES NOT EXTEND THIS LICENSE IF THE SOFTWARE WAS OBTAINED FROM ANYONE OTHER THAN AVAYA, AN AVAYA AFFILIATE OR AN AVAYA CHANNEL PARTNER; AVAYA RESERVES THE RIGHT TO TAKE LEGAL ACTION AGAINST YOU AND ANYONE ELSE USING OR SELLING THE SOFTWARE WITHOUT A LICENSE. BY INSTALLING, DOWNLOADING OR USING THE SOFTWARE, OR AUTHORIZING OTHERS TO DO SO, YOU, ON BEHALF OF YOURSELF AND THE ENTITY FOR WHOM YOU ARE INSTALLING, DOWNLOADING OR USING THE SOFTWARE (HEREINAFTER REFERRED TO INTERCHANGEABLY AS "YOU" AND "END USER"), AGREE TO THESE TERMS AND CONDITIONS AND CREATE A BINDING CONTRACT BETWEEN YOU AND AVAYA INC. OR THE APPLICABLE AVAYA AFFILIATE ("AVAYA").

Avaya grants You a license within the scope of the license types described below, with the exception of Heritage Nortel Software, for which the scope of the license is detailed below. Where the order

documentation does not expressly identify a license type, the applicable license will be a Designated System License. The applicable number of licenses and units of capacity for which the license is granted will be one (1), unless a different number of licenses or units of capacity is specified in the documentation or other materials available to You. "Software" means computer programs in object code, provided by Avaya or an Avaya Channel Partner, whether as stand-alone products, pre-installed on hardware products, and any upgrades, updates, patches, bug fixes, or modified versions thereto. "Designated Processor" means a single stand-alone computing device. "Server" means a Designated Processor that hosts a software application to be accessed by multiple users. "Instance" means a single copy of the Software executing at a particular time: (i) on one physical machine; or (ii) on one deployed software virtual machine ("VM") or similar deployment.

License types

Concurrent User License (CU). End User may install and use the Software on multiple Designated Processors or one or more Servers, so long as only the licensed number of Units are accessing and using the Software at any given time. A "Unit" means the unit on which Avaya, at its sole discretion, bases the pricing of its licenses and can be, without limitation, an agent, port or user, an e-mail or voice mail account in the name of a person or corporate function (e.g., webmaster or helpdesk), or a directory entry in the administrative database utilized by the Software that permits one user to interface with the Software. Units may be linked to a specific, identified Server or an Instance of the Software.

Shrinkwrap License (SR). You may install and use the Software in accordance with the terms and conditions of the applicable license agreements, such as "shrinkwrap" or "clickthrough" license accompanying or applicable to the Software ("Shrinkwrap License").

Copyright

Except where expressly stated otherwise, no use should be made of materials on this site, the Documentation, Software, Hosted Service, or hardware provided by Avaya. All content on this site, the documentation, Hosted Service, and the product provided by Avaya including the selection, arrangement and design of the content is owned either by Avaya or its licensors and is protected by copyright and other intellectual property laws including the sui generis rights relating to the protection of databases. You may not modify, copy, reproduce, republish, upload, post, transmit or distribute in any way any content, in whole or in part, including any code and software unless expressly authorized by Avaya. Unauthorized reproduction, transmission, dissemination, storage, and or use without the express written consent of Avaya can be a criminal, as well as a civil offense under the applicable law.

Virtualization

The following applies if the product is deployed on a virtual machine. Each product has its own ordering code and license types. Note that each Instance of a product must be separately licensed and ordered. For example, if the end user customer or Avaya Channel Partner would like to install two Instances of the same type of products, then two products of that type must be ordered.

Third Party Components

"Third Party Components" mean certain software programs or portions thereof included in the Software or Hosted Service may contain software (including open source software) distributed under third party agreements ("Third Party Components"), which contain terms regarding the rights to use certain portions of the Software ("Third Party Terms"). As required, information regarding distributed Linux OS source code (for those products that have distributed Linux OS source code) and identifying the copyright holders of the Third Party Components and the Third Party Terms that apply is available in the products, Documentation or on Avaya's website at: <https://support.avaya.com/Copyright> or such successor site as designated by Avaya. The open source software license terms provided as Third Party Terms are consistent with the license rights granted in these Software License Terms, and may contain additional rights benefiting You, such as modification and distribution of the open source software. The Third Party Terms shall take precedence over these Software License Terms, solely with respect to the applicable Third Party Components to the extent that these Software License Terms impose greater restrictions on You than the applicable Third Party Terms.

Preventing Toll Fraud

"Toll Fraud" is the unauthorized use of your telecommunications system by an unauthorized party (for example, a person who is not a corporate employee, agent, subcontractor, or is not working on your company's behalf). Be aware that there can be a risk of Toll Fraud associated with your system and that, if Toll Fraud occurs, it can result in substantial additional charges for your telecommunications services.

Avaya Toll Fraud intervention

If You suspect that You are being victimized by Toll Fraud and You need technical assistance or support, call Technical Service Center Toll Fraud Intervention Hotline at +1-800-643-2353 for the United States and Canada. For additional support telephone numbers, see the Avaya Support website: <https://support.avaya.com> or such successor site as designated by Avaya.

Trademarks

Avaya, the Avaya logo, Avaya Aura® Experience Portal, Avaya Aura® Communication Manager, and Avaya Aura® Orchestration Designer are either registered trademarks or trademarks of Avaya Inc. in the United States of America and/or other jurisdictions.

All non-Avaya trademarks are the property of their respective owners. Linux® is the registered trademark of Linus Torvalds in the U.S. and other countries.

Downloading Documentation

For the most current versions of Documentation, see the Avaya Support website: <https://support.avaya.com>, or such successor site as designated by Avaya.

Contact Avaya Support

See the Avaya Support website: <https://support.avaya.com> for product or Hosted Service notices and articles, or to report a problem with your Avaya product or Hosted Service. For a list of support telephone numbers and contact addresses, go to the Avaya Support website: <https://support.avaya.com> (or such successor site as designated by Avaya), scroll to the bottom of the page, and select Contact Avaya Support.

Contents

Chapter 1: Introduction	17
Purpose	17
Chapter 2: User management	18
Users in Avaya Aura® Experience Portal	18
Roles-based access in Experience Portal	18
User roles	18
Password administration	20
Logging in to the Experience Portal Web interface	20
Changing your account password	21
Setting global login parameters	22
Unlocking a locked user account	22
Viewing existing user accounts	22
Adding user accounts	23
Changing user accounts	23
Deleting EPM user accounts	24
Using a corporate directory to specify Experience Portal users	24
Users page field descriptions	25
Add User page field descriptions	27
Change User page field descriptions	29
Login Options page field descriptions	30
OS User Settings page field descriptions	33
View OS User Settings page field descriptions	33
Roles page field descriptions	34
Add New Role page field descriptions	35
Adding a new user role	36
Changing a user role	37
Deleting a custom user role	38
Chapter 3: System configuration	39
Licenses and ports	39
Avaya Aura® Experience Portal licenses	39
Viewing your licenses	40
Configuring the connection to the Avaya license server	40
Updating license information manually	41
Licensing page field descriptions	41
Allocations page field descriptions	44
License Server URL page field descriptions	45
Avaya Aura Experience Portal License Settings page field descriptions	46
Viewing telephony port distribution	47
Telephony port states	48

Port Distribution page field descriptions.....	48
Port Distribution Report page field descriptions.....	49
Port Information window field descriptions.....	51
VoIP connections.....	53
H.323 connections in Experience Portal.....	53
SIP connections in Experience Portal.....	62
Comparison of features supported on H.323 and SIP.....	80
VoIP in Experience Portal.....	82
Directory details of the EPM system components.....	91
Determining the installation history on an Experience Portal server.....	92
Configuring the PostgreSQL database user accounts.....	93
Importing a Primary EPM server security certificate.....	96
Importing an Auxiliary EPM server security certificate.....	99
Importing a MPP server security certificate.....	101
Importing a Single server security certificate.....	103
Generating a new Primary EPM server security certificate.....	106
Generating a new Auxiliary EPM server security certificate.....	109
Generating a new MPP server security certificate.....	111
Generating a new Single server security certificate.....	113
Third-party signed security certificates.....	115
Importing a Primary EPM Third-Party Signed Security Certificate.....	115
Importing an Auxiliary EPM Third-Party Signed Security Certificate.....	118
Importing a MPP Third-Party Signed Security Certificate.....	120
Importing a Single server Third-Party Signed Security Certificate.....	123
Chapter 4: Organization level access.....	126
Organization level access in Avaya Aura® Experience Portal.....	126
Organization level roles.....	127
Configuring organization level access in Experience Portal.....	128
Enabling organization level access in Experience Portal.....	128
Disabling organization level access in Experience Portal.....	129
Organizations page field descriptions.....	130
Chapter 5: Zoning Topology.....	132
Overview.....	132
Failover within a zone.....	134
Real-time management	134
Licenses.....	134
Zone filters.....	136
Restrictions on moving resources between zones.....	136
Adding a zone.....	137
Changing the configuration of a zone.....	138
Deleting a zone.....	138
Filtering a zone.....	138
Viewing the details of a zone.....	139

Chapter 6: Email management	140
Email overview.....	140
Email typical flow.....	141
Email processors.....	142
Email processor states.....	143
Adding an email processor.....	143
Changing the configuration of an email processor.....	144
Deleting an email processor.....	145
Email connections.....	145
Adding an email connection.....	145
Changing the configuration of an email connection.....	147
Deleting an email connection.....	148
Adding an email application to Experience Portal.....	149
Changing the settings of an email application.....	149
Deleting an email application.....	149
Configuring system parameters for email browser settings.....	150
Configuring system parameters for email settings.....	150
Multimedia Tomcat server.....	151
Email reporting filters.....	151
Chapter 7: SMS management	153
SMS overview.....	153
SMS typical flow.....	154
SMS Processors.....	155
SMS processor states.....	156
Adding an SMS processor.....	156
Changing the configuration of an SMS processor.....	157
Deleting an SMS processor.....	158
Adding an SMS application to Experience Portal.....	158
Changing the settings of an SMS application.....	158
Deleting an SMS application.....	159
Configuring HTTP and SMPP connections.....	159
Adding an HTTP connection.....	159
Changing the configuration of an HTTP connection.....	160
Deleting an HTTP connection.....	161
Adding an SMPP connection.....	161
Changing the configuration of an SMPP connection.....	162
Testing SMPP connections.....	163
Deleting an SMPP connection.....	164
SMS Browser.....	164
Configuring system parameters for SMS browser settings.....	165
Configuring system parameters for SMS settings.....	166
SMS web services.....	166
Reporting filters for SMS.....	167

SMS delivery receipt flow sequence.....	167
SMSC success and failure responses.....	168
Chapter 8: HTML management.....	169
HTML overview.....	169
HTML typical flow.....	169
Data collection.....	170
Adding an HTML application to Experience Portal.....	170
Changing the settings of an HTML application.....	171
Deleting an HTML application.....	171
Configuring HTML Redirector.....	171
Chapter 9: Configuring System Manager Single Sign-On.....	173
Prerequisites.....	173
Configuring the EPM System Manager Settings page.....	173
System Manager Settings page field descriptions.....	174
Creating a System Manager user.....	176
Items created on System Manager after enabling Single Sign-on	177
Experience Portal roles and permissions assignment.....	178
Single Sign-on.....	178
Reconfiguring Single Sign-On following a System Manager upgrade.....	179
System Manager Single Sign-On limitations in Experience Portal Release 7.1	180
Chapter 10: Server and database administration.....	182
EPM server administration.....	182
Changing EPM server settings.....	182
Configuring an auxiliary EPM server.....	182
Changing the configuration information for a EPM server.....	184
Reconnecting the primary and auxiliary EPM servers.....	184
Deleting the auxiliary EPM server.....	185
Stopping the vpms service.....	185
Associating Engagement Development Platform with an Experience Portal system.....	186
Configuring Conversation Repository.....	186
Moving the Avaya Aura Experience Portal software.....	187
Move the Experience Portal software to a different server machine.....	187
Move the EPM software to a different server machine.....	187
Moving an MPP to a different dedicated server.....	189
Move a single-server Experience Portal system to a different server.....	190
Packing MPP logs and transcriptions in a TAR file.....	191
Packing MPP logs and transcriptions using getmpplogs.sh.....	192
Restoring packed MPP log files.....	194
Diagnostics page field descriptions.....	196
Pack Files Options page field descriptions.....	197
Port Distribution Report page field descriptions.....	197
Changing a server hostname or IP address.....	199
Hostname or IP address changes for Experience Portal servers.....	199

Changing the hostname or IP address on a dedicated primary EPM server.....	200
Reconnecting an existing MPP server with the EPM server.....	201
Changing the hostname or IP address for a dedicated MPP server.....	202
Changing the hostname or IP address on the auxiliary EPM server.....	203
Changing the hostname or IP address for the Experience Portal single server system.....	205
Local database maintenance.....	207
System Backup.....	207
Database Restore utility.....	217
Purging report data from a local Experience Portal database.....	221
External database configuration.....	222
Shared external database configuration for multiple Experience Portal systems.....	222
External database requirements.....	223
Creating the required tables in the external database.....	223
Connecting the Experience Portal system to a shared external database.....	225
Disconnecting the Experience Portal system from a shared external database.....	226
Purging Experience Portal report data from an external database.....	227
EPM Servers page field descriptions.....	228
EPM Settings page field descriptions.....	230
Avaya Services information.....	233
Avaya Services MPPmap.data file.....	233
Maintaining the server IP addresses in the MPPmap.data file.....	233
Using the MPPmap.sh script.....	234
Logging in to an MPP manually through the MPP map file.....	235
Viewing the AF ID for the Experience Portal system.....	236
Chapter 11: SNMP agents and traps.....	237
SNMP Agents and Traps.....	237
Configuring Avaya Aura® Experience Portal as an SNMP agent.....	238
Viewing existing SNMP traps.....	238
Adding an SNMP trap.....	238
Changing an SNMP trap.....	239
Disabling SNMP traps.....	239
Testing SNMP traps.....	239
Deleting SNMP traps.....	240
Configuring IBM Tivoli or HP OpenView with Experience Portal.....	240
SNMP page field descriptions.....	240
SNMP Agent Settings page field descriptions.....	242
Add SNMP Trap Configuration page field descriptions.....	244
Change SNMP Trap Configuration page field descriptions.....	246
View SNMP Device Notification Settings page field descriptions.....	248
Chapter 12: Media Processing Platforms.....	251
Media Processing Platform server overview.....	251
System Manager component.....	252
The Web services component.....	253

The Session Manager component.....	254
The Avaya Voice Browser component.....	254
The CCXML Browser component.....	255
Speech proxy component.....	255
The Telephony component.....	255
Setting the global grace period and trace level parameters.....	256
Viewing all MPP servers.....	257
Viewing details for a specific MPP.....	257
Adding an MPP.....	258
Changing an MPP.....	258
MPP server capacity.....	259
MPP operational modes.....	260
Changing the operational mode of an MPP.....	260
MPP operational states.....	261
Checking the operational state for one or more MPPs.....	262
Changing the operational state for one or more MPPs.....	263
Setting the license reallocation time.....	264
MPP processes.....	265
Software Upgrade.....	266
Software Upgrade overview.....	266
Software Upgrade page field descriptions.....	266
Upgrading all MPP servers.....	270
Upgrading an MPP server.....	271
Starting all MPP servers.....	272
Starting an MPP server.....	273
Restarting one or more MPP servers.....	273
Setting the restart options for an MPP.....	274
Viewing MPP configuration history.....	274
Configuring Experience Portal to use the Test operational mode.....	275
Using the Test operational mode.....	276
Reestablishing the link between the EPM and an MPP.....	277
Deleting MPP servers.....	278
MPPServiceMenu.....	278
Logging in to the Media Server Service Menu.....	280
Using the Media Server Service Menu with a proxy server.....	280
Moving the MPP logs to a different location.....	281
Add MPP Server page field descriptions.....	283
Restart Automatically <MPP Name> page field descriptions.....	289
Change MPP Server page field descriptions.....	289
<MPP name> Details page field descriptions.....	294
MPP Manager page field descriptions.....	297
MPP Servers page field descriptions.....	301
MPP Settings page field descriptions.....	302

Restart <MPP Name> Today page field descriptions.....	308
Restart Schedule for <MPP Name> page field descriptions.....	308
<System name> Details tab on the System Monitor page field descriptions.....	309
Summary tab on the System Monitor page field descriptions.....	314
<Media server Name> Configuration History page field descriptions.....	316
Chapter 13: Speech applications in Avaya Aura® Experience Portal	317
Speech applications in Avaya Aura® Experience Portal.....	317
Call flow example.....	317
Deploying a speech application.....	319
Tomcat and WebSphere speech application deployment guidelines.....	319
Adding a speech application to Experience Portal.....	320
Changing speech application settings through Avaya Aura® Experience Portal.....	321
Viewing speech applications added to the Experience Portal system.....	321
Deleting speech applications from Avaya Aura® Experience Portal.....	321
Speech application priority.....	322
Changing speech application priority.....	322
Specifying the default application for inbound calls.....	323
Accessing VoiceXML and CCXML Log tag data through Experience Portal.....	323
Viewing application transcription data.....	324
Speech application design guidelines.....	325
Best practices for speech application design.....	325
Design for user experience.....	325
Design for potential problems.....	326
Design for application flow.....	327
Design for modularity.....	328
Design for application resources.....	328
CCXML and VoiceXML considerations.....	329
DTMF digits sending by a VoiceXML application.....	330
CCXML elements and attributes.....	331
VoiceXML elements and attributes.....	337
Call classification in speech applications.....	346
Call classification overview.....	346
Call classification analysis results.....	347
Call classification for inbound calls.....	348
Call classification for outbound calls.....	349
Call classification with the LaunchVXML method.....	350
SIP application support.....	352
User-to-User Interface (UI) data passed in SIP headers.....	352
SIP header support for CCXML and VoiceXML applications.....	355
Sample VoiceXML page logging SIP headers.....	358
Support for unknown headers.....	359
RFC 3261 SIP headers.....	359
Creating a custom header.....	360

Sample VoiceXML page setting SIP headers in a VoiceXML application.....	361
SIP UPDATE method.....	361
Experience Portal event handlers.....	362
Adding application event handlers and prompts.....	363
Setting the default application event handlers.....	364
Avaya Voice Browser overview.....	365
Setting Avaya Voice Browser options.....	365
AVB-specific VoiceXML events.....	366
Browser Settings page field descriptions.....	367
INET and cache Interface.....	371
Cache control mechanisms.....	372
ETag Directives.....	372
Component details of a request.....	372
Cache performance factors.....	376
Using a secure connection between the MPP and the application server.....	377
Chapter 14: Speech servers in Avaya Aura Experience Portal	378
Speech servers in Avaya Aura [®] Experience Portal.....	378
Mixed Protocols for configuring speech servers.....	378
ASR servers in Avaya Aura Experience Portal	379
ASR servers in Avaya Aura [®] Experience Portal.....	379
Viewing existing ASR servers.....	379
Adding ASR servers.....	380
Changing ASR servers.....	380
Deleting ASR servers.....	381
ASR tab on the Speech Servers page field descriptions.....	381
Add ASR Server page field descriptions.....	383
Change ASR Server page field descriptions.....	387
TTS servers in Avaya Aura Experience Portal	393
TTS servers in Experience Portal.....	393
Viewing existing TTS servers.....	394
Adding TTS servers.....	394
Changing TTS servers.....	394
Deleting TTS servers.....	395
Custom RealSpeak TTS dictionaries.....	396
TTS tab on the Speech Servers page field descriptions.....	400
Add TTS Server page field descriptions.....	401
Change TTS Server page field descriptions.....	406
Chapter 15: Application Server Manager.....	413
Application Server Manager in Avaya Aura [®] Experience Portal.....	413
Application Server page field descriptions.....	413
Starting Application server.....	414
Logging in to the Tomcat Manager web interface from Avaya Aura [®] Experience Portal	415
Chapter 16: Managed Applications in Avaya Aura Experience Portal	416

Managed applications in Avaya Aura® Experience Portal overview.....	416
Acquire and maintain licenses.....	417
Add managed application to EPM.....	417
Role-based access.....	418
Multi-tenancy.....	418
Logging and Alarming.....	418
Reports related to managed applications.....	419
Chapter 17: Intelligent Customer Routing (ICR) functionality in Avaya Aura Experience Portal	420
Intelligent Customer Routing overview.....	420
Acquire and maintain licenses.....	421
Configure ICR in EPM.....	421
Role-based access.....	422
Multi-tenancy.....	422
Database Backup and Restore.....	422
Logging and Alarming.....	423
Reports related to ICR.....	423
Chapter 18: Integrated Voice and Video Response	424
Chapter 19: Avaya Aura Experience Portal system events	425
Viewing Avaya Aura® Experience Portal system status.....	425
Summary tab on the System Monitor page field descriptions.....	425
<System name> Details tab on the System Monitor page field descriptions.....	427
Events and alarms.....	432
Events and alarms.....	432
Event and alarm categories.....	433
Event severities.....	435
Alarm severities.....	435
Alarm statuses.....	435
Resource thresholds for events and alarms.....	436
Setting log data retention periods.....	437
Creating an event report.....	438
Creating an alarm report.....	438
Viewing alarms by alarm category.....	439
Changing the status of an alarm.....	439
Viewing the status changes made to an alarm.....	440
Alarm Manager page field descriptions.....	440
Alarm Report page field descriptions.....	445
Trace Viewer.....	446
MPP Traces tab on Trace Viewer page field descriptions.....	446
MPP Trace Report page field descriptions.....	451
EPM Traces tab on Trace Viewer page field descriptions.....	451
EPM Trace Report page field descriptions.....	454
Log Viewer page field descriptions.....	454

Log Report page field descriptions.....	457
<System name> Details tab on the System Monitor page field descriptions.....	458
Alarm/Log Options page field descriptions.....	463
Alarm History window field descriptions.....	464
Creating an Audit Log report.....	465
Audit Log Viewer page field descriptions.....	466
Audit Log Report page field descriptions.....	468
Chapter 20: Reports	469
Configuring report data settings.....	469
Printing reports.....	470
Exporting reports.....	470
Report generation flow diagram.....	470
Application activity reports.....	471
Creating an Application Summary report.....	472
Creating an Application Detail report.....	472
Call activity reports.....	473
Contact activity reports.....	473
Creating a Contact Detail report.....	474
Creating a Contact Summary report.....	474
Creating a Session Detail report.....	475
Creating a Session Summary report.....	476
Viewing application transcription data.....	476
Show/Hide the Extended Exit Info #3 to Info #10 filters/columns in reports.....	477
Creating a Performance report.....	479
Advanced reporting in Experience Portal.....	479
Data Export report.....	480
Data Export reports.....	480
Creating a Data Export report.....	481
Generating Custom reports using third-party software.....	481
Generating Custom reports using third-party software.....	481
Custom application activity reports.....	482
Custom Contact Detail report.....	484
Custom Session Detail report.....	488
VPApplication table.....	493
Custom VPPerformance Reports.....	494
VPMpps table.....	495
VPSystems table.....	496
VPUCIDMap table.....	498
Generating Custom reports using Experience Portal Manager	498
Custom Reports using EPM.....	498
Generating a Custom report using EPM.....	499
Trending By report.....	500
Scheduled reports.....	501

Scheduled Reports.....	501
Scheduling a Report.....	501
SQL queries for the EPM reports.....	502
Chapter 21: Security.....	505
Enabling password protection for Single User Mode on Avaya Enterprise Linux.....	505
Disabling MPP core files.....	506
Chapter 22: Experience Portal Manager main menu customizations.....	507
EPM main menu customizations.....	507
The EPM main menu configuration files.....	507
Add a new menu group and items.....	508
Defining a new menu group and its items.....	509
Defining labels for the new menu group and its items.....	511
Setting user access permissions for the new menu group and its items.....	511
Defining labels for the features in the new menu group and its items.....	513
Add menu items to an existing menu group.....	515
Defining new menu items under an existing group.....	515
Defining a label for the new menu item.....	517
Setting user access permissions for the new menu items.....	518
Defining labels for features in the new menu item.....	519
Defining a unique extensions directory.....	520
Chapter 23: The Application Logging web service.....	522
The Application Logging web service for third-party speech applications.....	522
Best practices.....	522
Application Logging web service flow diagram.....	523
Configuring the Application Logging web service.....	524
Application Logging web service methods.....	525
logFailed method.....	525
reportBatch method for application logging.....	526
reportBatch method for call flow data.....	528
logApplicationEventAlarm method for application Logging / Alarming.....	529
Sample Application Logging web service WSDL file.....	531
Chapter 24: The Application Interface web service.....	534
The Application Interface web service.....	534
Best practices.....	535
Application Interface web service flow diagram.....	535
Configuring the Application Interface web service.....	536
Application Interface web service methods.....	537
GetStatus method.....	537
GetStatusEx method.....	538
LaunchCCXML method.....	540
Returning the status of a LaunchCCXML request.....	543
CCXML session properties.....	544
LaunchEmail method.....	545

LaunchSMS method.....	546
LaunchHTML method.....	548
LaunchVXML method.....	549
Call classification with the LaunchVXML method.....	551
VoiceXML session properties.....	553
QueryResources method.....	555
SendCCXMLEvent method.....	555
SendEmail method.....	556
SendSMS method.....	557
Additional parameters in the LaunchEmail and SendEmail methods.....	558
Additional parameters in the LaunchSMS and SendSMS methods.....	559
Return Values.....	560
Sample Application Interface web service WSDL file.....	562
Chapter 25: Managing external messages	588
External messages overview.....	588
Receiving an external message asynchronously.....	589
Receiving external message synchronously.....	590
Sending messages from a voice application.....	591
Chapter 26: The Management Interface web service	595
Overview.....	595
Authentication and Authorization.....	595
Management web services WSDL.....	596
Best Practices.....	596
Management Interface web service flow diagram.....	597
Configuring Management Interface web service.....	597
Management Interface web service method objects.....	598
Field.....	598
Field array.....	599
Status.....	599
Management Interface web service methods.....	599
getZoneNames method.....	600
getZoneInfo method.....	600
getApplicationNames method.....	600
getApplicationInfo method.....	601
setApplicationInfo method.....	601
addApplicationInfo method.....	602
deleteApplicationInfo method.....	602
getAppConfigurableVars method.....	603
setAppConfigurableVars method.....	603
Exception codes.....	604
FileUpload Servlet Interface.....	605
FileUpload method.....	606
Management Interface web service client.....	606

Management Interface web service client examples..... 607

Chapter 27: Resources..... 609

Documentation..... 609

 Finding documents on the Avaya Support website..... 610

Training..... 611

Viewing Avaya Mentor videos..... 611

Support..... 612

Chapter 1: Introduction

Purpose

This document provides general information about administering and configuring specific Avaya Aura® Experience Portal functions and features using a web-based interface.

This document is intended for anyone who is involved with configuring and administering the functions and features of Avaya Aura® Experience Portal at a customer site. The audience includes and is not limited to system administrators, implementation engineers, business partners, and customers.

Chapter 2: User management

Users in Avaya Aura[®] Experience Portal

In Avaya Aura[®] Experience Portal, users are people authorized to access the:

- Experience Portal Manager (EPM) web interface, which enables users to perform administrative, configuration, and maintenance tasks.
- Media Server Service Menu web interface, which helps administrators troubleshoot problems on a Media Processing Platform (MPP).

Both web interfaces require a unique user name and password created by an Experience Portal administrator. You can also create an unlimited number of accounts and ensure that the passwords they use are secure.

Roles-based access in Experience Portal

Experience Portal provides role-based access to the EPM pages. With the role based access, you can perform only those actions for which you have access permissions. The options for performing other actions are either not displayed or disabled on the EPM pages for that particular feature. For example, if you have the View Only permission on the Users EPM page, you cannot add, change, or delete a user. To gain access to these pages, you must obtain a user account with a different user role.

These roles are default EP roles, but you can create a custom role for any particular purpose.

User roles

Experience Portal provides role based access to the EPM pages. The user roles determine which pages the user can see and what actions the user can perform on those pages. The roles are:

Role	Description
Administration	User accounts with Administration access can perform all system-related functions through the EPM, such as managing MPPs, VoIP connections, and speech applications. The only things Administrators <i>cannot</i> do are managing user accounts and viewing the audit logs. Administrators also have some other limitations. For example, administrators do not have Privacy Manager permissions. Because users with the Administration role have such a wide range of access and privilege, you must strictly limit the use of these accounts.
Auditor	User accounts with Auditor access can generate the Audit Log report and set the retention period for records in the audit log.
Maintenance	User accounts with Maintenance access can view system information, but they cannot make any changes to the Experience Portal system.
Operations	User accounts with Operations access can control the operation of MPPs, including stopping, starting, and rebooting those systems. Operators can also change the status of alarms to denote that they have been acknowledged or can be retired. Operators <i>cannot</i> configure an MPP. They can only control the ones that an Administrator has already added to the Experience Portal system.
Privacy Manager	User accounts with Privacy Manager role can update: • All the Transcription related configuration under Reporting Parameters group for an application. • Privacy Settings for traces. User accounts with Privacy Manager role can access the Privacy Settings menu in EPM > System Configuration > EPM Server.
Reporting	User accounts with Reporting access can generate the standard reports, add, edit, or delete the custom and scheduled reports. They can also change the schedules for the scheduled reports. User accounts with Reporting access cannot make any changes to the other features in the Experience Portal system.
User Manager	User accounts with User Manager access can add and change Experience Portal user accounts. User Managers can create new roles with specific access permissions. They can change or delete the defined roles, and assign these roles to the user accounts. They can also configure an LDAP connection between a corporate directory and the EPM so that EPM users no longer need to be defined locally on the EPM. Users with just the User Manager role can only see the User Management section of the main EPM menu.
Web Services	User accounts with Web Services access can use Application Interface Web Service to launch any application configured on the Experience Portal system. They can also use Application Logging Web Service to save application and call flow data information for any application.

 Note:

Additional roles may be available if you have installed a managed application on Experience Portal. For more information on managed application based roles, see the documentation delivered with the managed application.

Password administration

Passwords are keys to the Experience Portal system. They must be protected and *strong*. A strong password is one that is not easily guessed and is not listed in any dictionary. Protected and strong passwords are especially important for root and administrative-level passwords since they have no access restrictions. Passwords created during Experience Portal installation are checked for minimal characteristics as follows:

- Passwords must contain at least one alphabetic character and one digit.
- Passwords are case-sensitive and should contain a combination of upper and lower case letters.
- A password cannot be the same as its associated user name.
- Although you can determine the minimum password length, you must not use fewer than eight characters.

After installation, when you use the EPM to create additional user accounts, the minimal characteristics for passwords are enforced. However, administrators can customize the minimum password length. Password length can be between 4 to 256 characters. You should set this value to at least eight characters.

For security reasons, you should change your default password when you log on to Experience Portal for the first time. Password reset is not required on first logon in the following scenarios:

- If the password longevity is not checked at the time of adding a user.
- If the login options password longevity is set to 0.

To ensure that strong passwords are created, you should use a nonsensical combination of letters and digits when creating passwords.

Logging in to the Experience Portal Web interface

The Experience Portal Manager (EPM) Web interface is the main interface to the Experience Portal system.

About this task

You must log in to the EPM Web interface on the primary EPM server before you can perform any Experience Portal administrative tasks.

Procedure

1. Open an Internet Explorer browser and enter the URL for your Experience Portal system.

The default URL is: `https://<EPM-server>/VoicePortal`, where `<EPM-server>` is the hostname or IP address of the system where the primary EPM software is installed.

 Note:

Transport Layer Security (TLS) must be enabled in your IE browser. For more information on configuring browsers to use TLS security, see *Implementing Avaya Aura® Experience Portal on multiple servers*.

2. On the login page, enter your EPM user name in the **User Name** field.

The user name must match an existing Experience Portal EPM account name exactly, including case.

If organization level access is enabled in the Experience Portal system and you are assigned to an organization, prefix your user name with the organization name and a forward slash character.

3. Click **Submit**.

4. In the **Password** field, enter your login password.

The password must match the password assigned to the specified user name exactly, including case.

5. Click **Logon**.

6. If you are forced to change the password on the first log in, or your password expires or you want to change or reset the password, click the **Change Password** link, specify the **User Name**, **Old Password**, **New Password** and re-enter the new password in the **Verify Password** field.

7. Click **Submit**.

Changing your account password

Procedure

1. In Internet Explorer, enter the URL for your Experience Portal system.

The URL is `https://<EPM-server>/VoicePortal` where `<EPM-server>` is the name of the system where the EPM software is installed.

2. On the Login page, click the **Change Password** link at the bottom of the page.
3. On the **Change Password** page, enter your user name in the **User Name** field.
4. Enter your old password in the **Old Password** field.
5. Enter your new password in the **New Password** field.

The password is case-sensitive and must have at least the number of characters defined in the **Minimum Password Length** field.

6. Reenter your new password in the **Verify Password** field.
7. To change your password, click **Submit**.

Setting global login parameters

Procedure

1. Log on to the EPM Web interface using an account with the User Manager user role.
2. From the EPM main menu, select **User Management > Login Options**.
3. On the Login Options page, set the global login parameters in the **User Login Options** group.
4. If you changed one or more parameters, click **Save**.

Unlocking a locked user account

About this task

If a user has attempted to log in several times unsuccessfully, that user might be locked out for a certain length of time based on the settings for the global login parameters **Failed Login Lockout Threshold** and **Failed Login Lockout Duration**. User Managers can unlock an account manually before the **Failed Login Lockout Duration** expires.

Procedure

1. Log on to the EPM Web interface using an account with the User Manager user role.
2. From the EPM main menu, select **User Management > Users**.
3. On the Users page, click the **Unlock** link in the **Locked** column for each user account you want to unlock.

Viewing existing user accounts

Procedure

1. Log on to the EPM Web interface using an account with the Administration, Operations, Maintenance, or User Manager user role.
2. From the EPM main menu, select **User Management > Users**.

If you are not logged in with the User Manager user role, the EPM displays the Users page in view only mode.

Adding user accounts

Procedure

1. Log on to the EPM Web interface using an account with the User Manager user role.
2. From the EPM main menu, select **User Management > Users**.
3. On the Users page, click **Add** in the User accounts section.
4. On the Add User page, enter the appropriate information and click **Save**.

 Note:

If you select the Administration user role, this EPM account can also access the Media Server Service Menu on each MPP server.

Changing user accounts

About this task

 Note:

You cannot change the existing user name.

Procedure

1. Log on to the EPM Web interface using an account with the User Manager user role.
2. From the EPM main menu, select **User Management > Users**.
3. On the Users page, click the name of the account that you want to change in the **User Name** column.
4. On the Change User page, enter the appropriate information and click **Save**.

Deleting EPM user accounts

You can delete all EPM user accounts except for the user account that you used to log into the EPM, and if the Avaya Services is maintaining this system, the init account that was created when the Avaya Service accounts were configured.

About this task

 Note:

Ensure that the user account you want to delete is not the only user account with user manager role. Without a user manager account you cannot add or change user accounts in EPM and will need to reinstall Experience Portal in order to create a user manager account. If you have two user accounts and log in as the “non-admin” user, then you can delete the “admin” user.

Procedure

1. Log on to the EPM Web interface using an account with the User Manager user role.
2. From the EPM main menu, select **User Management > Users**.
3. On the Users page:
 - Select the check box to the left of the account's **User Name** for each user account that you want to delete.
 - Click the Selection check box in the header row of the table, which automatically selects all user accounts.

If you select the accounts of any users who are currently logged into the EPM, those users will continue to have access until their current sessions end. At that point, the users will be unable to log back into the EPM.

 Note:

An account that displays **Remote User** in the **Assigned Roles** column belongs to a user who has logged in using an authorized account in the corporate directory. If you delete this account, the EPM removes it from the table in this section, but it does *not* keep the user from logging back into the EPM. In order to do that, you need to change the corporate directory account access rules defined in the **LDAP Settings** group on the Login Options page.

4. Click **Delete**.

The EPM deletes all selected EPM user accounts *without* requesting confirmation.

Using a corporate directory to specify Experience Portal users

In addition to creating user accounts through the EPM, you can also establish a link between Experience Portal and a corporate directory using Lightweight Directory Access Protocol (LDAP).

Before you begin

Consult your corporate directory administrator to determine what LDAP settings you need to use to establish a connection to the corporate directory, and how your directory is structured so that you can enter the appropriate search filters and paths.

About this task

The first time a user in the directory logs into the EPM, Experience Portal verifies what permissions that user should have based on his or her directory settings and creates a temporary account for that user with the appropriate user roles.

Important:

If an account with the same user name exists on both the EPM and in the corporate directory, Experience Portal uses the permissions specified on the EPM account regardless of the directory settings.

Procedure

1. In your corporate directory, add an attribute to each record that specifies what Experience Portal permissions that user should have.

This attribute can specify the exact roles or be a custom group map name whose permissions you set within Experience Portal.

2. Log on to the EPM Web interface using an account with the User Manager user role.
3. From the EPM main menu, select **User Management > Users**.
4. On the Login Options page, enter the appropriate information in the fields in the **LDAP Settings** group.
5. Click **Save**.
6. Verify that the connection was properly established by logging into the EPM using one of the user names associated with an authorized Experience Portal group in the corporate directory.

Users page field descriptions

Use this page to add, view, or change the existing Experience Portal Manager (EPM) user accounts and global account settings. You can also delete the existing user accounts.

Column or Button	Description
Selection check box	Use this Selection check box to select which accounts you want to delete.
User Name	The unique identifier for this account. This name is case-sensitive and must be unique across all EPM user accounts.

Table continues...

Column or Button	Description
	 Note: You cannot change a user name once it is created.
Enable	The options are: • Yes: The user account is active and can be used to log into the EPM. • No: The user account is inactive and cannot be used to log into the EPM.  Note: The Enable option is available to the EPM Administrator user account that is added during the EP installation and is by default set to “Yes”.
Type	The type of the user. The options are: • EP (Password): The EP Web user. • LDAP: The LDAP user • OS: The Linux OS user. • SMGR: The System Manager user.
Assigned Roles/Features	The options are: • One or more of the Experience Portal user roles. This indicates a locally-defined EPM user account or LDAP or Linux OS user.  Note: For LDAP and Linux OS users, this field shows the roles that were assigned when the LDAP and Linux OS users login to the Experience Portal system successfully last time. • One or more of the Experience Portal Portal features. This indicates a System Manager user Single Sign-On to EPM.
Last Login	The options are: • Never: No one has ever logged in with this user name. • The most recent day, date, and time that a user logged in using that account. For the current user, this column displays the day, date, and time that the user logged in to the current session. If this field displays in red, then the inactivity timeout set in the Inactivity Lockout Threshold field has been exceeded. Hover the mouse over any red field to see the date on which the account was last locked or unlocked.
Failed Attempts	The number of failed login attempts for this user, if any. This number is reset to 0 after a successful login. If this number is greater than or equal to the value set in the Failed Login Lockout Threshold field, this number displays in red. Hover the mouse over any red value in this field to view the date and time of the last failed login attempt.

Table continues...

Column or Button	Description
Locked	This field displays (Unlock) if the user has: • Tried to log in unsuccessfully more times than allowed in the Failed Login Lockout Threshold field, and the lockout duration specified in the Failed Login Lockout Duration field is still in effect. • Not logged in within the time period allotted in the Inactivity Lockout Threshold field. Click this link to unlock the account.
Password Longevity (days)	The options are: • <The Number of Days Password Longevity is Enforced>: The Password Longevity option is enabled for this account. Password Longevity, configured in EPM > User Management > Login Options, specifies the number of days for which a given password is valid. After this amount of time has passed, the user is required to change the password.  Note: If a user has multiple roles assigned, and each role has a different password longevity in terms of days, the user is warned about the expiry of the password that expires the earliest. The default is 60 days. • Not Enforced: The password for this account is not enforced. • N/A: The Enforce Password Longevity option is not applicable for the user. The user can be local OS, or LDAP.
Add	Opens the Add User page.
Delete	Deletes the user accounts whose Selection check box has been checked.  Note: If you delete a remote user account, the EPM removes it from the table in this section, but it does <i>not</i> keep the user from logging back into the EPM. In order to do that, you need to change the corporate directory account access rules defined in the LDAP Settings group.  Note: Ensure that the user account you want to delete is not the only user account with user manager role. Without a user manager account you cannot add or change Experience Portal user accounts and will need to reinstall Experience Portal in order to create a user manager account.

Add User page field descriptions

Use this page to create a user account that can access the Experience Portal Manager (EPM) web interface.

Field	Description
Organization	The organization associated with the user you want to add.  Note: This field is displayed only if organization level access is enabled in the Experience Portal system and you have logged in as a user not assigned to any organization. For more information on organization level access see Organization level access in on page 126.
User Name	The unique identifier for this account. This name is case-sensitive and must be unique across all EPM user accounts. Enter from 1 to 95 characters. The user name must not contain <code>;</code>, <code>/</code>, or <code>!</code> characters.  Note: • If you select an organization in the field above, the selected organization and forward slash character are automatically prefixed to the user name. If you do not select the organization name, this indicates that the user does not belong to any organization. For more information on organization level access see Organization level access in on page 126. • Once you save the user, this name cannot be changed.
Enable	The options are: • Yes: The user account is active and can be used to log into the EPM. • No: The user account is inactive and cannot be used to log into the EPM.  Note: The Enable option is available to the EPM Administrator user account that is added during the EP installation and is by default set to “Yes”.
Roles	Each user account can have one or more roles.
Password	The initial password for this account. The password is case-sensitive and must have at least the number of characters defined in the Minimum Password Length field. If you are changing the role for an existing account but do not want to change the password, leave this field and Verify Password field blank.  Important: The Experience Portal system forces the user to change the default password on first login only if you have configured the Password Longevity field in EPM > User Management > Login Options.
Verify Password	The initial password again for verification purposes.
Enforce Password Longevity	Enables the Password Longevity option for this account. Password Longevity, configured in <i>EPM > User Management > Login Options</i> , specifies the number of days for which a given password is valid. After this amount of time has passed,

Table continues...

Field	Description
	the user is required to change the password. If you do not select this option, the password for this account will not expire.  Note: This field does not have any effect if the Password Longevity is not set. If this field is not checked, password change option on first login will not be enforced.

Change User page field descriptions

Use this page to change an existing user account for the Experience Portal Manager (EPM) web interface.

Field	Description
User Name	The unique identifier for this account. This name is case-sensitive and must be unique across all EPM user accounts.  Note: This field cannot be changed.
Enable	The options are: • Yes: The user account is active and can be used to log into the EPM. • No: The user account is inactive and cannot be used to log into the EPM.  Note: The Enable option is available to the EPM Administrator user account that is added during the EP installation and is by default set to “Yes”.
Roles	Each user account can have one or more roles.
Created	The options are: • The date and time at which this user account was created. • N/A if the account creation time is not available.
Password	The password for this account. The password is case-sensitive and must have at least the number of characters defined in the Minimum Password Length field. If you are changing the role for an existing account but do not want to change the password, leave this field and Verify Password field blank.  Important: If you change the password, the Experience Portal system forces the user to change the password on login.

Table continues...

Field	Description
Verify Password	The password again for verification purposes.
Enforce Password Longevity	Enables the Password Longevity option for this account. Password Longevity, configured in EPM > User Management > Login Options, specifies the number of days for which a given password is valid. After this amount of time has passed, the user is required to change the password. If you do not select this option, the password for this account will not expire.  Note: This field does not have any effect if the Password Longevity is not set. If this field is not checked, password change option on first login will not be enforced.

Login Options page field descriptions

Use this page to configure security options for all user accounts.

To avoid defining the EPM users locally on the EPM, you can configure:

- An LDAP connection between a corporate directory and the EPM.
- OS user settings for authentication of local operating system users.
- System Manager Settings for Single Sign-On with System Manager.

You can choose to use any one or both of the above mentioned configurations.

User Login Options group

Field	Description
Failed Login Lockout Threshold	The number of attempts users get to successfully log in to the system. If they exceed this number of attempts, they are locked out of the system and cannot log in until the amount of time designated in the Failed Login Lockout Duration field has passed. The default is 3. Enter an integer between 0 and 100.  Note: To disable the account lockout feature, set this field to 0 (zero).
Failed Login Lockout Duration	The amount of time, in minutes, to lock out users who do not successfully log in within the number of attempts defined in the Failed Login Lockout Threshold field. If a user is locked out because of repeated unsuccessful login attempts, then that user cannot attempt to log in again until this amount of time has passed. The default is 10.

Table continues...

Field	Description
	The valid range is between 0 and 1440. • 0 - Do not lock. • -1 - Indefinite user lock out. The user remains locked until the administrator manually unlocks the user.
Failed Login Alarm Threshold	The number of attempts users get to successfully log in to the system before the system raises an alarm. This value is usually the same as the Failed Login Lockout Threshold. The default is 3. Enter an integer between 0 and 100.  Note: To disable these alarms, set this field to 0 (zero).
Inactivity Lockout Threshold	The number of days to wait until Experience Portal should consider the account inactive and lock it out of the system. The inactivity counter: • Is reset to 0 each time a user logs in. • Starts counting as soon as a new account is created. Therefore, you could have an account locked out for inactivity before the first login attempt is made. • Is reset to 0 if a user manager unlocks the account, either for inactivity or for exceeding the number of failed login attempts. The default is 0, which means that accounts are never locked out regardless of how much time passes between logins. Enter an integer between 0 and 365.  Note: This field is only used for local user accounts. Any user accounts created through a corporate directory do not expire.
Minimum Password Length	The minimum number of characters users must use in setting their passwords. The default is 8 characters. The length of the password must be between 4 characters and 256 characters.  Note: For security purposes, set this field to 8 or more characters.
Password Longevity	The number of days for which a given password is valid. After this amount of time has passed, the user is required to change the password. The default is 60. Enter an integer between 0 and 365, where 0 means that passwords never expire.
Password Expiration Warning	The maximum number of days before a user password expires when Experience Portal displays a message to warn the user that they need to change their password. Once this

Table continues...

Field	Description
	time limit has been reached, Experience Portal will display the warning message every time the user logs in until they have changed their password. The default is 10. Enter an integer between 0 and 30.  Note: This field is ignored if Password Longevity is set to 0.
Maximum Password changes in 24 Hours	The maximum password changes allowed within a 24 hour time period. The default is 3. Enter an integer between 0 and 24. The value 0 implies unlimited.  Note: The 24-hour period is the last 24 hours from the current time. If the number of times a user has updated his password exceeds the value specified in this field, then the user is restricted from changing the password.
Maximum Password History	Determines the number of unique new passwords that are associated with a user account before an old password can be reused. The default is 12. Enter an integer between 1 and 24.
Session Timeout (minutes)	The number of minutes a user's logged in session remains active. A logged-in user's session is timed-out if the inactivity time is greater than the timeout value. The timeout value can be changed. The default is 10 minutes. Enter an integer between 5 and 60.  Note: Once the session timeout is updated, you must restart Experience Portal Manager for the new session timeout value to take effect. You can restart the Experience Portal Manager Service using the <code>command service vpms restart</code> from the Linux command prompt
Failed Login Lockout Message	The system displays the message on the login page instead of the regular login error message. This field is optional and the maximum length is of 120 characters. The following special characters are not allowed in this field: • & • < • >
LDAP Settings	Opens the LDAP Settings page.

Table continues...

Field	Description
OS User Settings	Opens the OS User Settings page.
System Manager Settings	Opens the System Manager Settings page.

OS User Settings page field descriptions

Use this page to configure the parameters for OS User Settings, which enable EPM to access local Operating System user accounts.

Field	Description
Enable OS Authentication field	The options are: • Yes: OS authentication is enabled. • No: OS authentication is disabled.

Role Assignment Settings section

Field	Description
OS Group/User	The OS group name or the OS user name to associate with a given set of Avaya Aura[®] Experience Portal user roles. This column displays the names of any previously-defined group maps as well as a text field that lets you specify a new group map name. If you specify a new group name, use the Assigned Roles field to select the roles to associate with this map name.
Assigned Roles	Displays the roles associated with the existing group maps. You can also use the check boxes to select one or more user roles to associate with a new group map name.
add link	Associates a new group map name with the selected user roles.
del link	Deletes the group map name along with the associated user roles.

View OS User Settings page field descriptions

Use this page to view the parameters for OS User Settings, which enable EPM to access local Operating System user accounts.

Field	Description
Enable OS Authentication field	The options are: • Yes: OS authentication is enabled. • No: OS authentication is disabled.

Role Assignment Settings section

Field	Description
OS Group/User	The OS group name or the OS user name to associate with a given set of Avaya Aura® Experience Portal user roles. This column displays the names of any previously-defined group maps.
Assigned Roles	The roles associated with the existing group maps.

Roles page field descriptions

Use this page to view the existing Experience Portal Manager (EPM) user roles.

You can also use this page to add a new custom role and modify an existing custom role.

Field or Button	Description
Selection check box	Use this Selection check box to select which roles you want to delete.  Note: You cannot delete the System or Organization roles. You cannot delete Custom roles to which users are assigned.
Name	The unique identifier for the user role.  Note: You cannot change a role name once it is created.
Type	This field displays one of the following role types: • System: The system roles are the predefined roles. You cannot add, modify, or delete a system role. However, you can view the details of any system role. • System (Organizations) : The organization roles are system defined roles for the organization level access. For more information on organization level access, see Organization level access in Avaya Aura® Experience Portal on page 126 and Organization level roles on page 127 • Custom: The custom roles are the user defined roles. You can add a new custom role and modify an existing role.  Note: You cannot delete a custom-defined role that has a user assigned to it. Remove the role assignment from all users in order to proceed.

Table continues...

Field or Button	Description
	• Custom (Organizations) : For custom roles for organizations, the list of roles is restricted to only organization-level roles. The feature selection web page only allows selection of features which are limited to organization users. For example, since an organization user cannot start or stop a media server, this feature is not available when defining a custom role for an organization.
Assigned To	List of users who are assigned to the corresponding role in the Name field.
Password Longevity (days)	The number of days for which the given password is valid for the users assigned to the role. A user can have multiple roles that have values specified either to use custom password longevity or System password longevity. The smallest value of the two values is used to determine the user password longevity. By default, the System password longevity takes precedence if a role has not been configured custom password longevity.
 Pencil icon	Click this icon to change the password longevity.
show	Shows all users who are assigned to the corresponding roles.  Note: This field is displayed only if the total length of all the user names assigned to a particular role exceeds 115 characters.
hide	Shows only the first few users who are assigned to the corresponding roles.  Note: This field is displayed only if you click Show to view all the users assigned to the corresponding roles.
Add	Opens the Add New Role page for the creation of a new role.
Delete	Deletes the selected user roles. You can select roles using the check box next to the custom user roles.  Note: You can only delete custom roles to which users are not assigned. If you select multiple roles to delete, only the roles that are not assigned are deleted. A warning message is shown on the page to show which roles are not deleted. For more information about deleting a user role completely, see Deleting a custom user role on page 38.

Add New Role page field descriptions

Use this page to create a new Experience Portal Manager (EPM) user roles.

Field or Button	Description
Name	The unique identifier for the user role you want to create.  Note: You cannot create a new role with the same name as a system role.
Organization	The organization to which roles are assigned. Select Yes to enable the drop-down box with the list of organizations configured in the system. You can select the relevant organization from the list.
Password Longevity	The number of days for which the given password is valid for a role. The options are: • System: The password longevity is assigned to the system role. • Custom: The password longevity is assigned to the custom role. If you select Custom, you can configure the number of days for password longevity. If you select System, then the default range appears in the text box. The default range is 0, which means that the password never expires.
Start with Role	Existing system or custom user role names. On selecting a predefined system or custom role, the new role is created using the permissions defined for the selected role. You can modify the permissions for the new role using the Edit Role page.
Continue	Opens the Edit Role page. Use this page to modify the user role permissions.

Adding a new user role

About this task

 Note:

You cannot create and add a new system user role.

Procedure

1. Log on to the EPM Web interface using an account with the User Manager user role.
2. From the EPM main menu, select **User Management > Roles**.
3. On the Roles page, click **Add**.
4. On the Add New Role page, enter a name for the custom role that you want to add. The role name must be 1 to 256 alphanumeric characters in length.

 Note:

Once you save the role, the role name cannot be changed.

5. Select a role from the **Start with Role** list. The privileges assigned to the role that you select in this list are used as a base for creating a new user role.

6. Click **Continue**. The Edit Role page opens.

(Optional) Click the required role to give or remove permissions.

The status of user permissions is indicated as follows:

- **Red**: indicates that a user does not have permissions for the role
- **Green**: indicates that a user has permissions for the role
- **Yellow**: indicates that a user does not have permissions for a particular node under a parent node.

7. Click **Save**.

Changing a user role

About this task

 Note:

You cannot change the existing user role name.

Procedure

1. Log on to the EPM Web interface using an account with the User Manager user role.
2. From the EPM main menu, select **User Management > Roles**.
3. On the Roles page, click the name of the role that you want to change in the **Name** column.

 Note:

You cannot select the System roles for changing.

4. The Edit Role page is displayed with a hierarchical list of the features made available by the Experience Portal system.
5. On the Edit Role page, select or clear the check boxes associated with the required feature node, to assign privileges to access the various pages and functions of each feature.

 Note:

Nodes that are children of a particular feature are considered its dependents. Granting access to a child node automatically grants access to the parent features.

6. Click **Save**.

Deleting a custom user role

About this task

Important:

You cannot delete a custom-defined role that has a user assigned to it. Remove the role assignment from all users in order to proceed.

Procedure

1. Log on to the EPM Web interface using an account with the User Manager user role.
2. From the EPM main menu, select **User Management > Roles**.
3. On the Roles page:
 - Select the check box for the custom user role that you want to delete.
 - Click the Selection check box in the header row of the table, which automatically selects all user roles.
4. Click **Delete**.

If you select multiple roles to delete, EPM deletes only the roles that are not assigned. A warning message is shown on the page to show which roles are not deleted.

Chapter 3: System configuration

Licenses and ports

Avaya Aura® Experience Portal licenses

The Experience Portal Manager (EPM) contacts an Avaya WebLM server on a regular basis to determine the number of licenses that are authorized for your system. For security reasons, the license server must run WebLM 7.0 or later, and a valid Avaya Aura® Experience Portal Release 7 license must be installed on the license server. You must reinstall the license file while upgrading from a previous Experience Portal version that uses older WebLM versions.

After the EPM receives current information about authorized licenses, it allocates the available licenses among the servers in the system.

Experience Portal requires a license for:

Component	Description
Telephony ports	Each license authorizes you to use one port for telephony activities.  Note: To configure an authorized telephony port on the Experience Portal system, you must establish an H.323 or SIP connection.
Automatic Speech Recognition (ASR) connections	Each license authorizes you to use one connection, or port, for speech recognition activities. If you do not purchase any ASR licenses, you cannot configure ASR servers on your system. You need one ASR proxy license for each call that requires ASR resources. The license will not become available again until the call completes.
Text-to-Speech (TTS) connections	Each license authorizes you to use one connection, or port, for speech synthesis activities. If you did not purchase any TTS licenses, you cannot configure TTS servers on your system. You need one TTS proxy license while a call is using TTS resources. As soon as the call stops using TTS resources, the license becomes available to other calls.
Zones	You need these licenses for configuring zones in the system.
Email units	You need these licenses for configuring email resources (email processors and email connections)

Table continues...

Component	Description
	The licenses features for email units provides the ability to charge customers according to the capacity required.
SMS units	You need these licenses for configuring SMS resources (SMS processors and SMPP/HTTP connections). The licenses features for SMS units provides the ability to charge customers according to the capacity required.
HTML Units	The number represents the daily HTML processing capacity on your system. An HTML unit is required to handle an incoming HTML request.

Viewing your licenses

Procedure

1. Log on to the EPM Web interface using an account with the Administration, Operations, or Maintenance user role.
2. From the EPM main menu, select **Security > Licensing**.

The EPM displays the Licensing page if you are authorized to change the license information, or the View Licensing page otherwise.

Configuring the connection to the Avaya license server

Procedure

1. Log on to the EPM Web interface using an account with the Administration user role.
2. From the EPM main menu, select **Security > Licensing**.
3. Click **License Server URL** icon .
4. On the License Server Information page, enter the new URL in the **License Server URL** field.

The URL must be in the format `https://<WebLM-machine>:port/WebLM/LicenseServer`, where `<WebLM-machine>` is the hostname or IP address of the WebLM server and `:port` consists of a colon followed by the port number for the WebLM server. If WebLM uses the default configuration, specify `:52233`. If a customer is using an older version of WebLM, then the default port number is `8443`.

5. Click **Verify** to ensure that the URL is correct.
6. If your system can connect to the Avaya license server, click **Apply** then click **OK** to confirm.

Experience Portal immediately polls the Avaya WebLM server to retrieve the current license information and, if successful, updates the fields in the Licensing page.

Updating license information manually

About this task

If the license information changes on the WebLM server, it can take up to ten (10) minutes before Experience Portal polls that server and is informed of the changes. If you do not want to wait, you can make Experience Portal poll the license server immediately.

Procedure

1. Log on to the EPM Web interface using an account with the Administration user role.
2. From the EPM main menu, select **Security > Licensing**.
3. Click **License Server URL** icon .
4. Click **Save** on the License Server URL page.

Experience Portal polls the license server immediately even if no changes have been made on that page.

Licensing page field descriptions

Use this page to:

- View the number of licenses currently available on the Experience Portal system.
- View the URL that links Experience Portal to the Avaya WebLM license server.
- Verify that the connection to the WebLM license server is valid.
- View the number of licenses currently available on the managed application installed on Experience Portal.

Note:

You can view the managed application license details only if you have installed a managed application on Experience Portal. For more information on the fields related to the managed application, see the documentation delivered with the respective managed application.

Important:

Experience Portal requires a valid license from Avaya. If this system is currently operating with an invalid license, a message is displayed in red stating the problem and when the grace period expires. If you do not replace the license within that time, Experience Portal sets all the acquired licenses to 0 (zero) and cannot handle any inbound or outbound calls.

This page contains the:

- [License Server Information section](#) on page 42
- [Licensed Products section](#) on page 42

License Server Information section

Field	Description
License Server URL	The complete URL to the Avaya WebLM license server that is currently in use.
Last Updated	The last successful time that the License Server URL was changed.
Last Contacted	The last time that the communication with the license server was attempted.  Note: This field is displayed only if the server was never able to successfully poll the license server.
Last Successful Poll	The last successful time that the licenses were acquired from the license server.
License Server Information icon 	Opens the License Server URL page for updating the license server URL.

Licensed Products section

Field or Button	Description
Announcement Ports	The number of Announcement Ports licenses on your system. The system requires an announcement port license to handle calls that do not require DTMF processing and/or ASR and TTS capability.
ASR Connections	The number of Automated Speech Response (ASR) licenses on your system. ASR technology enables an interactive voice response (IVR) system to collect verbal responses from callers. This setting is the maximum number of MRCP connections to ASR servers that can be active at any one time.
Email Units	The number represents the email processing capacity that is on your system. If the value is non-zero (positive), the email feature is enabled. If the value is zero, the email feature is disabled.  Note: This feature is not required for using generation of email for reports and alarms.
Enable Media Encryption	Indicates if Media Encryption is enabled on your system. Media Encryption provides data security. If the value is a non-zero (positive) number, the media encryption is enabled. If it is zero, media encryption is disabled.

Table continues...

Field or Button	Description
Enhanced Call Classification	The number of enhanced call classification licenses on your system. Enhanced Call Classification licenses on the Experience Portal system provide the functionality to differentiate between human and answering machine responses to outbound calls. If the value is a non-zero (positive) number, the enhanced call classification is enabled. If the value is zero, the enhanced call classification feature is disabled.
HTML Units	The number represents the daily HTML processing capacity on your system. An HTML unit is required to handle an incoming HTML request.
SIP Signaling Connections	The number of SIP Signaling connections licenses on your system. The system requires a SIP Signaling Connection to handle calls that do not require media (i.e. no RTP stream is created).
SMS Units	The number represents the SMS processing capacity that is on your system. If the value is non-zero (positive), the SMS feature is enabled. If the value is zero, the SMS feature is disabled.
Telephony Ports	The number of Telephony Ports licenses on your system. The system requires a telephony port license to handle calls that require DTMF processing and/or ASR capability and TTS capability.
TTS Connections	The number of Text-to-Speech (TTS) licenses on your system. TTS technology enables an IVR system to render text content into synthesized speech output according to algorithms within the TTS software This setting is the maximum number of MRCP connections to TTS servers that can be active at any one time.
Video Server Connections	Specifies the maximum number of video connections to the video servers on the MPP. Enter 0 (zero) to disable the video feature.
Zones	The number represents whether the Zone feature is enabled for the system or not. If the value is non-zero (positive), the zone feature is enabled. If the value is zero, the zone feature is disabled.
Version	The version number of the license.
Expiration Date	The date when the license expires.
Last Contacted	The last time that the license server was contacted for acquiring licenses.

Table continues...

Field or Button	Description
	 Note: This field is displayed only if the server was never able to successfully acquire licenses.
Last Successful Poll	The last successful time that the licenses were acquired from the license server.
Last Changed	The last successful time that the licenses were different on the license server.
Avaya Aura® Experience Portal icon 	Opens the Avaya Aura® Experience Portal License Settings page for updating the license settings.
Allocations button	Opens the Allocations page for displaying the H.323 and SIP ports configured and licensed for the system.

Allocations page field descriptions

This page displays the H.323 and SIP resources that are configured, licensed, and allocated for the system. To accept or initiate a call, a resource must be configured, licensed, and allocated.

Field	Description
Zones	The zones to which telephony resources are allocated.  Note: This field is displayed only if zones are configured in the system.
Type	The VoIP connection types that are configured and licensed for the system. The options are: • H.323 • SIP
Configured	The number of resources that are configured on the H.323 Connection or SIP Connection pages.
Licensed	The number of telephony resources that are licensed by WebLM. If the total number of telephony ports, including announcement ports, specified by the license is sufficient, then all configured VoIP resources are licensed. In this case the value shown in the Licensed column matches the value shown in the Configured column. If the licensed resources are not sufficient, then the licenses are distributed proportionally based on the number of VoIP resources configured. Configured VoIP resources above what is licensed will not be used.
Allocated	The number of telephony resources that are allocated to media servers. If the total capacity of the media servers is sufficient, then all licensed VoIP resources are allocated to media servers. In this case, the value shown in the Allocated column matches the value shown in the Licensed column. If the

Table continues...

Field	Description
	capacity of the media servers is not sufficient, the allocated value is reduced. The Allocated resource cannot exceed the capacity of the media servers. If both H.323 and SIP are configured, then they are reduced in proportion to the licensed value. Licensed VoIP resources for which no media server is available will not be used.
Details link icon 	The details link (zoom lens icon) displays additional information for SIP allocations.
 Zones filter icon	To filter zones, click this icon located at the right side of the page. The system opens the Zone filter window for selecting one or more zones.  Note: The system displays the Zones filter icon only when you create new zones. If you do not create any new zones, you do not see the icon.

License Server URL page field descriptions

Use this page to:

- Update the license server URL
- Access the License Administration page for the WebLM server

Column or Button	Description
License Server URL	The complete URL to the Avaya WebLM license server. The URL must be in the format <code>https://<WebLM-machine>:port/WebLM/LicenseServer</code>, where <code><WebLM-machine></code> is the hostname or IP address of the WebLM server and <code>:port</code> consists of a colon followed by the port number for the WebLM server. If WebLM uses the default configuration, specify : 52233 . If a customer is using an older version of WebLM, then the default port number is 8443 .  Note: Unless your site uses a dedicated WebLM server machine, the WebLM server is installed on the Experience Portal EPM server.
Verify	Opens a new browser window and loads the License Administration page for the WebLM license server. If this page loads properly, then Experience Portal can connect to the license server.

Avaya Aura Experience Portal License Settings page field descriptions

Use this page to update the license settings.

Column or Button	Description
Announcement Ports	Specify the minimum and maximum number of licenses. • Minimum: Indicates the minimum number of licenses below which the Experience Portal system generates an event that the system does not have enough licenses. Enter a value in the range 0 to 50,000. • Maximum: Indicates the maximum number of licenses to be retrieved by EPM for that feature. Enter a value in the range 0 to 50,000.
Email Units	Specify the minimum and maximum number of licenses. • Minimum: Indicates the minimum number of licenses below which the Experience Portal system generates an event that the system does not have enough licenses. Enter a value in the range 0 to 5,000. • Maximum: Indicates the maximum number of licenses to be retrieved by EPM for that feature. Enter a value in the range 0 to 5,000.
HTML Units	Specify the minimum and maximum number of licenses. • Minimum: Indicates the minimum number of licenses below which the Experience Portal system generates an event that the system does not have enough licenses. Enter a value in the range 0 to 1,000,000. • Maximum: Indicates the maximum number of licenses to be retrieved by EPM for that feature. Enter a value in the range 0 to 1,000,000.

Table continues...

Column or Button	Description
SIP Signaling Connections	Specify the minimum and maximum number of licenses. • Minimum: Indicates the minimum number of licenses below which the Experience Portal system generates an event that the system does not have enough licenses. Enter a value in the range 0 to 50,000. • Maximum: Indicates the maximum number of licenses to be retrieved by EPM for that feature. Enter a value in the range 0 to 50,000.
SMS Units	Specify the minimum and maximum number of licenses. • Minimum: Indicates the minimum number of licenses below which the Experience Portal system generates an event that the system does not have enough licenses. Enter a value in the range 0 to 5,000. • Maximum: Indicates the maximum number of licenses to be retrieved by EPM for that feature. Enter a value in the range 0 to 5,000.
Telephony Ports	Specify the minimum and maximum number of licenses. • Minimum: Indicates the minimum number of licenses below which the Experience Portal system generates an event that the system does not have enough licenses. Enter a value in the range 0 to 50,000. • Maximum: Indicates the maximum number of licenses to be retrieved by EPM for that feature. Enter a value in the range 0 to 50,000.

Viewing telephony port distribution

About this task

Experience Portal automatically distributes telephony ports across all Media Processing Platform (MPP) servers.

Procedure

1. Log on to the EPM Web interface using an account with the Administration, Operations, or Maintenance user role.

2. From the EPM main menu, select **Real-Time Monitoring > Port Distribution**.
3. From the **Servers** field, select the relevant MPP server.
4. On the Port Distribution page, if you want to view more information about a particular port, click its number in the **Port** column.

The EPM displays the Port Information window.

Telephony port states

State	Description
Active	The port has been assigned to an MPP but the MPP does not know the status of the port because the EPM and the MPP are out of sync.
Adding	The port has been assigned to an MPP but the MPP has not taken the port yet.
Alerting	The port is ringing and checking resources.
Available	The port is ready to be assigned to an MPP.
Connected	The port is in service and calls are in progress.
Delete	The port is in the process of being deleted from the system, but there is a call in progress. The port will stay in use until the call ends or the grace period expires, whichever comes first. For more information, see Setting the global grace period and trace level parameters on page 256.
Idle	The port is assigned to an MPP but the MPP is not registered with the switch. The port cannot take calls.
In Service	The port is assigned to an MPP and the MPP is registered with the switch. The port is ready to take a call.
None	The assigned port is missing.
Out of Service - Fault	The MPP is trying to register with the port.
Out of Service - Manual	The port is being manually taken offline from the MPP.
Proceeding	The port was taken offline but is currently coming back into service.
Removing	The port is being deleted from the MPP. It will soon be available for assignment to another MPP.
Trying	The MPP is trying to register with the port.

Port Distribution page field descriptions

Use this page to specify the filter criteria for the Port Distribution report.

Name	Description
Zones	The <Default> zone exists by default. The Zones drop-down box appears only when you create new zones, apart from the already existing <Default> zone.

Table continues...

Name	Description
	Select the name of the zone from the drop-down box. You can filter the records based on the zone that you select. * Note: The Zones drop-down box appears only when you create new zones. If you do not create any new zones, you do not see the drop-down box. You can see only the <Default> zone.
 Zones filter icon	To filter zones, click this icon located at the right side of the page. The system opens the Zone filter window for selecting one or more zones and for setting the time zone display. * Note: The Zones filter icon only appears when you create new zones. If you do not create any new zones, you do not see the icon.
Servers	The MPP servers that are configured on the system for the selected zone. * Note: If no servers are configured for the selected zone, then the drop-down box only shows the All Servers option.

Port Distribution Report page field descriptions

Use this page for a real-time view of telephony port distribution across all Media Processing Platform (MPP) servers. You can configure the telephony resources on the VoIP Connections page.

*** Note:**

If there is a port conflict, the text for a particular port appears in red. For more information, see the **Current Allocation** column.

Column	Description
Zone	The name of the zone within which the MPP server is configured.
Servers	The MPP servers for which you want to see the Port Distribution Report. * Note: This field appears only if you have selected one or more servers from the Port Distribution page. If you select All Servers from the Servers list on the Port Distribution page, the system does not display this field.
Port	The Experience Portal port number associated with the port. * Note: The port distribution report for SIP protocol displays only the highest port distribution record.

Table continues...

Column	Description
	For detailed port information, click the number of the port to access the Port Information window. Click the Up arrow in the column header to sort the ports in ascending order and the Down arrow to sort the ports in descending order.
Mode	The operational mode of the port. The options are: • Online: The port is available for normal inbound and outbound calls and is allocated to an MPP. • Inbound: The port is available for normal inbound calls and is allocated to an MPP. • Test: The port is available for calls made to one of the defined H.323 maintenance stations and is allocated to an MPP in Test mode. • Offline: The port is not available and is not allocated to any MPP. Click the Up arrow in the column header to sort the modes in ascending order and the Down arrow to sort the modes in descending order
State	The state of the port. The options are: • Active: The port has been assigned to an MPP but the MPP does not know the status of the port because the EPM and the MPP are out of sync. • Adding: The port has been assigned to an MPP but the MPP has not taken the port yet. • Alerting: The port is ringing and checking resources. • Available: The port is ready to be assigned to an MPP. • Connected: The port is in service and calls are in progress. • Delete: The port is in the process of being deleted from the system. It is in use until the grace period expires. • Idle: The port is assigned to an MPP but the MPP is not registered with the switch. The port cannot take calls. • In Service: The port is assigned to an MPP and the MPP is registered with the switch. The port is ready to take a call. • None: The assigned port is missing. • Out of Service - Fault: The MPP is trying to register with the port. • Out of Service - Manual: The port is manually taken offline from the MPP. • Proceeding: The port was taken offline but is currently coming back into service. • Removing: The port is being deleted from the MPP. It will soon be available for assignment to another MPP. • Trying: The MPP is trying to register with the port.

Table continues...

Column	Description
	 Tip: You can hover the mouse over this column to view more information about the state, including any fault information if the port could not be registered.
Port Group	The name of the port group that the port belongs to. Port groups are administered on the System Configuration pages. Click the Up arrow in the column header to sort the groups in ascending order and the Down arrow to sort the groups in descending order
Protocol	The port protocol.  Note: The port distribution data for SIP is consolidated to a single line in each MPP. The port distribution report for SIP protocol displays only the highest port distribution record. Click the Up arrow in the column header to sort the protocols in ascending order and the Down arrow to sort the protocols in descending order.
Current Allocation	The name of the MPP to which the port is currently allocated. If there is a port conflict, you can hover the mouse over this field to view a tooltip containing one of the following error messages: • Unconfigured port currently owned by <MPP Name>. • Port allocated to <MPP1 Name> but currently owned by <MPP2 Name>. • Port not yet allocated but owned by <MPP Name>. • Port allocated to <MPP Name> but not owned by it. • Port allocation not yet sent. • Waiting for confirmation of the port allocation.
Base Allocation	The options are: • " " (blank): The port is currently allocated to the optimal MPP. • An MPP name: The optimal allocation for the port. If the base allocation field is not blank, it probably means that the optimal MPP went out of service and the port was reallocated.

Port Information window field descriptions

Use this window to view detailed information about an Experience Portal telephony port.

This window contains the:

- [Details group](#) on page 52
- [Status group](#) on page 52
- [Allocation group](#) on page 53

Details group

Field	Description
Port	The Experience Portal port number associated with the port.  Note: The port information for SIP displays a range from 1 to the port number of the selected port.
Port Group	The name of the port group that the port belongs to.
Gatekeeper	The IP address of the H.323 Gatekeeper.
Gatekeeper Port	The port number of the H.323 Gatekeeper port.

Status group

Field	Description
State	The state of the port. The options are: • Active: The port has been assigned to an MPP but the MPP does not know the status of the port because the EPM and the MPP are out of sync. • Adding: The port has been assigned to an MPP but the MPP has not taken the port yet. • Alerting: The port is ringing and checking resources. • Available: The port is ready to be assigned to an MPP. • Connected: The port is in service and calls are in progress. • Delete: The port is in the process of being deleted from the system. It is in use until the grace period expires. • Idle: The port is assigned to an MPP but the MPP is not registered with the switch. The port cannot take calls. • In Service: The port is assigned to an MPP and the MPP is registered with the switch. The port is ready to take a call. • None: The assigned port is missing. • Out of Service - Fault: The MPP is trying to register with the port. • Out of Service - Manual: The port is manually taken offline from the MPP. • Proceeding: The port was taken offline but is currently coming back into service. • Removing: The port is being deleted from the MPP. It will soon be available for assignment to another MPP. • Trying: The MPP is trying to register with the port.
Fault Code and Reason	If this port encountered a fault condition, this will be PTELE00031 - Channel Out of Service .

Table continues...

Field	Description
	Hover the mouse over this field to display the reason provided to Experience Portal by the switch.
Call Type	If the port is currently being used, displays the type of call that is currently using the port.
Mode	The operational mode of the port. The options are: • Online: The port is available for normal inbound and outbound calls and is allocated to an MPP. • Inbound: The port is available for normal inbound calls and is allocated to an MPP. • Test: The port is available for calls made to one of the defined H.323 maintenance stations and is allocated to an MPP in Test mode. • Offline: The port is not available and is not allocated to any MPP.

Allocation group

Field	Description
Current Allocation	The options are: • <None>: The port is not currently allocated to an MPP. • The name of the MPP to which the port is currently allocated along with any error messages that may have been generated by port conflicts.
Base Allocation	The options are: • " " (blank): The port is currently allocated to the optimal MPP. • An MPP name: The optimal allocation for the port. If the base allocation field is not blank, it probably means that the optimal MPP went out of service and the port was reallocated.

VoIP connections

H.323 connections in Experience Portal

H.323 is an Internet standard set of protocols for the transmission of real-time audio, video, and data using packet-switching technology. Experience Portal uses H.323 connections with an Communication Manager to handle Voice over IP (VoIP) telephony.

To provide VoIP capabilities, H.323 uses:

- Terminals, which can be PCs or dedicated IP softphone devices.
- Gateways, which “translate” communications between dissimilar networks, such as IP networks and Public Switched Telephone Network (PSTN). In the Experience Portal system, the Communication Manager handles this function.

- A gatekeeper, which acts as the control center for all H.323 VoIP interactions in the system. In the Experience Portal system, the Communication Manager handles this function.

 Important:

You must use Communication Manager 3.1 build 369 or later with the Avaya Special Application SA8874 feature. This combination provides:

- VoiceXML supervised transfers. Without the SA8874 feature, supervised transfers have no access to call progress information and behave like a blind transfer.
- The Application Interface web service for outbound calling. Without the SA8874 feature, the web service has no access to call progress information and may start a VoiceXML application even when the connection attempt receives a busy signal.

 Note:

The SA8874 feature comes with Communication Manager version 3.1 or later, but it requires a separate license before it can be enabled.

Viewing existing H.323 connections

Procedure

1. Log on to the EPM Web interface using an account with the Administration, Operations, or Maintenance user role.
2. From the EPM main menu, select **System Configuration > VoIP Connections** and go to the H.323 tab.

From this page, authorized users can also add, delete, or change connections.

Adding H.323 connections

Procedure

1. Log on to the EPM Web interface using an account with the Administration user role.
2. From the EPM main menu, select **System Configuration > VoIP Connections** and go to the H.323 tab.
3. Click **Add**.
4. On the Add H.323 Connection page, enter the appropriate information and click **Save**.

Changing H.323 connections

Procedure

1. Log on to the EPM Web interface using an account with the Administration user role.
2. From the EPM main menu, select **System Configuration > VoIP Connections** and go to the H.323 tab.
3. Click the name of the connection that you want to change.
4. On the Change H.323 Connection page, enter the appropriate information and click **Save**.

Defining maintenance stations for an H.323 connection

About this task

Maintenance stations allow you to isolate call activity to an MPP running in the Test operational mode.

Experience Portal creates a port running in Test mode for each defined maintenance station. It then assigns one of those ports to an MPP when it enters Test mode. If you have:

- More Test mode ports than you have MPPs in Test mode, each Test mode MPP is assigned one port and the extra ports are ignored
- More MPPs in Test mode than you have Test mode ports, Experience Portal randomly distributes the available ports to a subset of the MPPs in Test mode

Procedure

1. Log on to the EPM Web interface using an account with the Administration user role.
2. From the EPM main menu, select **System Configuration > VoIP Connections** and go to the H.323 tab.
3. If you want to create a new connection:
 - a. Click **Add**.
 - b. On the Add H.323 Connection page, enter the required information in the General section.
4. If you want to add one or more maintenance stations to an existing connection, click the name of the connection to open the Change H.323 Connection page for that connection.
5. In the **New Stations** group:
 - a. Enter the first maintenance station in the **Station From** field.
 - b. If you want to enter a range of numbers, enter the last number in the range in the **To** field.
 - c. Enter a password in the **Password** field.
 - d. Select **Maintenance** in the **Station Type** list box.
 - e. Click **Add**.
6. If you want to define another maintenance station or range of numbers, repeat step 5.
7. Click **Save**.

Deleting H.323 connections

Procedure

1. Log on to the EPM Web interface using an account with the Administration user role.
2. From the EPM main menu, select **System Configuration > VoIP Connections** and go to the H.323 tab.
3. For each connection that you want to delete, select the check box to the left of the connection's name.

+ Tip:

To delete all connections, click the Selection check box in the header row of the table, which automatically selects all connections.

4. Click **Delete**.

Add H.323 Connection page field descriptions

Use this page to add a new H.323 connection to the Experience Portal system.

This page contains the:

- [General section](#) on page 56
- [New Stations group](#) on page 57
- [Configured Stations group](#) on page 58

General section

Field	Description
Zone	The name of the zone where the H.323 connection is configured. Select the name of the zone from the drop-down box. * Note: The Zone drop-down box appears only if you have created zones on your Experience Portal system. If you do not create any new zones, you do not see the drop-down box.
Name	The unique identifier for this H.323 connection on the Experience Portal system. The name can be up to 32 alphanumeric characters. Do not use any special characters. * Note: Once you save the H.323 connection, this name cannot be changed.
Enable	Whether this H.323 connection is available for use by the Experience Portal system. The default is Yes, which means the connection is available.
Gatekeeper Address	The network address of the H.323 gatekeeper. The gatekeeper resides on the Communication Manager and acts as the control center for all H.323 VoIP interactions in the Experience Portal system. This must be a valid network address in the form of a fully qualified hostname or an IP address.
Alternative Gatekeeper Address	The network address of the alternate H.323 gatekeeper that resides on Communication Manager. The Gatekeeper address and the Alternate Gatekeeper Address are used for initial contact with Communication Manager, and Communication Manager can instruct the media manager to use other addresses for further communications. For more information on the alternate H.323 gatekeeper, refer to <i>Avaya Aura® Communication Manager Feature Description and Implementation</i> on http://support.avaya.com. This must be a valid network address in the form of a fully qualified hostname or an IP address.

Table continues...

Field	Description
Gatekeeper Port	The port on the gatekeeper that Experience Portal uses for this connection. This value must be in the range from 1024 to 65535. The default port is 1719.
Media Encryption	The options are: • Yes: Experience Portal encrypts all calls that use this connection. This is the default. • No: Calls are not encrypted.  Note: The use of encryption can affect system performance, especially if you are using the connection for a large number of simultaneous calls.

New Stations group

Field or Button	Description
Station	The stations to use for this H.323 connection. These stations represent the telephone numbers or extensions that can use this H.323 connection for VoIP calls. The options are: • A single station. Enter the station number in the From field. • A range of stations. Enter the lowest number of the range in the From field, and the highest number of the range in the To field. When you specify the stations, keep in mind that: • Each station can be a maximum of 15 digits in length. • This station or range of stations must be unique. That is, you cannot assign the same stations or an overlapping range of stations to different H.323 connections. • The total number of stations you enter cannot exceed the number of Experience Portal ports you have licensed. For more information on the number of available licenses, see Viewing your licenses on page 40.
Password	The numeric password to be associated with either the first station or all stations. The H.323 gatekeeper uses passwords as an extra measure of security when using the stations on this connection. The password can be a maximum of 8 digits in length.
Password type radio buttons	The options are: • Same Password: Experience Portal uses the password specified in the Password field for all stations in the specified range. • Use sequential passwords: Experience Portal uses the password specified in the Password field for the first station in the specified range. The system automatically increments this base password by one for each of the other stations in the specified range.

Table continues...

Field or Button	Description
Station Type	The options are: • Inbound and Outbound: The specified stations can be used for inbound or outbound calls. • Inbound Only: The specified stations can be used for inbound calls only. • Maintenance: The specified stations are special numbers that you can configure on the switch and on the MPP for use in troubleshooting problems with the MPP. Maintenance stations make it possible to isolate a single MPP for troubleshooting purposes in multiple-MPP systems. For more information, see Using the Test operational mode on page 276.  Note: If you select Maintenance: • Experience Portal only allocates one maintenance port to each MPP that is currently in Test mode. Therefore, specifying a range of stations is only useful if you put several MPPs into Test mode at the same time.
Add	Associates the station or range of stations with the connection.

Configured Stations group

Field or Button	Description
Display text box	The stations that can use this H.323 connection. If an entry is followed by: • (I): the stations are inbound only. • (M): the stations are maintenance stations. • " " (blank), the stations are both inbound and outbound. Select an individual entry in this list by clicking on it, or use Ctrl+Click and Shift+Click to select multiple entries.
Remove	Removes the selected entries from the list of Configured Stations.

Change H.323 Connection page field descriptions

Use this page to change an existing H.323 connection.

This page contains the:

- [General section](#) on page 58
- [New Stations group](#) on page 59
- [Configured Stations group](#) on page 61

General section

Field	Description
Zone	The name of the zone where the H.323 connection is configured. Select the name of the zone from the drop-down box.

Table continues...

Field	Description
	 Note: The Zone drop-down box appears only if you have created zones on your Experience Portal system. If you do not create any new zones, you do not see the drop-down box.
Name	The unique identifier for this H.323 connection on the Experience Portal system.  Note: This field cannot be changed.
Enable	Whether this H.323 connection is available for use by the Experience Portal system. The default is Yes, which means the connection is available.
Gatekeeper Address	The network address of the H.323 gatekeeper. The gatekeeper resides on the Communication Manager and acts as the control center for all H.323 VoIP interactions in the Experience Portal system. This must be a valid network address in the form of a fully qualified hostname or an IP address.
Alternative Gatekeeper Address	The network address of the alternate H.323 gatekeeper that resides on Communication Manager. The Gatekeeper address and the Alternate Gatekeeper Address are used for initial contact with Communication Manager, and Communication Manager can instruct the media manager to use other addresses for further communications. For more information on the alternate H.323 gatekeeper, refer to <i>Avaya Aura® Communication Manager Feature Description and Implementation</i> on http://support.avaya.com. This must be a valid network address in the form of a fully qualified hostname or an IP address.
Gatekeeper Port	The port on the gatekeeper that Experience Portal uses for this connection. This value must be in the range from 1024 to 65535. The default port is 1719.
Media Encryption	The options are: • Yes: Experience Portal encrypts all calls that use this connection. This is the default. • No: Calls are not encrypted.  Note: The use of encryption can affect system performance, especially if you are using the connection for a large number of simultaneous calls.

New Stations group

Field or Button	Description
Station	The stations to use for this H.323 connection. These stations represent the telephone numbers or extensions that can use this H.323 connection for VoIP calls. The options are: • A single station. Enter the station number in the From field.

Table continues...

Field or Button	Description
	- A range of stations. Enter the lowest number of the range in the From field, and the highest number of the range in the To field. When you specify the stations, keep in mind that: - Each station can be a maximum of 15 digits in length. - This station or range of stations must be unique. That is, you cannot assign the same stations or an overlapping range of stations to different H.323 connections. - The total number of stations you enter cannot exceed the number of Experience Portal ports you have licensed. For more information on the number of available licenses, see Viewing your licenses on page 40.
Password	The numeric password to be associated with either the first station or all stations. The H.323 gatekeeper uses passwords as an extra measure of security when using the stations on this connection. The password can be a maximum of 8 digits in length.
Password type radio buttons	The options are: Same Password: Experience Portal uses the password specified in the Password field for all stations in the specified range. Use sequential passwords: Experience Portal uses the password specified in the Password field for the first station in the specified range. The system automatically increments this base password by one for each of the other stations in the specified range.
Station Type	The options are: Inbound and Outbound: The specified stations can be used for inbound or outbound calls. Inbound Only: The specified stations can be used for inbound calls only. Maintenance: The specified stations are special numbers that you can configure on the switch and on the MPP for use in troubleshooting problems with the MPP. Maintenance stations make it possible to isolate a single MPP for troubleshooting purposes in multiple-MPP systems. For more information, see Using the Test operational mode on page 276.  Note: If you select Maintenance: - Experience Portal only allocates one maintenance port to each MPP that is currently in Test mode. Therefore, specifying a range of stations is only useful if you put several MPPs into Test mode at the same time.
Add	Associates the station or range of stations with the connection.

Configured Stations group

Field or Button	Description
Display text box	The stations that can use this H.323 connection. If an entry is followed by: • (I): the stations are inbound only. • (M): the stations are maintenance stations. • " " (blank), the stations are both inbound and outbound. Select an individual entry in this list by clicking on it, or use Ctrl+Click and Shift+Click to select multiple entries.
Remove	Removes the selected entries from the list of Configured Stations.

H.323 tab on the VoIP Connections page field descriptions

Use this tab to view, add, or change H.323 connections on the Experience Portal system.

+ Tip:

To sort the connections by any column, click the up arrow (sort ascending) or down arrow (sort descending) in the column header.

Column or Button	Description
Selection check box	Use this Selection check box to select which connections you want to delete.
Zone	The name of the zone where the H.323 connection is configured.
 Zones filter icon	To filter zones, click this icon located at the right side of the page. The system opens the Zone filter window for selecting one or more zones. * Note: The Zones filter icon only appears when you create new zones. If you do not create any new zones, you do not see the icon.
Name	The unique identifier for this H.323 connection on the Experience Portal system. Click the name to open the Change H.323 Connection page.
Enable	The options are: • Yes: This connection is available for use by the Experience Portal system. • No: This connection is disabled.
Gatekeeper Address	The network address of the H.323 gatekeeper. The gatekeeper resides on the Communication Manager and acts as the control center for all H.323 VoIP interactions in the Experience Portal system.
Alternative Gatekeeper Address	The network address of the alternate H.323 gatekeeper that resides on Communication Manager. The Gatekeeper address and the Alternate Gatekeeper Address are used for initial contact with Communication Manager, and Communication Manager can instruct the media manager to use other addresses for further communications. For more

Table continues...

Column or Button	Description
	information on the alternate H.323 gatekeeper, refer to <i>Avaya Aura® Communication Manager Feature Description and Implementation</i> on http://support.avaya.com .
Gatekeeper Port	The port on the gatekeeper that Experience Portal uses for this connection.
Stations	The stations that can use this H.323 connection. If an entry is followed by: • (I): the stations are inbound only. • (M): the stations are maintenance stations. • " " (blank), the stations are both inbound and outbound.
Media Encryption	If this field displays Yes , Experience Portal encrypts all calls that use this connection.
Add	Opens the Add H.323 Connection page.
Delete	Deletes the H.323 connections whose associated Selection check box is checked.

SIP connections in Experience Portal

Session Initiation Protocol (SIP) is an IP telephony signaling protocol developed by the IETF. Primarily used for Voice over Internet Protocol (VoIP) calls, SIP can also be used for video or any media type.

SIP is a text-based protocol that is based on HTTP and MIME, which makes it suitable and very flexible for integrated voice-data applications. SIP is designed for real time transmission, uses fewer resources and is considerably less complex than H.323. Its addressing scheme uses URLs and is human readable; for example: `sip:john.doe@company.com`.

SIP relies on the Session Description Protocol (SDP) for session description and the Real-time Transport Protocol (RTP) for actual transport.

You can configure the Experience Portal SIP connection as either a TCP connection or a TLS connection. The Avaya Aura® Session Manager (ASM) is used as the SIP proxy when configuring Experience Portal to use SIP. For more information on SIP integration with Experience Portal and ASM, see *Application Notes for Avaya Aura® Experience Portal 6.0, Avaya Aura® Communication Manager 6.0.1, Avaya Aura® Session Manager 6.1 and Acme Packet Net-Net 6.2.0 with AT&T IP Toll Free Service using MIS/PNT or AVPN Transport – Issue 1.0* on the Avaya online support Web site, <http://support.avaya.com>.

Note:

While configuring the SIP proxy for a system with Experience Portal zones, you must take the following into consideration:

- In a system with zones, the applications, media servers, and other resources are grouped into zones.
- A SIP proxy is configured for each zone.

- When the target application resides in only one zone, configure the SIP proxy for the application with only those media servers that are assigned to the target zone.
- If the same SIP proxy is used across multiple zones and the application is configured in multiple zones, the media servers from the multiple zones can be targeted.

Viewing existing SIP connections

Procedure

1. Log in to the EPM web interface.
2. From the EPM main menu, select **System Configuration > VoIP Connections**.
3. Click the SIP tab.

From this page, users logged in with the Administration user role can also add, delete, or change connections.

Adding SIP connection

About this task

To configure TLS as the Proxy Transport for SIP signaling, you must install a certificate for TLS authentication on EPM server and the Experience Portal security certificate on Avaya Aura® Session Manager. For more information, see [Installing a certificate for TLS authentication on server](#) on page 64 and [Installing a certificate for TLS authentication with Session Manager](#) on page 67.

The digital certificates are used to establish a mutually authenticated connection between Experience Portal and the SIP Proxy. Session Manager is typically used as the SIP Proxy server.

Procedure

1. Log in to the EPM web interface.
2. From the EPM main menu, select **System Configuration > VoIP Connections**.
3. Click the SIP tab.
4. Click **Add**.
5. Enter the appropriate information on the Add SIP Connection page, and click **Save**.

Changing SIP connections

Procedure

1. Log in to the EPM Web interface.
2. From the EPM main menu, select **System Configuration > VoIP Connections**.
3. Click the SIP tab.
4. Click the name of the connection that you want to change.
5. On the Change SIP Connection page, enter the appropriate information and click **Save**.

Deleting SIP connections

Procedure

1. Log on to the EPM Web interface using an account with the Administration user role.
2. From the EPM main menu, select **System Configuration > VoIP Connections**.
3. Click the SIP tab.
4. For each connection that you want to delete, select the check box to the left of the connection name.

Tip:

To delete all connections, click the Selection check box in the header row of the table, which automatically selects all connections.

5. Click **Delete**.

Installing a root certificate for TLS authentication on the EPM server

About this task

The root certificate is installed on EPM by default.

You can upload or generate a new security certificate on EPM.

Note:

Ensure that you replace the SHA-1 security certificate with a SHA-2 security certificate. Avaya recommends that you update your certificates from SHA-1 to SHA-2 to improve security. It is not mandatory to replace the SHA-1 certificate, but in that case some security concerns will be present. If you do replace the certificate, you must take additional steps to update any third party systems with the new certificate so that connections to the third party systems remain operational. For example, Session Manager requires the Sha-2 certificate.

Procedure

1. Log in to the EPM Web interface.
2. From the EPM main menu, select **Security > Certificates**.
3. Click the Root Certificates tab.
4. To upload a certificate:
 - a. Click **Upload**.
 - b. On the Upload Root Certificate page, click **Browse** and select the certificate file from the Choose File to Upload dialog box.
 - c. Enter the appropriate password in the **Password** field.
 - d. Click **Install**.

! Important:

To use a self signed or third party certificate:

- The certificate must be formatted as a PKCS#12 file. A PKCS#12 file always includes a certificate and its corresponding key. The certificate is encrypted and requires a password. If the certificate is not self-signed, then the PKCS#12 file must include all CA certificates.
- The certificate must include the standard extension Basic Constraints with the CA:true attribute.
- The certificate must be a CA certificate which can sign end user certificates.
- If the Extended Key Usage is specified in the X509.V3 certificate extension, specify `Server Authentication` (serverAuth), and `Client Authentication` (clientAuth) for the usage.

5. To generate a new security certificate with SHA-256 signature algorithm, click **Generate**.

Root Certificate tab on the Certificates page field descriptions

Use this tab to view the currently installed security certificate for Experience Portal to use for TLS authentication. You can also upload or generate a new security certificate.

Field or Button	Description
Security Certificate	Displays the current security certificate.
Upload	Opens the Upload Root Certificate page.
Generate	Generates a new security certificate with SHA-256 signature algorithm.
Disable Signing	Removes the root certificate from the system. The existing signed certificates, for example MPP Proxy certificates continues to work till they are replaced or a new Root certificate is installed. For more information, see the section <i>Use Third-Party Signed Certificates</i> .

*** Note:**

Ensure that you replace the SHA-1 security certificate with a SHA-2 security certificate. Avaya recommends that you update your certificates from SHA-1 to SHA-2 to improve security. It is not mandatory to replace the SHA-1 certificate, but in that case some security concerns will be present. If you do replace the certificate, you must take additional steps to update any third party systems with the new certificate so that connections to the third party systems remain operational. For example, Session Manager requires the Sha-2 certificate.

Upload Trusted Certificate page field descriptions

Use the two Upload Trusted Certificate pages to upload a certificate for:

- Application server: These certificates allow Avaya Aura® Experience Portal to use a secure connection between the MPPs and the application server.
- LDAP server: These certificates allow Avaya Aura® Experience Portal to use a secure connection between the Primary EPM server and the LDAP server.
- SIP Connection: These certificates allow a secure connection between Avaya Aura® Experience Portal and the VoIP servers.

- Speech server: These certificates are used by the MPP for communicating with the speech servers when using MRCP V2 TLS protocol.
- System Manager: These certificates allow the EPM to Single Sign-On with the System Manager.

Upload Trusted Certificate page (page 1 of 2)

Field	Description
Name	The name of this certificate on the Avaya Aura® Experience Portal system. Once you click Continue , this name cannot be changed.
Type	The options are: • Application • LDAP Server • SIP Connection • Speech Server • System Manager
Security Certificate File	The file name of the security certificate. Once you click Continue, this path cannot be changed.  Important: If you select Speech server in the Type field, please ensure: • The MRCP v2/TLS connection requires certificates and only the Nuance speech server supports this connection. So you need to add details in this field only for the Nuance speech server. • The Nuance certificate must be formatted as a .pem file. The following 4 certificates must reside in a certificate folder in Nuance speech server; domain_cert_localdomain.pem and _cert.pem, domain_key_localdomain.pem and _key.pem files. • Select only the _cert.pem certificate. Click the Browse field if you want to select the certificate file from the Choose File to Upload dialog box.
Continue	Submits the location to Avaya Aura® Experience Portal for verification. Avaya Aura® Experience Portal downloads the SSL (Secure Sockets Layer) certificate from the designated location. If the SSL certificate fails to download, Avaya Aura® Experience Portal prompts you to correct the Location field entry and try again. When the SSL certificate downloads successfully, Avaya Aura® Experience Portal displays the second Upload Trusted Certificate page.

Upload Trusted Certificate page (page 2 of 2)

The fields on this page are presented for confirmation purposes only. If you want to make any changes, you need to cancel this submission and repeat the process from the beginning.

Field	Description
Name	The name of this certificate on the Avaya Aura® Experience Portal system.
Display text box	The text of the security certificate.
Save	Installs the displayed certificate on the EPM.

Installing a certificate for TLS authentication with Avaya Aura® Session Manager

About this task

To configure TLS as the Proxy Transport for SIP signaling between Experience Portal, Avaya Aura® Session Manager (ASM), and Communication Manager, you require the following:

- A security certificate on Experience Portal.
- A complementary trusted certificate on ASM.
- The ASM certificate imported to EPM.

The digital certificates are used to establish a mutually authenticated connection with ASM.

The root certificate is installed on EPM by default. If you want to replace the root certificate on EPM with a new certificate or a third party certificate, see [Installing a root certificate for TLS authentication on the EPM server](#), on page 64

Procedure

1. Log in to the EPM web interface.
2. From the EPM main menu, select **Security > Certificates**.
3. Click **Export** on the **Root Certificate** tab, and follow the prompts.
4. Log in to System Manager and add the Experience Portal trusted certificate to ASM.

For information about how to add trusted certificates, see Administering Avaya Aura® Session Manager on <http://support.avaya.com>.

Next steps

1. Log in to the System Manager console and configure the ASM Entity Link for TLS on port 5061.
2. Log in to EPM, configure a SIP connection for TLS on port 5061, and restart the MPP.

Add SIP Connection page field descriptions

Use this page to add a new Session Initiation Protocol (SIP) connection to the Experience Portal system. Using this page you can also specify more than one proxy server address for the SIP connection.

Add SIP Connection page

If MPP is installed with the Experience Portal system, this page contains the:

- [General section](#) on page 68

- [Proxy Servers and DNS SRV Domain section](#) on page 68
- [SIP Timers section](#) on page 71
- [Call Capacity section](#) on page 72
- [SRTP group](#) on page 72
- [Configured SRTP List group](#) on page 73

General section

Column	Description
Zone	The name of the zone where the SIP connection is configured. Select the name of the zone from the drop-down box.  Note: The Zone drop-down box appears only if you have created zones on your Experience Portal system. If you do not create any new zones, you do not see the drop-down box.
Name	The unique identifier for this SIP connection on the Experience Portal system. The name can be up to 32 alphanumeric characters. Do not use any special characters.  Note: This field cannot be changed.
Enable	Whether this SIP connection is available for use by the Experience Portal system. The default is Yes, which means the connection is available.  Note: While you can configure multiple SIP connections, only one can be active at any one time.
Proxy Transport	The IP Protocol used by the SIP connection. The options are: • TCP • TLS

Proxy Servers and DNS SRV Domain section

Field	Description
Address	The address of the proxy server.

Table continues...

Field	Description
	This must be a valid network address in the form of a fully qualified hostname or an IP address. This field is enabled only when you select the Proxy Server option.
Port	The port used by the proxy server. The default for TCP is 5060, and the default for TLS is 5061. This field is enabled only when you select the Proxy Server option.
Priority	When you configure more than one proxy server, this field determines the order in which outbound calls are sent to the list of proxy servers. Calls are sent to the proxy server with the lowest priority value first. If this proxy server fails, calls are sent to the proxy server with the second lowest priority value. This continues up the proxy server list in priority order until either the call succeeds or the list is exhausted. Enter a number in the range 0 to 65535. The default is 0. This field is enabled only when you select the Proxy Server option.
Weight	When you add more than one proxy server with the same priority value, this field determines the relative chances of which proxy server is used for an outbound call. The proxy server with the highest weight has the greatest odds of receiving a call. For example, if proxy servers 1 and 2 are assigned a priority of 1, and weight of 4 and 6 respectively, then proxy server 1 has a 40% ($4/(4+6)$) chance of receiving a call while proxy server 2 has a 60% ($6/(4+6)$) chance. Enter a number in the range 0 to 65535. The default is 0. This field is enabled only when you select the Proxy Server option.
Remove	Removes the proxy server. This field is enabled only when you select the Proxy Server option.
Additional Proxy Server	Adds additional proxy addresses and ports. You cannot use the same proxy server address and port for adding another proxy server. This field is enabled only when you select the Proxy Server option.
DNS Server Domain	This is the domain name under which the SIP proxy list is configured in the DNS server.  Note: The DNS server must support the DNS SRV protocol. The entry must be a valid hostname.

Table continues...

Field	Description
	Ensure that the DNS server domain is configured to retrieve the ordered list of available server records which can be used to handle calls. This field is enabled only when you select the DNS Server Domain option.
Listener Port	The port used by the Listener. The default for TCP is 5060, and the default for TLS is 5061.
SIP Domain	The domain in which the SIP connection is configured. The SIP domain must match the domain name of the connected proxy (that is the domain name in SIP URIs for incoming calls). * (asterisk) means that all calls are routed to this trunk.
P-Asserted-Identity	The assumed identity used to determine the service class and the restriction permissions class for the SIP connection. For Communications Manager, this should map to an extension configured on the switch.
Maximum Redirection Attempts	The number of redirection attempts allowed before the call is considered to have failed. The MPP redirects a call when it receives a 302 response code from an INVITE request. This response code indicates that the endpoint which received the call has moved to another location, and the call should be redirected to the new location. The call continues to be redirected until either no further 302 response is received or the retry count is exhausted. Enter a number in the range 0 to 100. The default is 0. Redirect attempt is disabled when the number in this field is set to 0.
Consultative Transfer	If a connection cannot be established, Consultative Transfer allows Experience Portal to regain control of the call. The following options determine the SIP messages used for a VXML Consultative Transfer: • INVITE with REPLACES: When Experience Portal receives INVITE with REPLACES in the SIP message, it establishes a secondary call to the transfer destination to: - Determine availability - Ensure that the destination answers within the established timeout The secondary call is then merged with the primary call that is being transferred. Experience Portal sends a request to the transferee for an INVITE message with a Replaces header that contains the information necessary to take control over the primary call. Experience Portal controls the progress of the call in case the response of the second call is not positive.

Table continues...

Field	Description
	 Note: This option requires the transfer destination to support the INVITE with Replaces SIP message. • REFER: With this option, the transferee determines the entire process of establishing the new call to the transfer destination. If the transfer destination is unavailable or does not respond to the call, the transferee sends the call to Experience Portal. The default option is INVITE with REPLACES.
SIP Reject Response Code	The response code that is sent to a SIP proxy when all SIP resources for an MPP are in use. The options are: • ASM (503): Sends a request to ASM to call another MPP that might be available. • SES (480): Sends a request to SES to call another MPP that might be available. • Custom: Allows custom response codes to be set for interoperability with other proxies and media gateways that might require a different response code to initiate a similar operation as stated above.

SIP Timers section

Field	Description
T1	Timer T1 is a general estimate of the maximum round trip time for SIP packets between the MPP and the proxy. It is used to determine the minimum retransmit interval for SIP messages. The default value is 250 millisecond(s). Enter a number in the range of 10 to 8000 millisecond(s).
T2	Timer T2 is the maximum retransmit interval for SIP messages. The T1 and T2 values are used together in an algorithm that backs off message retransmits in case of congestion. The default value is 2000 millisecond(s). Enter a number in the range of 10 to 8000 millisecond(s).
B and F	Timers B and F are the transaction timeouts for INVITE and non-INVITE requests, respectively. They determine the amount of wait time before a SIP request is aborted, when no response is received.

Table continues...

Field	Description
	The default value is 4000 millisecond(s). Enter a number in the range of 500 to 180000 millisecond(s).

Call Capacity section

Field	Description
Maximum Simultaneous Calls	The maximum number of calls that this trunk can handle at one time. Enter a number from 1 to 99999.
Call type radio buttons	The options are: • All Calls can be either inbound or outbound: This connection accepts any number of inbound or outbound calls up to the maximum number of calls defined in Maximum Simultaneous Calls. • Configure number of inbound and outbound calls allowed: If this option is selected, Experience Portal displays the fields: - Inbound Calls Allowed: Enter the maximum number of simultaneous inbound calls allowed. This value must be less than or equal to the number of Maximum Simultaneous Calls. - Outbound Calls Allowed: Enter the maximum number of simultaneous outbound calls allowed. This value must be less than or equal to the number of Maximum Simultaneous Calls. The combined number of inbound and outbound calls must be equal to or greater than the number of Maximum Simultaneous Calls.  Note: If all the SIP capacity configured (Maximum Simultaneous Calls) cannot be used because either the license or the total MPP capacity is not sufficient, then the number of inbound calls and outbound calls allowed will be reduced in proportion to the usable capacity.

SRTP group

Field	Description
Enable	The options are: • Yes: This connection uses SRTP. • No: This connection does not use SRTP.
Encryption Algorithm	The options are: • AES_CM_128: This connection uses 128 key encryption. • None: Messages sent through this connection are not encrypted.

Table continues...

Field	Description
Authentication Algorithm	The options are: • HMAC_SHA1_80: Authentication is done with HMAC SHA-1. • HMAC_SHA1_32: Authentication is done with HMAC SHA-1.
RTCP Encryption Enabled	The options are: • Yes: This connection uses RTCP encryption. • No: This connection does not use RTCP encryption.
RTP Authentication Enabled	The options are: • Yes: This connection uses RTP authentication. • No: This connection does not use RTP authentication.
Add	Adds the SRTP configuration to the connection.

Configured SRTP List group

This group displays any SRTP configurations defined for the connection.

 Note:

This group only appears if the **Proxy Transport** field is set to **TLS**.

Field	Description
Display	Displays the SRTP configurations for this connection.
Remove	Removes the association between the SRTP configuration selected in the display text box and the SIP connection.

Change SIP Connection page field descriptions

Use this page to change an existing Session Initiation Protocol (SIP) connection. Using this page you can also add or remove more than one proxy server address on the same SIP connection, and change the proxy transport option.

If MPP is installed with the Experience Portal system, this page contains the:

- [General section](#) on page 74
- [Proxy Servers and DNS SRV Domain section](#) on page 74
- [SIP Timers section](#) on page 77
- [Call Capacity section](#) on page 77
- [SRTP group](#) on page 78
- [Configured SRTP List group](#) on page 78

General section

Column	Description
Zone	The name of the zone where the SIP connection is configured. Select the name of the zone from the drop-down box.  Note: The Zone drop-down box appears only when you create new zones. If you do not create any new zones, you do not see the drop-down box.
Name	The unique identifier for this SIP connection on the Experience Portal system.  Note: This field cannot be changed.
Enable	Whether this SIP connection is available for use by the Experience Portal system. The default is Yes, which means the connection is available.  Note: While you can configure multiple SIP connections, only one can be active at any one time.
Proxy Transport	The IP Protocol used by the SIP connection. The options are: • TLS • TCP

Proxy Servers and DNS SRV Domain section

Field	Description
Address	The address of the proxy server. This must be a valid network address in the form of a fully qualified hostname or an IP address. This field is enabled only when you select the Proxy Server option.
Port	The port used by the proxy server. The default for TCP is 5060, and the default for TLS is 5061. This field is enabled only when you select the Proxy Server option.
Priority	When you configure more than one proxy server, this field determines the order in which outbound calls are sent to the list of proxy servers. Calls are sent to the proxy server with the lowest priority value first. If this proxy server fails, calls are sent to the proxy server with the second lowest priority value. This continues up the proxy server list in priority order until either the call succeeds or the list is exhausted. Enter a number in the range 0 to 65535. The default is 0.

Table continues...

Field	Description
	This field is enabled only when you select the Proxy Server option.
Weight	When you add more than one proxy server with the same priority value, this field determines the relative chances of which proxy server is used for an outbound call. The proxy server with the highest weight has the greatest odds of receiving a call. For example, if proxy servers 1 and 2 are assigned a priority of 1, and weight of 4 and 6 respectively, then proxy server 1 has a 40% ($4/(4+6)$) chance of receiving a call while proxy server 2 has a 60% ($6/(4+6)$) chance. Enter a number in the range 0 to 65535. The default is 0. This field is enabled only when you select the Proxy Server option.
Remove	Removes the proxy server. This field is enabled only when you select the Proxy Server option.
Additional Proxy Server	Adds additional proxy addresses and ports. You cannot use the same proxy server address and port for adding another proxy server. This field is enabled only when you select the Proxy Server option.
DNS Server Domain	This is the domain name under which the SIP proxy list is configured in the DNS server.  Note: The DNS server must support the DNS SRV protocol. The entry must be a valid hostname. Ensure that the DNS server domain is configured to retrieve the ordered list of available server records which can be used to handle calls. This field is enabled only when you select the DNS Server Domain option.
Listener Port	The port used by the Listener. The default for TCP is 5060, and the default for TLS is 5061.
SIP Domain	The domain in which the SIP connection is configured. The SIP domain must match the domain name of the connected proxy (that is the domain name in SIP URIs for incoming calls). * (asterisk) means that all calls are routed to this trunk.
P-Asserted-Identity	The assumed identity used to determine the service class and the restriction permissions class for the SIP connection. For Communications Manager, this should map to an extension configured on the switch.

Table continues...

Field	Description
Maximum Redirection Attempts	The number of redirection attempts allowed before the call is considered to have failed. The MPP redirects a call when it receives a 302 response code from an INVITE request. This response code indicates that the endpoint which received the call has moved to another location, and the call should be redirected to the new location. The call continues to be redirected until either no further 302 response is received or the retry count is exhausted. Enter a number in the range 0 to 100. The default is 0. Redirect attempt is disabled when the number in this field is set to 0.
Consultative Transfer	If a connection cannot be established, Consultative Transfer allows Experience Portal to regain control of the call. The following options determine the SIP messages used for a VXML Consultative Transfer: • INVITE with REPLACES: When Experience Portal receives INVITE with REPLACES in the SIP message, it establishes a secondary call to the transfer destination to: - Determine availability - Ensure that the destination answers within the established timeout The secondary call is then merged with the primary call that is being transferred. Experience Portal sends a request to the transferee for an INVITE message with a Replaces header that contains the information necessary to take control over the primary call. Experience Portal controls the progress of the call in case the response of the second call is not positive.  Note: This option requires the transfer destination to support the INVITE with Replaces SIP message. • REFER: With this option, the transferee determines the entire process of establishing the new call to the transfer destination. If the transfer destination is unavailable or does not respond to the call, the transferee sends the call to Experience Portal. The default option is INVITE with REPLACES.
SIP Reject Response Code	The response code that is sent to a SIP proxy when all SIP resources for an MPP are in use. The options are: • ASM (503): Sends a request to ASM to call another MPP that might be available.

Table continues...

Field	Description
	• SES (480): Sends a request to SES to call another MPP that might be available. • Custom: Allows custom response codes to be set for interoperability with other proxies and media gateways that might require a different response code to initiate a similar operation as stated above.

SIP Timers section

Field	Description
T1	Timer T1 is a general estimate of the maximum round trip time for SIP packets between the MPP and the proxy. It is used to determine the minimum retransmit interval for SIP messages. The default value is 250 millisecond(s). Enter a number in the range of 10 to 8000 millisecond(s).
T2	Timer T2 is the maximum retransmit interval for SIP messages. The T1 and T2 values are used together in an algorithm that backs off message retransmits in case of congestion. The default value is 2000 millisecond(s). Enter a number in the range of 10 to 8000 millisecond(s).
B and F	Timers B and F are the transaction timeouts for INVITE and non-INVITE requests, respectively. They determine the amount of wait time before a SIP request is aborted, when no response is received. The default value is 4000 millisecond(s). Enter a number in the range of 500 to 180000 millisecond(s).

Call Capacity section

Field	Description
Maximum Simultaneous Calls	The maximum number of calls that this trunk can handle at one time. Enter a number from 1 to 99999.
Call type radio buttons	The options are: • All Calls can be either inbound or outbound: This connection accepts any number of inbound or outbound calls up to the maximum number of calls defined in Maximum Simultaneous Calls.

Table continues...

Field	Description
	• Configure number of inbound and outbound calls allowed: If this option is selected, Experience Portal displays the fields: - Inbound Calls Allowed: Enter the maximum number of simultaneous inbound calls allowed. This value must be less than or equal to the number of Maximum Simultaneous Calls. - Outbound Calls Allowed: Enter the maximum number of simultaneous outbound calls allowed. This value must be less than or equal to the number of Maximum Simultaneous Calls. The combined number of inbound and outbound calls must be equal to or greater than the number of Maximum Simultaneous Calls.  Note: If all the SIP capacity configured (Maximum Simultaneous Calls) cannot be used because either the license or the total MPP capacity is not sufficient, then the number of inbound calls and outbound calls allowed will be reduced in proportion to the usable capacity.

SRTP group

Field	Description
Enable	The options are: • Yes: This connection uses SRTP. • No: This connection does not use SRTP.
Encryption Algorithm	The options are: • AES_CM_128: This connection uses 128 key encryption. • None: Messages sent through this connection are not encrypted.
Authentication Algorithm	The options are: • HMAC_SHA1_80: Authentication is done with HMAC SHA-1. • HMAC_SHA1_32: Authentication is done with HMAC SHA-1.
RTCP Encryption Enabled	The options are: • Yes: This connection uses RTCP encryption. • No: This connection does not use RTCP encryption.
RTP Authentication Enabled	The options are: • Yes: This connection uses RTP authentication. • No: This connection does not use RTP authentication.
Add	Adds the SRTP configuration to the connection.

Configured SRTP List group

This group displays any SRTP configurations defined for the connection.

*** Note:**

This group only appears if the **Proxy Transport** field is set to **TLS**.

Field	Description
Display	Displays the SRTP configurations for this connection.
Remove	Removes the association between the SRTP configuration selected in the display text box and the SIP connection.

SIP tab on the VoIP Connections page field descriptions

Use this tab to view, add, or change Session Initiation Protocol (SIP) connections on the Experience Portal system.

+ Tip:

To sort the connections by any column, click the up arrow (sort ascending) or down arrow (sort descending) in the column header.

Column	Description
Selection check box	Use this Selection check box to select which SIP connections you want to delete.
Zone	The name of the zone where the SIP connection is configured.
 Zones filter icon	To filter zones, click this icon located at the right side of the page. The system opens the Zone filter window for selecting one or more zones. * Note: The Zones filter icon only appears when you create new zones. If you do not create any new zones, you do not see the icon.
Name	The unique identifier for this SIP connection on the Experience Portal system. Click the name to open the Change SIP Connection page.
Enable	The options are: • Yes: This connection is available for use by the Experience Portal system. • No: This connection is disabled.
Proxy Transport	The IP Protocol used by the SIP connection. The options are: • TCP • TLS
Proxy/DNS Server Address	The address of the proxy server or the DNS server. This must be a valid network address in the form of a fully qualified hostname or an IP address.
Proxy Server Port	The port used by the proxy server.
Listener Port	The port used by the Listener.

Table continues...

Column	Description
SIP Domain	The domain in which the SIP connection is configured. The SIP domain must match the domain name of the connected proxy (that is the domain name in SIP URIs for incoming calls).
Add	Opens the Add SIP Connection page.
Delete	Deletes the SIP connections whose associated Selection check box is checked.

Comparison of features supported on H.323 and SIP

This table compares:

- Standard H.323.
- H.323 with the Avaya Special Application SA8874 feature enabled in Communication Manager.
- SIP.

Feature	H.323	H.323 with SA8874 feature	SIP
Outbound calling using the Application Interface web service	Partially supported No call progress information is available, so an application may start before a call is answered	Supported	Supported
Call conferencing	Supported	Supported	Supported
Call classification	Supported	Supported	Supported
Blind transfer	Supported	Supported	Supported
Supervised transfer (also called consultative transfer) * Note: If a connection cannot be established, the Consultative Transfer feature in Experience Portal allows the application to regain	Operates like a blind transfer * Note: The only supported VoiceXML event for this transfer is <code>error.connection.noroute</code> .	Supported	Supported

Table continues...

Feature	H.323	H.323 with SA8874 feature	SIP
control of the call.			
Bridge transfer)	Partially supported No call status information, such as "line is busy", is available	Supported	Supported except for the VoiceXML <transfer> tag's connecttimeout parameter, which is not supported
DTMF detection  Note: Experience Portal supports only out-band DTMF detection for H.323 and H.323 with SA8874 feature.	Supported	Supported	 Note: In case of SIP VoIP connection, the signaling group doesn't support the out-band option. It supports the in-band and RTP-payload DTMF options.
Playing prompt files	Supported	Supported	Supported
Recording	Supported	Supported	Supported
Converse-on vectoring	Supported	Supported	Not supported
Encryption options	• Disabled • AES • AEA	• Disabled • AES • AEA	• Disabled • TLS • SRTP
Quality of Service	Supported	Supported	Supported
User to User Information (UUI)	Not supported	Not supported	For an incoming call, UUI values are populated in the VoiceXML session variables for both UUI and Application to Application Information (AAI). For more information, see Universal Call Identifier (UCID) values included in UUI data on page 353.
Universal Call Identifier (UCID)	Supports the capability to receive UCID over H323 from Communication Manager.	Supports the capability to receive UCID over H323 from	Supports the capability to both send and receive UCID.

Table continues...

Feature	H.323	H.323 with SA8874 feature	SIP
	★ Note: This capability is available in Communication Manager 5.2. To enable this feature, you need to administer ucid-info on button 10 on the 7434ND stations used by Experience Portal.	Communication Manager. ★ Note: This capability is available in Communication Manager 5.2. To enable this feature, you need to administer ucid-info on button 10 on the 7434ND stations used by Experience Portal.	For more information, see Universal Call Identifier (UCID) values included in UUI data on page 353.
Switch failover	An alternate gatekeeper address can be specified in the EPM, and an alternate gatekeeper address list can come from Communication Manager	An alternate gatekeeper address can be specified in the EPM, and an alternate gatekeeper address list can come from Communication Manager	No additional support is supplied by Experience Portal, but the Avaya SIP Enablement Services (SES) hardware has failover support and MPPs can be configured as members of an adjunct in the SES
Merge (Refer with replaces)	Not supported	Not supported	Supported

Bridge transfers in a mixed SIP/H.323 environment

If you have both SIP and H.323 connections defined in your Experience Portal system, Experience Portal handles bridge transfers in the following manner. For an outbound call with:

- SIP or SIPS in the `TOURI` field, there must be a SIP outbound channel available.
- TEL in the `TOURI` field, Experience Portal tries to get an outbound port from the same H.323 port group. If none are available, Experience Portal tries any H.323 port.

If no H.323 ports are available, Experience Portal converts the TEL into SIP in the `TOURI` field and tries and get a SIP outbound channel.

VoIP in Experience Portal

Experience Portal uses H.323 or SIP connections to switches to transmit and receive Voice over IP (VoIP) data. The system makes use of a variety of Internet protocols to allow the real-time transmission and reception of voice data. In particular, the Media Processing Platform (MPP) servers use protocols such as the User Datagram Protocol (UDP), the Transmission Control Protocol (TCP), and the Media Resource Control Protocol (MRCP) to establish Real-time Transport Protocol (RTP) sessions and to transmit and receive voice data packets.

*** Note:**

To function effectively, the TCP and MRCP ports should not overlap.

In addition, the Experience Portal system can use a Real-time Transport Control Protocol (RTCP) monitor to collect data about the real-time transport of data as delivered by the MPP, the switches, and any other IP components that are configured to send status information about RTP sessions. The RTCP monitor then aggregates all the RTP session data into reports that contain information about packet loss, “jitter,” and other variables concerned with the health of RTP connections in the network. This RTCP monitor provides the system administrator one central location from which to gauge the status and performance of the network with respect to the bandwidth and latency requirements of VoIP.

Viewing the Avaya Aura® Experience Portal VoIP settings

Procedure

1. Log on to the EPM Web interface using an account with the Administration, Operations, or Maintenance user role.
2. From the EPM main menu, select **System Configuration > MPP Servers**.
3. On the MPP Servers page, click the **VoIP Settings** button.

If you are not logged in with the Administration user role, the EPM displays the VoIP Settings page in view only mode.

Configuring the Avaya Aura® Experience Portal VoIP settings

Procedure

1. Log on to the EPM Web interface using an account with the Administration user role.
2. From the EPM main menu, select **System Configuration > MPP Servers**.
3. On the MPP Servers page, click the **VoIP Settings** button.
4. On the VoIP Settings page, enter the appropriate information and click **Save**.
5. If you have changed any VoIP settings, restart all MPPs as described in [Restarting one or more MPP servers](#) on page 273.

VoIP Settings page field descriptions for MPP

Use this page to configure Voice over IP (VoIP) on your Experience Portal system.

This page contains the:

- [Port Ranges group](#) on page 84
- [RTCP Monitor Settings group](#) on page 85
- [VoIP Audio Formats group](#) on page 85
- [Audio Codecs group](#) on page 86
- [QoS Parameters group](#) on page 87
- [Out of Service Threshold group](#) on page 87

- [Call Progress group](#) on page 89
- [Miscellaneous group](#) on page 91

Port Ranges group

Field	Description
UDP	The range of port numbers used by User Datagram Protocol (UDP) transactions. Enter the lower value of the range of port numbers in the Low field, and the higher value in the High field. The range must be within 1024 to 65535. The default range is 11000 to 30999.  Note: Each call that uses ASR and TTS resources requires a total of six UDP ports.
TCP	The TCP range which you specify in this field must be large enough for the network connections, which vary based on the configuration as well as the load. Enter the lower value of the range of port numbers in the Low field, and the higher value in the High field. The range must be within 1024 to 65535. The default range is 31000 to 33499.  Important: Do not limit the TCP range to the absolute minimum as it will possibly impact functionality such as failover. Do not overlap ranges for the TCP and MRCP protocols.
MRCP	The port numbers used by Transmission Control Protocol (TCP) transactions. Enter the lower value of the range of port numbers in the Low field, and the higher value in the High field. The range must be within 1024 to 65535. The default range is 34000 to 36499. The number of MRCP ports you need depends on the setting of the New Connection per Session option for the Experience Portal speech servers. If this option is enabled, you need one MRCP port for each speech server license. If this option is not enabled, you need one MRCP port per speech server. For example, if you have one ASR server with five ASR licenses and one TTS server with two TTS licenses and: • The New Connection per Session option is enabled for both the ASR and TTS server, you would need seven MRCP ports because you have seven total licenses. • The New Connection per Session option is enabled for the ASR server but not the TTS server, you would need six MRCP ports because you have five ASR licenses plus one TTS server. • The New Connection per Session option is not enabled for either the ASR or TTS server, you would need two MRCP ports because you have two speech servers.
H.323 Station	The H.323 Station port range configures a range of UDP ports that are used exclusively for gatekeeper discovery and registration. However, the bulk of H.323 communication

Table continues...

Field	Description
	occurs over a TCP socket that is allocated from the TCP range. For each H.323 station, you need to configure one UDP and one TCP port. If either port fails to be allocated, the H.323 station will be marked out of service. Enter the lower value of the range of port number in the Low field, and the last number of the range in the High field. The range must be within 1024 to 65535. The default range is 37000 to 39499.  Important: The H.323 Station range must not overlap with UDP range.

RTCP Monitor Settings group

Field	Description
Host Address	The network address of the RTCP monitor, which collects status data about RTP sessions from the MPP and other components in the system. This must be a valid network address in the form of a fully qualified hostname or an IP address.
Port	The number of the port on the RTCP monitor that the EPM uses to communicate with the RTCP monitor.

VoIP Audio Formats group

Field	Description
MPP Native Format	The audio encoding codec the MPP uses as the default for audio recording within the Avaya Voice Browser (AVB) when the speech application does not specify the format for recording caller inputs. The options are: • audio/basic: The AVB uses the mu-Law encoding format, which is used mostly in the United States and Japan. If you select this option then the codec set on the switch must include G711MU. • audio/x-alaw-basic: The AVB uses the A-Law encoding format, which is used in most countries other than the United States and Japan. If you select this option then the codec set on the switch must include G711A. With either option, the AVB records input using a G.711-compliant format that is a raw (headerless) 8kHz 8-bit mono [PCM] single channel format.  Note: The AVB ignores this setting if a recording format is specified in a given speech application. If you make any change to the setting of this field, you must restart the MPP for the changes to take effect.

Audio Codecs group

Field	Description
Packet Time	The interval in milliseconds, for transmitting each audio packet. The time intervals you can select are: 10, 20, 30, 40, 50, 60, 70, and 80. The default is 20.
G729	G.729 codec is used for audio data compression for both H.323 and SIP connections. It supports G.729 Annexes A and B. The options are: • Yes: Select Yes to enable this option. • No: Select No to disable this option. The default is Yes.
Reduced Complexity Encoder	The G.729A reduced complexity encoding algorithm lowers the performance cost of G.729 transcoding. This setting affects only the encoding of G.729 audio sent by Experience Portal. The audio quality is reduced slightly when you enable this option. Experience Portal continues to receive and decode G.729 and G.729A audio data, regardless of the option selected in this field.  Note: This field is enabled only if you have selected Yes in the G729 field. The options are: • Yes: Select Yes to enable this option. • No: Select No to disable this option. The default is Yes.
Discontinuous Transmission	The G.729B discontinuous transmission algorithm allows Experience Portal to access and process a far end media offer with G.729B. The Annex B specification further reduces network bandwidth as it sends only the audio packets that contain speech data (packets that contain silence are not transmitted).  Note: This field is enabled only if you have selected Yes in the G729 field. The options are: • Yes: Select Yes to enable this option. • No: Select No to disable this option. With this option Annex B is not used.  Note: The G.729 offers may still be accepted.
First Offered	The media codec that is offered first in the SIP SDP media list. The codecs are offered in the most preferred to the least preferred order, so that a far end media selects the first media codec that it can accept.

Table continues...

Field	Description
	 Note: This field is enabled only if you have selected Yes in the G729 field. The options are: • G729 • G711

QoS Parameters group

Quality of Service (QoS) is used in network routing to improve performance for certain data streams. For example, RTP negotiated by various signaling protocols, but not the signaling itself. This is especially valuable for VoIP traffic because VoIP is susceptible to jitter caused by network delays. The QoS settings in this group are defined as per the signaling protocols parameters, but apply to the RTP streams that are the result of these signaling connections. This allows the various categories of RTP data to be prioritized independently. The QoS settings, however, do not apply to the signaling connections which are much less sensitive to latency and bandwidth limitations.

 Note:

The QoS settings are not in a continuous range. Increasing or decreasing the values will disable QoS. The numbers must exactly match the configuration on the network routers for the settings to have any effect. Therefore, if you are using QoS and the defaults do not seem to be working, contact your network administrator for suggested values.

Field	Description
H.323	The H.323 QoS parameters are: • VLAN. The QoS settings for H.323 connections running over a virtual LAN. • Diffserv. The QoS settings for H.323 connections running over a network using the Differentiated Services architecture. The default for VLAN is 6 and the default for Diffserv is 46.
SIP	The Session Initiation Protocol (SIP) QoS parameters are: • VLAN. The QoS settings for SIP connections running over a virtual LAN. • Diffserv. The QoS settings for SIP connections running over a network using the Differentiated Services architecture. The default for VLAN is 6 and the default for Diffserv is 46.
RTSP	The Real-Time Streaming Protocol (RTSP) QoS parameters are: • VLAN. The QoS settings for Real RTSP running over a virtual LAN. • Diffserv. The QoS settings for RTSP running over a network using the Differentiated Services architecture. The default for VLAN is 6 and the default for Diffserv is 46.

Out of Service Threshold group

The **Trigger** settings in this group determine when an MPP server issues an event or alarm message based on the percentage of ports that have gone out of service. In all cases, once the

MPP server has issued an event or alarm message, it will not issue another message until the percentage of out of service ports changes to the value set in the associated **Reset** field or below.

For example, if the **Warn Trigger** value is 10 and the **Reset** value is 0, then the MPP will respond in the following manner as the percentage of out of service ports changes:

Percentage of out of service ports	MPP server response
10%	A warning event is generated and the MPP enters the Degraded state.
8%	No event is generated.
12%	12%, no event is generated because it has not yet fallen below the Reset value.
0%	No event is generated but the MPP returns to the Running state.
6%	No event is generated.
11%	An event is generated and the MPP returns to the Degraded state.  Note: When the warning event is generated after the percentage of out of service ports reaches the trigger value, no more warning is generated until you reach reset value again.

Field	Description
Warn	The Trigger field determines the percentage of ports that must go out of service on an MPP before the MPP sends a warning-level event to Experience Portal and enters the Degraded state. Once the Reset value is reached, the MPP returns to the Running state. The Trigger default is 10 and the Reset default is 0.
Error	The Trigger field determines the percentage of ports that must go out of service on an MPP before the MPP sends an error-level event to Experience Portal and enters the Degraded state. Once the reset value is reached, the MPP will send another error event when appropriate, but it does not return to the Running state until the Reset value associated with the Warn field has been reached. The Trigger default is 20 and the Reset default is 10.
Fatal	The Trigger field determines the percentage of ports that must go out of service on an MPP before the MPP issues a fatal-level alarm and enters the Degraded state. Once the reset value is reached, the MPP will send another fatal event when appropriate, but it does not return to the Running state until the Trigger value associated with the Warn field has been reached. The Trigger default is 100 and the Reset default is 50.

Call Progress group

Field	Description
Threshold	The options are: • Voice — The Voice Threshold parameter is used by the call classification engine in determining whether a given frame of audio data should be interpreted as voice energy. Lower values are more inclusive and tends toward marking even white background noise as voice. Higher values will reject more noise, picking out only audio frames that are very clearly voice sounds. The range is 0.0-1.0 and the default value is 0.50 • Tone — The Tone Threshold parameter is used conjunctively along with Periodicity Threshold parameter by the call classification engine to determine if a given frame of audio data contains a pure telephony tone. Lower values for either or both will allow the call classification engine to accept more distorted signals as valid telephony tones, but makes certain voice sounds more likely to be detected as pure tones, for example, Talk Off. The range is 0.0-1.0 and the default value is 0.95. • Periodicity — The Periodicity Threshold parameter is used conjunctively with Tone Threshold by the call classification engine to determine if a given frame of audio data contains a pure telephony tone. Lower values for either or both will allow the call classification engine to accept more distorted signals as valid telephony tones, but makes certain voice sounds more likely to be detected as pure tones, for example, Talk Off. The range is 0.0-1.0 and the default is 97. • Ring Count — Ring Count Threshold detects the number of ring back cycles . The purpose is to let the call progress engine to use different timers when a call is answered “quickly”, as determined by the ring count, tailoring the parameters appropriately under the assumption that calls answered after a couple of rings are more likely to be a live person. The cycles range from 0-8 and the default value is 4.
Cut Through	The Cut Through time is the number of milliseconds of consecutive silence after some voice energy that must be heard to determine that a live speaker is done talking.  Note: Setting this value lower, increases the responsiveness of the system. The system finishes Live voice detection to finish sooner and the VoiceXML dialog starts playing sooner. However, the system risks false detections for recordings where there are long gaps between speech energy. For example, a voice mail system might play a short recorded greeting, followed by a TTS name, followed by some more recorded prompts. If the silence between the recorded greeting and the TTS name is longer than the cut through time, the voice mail machine is mistakenly identified as a live person. Setting the value higher increases the likelihood that a call is properly classified. The following are the values of Cut Through time: • Initial — The Initial values are loaded first when the call classification engine is initialized for any given call. The value ranges from 200-2000 milliseconds and the default is 1100 milliseconds.

Table continues...

Field	Description
	• Short — The values for the Short timers are loaded when the call classification engine detects at least one ring back cycle . The value ranges from 200-2000 milliseconds and the default is 700 milliseconds. • Long — The values for the Long timers are loaded if the call classification engine detects successive ring back cycles and the count equals or exceeds the Ring Count Threshold. The value ranges from 200–2000 milliseconds and the default is 1100 milliseconds. Which value is used is determined by the number of ring back cycles heard by the call classification engine and the Ring Count Threshold. The purpose is to let the call progress engine to use different timers when a call is answered “quickly”, as determined by the ring count, tailoring the parameters appropriately under the assumption that calls answered after a couple of rings are more likely to be a live person.
Max Voice	The Max Voice time is the number of milliseconds of continuous voice energy except gaps of silence shorter than the Cut Through time that must be heard to determine that a greeting is a recorded message.  Note: Setting this value lower biases the call classification engine toward detecting answering machines. All but very short greetings are assumed to be answering machines. Conversely, setting the value higher biases the call classification engine toward detecting live voice. For instance, a greeting must be very long to be considered an answering machine. The following are the values of Max Voice time: • Initial — The Initial value is loaded first when the call classification engine is initialized for any given call. The value ranges from 1100-4000 milliseconds and the default is 2500 milliseconds. • Short — The values for the Short timers are loaded when the call classification engine detects at least one ring back cycle. The value ranges from 1100–4000 milliseconds and the default is 2500 milliseconds. • Long — The values for the Long timers are loaded if the call classification engine detects successive ring back cycles and the count equals or exceeds the Ring Count Threshold. The value ranges from 1100–4000 milliseconds and the default is 2500 milliseconds. Which value is used is determined by the number of ring back cycles heard by the call classification engine and the Ring Count Threshold. The purpose is to let the call progress engine to use different timers when a call is answered “quickly”, as determined by the ring count, tailoring the parameters appropriately under the assumption that calls answered after a couple of rings are more likely to be a live person.

Miscellaneous group

Field	Description
Inband DTMF Detection Enabled	This option allows Experience Portal to interoperate with media gateways and SIP endpoints • Yes: Select Yes to enable this option. • No: Select No to disable this option. The default is No.  Note: If you make any change to the Inband DTMF Detection Enabled field, you must restart the MPP for the changes to take effect.
Pre-Energy Record Time	The maximum number of milliseconds of audio data that are inserted in the recordings before the system detects the energy. • Range: 0 to 30000. • Default: 0  Note: If you make any change to the Pre-Energy Record Time field, you must restart the MPP for the changes to take effect.
H323 Force Registration	Controls the behavior of the H.323 station registration process. The settings are: • Always: The setting Always causes the MPP to forcibly register an extension, immediately bringing a port into service by, potentially, taking control from any other endpoint that may currently have the extension registered. Any calls in progress on the other endpoint are dropped when control of the station is removed. • Never: The default setting of Never causes station registration to fail if a registering extension is already in use and registered by another endpoint. The port does not immediately come into service, but the station remains in use by the other endpoint until the station is released or unregistered. The default is Never.

Directory details of the EPM system components

Most Experience Portal components and log files are located in the directory that you specify during installation. However, several components cannot be relocated and are stored in fixed paths even if you specify a path that is different from the default installation directory.

The following table describes some of the components that are stored in fixed paths.

Standard RHEL packages that might be installed with or used by Experience Portal, such as Apache and NTP, are not included in this list.

Component	Directory
Experience Portal Manager web application	/opt/Tomcat/tomcat/webapps/VoicePortal
Avaya Aura® Experience Portal Management web services	/opt/Tomcat/tomcat/webapps/axis2
Application log manager	/opt/Tomcat/tomcat/webapps/axis
Alarm manager	/opt/Tomcat/tomcat/webapps/axis
Network log manager	/opt/Tomcat/tomcat/webapps/axis
Avaya License Manager	The co-located WebLM is installed in the /opt/Tomcat/tomcat/webapps/WebLM directory.  Note: If you use an external WebLM, the license manager may be installed in a different directory on the external system.
Experience Portal database	The Postgres files are installed in the /var/lib/pgsql directory.  Note: Most of the database data is in the /var/lib/pgsql/data directory.
Java	/usr/java
Tomcat for EPM and HTML	/opt/Tomcat
Tomcat for SMS and Email Processor	/opt/MMServer
Apache Axis: web services container	/opt/Tomcat/tomcat/webapps/axis
Apache Axis2: Web services container	/opt/Tomcat/tomcat/webapps/axis2
Postgres Database	/var/lib/pgsql
Experience Portal Backup	/opt/Avaya/backup
Install Agent	/opt/Avaya/InstallAgent
Core Services	/opt/coreservices, /opt/Avaya/CoreServiceConfig, /opt/Avaya/CoreServiceInstall

Determining the installation history on an Experience Portal server

About this task

You can check the following data related to the installation history on the Experience Portal server:

- The current version installed on the server by using the `iaversion.php` command.

- All versions since Avaya Aura® Experience Portal 7.1 that have been installed on the server by using the `iahistory.php` command.

Procedure

1. Log on to Linux on the Primary or Auxiliary EPM or MPP server.

If you are an Avaya Services representative, and use Avaya Enterprise Linux or if the Avaya Service accounts are installed on this server:

- Log on to the local Linux console as `sroot`.
- Or log on remotely as a non-root user and then change the user to `sroot` by entering the `su - sroot` command.

Otherwise, log on to Linux locally as `root`, or log in remotely as a non-root user and then change the user to `root` by entering the `su -` command.

2. Navigate to the `$AVAYA_HOME/Support/VP-Tools` directory.
3. To search for the current installation that has been made in any subdirectory under `$AVAYA_HOME`, enter the `./iaversion.php` command
4. To search for all installations, made in any subdirectory under `$AVAYA_HOME`, enter the `bash ./iahistory.php` command.

Configuring the PostgreSQL database user accounts

Before you begin

If you have just installed the EPM software and are still logged into the EPM server, make sure that the environment variables are properly loaded as described in the *Reloading the Avaya Aura® Experience Portal environment variables* topic in the *Implementing Avaya Aura® Experience Portal on multiple servers* guide.

About this task

Experience Portal uses the following PostgreSQL user accounts:

Default account name	Description
postgres	The database administrator can use this account to log in to the local Avaya Aura® Experience Portal database and perform database administration tasks. The password for this account is automatically generated. You cannot add other accounts of this type, delete this account, or change the account name.

Table continues...

Default account name	Description
	 Important: Contact the Avaya Services representative to modify the local VoicePortal database as the database contains critical configuration information used to run the system.
report	This user account can only read those tables in the Experience Portal database that store report data. Speech application developers can use this account to log in to the database to create custom reports using any SQL-enabled report generation tool. You can have any number of accounts of this type with any account names.
reportwriter	This user account can only change the data in the tables that store report data in the Experience Portal database on the Auxiliary EPM server. You can have any number of accounts of this type with any account names.  Important: Contact the Avaya Services representative to modify the tables that store report data in the local VoicePortal database.
vpcommon	This account allows the Auxiliary EPM servers limited access to the main Experience Portal database, and it is required if you plan to configure an Auxiliary EPM server. You can delete this account or set the password for it, but you cannot add other accounts of this type or change the account name.

The `SetDbPassword.sh` script allows you to change all account passwords and add and delete all accounts except for postgres, which cannot be deleted.

Procedure

1. Log in to Linux on the Primary EPM or Auxiliary EPM server.

If you are an Avaya Services representative and are using Avaya Enterprise Linux, or if the Avaya Service accounts are installed on this server:

- Log in to the local Linux console as `sroot`.
- Or log in remotely as a non-root user and enter the `su - sroot` command to change the user to `sroot`.

Otherwise, log in to Linux locally as `root`, or log in remotely as a non-root user and enter the `su -` command to change the user to `root`.

2. Enter the `cd $AVAYA_HOME/Support/VP-Tools/SetDbPassword` command.

`$AVAYA_HOME` is an environmental variable pointing to the name of the installation directory specified during the Experience Portal software installation.

3. Enter `bash SetDbPassword.sh` followed by the additional parameters to perform the required operation.

For the details on the supported operations, see the following step.

4. If you want to:

View a list of all Avaya Aura® Experience Portal PostgreSQL accounts	Enter the <code>bash SetDbPassword.sh list</code> command.
Change the password for a PostgreSQL user account	a. Enter the <code>bash SetDbPassword.sh update -u <i>username</i></code> command, where: <i>username</i> is the name of the user account whose password you want to change b. Type the password you want to use for this account and press <code>Enter</code>.  Note: If you change the password for the: • <code>postgres</code> account, Avaya Aura® Experience Portal stops and then restarts the <code>vpms</code> service. • <code>vpcommon</code> account on the Primary EPM server, you must also change the password on the Auxiliary EPM server as well.
Generate a random password for the PostgreSQL user account <code>postgres</code>	Enter the <code>bash SetDbPassword.sh reset_postgres</code> command.
Add a new report user with read only privileges	a. Enter the <code>bash SetDbPassword.sh add_report_r -u <i>username</i></code> command, where: <i>username</i> is the PostgreSQL account name for the new report user b. Type the password you want to use for this account and press <code>Enter</code>.
Add a new report user with read/write privileges on an Auxiliary EPM server  Note: You cannot add a report user with read/write privileges on the Primary EPM server.	a. Enter the <code>bash SetDbPassword.sh add_aux_report_w -u <i>username</i></code> command, where: <i>username</i> is the PostgreSQL account name for the new report user b. Type the password you want to use for this account and press <code>Enter</code>.
Delete a report account from either EPM server or delete the <code>vpcommon</code> account from the Primary EPM server  Note: You cannot delete the <code>postgres</code> user account.	Enter the <code>bash SetDbPassword.sh delete -u <i>username</i></code> command, where <i>username</i> is either <code>vpcommon</code> or the report account name that you want to delete. For example, to delete the report account named <code>RptReadWrite</code>, you would enter:

	<code>bash SetDbPassword.sh delete -u RptReadWrite</code>
Add the vpcommon user account on the Primary EPM server so that an Auxiliary EPM server can access the database  Note: You cannot add the vpcommon account to an Auxiliary EPM server.	a. Enter the <code>bash SetDbPassword.sh add_primary_vpcommon</code> command. b. Type the password you want to use for this account and press Enter.
Verify the vpcommon user on the local database that can connect to the 'auxname' (Auxiliary EPM) This option is applicable only on the Primary EPM.	Enter the <code>bash SetDbPassword.sh verify_aux_vpcommon -a auxname</code> command where: -a auxname is the configured name for the Auxiliary EPM.
Verify the Primary EPM's vpcommon user. This option is applicable only on the Auxiliary EPM.	Enter the <code>bash SetDbPassword.sh verify_primary_vpcommon</code> command.
View the help for this command	Enter the <code>bash SetDbPassword.sh help</code> command.

Importing a Primary EPM server security certificate

Before you begin

- Ensure that the Primary EPM server is not processing any multi-channel messages such as Emails or SMS.
- If a managed application is installed, you might need to perform additional steps before and after the server certificate is updated. For more information, see the documentation of the managed application.

About this task

Use the `ImportServerCertificate.sh` script to import a self-signed or third party signed certificate for the Primary EPM without the need to re-install the Experience Portal software.

Procedure

1. Log in to Linux on the Primary EPM server.

If you are an Avaya service representative, and use Avaya Enterprise Linux or if the Avaya services account are installed on this server:

- Log in to the local Linux console as `sroot`.
- Or log in remotely as a non-root user and then change the user to `sroot` by entering the `su - sroot` command.

Otherwise, log in to Linux locally as root, or log in remotely as a non-root user and then change the user to root by entering the `su -` command.

2. Stop the services in the following order:

- a. If the appserver service is installed, stop the service by entering the `/sbin/service appserver stop` command.
- b. Stop the avpSNMPAgentSvc service by entering the `/sbin/service avpSNMPAgentSvc stop` command.
- c. Stop the epmcompmgr service by entering the `/sbin/service epmcompmgr stop` command.
- d. Stop the mmsserver service by entering the `/sbin/service mmsserver stop` command.
- e. Stop the vpms service by entering the `/sbin/service vpms stop` command.
- f. Stop the httpd service by entering the `/sbin/service httpd stop` command.

3. If Experience Portal is installed in a virtualized environment:

- a. Navigate to the directory where the ImportServerCertificate.sh script is located by entering the `cd /opt/Avaya/VE/bin` command.
- b. Skip step 4, 5 and 6.

 Note:

If Experience Portal is not installed in a virtualized environment, skip this step.

4. Mount the Avaya Aura Experience Portal 7.1 software installation DVD. The mount command depends on the server's hardware and operating system.

- If you are working with Avaya Enterprise Linux, mount the DVD by entering the `mount /mnt/cdrom` command, where `/mnt/cdrom` is the mount point typically associated with the DVD drive in the `fstab` file.
- If you working with a supported version of Red Hat Enterprise Linux Server, to mount the DVD:
 - Run the `mkdir /media/cdrom` command.

 Note:

This command is required only if the `/media/cdrom` mount point does not exist.

- Run the `mount /dev/cdrom /media/cdrom` command.

 Warning:

When the Red Hat Enterprise Linux Server automatically mounts the DVD, the files on the DVD are not executable. You must manually mount the Experience Portal installation DVD using the command shown above.

5. If the mount commands shown above do not work, consult your server documentation for the appropriate mount command.

6. Change to the mount point directory and navigate to the Utilities directory.
7. Enter the `bash ImportServerCertificate.sh --server` command.

The system prompts you to enter the file path and the name of the security certificate.

8. Type the file path and name of the security certificate, and press `Enter`.

 Note:

- The certificate is in PKCS#12 format. The certificate must be formatted as PKCS#12 file. A PKCS#12 file includes a certificate and the corresponding key. The certificate is encrypted and requires a password. If the certificate is not self-signed, then the PKCS#12 file must include all CA certificates.
- If the **Extended Key Usage** is specified in the X509.V3 certificate extension, specify `Server Authentication`, also called as `serverAuth`, and `Client Authentication`, also called as `clientAuth`, for the usage.
- The certificate resides on a local server or on an NFS-mounted drive that is locally accessible.

The system prompts you to enter the password for the security certificate.

9. Type the password for the security certificate, and press `Enter`.

The system displays the imported certificate content.

10. Enter `Y` to accept the imported certificate or enter `n` to cancel.

11. Start the services in the following order:

- a. Start the `httpd` service by entering the `/sbin/service httpd start` command.
- b. Start the `vpms` service by entering the `/sbin/service vpms start` command.
- c. Start the `mmsserver` service by entering the `/sbin/service mmsserver start` command.
- d. Start the `epmcompmgr` service by entering the `/sbin/service epmcompmgr start` command.
- e. Start the `avpSNMPAgentSvc` service by entering the `/sbin/service avpSNMPAgentSvc start` command.
- f. If the `appserver` service is installed, start the `appserver` service by entering the `/sbin/service appserver start` command.

12. Accept the new certificate on all Auxiliary EPMs and MPPs as described in the following steps:

- a. On each auxiliary EPM and MPP, log in to the console as root user.
- b. Navigate to `$AVAYA_HOME/Support/VP-Tools`.
- c. Run the `./setup_vpms.php <Primary EPM>` command where Primary EPM is the IP address or hostname of the Primary EPM.
- d. Type `Y`, and press `Enter` to accept the new certificate.

*** Note:**

For NTP service, type `Y`, and press `Enter` to use EPM for NTP service.

Importing an Auxiliary EPM server security certificate

Before you begin

- Ensure that the Auxiliary EPM server is not processing any multi-channel messages such as Emails or SMS.
- If a managed application is installed, you might need to perform additional steps before and after the server certificate is updated. For more information, see the documentation of the managed application.

About this task

Use the `ImportServerCertificate.sh` script to import a self-signed or third party certificate for the Auxiliary EPM without the need to re-install the Experience Portal software.

Procedure

1. Log in to Linux on the Auxiliary EPM server.

If you are an Avaya Services representative, and use Avaya Enterprise Linux or if the Avaya Service accounts are installed on this server:

- Log on to the local Linux console as `sroot`.
- Or log on remotely as a non-root user and then change the user to `sroot` by entering the `su - sroot` command.

Otherwise, log on to Linux locally as `root`, or log in remotely as a non-root user and then change the user to `root` by entering the `su -` command.

2. Stop the services in the following order:
 - a. If the `appserver` service is installed, stop the service by entering the `/sbin/service appserver stop` command.
 - b. Stop the `epmcompmgr` service by entering the `/sbin/service epmcompmgr stop` command.
 - c. Stop the `mmsserver` service by entering the `/sbin/service mmsserver stop` command.
 - d. Stop the `vpms` service by entering the `/sbin/service vpms stop` command.
 - e. Stop the `httpd` service by entering the `/sbin/service httpd stop` command.
3. If Experience Portal is installed in a virtualized environment:
 - a. Navigate to the directory where the `ImportServerCertificate.sh` script is located by entering the `cd /opt/Avaya/VE/bin` command.

- b. Skip step 4, 5 and 6.

 Note:

If Experience Portal is not installed in a virtualized environment, skip this step.

4. Mount the Avaya Aura Experience Portal 7.1 software installation DVD. The mount command depends on the server's hardware and operating system.

- If you are working with Avaya Enterprise Linux, mount the DVD by entering the `mount /mnt/cdrom` command, where `/mnt/cdrom` is the mount point typically associated with the DVD file in the `fstab` file.
- If you are working with a supported version of Red Hat Enterprise Linux Server to mount the DVD:

- Run the `mkdir /media/cdrom` command.

 Note:

This command is required only if the `/media/cdrom` mount point does not exist

- Run the `mount /dev/cdrom /media/cdrom` command

 Warning:

When Red Hat Enterprise Linux Server automatically mounts the DVD, the files on the DVD are not executable. You must manually mount the Experience Portal installation DVD using the commands shown above

5. If the mount command shown above do not work, consult your server documentation for the appropriate mount commands.
6. Change to the mount point directory and navigate to the Utilities directory.
7. Enter the `bash ImportServerCertificate.sh --server` command.
- The system prompts you to enter the file path and the name of the security certificate.
8. Type the file path and name of the security certificate, and press `Enter`.

 Note:

- The certificate is in PKCS12 format. The certificate must be formatted as a PKCS#12 file. A PKCS#12 file includes a certificate and the corresponding key. The certificate is encrypted and requires a password. If the certificate is not self-signed, then the PKCS#12 file must include all CA certificates.
- If the Extended Key Usage is specified in the X509.V3 certificate extension, specify `Server Authentication`, also called as `serverAuth`, and `Client Authentication`, also called as `clientAuth`, for the usage.
- The certificate resides on the local server or on an NFS-mounted drive that is locally accessible.

The system prompts you to enter the password for the security certificate.

9. Type the password for the security certificate, and press `Enter`.

The system displays the imported certificate content.

10. Enter `y` to accept the imported certificate or enter `n` to cancel.
11. Start the services in the following order:
 - a. Start the `httpd` service by entering the `/sbin/service httpd start` command.
 - b. Start the `vpms` service by entering the `/sbin/service vpms start` command.
 - c. Start the `mmsserver` service by entering the `/sbin/service mmsserver start` command.
 - d. Start the `epmcompmgr` service by entering the `/sbin/service epmcompmgr start` command.
 - e. If the `appserver` service is installed, start the `appserver` service by entering the `/sbin/service appserver start` command.
12. Reestablish the link between the Primary EPM and the Auxiliary EPM:
 - a. Log in to the EPM Web interface using an account with the Administration user role.
 - b. From the EPM main menu, select **System Configuration > EPM Servers**.
 - c. Click the name of the Auxiliary EPM server.
 - d. On the **Change EPM Server** page, navigate to the **Auxiliary EPM Certificate** section and select the **Trust new certificate** check box if the check box is visible.
 - e. Click **Save**.
 - f. From the EPM main menu, select **Real-Time Monitoring > System Monitor**.

If the Config of the MPP displays **Restart needed**, you must restart the MPP.

Importing a MPP server security certificate

Before you begin

- Ensure that the MPP server is not handling any calls.
- If a managed application is installed, you might need to perform additional steps before and after the server certificate is updated. For more information, see the documentation of the managed application.

About this task

Use the `ImportServerCertificate.sh` script to import a self-signed or third party certificate for the MPP without the need to re-install the Experience Portal software.

Procedure

1. Log in to Linux on the MPP server.

If you are an Avaya Services representative, and use Avaya Enterprise Linux or if the Avaya Service accounts are installed on this server:

- Log on to the local Linux console as `sroot`.
- Or log on remotely as a non-root user and then change the user to `sroot` by entering the `su - sroot` command.

Otherwise, log on to Linux locally as root, or log in remotely as a non-root user and then change the user to root by entering the `su -` command.

2. Stop the services in the following order:

- a. Stop the MPP service by entering the `/sbin/service mpp stop` command.
- b. Stop the httpd service by entering the `/sbin/service httpd stop` command.

3. If Experience Portal is installed in a virtualized environment:

- a. Navigate to the directory where the `ImportServerCertificate.sh` script is located by entering the `cd /opt/Avaya/VE/bin` command.
- b. Skip step 4, 5 and 6.

 Note:

If Experience Portal is not installed in a virtualized environment, skip this step.

4. Mount the Avaya Aura® Experience Portal 7.1 software installation DVD. The `mount` command depends on the server's hardware and operating system.

- If you are working with Avaya Enterprise Linux, mount the DVD by entering the `mount /mnt/cdrom` command, where `/mnt/cdrom` is the mount point typically associated with the DVD drive in the `fstab` file.
- If you are working with a supported version of Red Hat Enterprise Linux Server, to mount the DVD:
 - Run the `mkdir /media/cdrom` command.

 Note:

This command is required only if the `/media/cdrom` mount point does not exist.

- Run the `mount /dev/cdrom /media/cdrom` command.

 Warning:

When Red Hat Enterprise Linux Server automatically mounts the DVD, the files on the DVD are not executable. You must manually mount the Experience Portal installation DVD using the commands shown above.

If the previous installation directory is different from the default directory, you must type the old path prior to pressing the enter key.

5. If the mount commands shown above do not work, consult your server documentation for the appropriate mount command
6. Change to the mount point directory and navigate to the Utilities directory.

7. Enter the `bash ImportServerCertificate.sh --server` command.

The system prompts you to enter the file path and the name of the security certificate.

8. Type the file path and name of the security certificate, and press `Enter`.

*** Note:**

- The certificate is in PKCS#12 format. The certificate must be formatted as PKCS#12 file. A PKCS#12 file includes a certificate and the corresponding key. The certificate is encrypted and requires a password. If the certificate is not self-signed, then the PKCS#12 file must include all CA certificates.
- If the **Extended Key Usage** is specified in the X509.V3 certificate extension, specify `Server Authentication`, also called as `serverAuth`, and `Client Authentication`, also called as `clientAuth`, for the usage.
- The certificate resides on the local server or on an NFS-mounted drive that is locally accessible.

The system prompts you to enter the password for the security certificate.

9. Type the password for the security certificate, and press `Enter`.

The system displays the imported certificate content.

10. Enter `y` to accept the imported certificate or enter `n` to cancel.

11. Start the services in the following order:

- a. Start the `httpd` service by entering the `/sbin/service httpd start` command.
- b. Start the `MPP` service by entering the `/sbin/service mpp start` command.

12. Reestablish the link between the Primary EPM and the MPP:

- a. Log in to the EPM Web interface using an account with the Administration user role.
- b. From the EPM main menu, select **System Configuration > MPP Servers**.
- c. Click the name of the MPP server.
- d. On the **Change MPP Server** page, navigate to the **MPP Certificate** section and select the **Trust new certificate** check box if the check box is visible.
- e. Click **Save**.

Importing a Single server security certificate

Before you begin

- Ensure that the Single EPM server is not processing any multi-channel messages such as Emails or SMS.

- If a managed application is installed, you might need to perform additional steps before and after the server certificate is updated. For more information, see the documentation of the managed application.

About this task

Use the `ImportServerCertificate.sh` script to import a self-signed or third party certificate for the Single EPM without the need to re-install the Experience Portal software.

Procedure

1. Log in to Linux on the Single EPM server.

If you are an Avaya Services representative, and use Avaya Enterprise Linux or if the Avaya Service accounts are installed on this server:

- Log on to the local Linux console as `sroot`.
- Or log on remotely as a non-root user and then change the user to `sroot` by entering the `su - sroot` command.

Otherwise, log on to Linux locally as `root`, or log in remotely as a non-root user and then change the user to `root` by entering the `su -` command.

2. Stop the services in the following order:
 - a. If the MPP service is installed, stop the service by entering the `/sbin/service mpp stop` command.
 - b. If the appserver service is installed, stop the service by entering the `/sbin/service appserver stop` command.
 - c. Stop the avpSNMPAgentSvc service by entering the `/sbin/service avpSNMPAgentSvc stop` command.
 - d. Stop the epmcompmgr service by entering the `/sbin/service epmcompmgr stop` command.
 - e. Stop the mmsserver service by entering the `/sbin/service mmsserver stop` command.
 - f. Stop the vpms service by entering the `/sbin/service vpms stop` command.
 - g. Stop the httpd service by entering the `/sbin/service httpd stop` command.
3. If Experience Portal is installed in a virtualized environment:
 - a. Navigate to the directory where the `ImportServerCertificate.sh` script is located by entering the `cd /opt/Avaya/VE/bin` command.
 - b. Skip step 4, 5 and 6.

Note:

If Experience Portal is not installed in a virtualized environment, skip this step.

4. Mount the Avaya Aura® Experience Portal 7.1 software installation DVD. The `mount` command depends on the server's hardware and operating system.
 - If you are working with Avaya Enterprise Linux, mount the DVD by entering the `mount /mnt/cdrom` command, where `/mnt/cdrom` is the mount point typically associated with the DVD drive in the `fstab` file.
 - If you are working with a supported version of Red Hat Enterprise Linux Server, to mount the DVD:
 - Run the `mkdir /media/cdrom` command.

 Note:

This command is required only if the `/media/cdrom` mount point does not exist.

- Run the `mount /dev/cdrom /media/cdrom` command.

 Warning:

When Red Hat Enterprise Linux Server automatically mounts the DVD, the files on the DVD are not executable. You must manually mount the Experience Portal installation DVD using the commands shown above.

If the previous installation directory is different from the default directory, you must type the old path prior to pressing the enter key.

5. If the mount commands shown above do not work, consult your server documentation for the appropriate mount command.
6. Change to the mount point directory and navigate to the Utilities directory.
7. Enter the `bash ImportServerCertificate.sh --server` command.

The system prompts you to enter the file path and the name of the security certificate.

8. Type the file path and name of the security certificate, and press `Enter`.

 Note:

- The certificate is in PKCS#12 format. The certificate must be formatted as PKCS#12 file. A PKCS#12 file includes a certificate and the corresponding key. The certificate is encrypted and requires a password. If the certificate is not self-signed, then the PKCS#12 file must include all CA certificates.
- If the **Extended Key Usage** is specified in the X509.V3 certificate extension, specify `Server Authentication`, also called as `serverAuth`, and `Client Authentication`, also called as `clientAuth`, for the usage.
- The certificate resides on the local server or on an NFS-mounted drive that is locally accessible.

The system prompts you to enter the password for the security certificate.

9. Type the password for the security certificate, and press `Enter`.

The system displays the imported certificate content.

10. Enter `y` to accept the imported certificate or enter `n` to cancel.
11. Start the services in the following order:
 - a. Start the `httpd` service by entering the `/sbin/service httpd start` command.
 - b. Start the `vpms` service by entering the `/sbin/service vpms start` command.
 - c. Start the `mmsserver` service by entering the `/sbin/service mmsserver start` command.
 - d. Start the `epmcompmgr` service by entering the `/sbin/service epmcompmgr start` command.
 - e. Start the `avpSNMPAgentSvc` service by entering the `/sbin/service avpSNMPAgentSvc start` command.
 - f. If the `appserver` service is installed, start the `appserver` service by entering the `/sbin/service appserver start` command.
 - g. Start the `MPP` service by entering the `/sbin/service mpp start` command.
12. Accept the new certificate on the MPP as described in the following steps:
 - a. Log in to the console as root user on the Single server.
 - b. Navigate to `$AVAYA_HOME/Support/VP-Tools`.
 - c. Run the `./setup_vpms.php <Primary EPM>` command where Primary EPM is the IP address or hostname of the Primary EPM.
 - d. Type `y`, and press `Enter` to accept the new certificate.

 Note:

For NTP service, type `y`, and press `Enter` to use EPM for NTP service.

Generating a new Primary EPM server security certificate

Before you begin

- Ensure that the Primary EPM server is not processing any multi channel messages such as Emails or SMS.
- If a managed application is installed, you might need to perform additional steps before and after the server certificate is updated. For more information, see the documentation of the managed application.

About this task

Use the `GenerateServerCertificate.sh` script to generate a new SHA256 signature hash 2048 bits self-signed server certificate for the Primary EPM without the need to re-install the Experience Portal software.

Procedure

1. Log in to Linux on the Primary EPM server.

If you are an Avaya Services representative, and use Avaya Enterprise Linux or if the Avaya Service accounts are installed on this server:

- Log on to the local Linux console as `sroot`.
- Or log on remotely as a non-root user and then change the user to `sroot` by entering the `su - sroot` command.

Otherwise, log on to Linux locally as root, or log in remotely as a non-root user and then change the user to root by entering the `su -` command.

2. Stop the services in the following order:

- a. If the `appserver` service is installed, stop the service by entering the `/sbin/service appserver stop` command.
- b. Stop the `avpSNMPAgentSvc` service by entering the `/sbin/service avpSNMPAgentSvc stop` command.
- c. Stop the `epmcompmgr` service by entering the `/sbin/service epmcompmgr stop` command.
- d. Stop the `mmsserver` service by entering the `/sbin/service mmsserver stop` command.
- e. Stop the `vpms` service by entering the `/sbin/service vpms stop` command.
- f. Stop the `httpd` service by entering the `/sbin/service httpd stop` command.

3. If Experience Portal is installed in a virtualized environment:

- a. Navigate to the directory where the `GenerateServerCertificate.sh` script is located by entering the `cd /opt/Avaya/VE/bin` command.
- b. Skip steps 4, 5 and 6.

Note:

If Experience Portal is not installed in a virtualized environment, skip this step.

4. Mount the Avaya Aura® Experience Portal 7.1 software installation DVD. The `mount` command depends on the server's hardware and operating system.

- If you are working with Avaya Enterprise Linux, mount the DVD by entering the `mount /mnt/cdrom` command, where `/mnt/cdrom` is the mount point typically associated with the DVD drive in the `fstab` file.
- If you are working with a supported version of Red Hat Enterprise Linux Server, to mount the DVD:
 - Run the `mkdir /media/cdrom` command.

 Note:

This command is required only if the `/media/cdrom` mount point does not exist.

- Run the `mount /dev/cdrom /media/cdrom` command.

 Warning:

When Red Hat Enterprise Linux Server automatically mounts the DVD, the files on the DVD are not executable. You must manually mount the Experience Portal installation DVD using the commands shown above.

If the previous installation directory is different from the default directory, you must type the old path prior to pressing the enter key.

5. Change to the mount point directory and navigate to the `Utilities` directory.
6. Enter the `bash GenerateServerCertificate.sh` command.

The system displays the newly generated SHA256 signature hash 2048 bits certificate content of the security certificate.

7. Enter `Y` to accept the certificate or enter `n` to cancel.
8. Start the services in the following order:
 - a. Start the `httpd` service by entering the `/sbin/service httpd start` command.
 - b. Start the `vpms` service by entering the `/sbin/service vpms start` command.
 - c. Start the `mmsserver` service by entering the `/sbin/service mmsserver start` command.
 - d. Start the `epmcompmgr` service by entering the `/sbin/service epmcompmgr start` command.
 - e. Start the `avpSNMPAgentSvc` service by entering the `/sbin/service avpSNMPAgentSvc start` command.
 - f. If the `appserver` service is installed, start the `appserver` service by entering the `/sbin/service appserver start` command.
9. Accept the new certificate on all Auxiliary EPMs and MPPs as described in the following steps:
 - a. On each auxiliary EPM and MPP, log in to the console as root user.
 - b. Navigate to `$AVAYA_HOME/Support/VP-Tools`.
 - c. Run the `./setup_vpms.php <Primary EPM>` command where Primary EPM is the IP address or hostname of the Primary EPM.
 - d. Type `Y`, and press `Enter` to accept the new certificate.

 Note:

For NTP service, type `Y`, and press `Enter` to use EPM for NTP service.

Generating a new Auxiliary EPM server security certificate

Before you begin

- Ensure that the Auxiliary EPM server is not processing any multi channel messages such as Emails or SMS.
- If a managed application is installed, you might need to perform additional steps before and after the server certificate is updated. For more information, see the documentation of the managed application.

About this task

Use the GenerateServerCertificate.sh script to generate a new SHA256 signature hash 2048 bits self-signed server certificate for the Auxiliary EPM without the need to re-install the Experience Portal software.

Procedure

1. Log in to Linux on the Auxiliary EPM server.

If you are an Avaya Services representative, and use Avaya Enterprise Linux or if the Avaya Service accounts are installed on this server:

- Log on to the local Linux console as `sroot`.
- Or log on remotely as a non-root user and then change the user to `sroot` by entering the `su - sroot` command.

Otherwise, log on to Linux locally as `root`, or log in remotely as a non-root user and then change the user to `root` by entering the `su -` command.

2. Stop the services in the following order:

- a. If the `appserver` service is installed, stop the service by entering the `/sbin/service appserver stop` command.
- b. Stop the `epmcompmgr` service by entering the `/sbin/service epmcompmgr stop` command.
- c. Stop the `mmsserver` service by entering the `/sbin/service mmsserver stop` command.
- d. Stop the `vpms` service by entering the `/sbin/service vpms stop` command.
- e. Stop the `httpd` service by entering the `/sbin/service httpd stop` command.

3. If Experience Portal is installed in a virtualized environment:

- a. Navigate to the directory where the `GenerateServerCertificate.sh` script is located by entering the `cd /opt/Avaya/VE/bin` command.
- b. Skip steps 4, 5 and 6.

Note:

If Experience Portal is not installed in a virtualized environment, skip this step.

4. Mount the Avaya Aura® Experience Portal 7.1 software installation DVD. The `mount` command depends on the server's hardware and operating system.
 - If you are working with Avaya Enterprise Linux, mount the DVD by entering the `mount /mnt/cdrom` command, where `/mnt/cdrom` is the mount point typically associated with the DVD drive in the `fstab` file.
 - If you are working with a supported version of Red Hat Enterprise Linux Server, to mount the DVD:
 - Run the `mkdir /media/cdrom` command.

 Note:

This command is required only if the `/media/cdrom` mount point does not exist.

- Run the `mount /dev/cdrom /media/cdrom` command.

 Warning:

When Red Hat Enterprise Linux Server automatically mounts the DVD, the files on the DVD are not executable. You must manually mount the Experience Portal installation DVD using the commands shown above.

If the previous installation directory is different from the default directory, you must type the old path prior to pressing the enter key.

5. Change to the mount point directory and navigate to the `Utilities` directory.
6. Enter the `bash GenerateServerCertificate.sh` command.

The system displays the newly generated SHA256 signature hash 2048 bits certificate content of the security certificate.
7. Enter `y` to accept the certificate or enter `n` to cancel.
8. Start the services in the following order:
 - a. Start the `httpd` service by entering the `/sbin/service httpd start` command.
 - b. Start the `vpms` service by entering the `/sbin/service vpms start` command.
 - c. Start the `mmsserver` service by entering the `/sbin/service mmsserver start` command.
 - d. Start the `epmcompmgr` service by entering the `/sbin/service epmcompmgr start` command.
 - e. If the `appserver` service is installed, start the `appserver` service by entering the `/sbin/service appserver start` command.
9. Reestablish the link between the Primary EPM and the Auxiliary EPM:
 - a. Log in to the EPM Web interface using an account with the Administration user role.
 - b. From the EPM main menu, select **System Configuration > EPM Servers**.
 - c. Click the name of the Auxiliary EPM server.

- d. On the **Change EPM Server** page, navigate to the **Auxiliary EPM Certificate** section and select the **Trust new certificate** check box if the check box is visible.
- e. Click **Save**.
- f. From the EPM main menu, select **Real-Time Monitoring > System Monitor**.
If the Config of the MPP displays **Restart needed**, you must restart the MPP.

Generating a new MPP server security certificate

Before you begin

- Ensure that the MPP server is not handling any calls.
- If a managed application is installed, you might need to perform additional steps before and after the server certificate is updated. For more information, see the documentation of the managed application.

About this task

Use the `GenerateServerCertificate.sh` script to generate a new SHA256 signature hash 2048 bits self-signed server certificate for the MPP without the need to re-install the Experience Portal software.

Procedure

1. Log in to Linux on the MPP server.

If you are an Avaya Services representative, and use Avaya Enterprise Linux or if the Avaya Service accounts are installed on this server:

- Log on to the local Linux console as `sroot`.
- Or log on remotely as a non-root user and then change the user to `sroot` by entering the `su - sroot` command.

Otherwise, log on to Linux locally as root, or log in remotely as a non-root user and then change the user to root by entering the `su -` command.

2. Stop the services in the following order:
 - a. Stop the MPP service by entering the `/sbin/service mpp stop` command.
 - b. Stop the httpd service by entering the `/sbin/service httpd stop` command.
3. If Experience Portal is installed in a virtualized environment:
 - a. Navigate to the directory where the `GenerateServerCertificate.sh` script is located by entering the `cd /opt/Avaya/VE/bin` command.
 - b. Skip steps 4, 5 and 6.

 Note:

If Experience Portal is not installed in a virtualized environment, skip this step.

4. Mount the Avaya Aura® Experience Portal 7.1 software installation DVD. The `mount` command depends on the server's hardware and operating system.
 - If you are working with Avaya Enterprise Linux, mount the DVD by entering the `mount /mnt/cdrom` command, where `/mnt/cdrom` is the mount point typically associated with the DVD drive in the `fstab` file.
 - If you are working with a supported version of Red Hat Enterprise Linux Server, to mount the DVD:
 - Run the `mkdir /media/cdrom` command.

 Note:

This command is required only if the `/media/cdrom` mount point does not exist.

- Run the `mount /dev/cdrom /media/cdrom` command.

 Warning:

When Red Hat Enterprise Linux Server automatically mounts the DVD, the files on the DVD are not executable. You must manually mount the Experience Portal installation DVD using the commands shown above.

If the previous installation directory is different from the default directory, you must type the old path prior to pressing the enter key.

5. Change to the mount point directory and navigate to the `Utilities` directory.
6. Enter the `bash GenerateServerCertificate.sh` command.

The system displays the newly generated SHA256 signature hash 2048 bits certificate content of the security certificate.

7. Enter `y` to accept the certificate or enter `n` to cancel.
8. Start the services in the following order:
 - a. Start the `httpd` service by entering the `/sbin/service httpd start` command.
 - b. Start the `MPP` service by entering the `/sbin/service mpp start` command.
9. Reestablish the link between the Primary EPM and the MPP:
 - a. Log in to the EPM Web interface using an account with the Administration user role.
 - b. From the EPM main menu, select **System Configuration > MPP Servers**.
 - c. Click the name of the MPP server.
 - d. On the **Change MPP Server** page, navigate to the **MPP Certificate** section and select the **Trust new certificate** check box if the check box is visible.
 - e. Click **Save**.

Generating a new Single server security certificate

Before you begin

- Ensure that the Single EPM server is not processing any multi channel messages such as Emails or SMS.
- If a managed application is installed, you might need to perform additional steps before and after the server certificate is updated. For more information, see the documentation of the managed application.

About this task

Use the GenerateServerCertificate.sh script to generate a new SHA256 signature hash 2048 bits self-signed server certificate for the EPM without the need to re-install the Experience Portal software.

Procedure

1. Log in to Linux on the Single EPM server.

If you are an Avaya Services representative, and use Avaya Enterprise Linux or if the Avaya Service accounts are installed on this server:

- Log on to the local Linux console as `sroot`.
- Or log on remotely as a non-root user and then change the user to `sroot` by entering the `su - sroot` command.

Otherwise, log on to Linux locally as `root`, or log in remotely as a non-root user and then change the user to `root` by entering the `su -` command.

2. Stop the services in the following order:

- a. If the MPP service is installed, stop the service by entering the `/sbin/service mpp stop` command.
- b. If the appserver service is installed, stop the service by entering the `/sbin/service appserver stop` command.
- c. Stop the avpSNMPAgentSvc service by entering the `/sbin/service avpSNMPAgentSvc stop` command.
- d. Stop the epmcompmgr service by entering the `/sbin/service epmcompmgr stop` command.
- e. Stop the mmsserver service by entering the `/sbin/service mmsserver stop` command.
- f. Stop the vpms service by entering the `/sbin/service vpms stop` command.
- g. Stop the httpd service by entering the `/sbin/service httpd stop` command.

3. If Experience Portal is installed in a virtualized environment:

- a. Navigate to the directory where the GenerateServerCertificate.sh script is located by entering the `cd /opt/Avaya/VE/bin` command.

- b. Skip steps 4, 5 and 6.

 Note:

If Experience Portal is not installed in a virtualized environment, skip this step.

4. Mount the Avaya Aura® Experience Portal 7.1 software installation DVD. The `mount` command depends on the server's hardware and operating system.
 - If you are working with Avaya Enterprise Linux, mount the DVD by entering the `mount /mnt/cdrom` command, where `/mnt/cdrom` is the mount point typically associated with the DVD drive in the `fstab` file.
 - If you are working with a supported version of Red Hat Enterprise Linux Server, to mount the DVD:
 - Run the `mkdir /media/cdrom` command.

 Note:

This command is required only if the `/media/cdrom` mount point does not exist.

- Run the `mount /dev/cdrom /media/cdrom` command.

 Warning:

When Red Hat Enterprise Linux Server automatically mounts the DVD, the files on the DVD are not executable. You must manually mount the Experience Portal installation DVD using the commands shown above.

If the previous installation directory is different from the default directory, you must type the old path prior to pressing the enter key.

5. Change to the mount point directory and navigate to the `Utilities` directory.
6. Enter the `bash GenerateServerCertificate.sh` command.

The system displays the newly generated SHA256 signature hash 2048 bits certificate content of the security certificate.

7. Enter `y` to accept the certificate or enter `n` to cancel.
8. Start the services in the following order:
 - a. Start the `httpd` service by entering the `/sbin/service httpd start` command.
 - b. Start the `vpms` service by entering the `/sbin/service vpms start` command.
 - c. Start the `mmsserver` service by entering the `/sbin/service mmsserver start` command.
 - d. Start the `epmcompmgr` service by entering the `/sbin/service epmcompmgr start` command.
 - e. Start the `avpSNMPAgentSvc` service by entering the `/sbin/service avpSNMPAgentSvc start` command.

- f. If the appserver service is installed, start the appserver service by entering the `/sbin/service appserver start` command.
 - g. Start the MPP service by entering the `/sbin/service mpp start` command.
9. Accept the new certificate on the MPP as described in the following steps:
- a. Log in to the console as root user on the Single server.
 - b. Navigate to `$AVAYA_HOME/Support/VP-Tools`.
 - c. Run the `./setup_vpms.php <Primary EPM>` command where Primary EPM is the IP address or hostname of the Primary EPM.
 - d. Type `Y`, and press `Enter` to accept the new certificate.

 Note:

For NTP service, type `Y`, and press `Enter` to use EPM for NTP service.

Third-party signed security certificates

Use this section to install a third-party signed security certificate, which replaces the certificate signed by the EPM Root certificate on each server. Experience Portal uses these certificates for mutual authentication with external servers such as SIP proxies and application servers. For email, HTML, and SMS applications, Primary and Auxiliary EPMs can mutually authenticate with applications servers. For voice applications, MPPs can mutually authenticate with application servers, speech servers, and telephony servers.

You must perform the installation procedures on each server to replace the security certificates signed by the EPM Root certificate.

Related links

- [Importing a Primary EPM Third-Party Signed Security Certificate](#) on page 115
- [Importing an Auxiliary EPM Third-Party Signed Security Certificate](#) on page 118
- [Importing a MPP Third-Party Signed Security Certificate](#) on page 120
- [Importing a Single server Third-Party Signed Security Certificate](#) on page 123

Importing a Primary EPM Third-Party Signed Security Certificate

Before you begin

- Ensure that signing is disabled for the EPM Root certificate. (Select Disable Signing on the EPM Certificates page).
- Ensure that the Primary EPM server is not processing any multi-channel messages such as Emails or SMS.

- If a managed application is installed, you might need to perform additional steps before and after the server certificate is updated. For more information, see the documentation of the managed application.

About this task

Use the `ImportServerCertificate.sh` script to import a self-signed or third party signed certificate which will replace the certificate signed by the EPM Root certificate.

Procedure

1. Log in to Linux on the Primary EPM server.

if you are an Avaya service representative, and use Avaya Enterprise Linux or if the Avaya services account are installed on this server:

- Log in to the local Linux console as `sroot`.
- Or log in remotely as a non-root user and then change the user to `sroot` by entering the `su - sroot` command.

Otherwise, log in to Linux locally as `root`, or log in remotely as a non-root user and then change the user to `root` by entering the `su -` command.

2. Stop the services in the following order:
 - a. If the `appserver` service is installed, stop the service by entering the `/sbin/service appserver stop` command.
 - b. Stop the `avpSNMPAgentSvc` service by entering the `/sbin/service avpSNMPAgentSvc stop` command.
 - c. Stop the `epmcompmgr` service by entering the `/sbin/service epmcompmgr stop` command.
 - d. Stop the `mmsserver` service by entering the `/sbin/service mmsserver stop` command.
 - e. Stop the `vpms` service by entering the `/sbin/service vpms stop` command.
 - f. Stop the `httpd` service by entering the `/sbin/service httpd stop` command.
3. If Experience Portal is installed in a virtualized environment:
 - a. Navigate to the directory where the `ImportServerCertificate.sh` script is located by entering the `cd /opt/Avaya/VE/bin` command.
 - b. Skip step 4, 5 and 6.

Note:

If Experience Portal is not installed in a virtualized environment, skip this step.

4. Mount the Avaya Aura Experience Portal 7.1 software installation DVD. The mount command depends on the server's hardware and operating system.
 - If you are working with Avaya Enterprise Linux, mount the DVD by entering the `mount /mnt/cdrom` command, where `/mnt/cdrom` is the mount point typically associated with the DVD drive in the `fstab` file.

- If you working with a supported version of Red Hat Enterprise Linux Server, to mount the DVD:

- Run the `mkdir /media/cdrom` command.

 Note:

This command is required only if the `/media/cdrom` mount point does not exist.

- Run the `mount /dev/cdrom /media/cdrom` command.

 Warning:

When the Red Hat Enterprise Linux Server automatically mounts the DVD, the files on the DVD are not executable. You must manually mount the Experience Portal installation DVD using the command shown above.

5. If the mount commands shown above do not work, consult your server documentation for the appropriate mount command.
6. Change to the mount point directory and navigate to the Utilities directory.
7. Enter the `bash ImportServerCertificate.sh --external` command.
The system prompts you to enter the file path and the name of the security certificate.
8. Type the file path and name of the security certificate, and press `Enter`.

 Note:

- The certificate is in PKCS#12 format. The certificate must be formatted as PKCS#12 file. A PKCS#12 file includes a certificate and the corresponding key. The certificate is encrypted and requires a password. If the certificate is not self-signed, then the PKCS#12 file must include all CA certificates.
- If the **Extended Key Usage** is specified in the X509.V3 certificate extension, specify `Server Authentication`, also called as `serverAuth`, and `Client Authentication`, also called as `clientAuth`, for the usage.
- The certificate resides on the local server or on an NFS-mounted drive that is locally accessible.

The system prompts you to enter the password for the security certificate.

9. Type the password for the security certificate, and press `Enter`.

The system displays the imported certificate content.

10. Enter `y` to accept the imported certificate or enter `n` to cancel.
11. Start the services in the following order:
 - a. Start the `httpd` service by entering the `/sbin/service httpd start` command.
 - b. Start the `vpms` service by entering the `/sbin/service vpms start` command.
 - c. Start the `mmsserver` service by entering the `/sbin/service mmsserver start` command.

- d. Start the `epmcompmgr` service by entering the `/sbin/service epmcompmgr start` command.
- e. Start the `avpSNMPAgentSvc` service by entering the `/sbin/service avpSNMPAgentSvc start` command.
- f. If the `appserver` service is installed, start the `appserver` service by entering the `/sbin/service appserver start` command.

Related links

[Third-party signed security certificates](#) on page 115

Importing an Auxiliary EPM Third-Party Signed Security Certificate

Before you begin

- Ensure that signing is disabled for the EPM Root certificate. (Select Disable Signing on the EPM Certificates page.)
- Ensure that the Auxiliary EPM server is not processing any multi-channel messages such as Emails or SMS.
- Ensure the task Importing a Primary EPM Third-Party Signed Security Certificate has completed successfully.
- If a managed application is installed, you might need to perform additional steps before and after the server certificate is updated. For more information, see the documentation of the managed application.

About this task

Use the `ImportServerCertificate.sh` script to import a self-signed or third party certificate to replace the certificate signed by the EPM Root certificate.

Procedure

1. Log in to Linux on the Auxiliary EPM server.

If you are an Avaya Services representative, and use Avaya Enterprise Linux or if the Avaya Service accounts are installed on this server:

- Log on to the local Linux console as `sroot`.
- Or log on remotely as a non-root user and then change the user to `sroot` by entering the `su - sroot` command.

Otherwise, log on to Linux locally as `root`, or log in remotely as a non-root user and then change the user to `root` by entering the `su -` command.

2. Stop the services in the following order:

- a. If the `appserver` service is installed, stop the service by entering the `/sbin/service appserver stop` command.

- b. Stop the `epmcompmgr` service by entering the `/sbin/service epmcompmgr stop` command.
 - c. Stop the `mmsserver` service by entering the `/sbin/service mmsserver stop` command.
 - d. Stop the `vpms` service by entering the `/sbin/service vpms stop` command.
 - e. Stop the `httpd` service by entering the `/sbin/service httpd stop` command.
3. If Experience Portal is installed in a virtualized environment:
 - a. Navigate to the directory where the `ImportServerCertificate.sh` script is located by entering the `cd /opt/Avaya/VE/bin` command.
 - b. Skip step 4, 5 and 6.

 Note:

If Experience Portal is not installed in a virtualized environment, skip this step.

4. Mount the Avaya Aura Experience Portal 7.1 software installation DVD. The mount command depends on the server's hardware and operating system.
 - If you are working with Avaya Enterprise Linux, mount the DVD by entering the `mount /mnt/cdrom` command, where `/mnt/cdrom` is the mount point typically associated with the DVD file in the `fstab` file.
 - If you are working with a supported version of Red Hat Enterprise Linux Server to mount the DVD:
 - Run the `mkdir /media/cdrom` command.

 Note:

This command is required only if the `/media/cdrom` mount point does not exist

- Run the `mount /dev/cdrom /media/cdrom` command

 Warning:

When Red Hat Enterprise Linux Server automatically mounts the DVD, the files on the DVD are not executable. You must manually mount the Experience Portal installation DVD using the commands shown above

5. If the mount command shown above do not work, consult your server documentation for the appropriate mount commands.
6. Change to the mount point directory and navigate to the Utilities directory.
7. Enter the `bash ImportServerCertificate.sh --external` command.
The system prompts you to enter the file path and the name of the security certificate.
8. Type the file path and name of the security certificate, and press `Enter`.

*** Note:**

- The certificate is in PKCS#12 format. The certificate must be formatted as PKCS#12 file. A PKCS#12 file includes a certificate and the corresponding key. The certificate is encrypted and requires a password. If the certificate is not self-signed, then the PKCS#12 file must include all CA certificates.
- If the **Extended Key Usage** is specified in the X509.V3 certificate extension, specify `Server Authentication`, also called as `serverAuth`, and `Client Authentication`, also called as `clientAuth`, for the usage.
- The certificate resides on the local server or on an NFS-mounted drive that is locally accessible.

The system prompts you to enter the password for the security certificate.

9. Type the password for the security certificate, and press `Enter`.

The system displays the imported certificate content.

10. Enter `y` to accept the imported certificate or enter `n` to cancel.
11. Start the services in the following order:
 - a. Start the `httpd` service by entering the `/sbin/service httpd start` command.
 - b. Start the `vpms` service by entering the `/sbin/service vpms start` command.
 - c. Start the `mmssserver` service by entering the `/sbin/service mmssserver start` command.
 - d. Start the `epmcompmgr` service by entering the `/sbin/service epmcompmgr start` command.
 - e. If the `appserver` service is installed, start the `appserver` service by entering the `/sbin/service appserver start` command.

Related links

[Third-party signed security certificates](#) on page 115

Importing a MPP Third-Party Signed Security Certificate

Before you begin

- Ensure that the MPP server is not handling any calls.
- Ensure that signing is disabled for the EPM Root certificate. (Select `Disable Signing` on the `EPM Certificates` page).
- Ensure the task `Importing a Primary EPM Third-Party Signed Security Certificate` has completed successfully
- If there is an Auxiliary EPM in the Experience Portal system, make sure the task `Importing an Auxiliary EPM Third-Party Signed Security Certificate` has completed successfully.

- If a managed application is installed, you might need to perform additional steps before and after the server certificate is updated. For more information, see the documentation of the managed application.

About this task

Use the `ImportServerCertificate.sh` script to import a self-signed or third party certificate to replace the certificate signed by the EPM Root certificate:

Procedure

1. Log in to Linux on the MPP server.

If you are an Avaya Services representative, and use Avaya Enterprise Linux or if the Avaya Service accounts are installed on this server:

- Log on to the local Linux console as `sroot`.
- Or log on remotely as a non-root user and then change the user to `sroot` by entering the `su - sroot` command.

Otherwise, log on to Linux locally as `root`, or log in remotely as a non-root user and then change the user to `root` by entering the `su -` command.

2. Stop the services in the following order:
 - a. Stop the MPP service by entering the `/sbin/service mpp stop` command.
 - b. Stop the `httpd` service by entering the `/sbin/service httpd stop` command.
3. If Experience Portal is installed in a virtualized environment:
 - a. Navigate to the directory where the `ImportServerCertificate.sh` script is located by entering the `cd /opt/Avaya/VE/bin` command.
 - b. Skip step 4, 5 and 6.

* Note:

If Experience Portal is not installed in a virtualized environment, skip this step.

4. Mount the Avaya Aura® Experience Portal 7.1 software installation DVD. The `mount` command depends on the server's hardware and operating system.
 - If you are working with Avaya Enterprise Linux, mount the DVD by entering the `mount /mnt/cdrom` command, where `/mnt/cdrom` is the mount point typically associated with the DVD drive in the `fstab` file.
 - If you are working with a supported version of Red Hat Enterprise Linux Server, to mount the DVD:
 - Run the `mkdir /media/cdrom` command.

* Note:

This command is required only if the `/media/cdrom` mount point does not exist.

- Run the `mount /dev/cdrom /media/cdrom` command.

 Warning:

When Red Hat Enterprise Linux Server automatically mounts the DVD, the files on the DVD are not executable. You must manually mount the Experience Portal installation DVD using the commands shown above.

If the previous installation directory is different from the default directory, you must type the old path prior to pressing the enter key.

5. If the mount commands shown above do not work, consult your server documentation for the appropriate mount command
6. Change to the mount point directory and navigate to the Utilities directory.
7. Enter the `bash ImportServerCertificate.sh --external` command.

The system prompts you to enter the file path and the name of the security certificate.

8. Type the file path and name of the security certificate, and press `Enter`.

 Note:

- The certificate is in PKCS#12 format. The certificate must be formatted as PKCS#12 file. A PKCS#12 file includes a certificate and the corresponding key. The certificate is encrypted and requires a password. If the certificate is not self-signed, then the PKCS#12 file must include all CA certificates.
- If the **Extended Key Usage** is specified in the X509.V3 certificate extension, specify `Server Authentication`, also called as `serverAuth`, and `Client Authentication`, also called as `clientAuth`, for the usage.
- The certificate resides on the local server or on an NFS-mounted drive that is locally accessible.

The system prompts you to enter the password for the security certificate.

9. Type the password for the security certificate, and press `Enter`.

The system displays the imported certificate content.

10. Enter `y` to accept the imported certificate or enter `n` to cancel.
11. Start the services in the following order:
 - a. Start the httpd service by entering the `/sbin/service httpd start` command.
 - b. Start the MPP service by entering the `/sbin/service mpp start` command.

Related links

[Third-party signed security certificates](#) on page 115

Importing a Single server Third-Party Signed Security Certificate

Before you begin

- Ensure that the Single EPM server is not processing any multi-channel messages such as Emails or SMS.
- Ensure that the MPP is not processing any traffic.
- Ensure that signing is disabled for the EPM Root certificate. (Select Disable Signing on the EPM Certificates page.)
- If a managed application is installed, you might need to perform additional steps before and after the server certificate is updated. For more information, see the documentation of the managed application.

About this task

Use the ImportServerCertificate.sh script to import a self-signed or third party certificate to replace the certificate signed by the EPM Root certificate.

Procedure

1. Log in to Linux on the Single EPM server.

If you are an Avaya Services representative, and use Avaya Enterprise Linux or if the Avaya Service accounts are installed on this server:

- Log on to the local Linux console as `sroot`.
- Or log on remotely as a non-root user and then change the user to `sroot` by entering the `su - sroot` command.

Otherwise, log on to Linux locally as `root`, or log in remotely as a non-root user and then change the user to `root` by entering the `su -` command.

2. Stop the services in the following order:
 - a. If the MPP service is installed, stop the service by entering the `/sbin/service mpp stop` command.
 - b. If the appserver service is installed, stop the service by entering the `/sbin/service appserver stop` command.
 - c. Stop the avpSNMPAgentSvc service by entering the `/sbin/service avpSNMPAgentSvc stop` command.
 - d. Stop the epmcompmgr service by entering the `/sbin/service epmcompmgr stop` command.
 - e. Stop the mmsserver service by entering the `/sbin/service mmsserver stop` command.
 - f. Stop the vpms service by entering the `/sbin/service vpms stop` command.
 - g. Stop the httpd service by entering the `/sbin/service httpd stop` command.

3. If Experience Portal is installed in a virtualized environment:

- a. Navigate to the directory where the ImportServerCertificate.sh script is located by entering the `cd /opt/Avaya/VE/bin` command.
- b. Skip step 4, 5 and 6.

 Note:

If Experience Portal is not installed in a virtualized environment, skip this step.

4. Mount the Avaya Aura® Experience Portal 7.1 software installation DVD. The **mount** command depends on the server's hardware and operating system.

- If you are working with Avaya Enterprise Linux, mount the DVD by entering the `mount /mnt/cdrom` command, where `/mnt/cdrom` is the mount point typically associated with the DVD drive in the `fstab` file.
- If you are working with a supported version of Red Hat Enterprise Linux Server, to mount the DVD:
 - Run the `mkdir /media/cdrom` command.

 Note:

This command is required only if the `/media/cdrom` mount point does not exist.

- Run the `mount /dev/cdrom /media/cdrom` command.

 Warning:

When Red Hat Enterprise Linux Server automatically mounts the DVD, the files on the DVD are not executable. You must manually mount the Experience Portal installation DVD using the commands shown above.

If the previous installation directory is different from the default directory, you must type the old path prior to pressing the enter key.

5. If the mount commands shown above do not work, consult your server documentation for the appropriate mount command.
6. Change to the mount point directory and navigate to the Utilities directory.
7. Enter the `bash ImportServerCertificate.sh --external` command.

The system prompts you to enter the file path and the name of the security certificate.

8. Type the file path and name of the security certificate, and press `Enter`.

 Note:

- The certificate is in PKCS12 format. The certificate must be formatted as PKCS#12 file. A PKCS#12 file includes a certificate and the corresponding key. The certificate is encrypted and requires a password. If the certificate is not self-signed, then the PKCS#12 file must include all CA certificates.

- If the **Extended Key Usage** is specified in the X509.V3 certificate extension, specify `Server Authentication`, also called as `serverAuth`, and `Client Authentication`, also called as `clientAuth`, for the usage.
- The certificate resides on the local server or on an NFS-mounted drive that is locally accessible.

The system prompts you to enter the password for the security certificate.

9. Type the password for the security certificate, and press `Enter`.

The system displays the imported certificate content.

10. Enter `y` to accept the imported certificate or enter `n` to cancel.
11. Start the services in the following order:
 - a. Start the `httpd` service by entering the `/sbin/service httpd start` command.
 - b. Start the `vpms` service by entering the `/sbin/service vpms start` command.
 - c. Start the `mmsserver` service by entering the `/sbin/service mmsserver start` command.
 - d. Start the `epmcompmgr` service by entering the `/sbin/service epmcompmgr start` command.
 - e. Start the `avpSNMPAgentSvc` service by entering the `/sbin/service avpSNMPAgentSvc start` command.
 - f. If the `appserver` service is installed, start the `appserver` service by entering the `/sbin/service appserver start` command.
 - g. Start the `MPP` service by entering the `/sbin/service mpp start` command.

Related links

[Third-party signed security certificates](#) on page 115

Chapter 4: Organization level access

Organization level access in Avaya Aura® Experience Portal

The multi-tenancy feature in Avaya Aura® Experience Portal allows the data maintained by the Experience Portal Manager (EPM) to be segmented for multiple organizations. This segmentation allows users within an organization to have restricted access in the EPM. You can use the **Organizations** page to configure multi-tenancy in EPM.

 Important:

The **Organizations** page in EPM is accessible only if the organization level access is enabled in Experience Portal.

For more information, see [Configuring organization level access in Experience Portal](#) on page 128.

In the following EPM web pages, the organization level users can only access the data which belongs to their organization:

- Reports: Standard, Custom and Scheduled
- Users
- Roles
- Applications
- Active Calls
- Audit Log Viewer

The pre-configured organization level roles in the EPM restrict the access rights of organization level users. They can access only that data which is specific to their organization.

Organizational level access is created in Experience Portal when you:

- Add an organization in the **Organizations** page.
- Assign the users to the organization in the **Add User** page.
- Assign the applications to the organization in the **Add Application** page.
- Assign the custom reports to the organization in the **Add Custom Report** page.

For example, you create an organization called `sales`. Assign a user called `John`, an application called `test` and a custom report called `test` to the `sales` organization. The user `John` can now access only the `test` application and `test` report in EPM.

*** Note:**

Only a user with the User Manager role can add new organizations.

When a user with the Org Administration role adds an application, a user or a custom report, the organization name and forward slash character are prefixed by default. For example, when a user belonging to the `sales` organization and with the Org Administration role adds a new user; `John`, the user name is saved as `sales/John`.

Organization level roles

The pre-configured organization level roles in EPM restrict the access rights of organization level users. The users can access only that data which is specific to their organization.

*** Note:**

Custom roles are not available for organization level users. For more information, see [Roles page field descriptions](#) on page 34.

The organization level roles are:

Organization level role	Description
Org Administration	User accounts with Org Administration access can perform all system-related functions that are specific to their organization.
Org Auditor	User accounts with Org Auditor access can view the audit log entries for the users in their organization.
Org Privacy Manager	User accounts with Org Privacy Manager role can update the following for their organization: • All the Transcription related configuration under Reporting Parameters group for an application. • Privacy Settings for traces.
Org Reporting	User accounts with Org Reporting role can generate standard reports, and add, edit, or delete the custom and scheduled reports for their organization.
Org User Manager	User accounts with Org User Manager access can do the following for their organization: • Add new users to their organization. They can change, delete, unlock, and reset the password for existing users in the organization. • Add, change, and delete custom organization roles.

Table continues...

Organization level role	Description
	• Change the password longevity for the users in their organization. • Change the password longevity for their organization.
Org Web Services	User accounts with Org Web Services access can use Application Interface Web Service to launch any application that is configured on the Experience Portal system, and is assigned to their organization. They can also use Application Logging Web Service to save application logging and call flow data information for any application that is assigned to their organization.

Configuring organization level access in Experience Portal

To configure multi-tenancy in Experience Portal Manager (EPM), you need to enable organization level access in Experience Portal.

Note:

By default, organization level access is disabled.

Related links

[Enabling organization level access in Experience Portal](#) on page 128

[Disabling organization level access in Experience Portal](#) on page 129

Enabling organization level access in Experience Portal

Procedure

1. Log in to the EPM using an administrative account and open a command window.

Log in to Linux on the primary EPM server. If you are an Avaya Services representative and are using Avaya Enterprise Linux, or if the Avaya Service accounts are installed on this server:

- Log in to the local Linux console as `sroot`.
- Or log in remotely as a non-root user and enter the `su - root` command to change the user to `sroot`.

Otherwise, log in to Linux locally as `root`, or log in remotely as a non-root user and enter the `su -` command to change the user to `root`.

2. Enter the `cd $AVAYA_HOME/Support/VP-Tools` command. `$AVAYA_HOME` is an environmental variable pointing to the name of the installation directory specified during the Experience Portal software installation.

The default value is `/opt/Avaya/ExperiencePortal`.

3. Enter the `EnableOrganizations` command to enable organization level access in Experience Portal.
4. Type `Y` and press `Enter` when prompted to restart the `vpms` service.

Result

From the EPM main menu, you can access the *Organizations* page by selecting **User Management > Organizations**.

* Note:

Log in to the EPM web interface using an account with the User Manager user role.

For more information on creating organization level access in Experience Portal, see [Organization level access in Avaya Aura Experience Portal](#) on page 126

Related links

[Configuring organization level access in Experience Portal](#) on page 128

Disabling organization level access in Experience Portal

About this task

* Note:

By default, organization level access is disabled.

Procedure

1. Log in to the EPM using an administrative account and open a command window.

Log in to Linux on the primary EPM server. If you are an Avaya Services representative and are using Avaya Enterprise Linux, or if the Avaya Service accounts are installed on this server:

- Log in to the local Linux console as `sroot`.
- Or log in remotely as a non-root user and enter the `su - root` command to change the user to `sroot`.

Otherwise, log in to Linux locally as `root`, or log in remotely as a non-root user and enter the `su -` command to change the user to `root`.

2. Enter the `cd $AVAYA_HOME/Support/VP-Tools` command. `$AVAYA_HOME` is an environmental variable pointing to the name of the installation directory specified during the Experience Portal software installation. The default value is `/opt/Avaya/ExperiencePortal`.
3. Enter the `EnableOrganizations --disable` command to disable organization level access in Experience Portal.

*** Note:**

You must delete all organizations before disabling organization level access.

4. Type `Y` and press `Enter` when prompted to restart the `vpms` service.

The **Organizations** page is disabled in **EPM > User Management**.

Related links

[Configuring organization level access in Experience Portal](#) on page 128

Organizations page field descriptions

Use this page to add organizations to the Experience Portal Management system (EPM). You can also delete an existing organization.

Using the defined organization, you can restrict a user's access to only the data which belongs to their organization.

Field or Button	Description
Selection check box	Use this Selection check box to select which organization you want to delete.
Name	The name for the organization. * Note: You cannot change the Organization Name after creating it.
Zone	The zone to which an organization is allocated.
 Zones filter icon	To filter zones, click this icon located at the right side of the page. The system opens the Zone filter window for selecting one or more zones. * Note: The system displays the Zones filter icon only when you create new zones. If you do not create any new zones, you do not see the icon.
Requested SIP Calls	The maximum or minimum number of requests for SIP calls within an organization.
 Zoom lens icon	Click this icon to view the SIP allocations within an organization.
Password Longevity (days)	You can set your password for a specified period of time. For an organization user: • If the values are not specified at the role level, the Experience Portal system uses the password longevity specified for the organization. • If the organization does not have any value specified, the Experience Portal system uses the system level password longevity.

Table continues...

Field or Button	Description
 Pencil icon	Click this icon to change the password longevity.

Chapter 5: Zoning Topology

Overview

Zoning is a feature of Avaya Aura® Experience Portal introduced in release 7.0.

This feature provides an advantage to customers at geographically distributed sites and to customers that have a large system in a single location.

Zoning entails three main advantages for Experience Portal (EP) customers:

- Easy management of large systems, such as MPPs
- Effective management of WAN traffic
- Local Access and Transport Area (LATA) considerations for outbound calls

Zone architecture:

Zones are extended Avaya Aura® Experience Portal systems. All resource management and configuration are centralized in zones. Each zone is either coresident to create artificial boundaries for resource management, or is deployed remotely so that all RTP traffic is contained within the location represented by the zone. All primary EPM data traffic crosses zonal boundaries including configuration information, control, status information, and report data. SIP traffic can also cross zonal boundaries though each zone must have a configured proxy.

The zone-specific resources are:

- Auxiliary EPMs
- Media servers
- Speech servers
- VoIP configuration

Note:

The proxies are shared across zones but traffic routing causes certain issues. The shared proxies provide call distribution across zones. For example, on ASM, you can choose to route calls to certain numbers only to MPPs in a particular zone. You can also set it up to distribute these calls across MPPs in different zones as well. If the SIP proxy is setup to distribute calls across zones, but one of the zones does not have an application configured for that particular number, the MPPs in that zone will end up rejecting those calls.

- Multi-media configuration

The system stores the resources in the primary EPM configuration database. The primary EPM OMS Poller distributes zone-specific data to each zone. The primary EPM performs the following functions:

- Downloads zone-specific configuration to Media servers, for example:
 - ASR/TTS resources assigned to a zone
 - Proxy configuration assigned to a zone
 - H.323 configuration assigned to a zone
 - Applications assigned to a zone

 Note:

Application servers are not configured and, therefore, are not assigned to a zone. Such Application servers are common resources.

- Polls for status and statistical data from each server.
- Manages the operational states, for example, **Starts**, **Stops**, **Restarts**, **Reboots**, and **Halts**.
- Downloads the report data, for example, the Contact Summary and Contact Detail reports.

Zonal Entities:

Zonal entities are resources that you can assign to a zone. You can add the following entities to a zone:

- Auxiliary EPM servers
- Media servers
- SMPP and HTTP connections
- Email connections
- Speech servers (ASR and TTS)
- Applications
- HTML Redirectors

Zone support:

- Zone support in H.323 deployment — Stations are not shared across zones.

 Note:

The system assigns each Communication Manager configuration to a zone. To use Communication Manager across zones, Communication Manager requires individual configuration for each zone.

- Zone support in SIP deployment

 Note:

The customer can configure the total concurrent SIP sessions that a tenant uses. This configuration includes all the zones belonging to the tenant.

Failover within a zone

Experience Portal supports Media server failover only within a zone, not across zones. In case of a Media server failover, the system redistributes the licenses of the failed Media server across the other Media servers within that zone. This redistribution ensures that the capacity allocated to the zone remains consistent.

 Note:

When a zone becomes unavailable, the administrator manually reassigns the licenses to a different zone.

Real-time management

A user can configure components, collect status from components, and control the operational state of components. The EP system supports each feature, from the primary EPM to the components in all zones. Zonal boundaries only exist for configurations where operational controls and status collection is zone independent and done in parallel to provide high-performance configuration services.

The polling process consists of the following:

- Retrieving component state and status information for every component in parallel including Media servers and auxiliary EPMservers.
- Saving the state and status information of the EPM servers in the database.
- Updating the configuration of the components if the components are in a configurable state. This state depends on the type of data to be configured. The configuration data is synchronized with Media servers and uploaded from auxiliary EPM components.
 - Running states: Telephony resources for media server, ASR/TTS configuration, and Application configuration.
 - Stopped states: All configurations except Telephony for Media servers, including configurations that require a restart.

Component failure within a zone causes licenses to be redistributed within that zone. However, zone licenses are not automatically redistributed across zonal boundaries.

Licenses

Resource Allocation by Zones

In a zonal partitioned system, EP provides the means to manually allocate telephony licenses to zones.

The total number of ports configured for all zones should not exceed the total number of configured telephony licenses allocated to the entire system. When the total number of configured telephony licenses for the entire system falls below the number configured for all zones, the allocation per zone is proportionately adjusted to meet the lower system configuration. Any newly added licenses to the system are not automatically distributed to the zones but must be manually assigned.

*** Note:**

Licenses are allocated to a zone for H.323 and SIP.

Zone licensing

Licenses are assigned to a zone and are not moved between zones unless the total number of available licenses drop below the capacity defined for all of the zones. In this case, the number of licenses are less in proportion to the licenses assigned to each zone. Excess WebLM licenses are not used when the licenses exceed the capacity of the zones.

Rounding errors are distributed to the zones in the following order:

- The remaining licenses are randomly distributed to zones with equal priorities.

Tenant Licensing

Telephony and Announcement Only licenses are taken from WebLM and the licenses are divided between SIP and H.323 in proportion to the number of SIP ports and H.323 stations configured.

$\text{WebLM Licenses allocated for SIP} = \text{Licenses} \times (\text{SIP} \div (\text{SIP} + \text{H323}))$

Where:

- Licenses = Total WebLM Licenses (Telephony + Announcement Only)
- SIP = Maximum Simultaneous Calls (SIP configuration)
- H323 = Total Number of H.323 stations configured

H.323 stations are assigned for applications within organizations through CM hunt groups or vectors. Port groups are configured through EP Administration pages to associated stations to a specific hunt group that becomes associated to a particular application through a pilot number. The application is assigned to an organization through EP configuration web pages.

WebLM SIP licenses can be assigned to organizations and in turn taken from the organizational license pool and assigned to specific applications within organizations. There are two types of organizations:

- Default Organization – The “Default Organization” is not configured and represents applications that are not owned by an organization. This allows applications to be managed with the exception that resource usage by an application is supported. There can be only one default organization that initially has no licenses allocated but which can be configured. Any licenses assigned to the default organization are taken from the Global Common Licenses pool called WebLM Licenses (SIP).
- Configured Organization (Organization A & B) – A “Configured Organization” is created and edited through the Administration web pages. Licenses are assigned to organizations through the Administration web pages. Any licenses assigned to the organization are taken from the Global Common Licenses pool [WebLM Licenses (SIP)].

There are two license types for applications:

- Guaranteed Licenses – These are licenses which only the application can use and are not given to any other application. Applications are assigned guaranteed licenses from the pool of

licenses assigned to a Configured organization or from the Default organization depending on where the application is configured. Applications can be configured with no guaranteed licenses and can be starved by other applications as the common licenses become exhausted.

- **Common Licenses** – These licenses are shared by all the applications after exhausting the guaranteed licenses. The guaranteed licenses are distributed across the media servers. It is possible for the guaranteed licenses to be exhausted on a media server forcing common licenses used to run the application when another media servers still have guaranteed licenses available for the application.

Zone filters

When you add or change resources or start with an application, only the zones selected by the **Zone Filter** icon are available in the **Zone** drop-down list.

The zone filter is applicable for the entire user session, that is, the web pages display the resources assigned to the selected zone till the user logs off. At any given time, the user is able to reset or change the zone filter. The zone filter is retained when the user logs off from the web pages.

Restrictions on moving resources between zones

The resources assigned to a zone can be moved from one zone to another zone. However there are certain restrictions for moving a resource from one zone to another.

Resource	Restrictions
Applications	No applications can be moved from one zone to another.
Organizations	No applications are configured in the zone from which the resource is being moved.
Auxiliary EPM servers	If a coresident SMS processor uses SMPP Connection that is not shared, changing zones is not possible.
Media servers	The media server being moved must be stopped.
ASR servers	All media servers are stopped in the zone from which the resource is being moved.
TTS servers	All media servers are stopped in the zone from which the resource is being moved.
H.323 Connections	All media servers are stopped in the zone from which the resource is being moved.
SIP Connections	All media servers are stopped in the zone from which the resource is being moved.

Table continues...

Resource	Restrictions
SMPP connections	All auxiliary EPM servers must be stopped in the zone from which the resource is being moved.
HTTP connections	All auxiliary EPM servers must be stopped in the zone from which the resource is being moved.
Email Connections	All auxiliary EPM servers must be stopped in the zone from which the resource is being moved.

Adding a zone

Before you begin

- Ensure that Experience Portal 7.1 is installed in your system.
- Buy a zone license with Experience Portal 7.1 to use the Zoning feature and to add zones to the **Zones** list.



Note:

The Zoning feature is available only with Experience Portal 7.0 and later. If you have Experience Portal 6.0 or any earlier version of Voice Portal, upgrade to Experience Portal 7.1 and purchase a zone license.

About this task

Use this page to add a zone.

Procedure

1. Log in to the EPM Web interface.
2. On the left pane, select **System Configuration > Zones**.
3. On the **Zones** page, click **Add** to navigate to the **Add Zone** page.
4. In the **Name** field, type the name of the zone.
5. In the **Description** field, give any additional details regarding the zone.
6. From the **Time Zone** field, select the time zone that you want to set.
7. Click **Save**.

Result

The system displays the **Zones** page with the zone added to the list of Zones. The system also displays the message: `The information that you entered has been saved.`

Changing the configuration of a zone

About this task

To change the configuration of a zone, perform the following steps.

Procedure

1. Log in to the EPM Web interface.
2. On the left pane, select **System Configuration > Zones**.
3. Click the name of the zone that you want to change to navigate to the **Change Zone** page.
4. On the **Change Zone** page, type the new values for the relevant fields.

 Note:

The relevant fields are the fields that you want to change. The fields available on the **Change Zones** page are **Name** and **Description**.

5. From the **Time Zone** field, select the time zone that you want to set.
6. Click **Save**.

Deleting a zone

Procedure

1. Log in to the EPM Web interface.
2. On the left pane, select **System Configuration > Zones**.
3. From the **Zones** list, select the check box next to the zone that you want to delete.
4. Click **Delete**.

Result

The selected zone is deleted from the system.

 Note:

You cannot delete the **Default** zone. You can only delete the zones that you have added.

Filtering a zone

About this task

To filter one or more zones and set the time zone, perform the following steps.

Procedure

1. Click the **Zones** filter icon that is located on the right side of the page.
2. To filter a particular zone, select the check box next to the name of the zone.
3. From the **Display Time Zone** field, select the time zone that you want to set.
4. Click **Save**.

Viewing the details of a zone

Procedure

1. Log in to the EPM Web interface.
2. On the left pane, select **System Configuration > Zones**.
The system displays the zones page with the list of zones.
3. Click the **View Zone Details** icon  to navigate to the **<Zone name> Details** page.
The **<Zone name> Details** page displays all the resources that are assigned to a zone.

Chapter 6: Email management

Email overview

Experience Portal 7.0 and the later versions support email as an additional communication channel.

The major features driving the email capability are:

- Sending outbound email messages.
- Receiving and processing inbound email messages.
- Sending a reply to inbound email messages.
- Handling of delivery receipts from email messages.

The major components that are enhanced or added to the system include:

- **Email Web Application** : A web application that provides a web user interface for configuring and managing the email-related components.
- **Email Processor** : A web application that interacts with an email server over the SMTP and POP3/IMAP4 protocols, routes messages to Orchestration Designer email applications, and provides methods for sending email messages.
- **Orchestration Designer**: A new application type called **Email** is added.
- **Application Interface Web Service** : The service is enhanced for sending multimedia messages.

Experience Portal provides additional support for the multichannel features in the following ways:

- Incoming email messages can be routed to Orchestration Designer email applications.
- Delivery receipts can be routed to Orchestration Designer email applications.
- Orchestration Designer applications of any type can send email messages. For example, a voice application can send an email message.

 Note:

Experience Portal supports the following protocols:

- POP3 or IMAP4 for incoming emails and SMTP for outgoing emails.
- TCP or TLS or STARTTLS connections for inbound connections and outbound connections
- Experience Portal provides multilingual email support.
- Experience Portal supports attachments for inbound and outbound email messages.
- Experience Portal provides built-in grammar support like word spotting for text-based messages.

- The EPM system monitor displays real-time email statistics.
- Contact and Session reports display the inbound and outbound email statistics. Emails have filters and summary options.
- EPM Log Viewer, Alarm Manager, and Audit Log display voice, email, and SMS-related information.
- The EPM installation program installs the email support application
- Experience Portal provides high availability and scalability with load balancing across connections.

Email typical flow

Inbound message with reply

The flow of a typical incoming email consists of the following steps:

- The incoming email message is routed through the Internet to an email server. For example, Microsoft Exchange.
- Email Processor monitors the mailbox on the email server and detects a new message.
- Email Processor launches the Orchestration Designer email application on an application web server based on **To**, **Subject**, or **Header** as specified in the application configuration on the EPM.
- The email application can gain access to the details of the incoming message by examining a variable called **Message** that has fields related to the email message: **To**, **From**, **Subject**, **Body**, and **Attachments**. The **Message** variable is similar to the **Session** variable, but only contains fields related to a message, such as email and SMS messages.
- The Orchestration Designer application can generate a reply using the Prompt tag mechanism or generate a new outbound email by using the Orchestration Designer notification connector. Both methods trigger the Orchestration Designer runtime to send an email message to Email Processor.

Note:

Experience Portal supports two types of inbound email messages:

- Regular
- Delivery Status Notification (DSN): This type of message might be generated by any email server that processes the message before reaching the final destination.

Outbound message

The Application Interface Web service is enhanced to provide a **launchEmail** method and a **sendEmail** method.

The **launchEmail** method is a web services request that calls an email application. The **launchEmail** web service request succeeds when the Orchestration Designer application begins to run. The launched Orchestration Designer application sends an email message by invoking the notification connector. After the message is sent, a **sendEmail** web service call is created.

The **sendEmail** method enables an application that can make web service calls to send an email message to an email server through Email Processor. The web service call succeeds when the Email Processor has accepted the message. An email application can be notified when an email message is delivered to the email server. This status is sent to the Notification URL that is specified when configuring the email application on the EPM. An application can be further notified of any errors that occur after the email server has accepted the message. These email DSN message types are sent to the application if the application was configured to support either **Delivery** or **Regular and Delivery** message types. Voice applications that call **sendEmail** must specify the name of a configured email application in order to receive error notifications.

 Note:

An Email Notification Connector (PDC) is a pluggable data connector that is used to send an email message from a speech application or a message application that is created for a channel other than the email channel.

Notifications are done through the configured applications. An application can be configured by short code that can have an application URL which is launched by Email Browser when notifications are received. The email server relies on the SMTP delivery status notification mechanism to support the registered delivery of email messages. The Email Processor submits the SMTP delivery notifications as requested by the client. On receiving the delivery receipt from SMTP, Email Processor stores all the information from the message in the delivery receipt record so that Email Browser can make that information available to the delivery receipt application, see the Orchestration Designer documentation.

For more information on these new web service methods, see:

- [LaunchEmail method](#) on page 545
- [SendEmail method](#) on page 556

Email processors

An email processor is an application that is hosted on the multimedia server. The multimedia server is a service that is deployed on the Primary and the Auxiliary EPMs. An email processor manages connections to one or more email servers and handles the routing of incoming messages to configured applications. The email processor additionally provides Web service interface methods that the Application Interface Web Service uses to send email messages.

Using the Email Processors web page, administrators can add, modify, and delete one or more email processors.

Configure an Auxiliary EPM before you configure an email processor to be hosted on that AuxiliaryEPM. The email processor inherits the name, host address, and zone of the EPM.

Related links

- [Email processor states](#) on page 143
- [Adding an email processor](#) on page 143
- [Changing the configuration of an email processor](#) on page 144
- [Deleting an email processor](#) on page 145

Email processor states

An email processor maintains the following states for managing the functions:

State	Description
Not Running	The server is either stopped or not started yet.
Starting	The server start request is initiated, and is in the process of initialization.
Running	The server is up and functional.
Stopping	The server shutdown is requested.
Need Configuration	The server does not find configuration.
Need Connections	The server has configuration but does not have any connections assigned or configured.
Degraded	The server has configuration and connections. However, some or all connections are not working.
Error	The server data returned has been deemed "stale" (no new data retrieved after a period of 3 minutes), or 2) unexpected return code retrieved from a poll to server.
Stopped	The server is stopped.

Related links

[Email processors](#) on page 142

Adding an email processor

Procedure

1. Log in to the EPM web interface.
2. From the EPM main menu, select Home > Multi-Media configuration > Email > Email Processors.
3. On the Email Processor page, click **Add**.
4. From the **Name** field, select the name of the EPM server from the drop-down box.
5. Select either the **Yes** or the **No** option for the Enable button.
6. From the **Categories and Trace Levels** group, select **Custom**.
If you select **Use Email Settings**, then the trace level buttons are disabled.
7. Set the trace level of Email Processors by selecting the appropriate button.

The options are:

- Off
- Fine
- Finer

- Finest

The default trace level setting is **Off**.

8. Set the trace level of the Email Browser by selecting the appropriate button.

The options are:

- Off
- Fine
- Finer
- Finest

The default trace level setting is **Off**.

9. Click **Save**.

Related links

[Email processors](#) on page 142

Changing the configuration of an email processor

Procedure

1. Log in to the EPM web interface.
2. From the EPM main menu, select Home > Multi-Media configuration > Email > Email Processor.
3. Click the name of the Email Processor.

The system opens the **Change Processor** page.

4. Select either the **Yes** or the **No** option for the **Enable** button.
5. From the **Categories and Trace Levels** group, select **Custom**.

If you select **Use Email Settings**, then the trace level buttons are disabled.

6. Select the trace level that you want to set for the Email Processor.

The options are:

- Off
- Fine
- Finer
- Finest

7. Select the trace level that you want to set for the Email Browser.

The options are:

- Off
- Fine

- Finer
- Finest

8. Click **Save**.

Related links

[Email processors](#) on page 142

Deleting an email processor

Procedure

1. Log in to the EPM web interface.
2. From the EPM main menu, select Home > Multi-Media configuration > Email > Email Processor.
3. Select the check box next to the email processor that you want to delete.
4. Click **Delete**.

Related links

[Email processors](#) on page 142

Email connections

You can add, modify, and delete the configuration of an email connection on the Email Connections Web page. An email connection specifies the configuration parameters an email processor uses to connect with an email server. The email processor and the email server interact over the SMTP protocol for sending messages and over the IMAP4 or POP3 protocol for receiving messages. An email connection can belong to a zone. An email processor uses the email connections that belong to the same zone as the email processor server.

In versions earlier than Experience Portal 7.0, email connections were called 'email servers' and facilitated only the configuration of SMTP related parameters. The capability to receive email messages over IMAP4 or POP3 was added in Experience Portal 7.0 release.

Related links

[Adding an email connection](#) on page 145

[Changing the configuration of an email connection](#) on page 147

[Deleting an email connection](#) on page 148

Adding an email connection

Procedure

1. Log in to the EPM web interface.

2. From the EPM main menu, select Home > Multi-Media configuration > Email > Email Connections.
3. On the **Email Connections** page, click **Add**. The system displays the **Add Email Connection** page.
4. From the **Zone** field, select the name of the zone.
5. Select one or more organizations from the **Organization** list.
6. In the **Name** field, type the name of the email connection.
7. From the **Enable** field, select the relevant option.
The options available are **Yes** and **No**.
8. From the **Registered Delivery** field, select the type of delivery.
9. From the **Type** field, select the type of email connection that you want to add.
The options available are **Outgoing** and **Incoming and Outgoing**.
10. In the **Outgoing Mail (SMTP)**, enter the address of the email server.
11. Select the accurate transport protocol.
The available options are **TCP**, **TLS**, and **STARTTLS**.
12. Enter the port number that is used for the email connection.
13. Enter the email address of the sender.
14. Enter the user name.
15. From the **Use Authentication** field, select **Yes**.
The available options are **Yes** and **No**. Enter the password only if you select **Yes**.
16. Enter the password.
17. In the **Incoming Mail**, select the name of the protocol.
The available options are POP3 and IMAP.
18. Enter the address of the server.
19. Select the appropriate transport protocol.
The available options are **TCP**, **TLS**, and **STARTTLS**.
20. Enter the port number that is used for the email connection.
For POP3 , the default port number is 110. For IMAP, the default port number is 143.
21. Select a folder to check for new messages.
The available folders are **Inbox** and **Other**.
22. In the Expunge field, select either **Yes** or **No**.
23. In the **Delete message after reading** field, select either **Yes** or **No**.
If you use **POP3** protocol, this field is disabled.

24. In the **Move message after reading** field, select either **Yes** or **No**.
If you use **POP3** protocol, this field is disabled.
25. In the **Mark message as read** field, select either **Yes** or **No**.
If you use **POP3** protocol, this field is disabled.
26. Enter the name of the folder in the field **Enter the name of the folder to** where you want to save the message.
27. Click **Save**.

Related links

[Email connections](#) on page 145

Changing the configuration of an email connection

Procedure

1. Log in to the EPM web interface.
2. From the EPM main menu, select Home > Multi-Media configuration > Email > Email Connections.
3. In the **Name** field, click the name of the email connection. The system opens the **Change Email Connection** page.
4. From the **Zone** field, select the name of the zone.
5. Select one or more organizations from the **Organization** list.
6. From the **Enable** field, select the relevant option.
The options available are **Yes** and **No**.
7. From the **Registered Delivery** field, select the type of delivery.
8. From the **Type** field, select the type of email connection that you want to add.
The options available are **Outgoing** and **Incoming and Outgoing**.
9. If you select the **Outgoing** group, then in the **Outgoing Mail** group box, enter the address of the email server.
10. Select the accurate transport protocol.
The available options are **TCP**, **TLS**, and **STARTTLS**.
11. Enter the port number that is used for the email connection.
12. Enter the email address of the sender.
13. Enter the user name.
14. From the **Use Authentication** field, select **Yes**.
The available options are **Yes** and **No**. You can enter the password only if you select **Yes**.

15. Enter the password.
16. If you select the **Incoming and Outgoing** group, then in the **Incoming Mail** group box, select the name of the protocol.
The available options are POP3 and IMAP.
17. Enter the address of the email server.
18. Select the appropriate transport protocol.
The available options are **TCP**, **TLS**, and **STARTTLS**.
19. Enter the port number that is used for the email connection.
For POP3 , the default port number is 110. For IMAP, the default port number is 143.
20. Select a folder to check for new messages
The available folders are **Inbox** and **Other**.
21. In the Expunge field, select either **Yes** or **No**
22. In the **Delete message after reading** field, select either **Yes** or **No**.
If you use **POP3** protocol, this field is disabled.
23. In the **Move message after reading** field, select either **Yes** or **No**.
If you use **POP3** protocol, this field is disabled.
24. In the **Mark message as read** field, select either **Yes** or **No**.
If you use **POP3** protocol, this field is disabled.
25. Enter the name of the folder in the field **Enter the name of the folder to** where you want to save the message.
26. Click **Save**.

Related links

[Email connections](#) on page 145

Deleting an email connection

Procedure

1. Log in to the EPM web interface.
2. From the EPM main menu, select Home > Multi-Media configuration > Email > Email Connections.
3. Select the check box next to the email connection that you want to delete.
4. Click **Delete**.

Related links

[Email connections](#) on page 145

Adding an email application to Experience Portal

Before you begin

Make sure that email processor and required connections are configured in the Experience Portal system.

Procedure

1. Log on to the EPM Web interface using an account with the Administration user role.
2. From the EPM main menu, select **System Configuration > Applications**.
3. On the Applications page, click **Add**.
4. On the Add Application page, enter the appropriate information and click **Save**.
To see descriptions of all the fields on the Add Applications page, click **Help**.

Changing the settings of an email application

Procedure

1. Log on to the EPM Web interface using an account with the Administration user role.
2. From the EPM main menu, select **System Configuration > Applications**.
3. On the Applications page, click the application name in the **Name** column.
4. On the Change Application page, enter the appropriate information and click **Save**.
To see descriptions of all the fields on the Change Applications page, click **Help**.

Deleting an email application

Procedure

1. Log on to the EPM Web interface using an account with the Administration user role.
2. From the EPM main menu, select **System Configuration > Applications**.
3. On the Applications page, for each application that you want to delete, select the check box to the left of the application name in the applications table.
4. Click **Delete**.

Configuring system parameters for email browser settings

Procedure

1. Log in to the EPM web interface.
2. From the EPM main menu, select Home > Multi-Media configuration > Email > Email Processors > Browser Settings.
3. In the **Fetch Timeout** field, enter the maximum number of seconds that the email browser must wait for the application server to return the requested page
4. In the **Proxy Server** field, enter the fully qualified path to the proxy server.
5. In the **Proxy Port** field, enter the port number for the proxy server.
6. In the **Number of Threads** field, enter the maximum number of threads that the email browser must use for an asynchronous fetch.

You can enter a number between 1 and 500. The default is 50.
7. Click **Save**.

Configuring system parameters for email settings

Procedure

1. Log in to the EPM web interface.
2. On the EPM main menu, select Home > Multi-Media configuration > Email > Email Processors > Email Settings.
3. In the **Log Level** field, select the level that you want to set.

The default is **Info**.
4. Select the check boxes next to the Call Data and Session Data fields to enable **Call Data** records and **Session Data** records.
5. Type the number of days for the retention period of the records.

 Note:

The retention period has an impact on how long Call Data Records and Session Data Records are saved in the operational database that are used by the processor. The retention period does not have an impact on how long these records are saved in the reporting database.

6. Select the appropriate option to set the trace levels for **Email Processor** and **Email Browser** fields.

If you select the buttons at the top of the list, the same trace levels are set for both **Email Processor** and **Email Browser** fields. The buttons next to both the fields are automatically selected.

If you do not select the top buttons, you can set different trace levels for **Email Processor** and **Email Browser** fields.

The default is **Fine**.

7. Click **Save**.

Next steps

For more information on parameters and return values of the email application, refer:

- [LaunchEmail method](#) on page 545
- [SendEmail method](#) on page 556

Multimedia Tomcat server

A new instance of Tomcat server is deployed on the Primary and the Auxiliary EPMs. This server hosts the following:

- An SMS service Web application comprising an SMS Processor and an SMS Browser
- An Email service web application comprising Email Processor and Email Browser.

This new server is another instance of Tomcat and is different from the coresident application server. The coresident application server is yet another instance of Tomcat server. The multimedia server hosts the SMS and email services.

The Tomcat multimedia server is installed in the \$MMSSERVER_HOME folder and runs as a Linux service as **mmsserver**.

mmsserver service supports the following commands:

- **service mmsserver status**: for checking the status of the mmsserver service
- **service mmsserver start**: for starting the mmsserver service
- **service mmsserver stop** : for stopping the mmsserver service
- **service mmsserver restart**: for restarting the mmsserver service

The multimedia service is a part of the EPM server and the commands issued to the EPM server through the EPM Manager web pages are also issued to the multimedia service.

Email reporting filters

Experience Portal 7.0 and later versions have a new media type filter for email that is added to the Contact Detail and Contact Summary reports.

The following are the main filters that are available for Email:

- Email
- Email DSN

Experience Portal 7.0 and later versions support the capability to filter the messages on Email servers. This capability consists of the number of messages sent to one or more Email servers as well as the number of messages received from one or more Email servers.

The following information is available in these reports:

- The number of messages sent
- The number of messages received
- The number of delivery receipts requested
- The number of receipts pending
- The number of receipts received

All existing filters for the Contact Detail and Contact Summary reports are applied to reporting records that are created by incoming or outbound email

Chapter 7: SMS management

SMS overview

Experience Portal 7.0 and later versions support SMS as an additional communication channel.

The major features driving the SMS capability are:

- Sending outbound SMS messages.
- Receiving and processing inbound SMS messages.
- Sending a response to inbound SMS messages.
- Handling of delivery receipts from SMS messages.

The major components that are enhanced or added to the system include:

- **SMS Web Application** : A web application that provides a web user interface for configuring and managing the SMS-related components.
- **SMS Processor** : A web application that interacts with an SMSC server over HTTP/HTTPS or the SMPP protocol , routes messages to Orchestration Designer SMS applications, and provides methods for sending SMS messages.
- Orchestration Designer: A new application type called **SMS** is added.
- **Application Interface Web Service** : The service is enhanced for sending multimedia messages.

Experience Portal provides additional support for the multichannel features in the following ways:

- Incoming SMS can be routed to Orchestration Designer SMS applications.
- Orchestration Designer SMS application can reply to an incoming SMS.
- Delivery receipts can be routed to Orchestration Designer SMS applications.
- Orchestration Designer applications of any type can send an SMS message. For example, a voice application can send an SMS message.
- Experience Portal provides support for http and https for an outbound SMS.
- Experience Portal provides support for SMPP for inbound and outbound SMS.
- Experience Portal provides multilingual SMS support.
- Experience Portal provides built-in grammar support like word spotting for text-based messages.
- The EPM system monitor displays real-time SMS statistics.
- Contact and Session reports display the inbound and outbound SMS statistics. Filters and summary options exist for SMS.

- EPM Log Viewer, Alarm Manager, and Audit Log display voice, email, and SMS-related information.
- The EPM installation program installs the SMS support application.
- Experience Portal provides high availability and scalability with load balancing across connections.

SMS typical flow

Inbound message with reply

The flow of a typical incoming SMS consists of the following steps:

- The incoming SMS message is routed to the Short Message Service Center (SMSC) that is located in the cloud. The SMSC is registered with cell phone providers as the owner of the short code or long number to which the message is addressed.
- SMS Processor maintains an open connection to the SMSC and receives a deliver event for the new message
- SMS Processor launches the Orchestration Designer SMS application on an application web server based on Short Code or Long Number and optional message content keywords as specified in the application configuration on the EPM.
- The SMS application can gain access to the details of the incoming message by examining a variable called **Message** that has fields related to the SMS message: **To**, **From**, and **Body**. The **Message** variable is similar to the **Session** variable, but only contains fields related to a message, such as email and SMS messages.
- The Orchestration Designer application can generate a reply using the Prompt tag mechanism or generate a new outbound SMS by using the notification connector. Both methods cause the Orchestration Designer runtime to communicate with the SMS Processor to send an SMS message.

Note:

Experience Portal supports three types of inbound SMS messages:

- Regular
- Notification: A Notification is received when the SMSC passes the outbound message on to the next hop.
- Delivery receipt: A Delivery receipt is received when an outbound message reaches the destination.

Outbound message

The Application Interface Web service is enhanced to provide a **launchSMS** method and a **sendSMS** method.

The **launchSMS** method is a web services request that calls an Orchestration Designer SMS application. The **launchSMS** web service request succeeds when the Orchestration Designer application begins to run. The launched Orchestration Designer application sends an SMS message

by invoking the notification connector. After the message is sent, a **sendSMS** web service call is created.

The **sendSMS** method enables an application that can make web service calls to send SMS to an SMSC through the SMS Processor. The web service call succeeds when the processor accepts the message. An SMS application can be notified when the message is delivered to the SMSC. These SMS notification messages are sent to the Notification URL that is specified when configuring the SMS application on the EPM. Voice applications that call **sendSMS** must specify the name of a configured SMS application to receive notifications. In addition, an application can send the message with a delivery receipt request. If the application is configured on the EPM to support delivery message types and if the cell phone provider of the recipient returns the delivery receipt, the message is routed to the original sending application. For more information about the notification application, see the Orchestration Designer documentation.

*** Note:**

An SMS Notification Connector pluggable data connector (PDC) is used to send an SMS message from a speech application or a message application that is created for a channel other than the SMS channel

For more information about these new web service methods, see:

- [LaunchSMS method](#) on page 546
- [SendSMS method](#) on page 557

SMS Processors

An SMS Processor is an application that is hosted on the multimedia server. The multimedia server is a service that is deployed on the Primary EPM and the Auxiliary EPMs. An SMS Processor manages connections to one or more SMSCs. The Processor handles the routing of incoming SMS, notifications, and receipts to configured applications and also provides web service interface methods that are used by the Application Interface Web Service to send an SMS message.

The SMS Processors web page allows administrators to add, modify, and delete one or more SMS Processors.

In order to configure an SMS Processor which is hosted on Auxiliary EPM, the Auxiliary EPM must be configured before configuring the associated SMS Processor. The SMS Processor that is configured and hosted on an EPM automatically inherits the name, host address and zone of the EPM on which the SMS Processor resides.

Related links

- [SMS processor states](#) on page 156
- [Adding an SMS processor](#) on page 156
- [Changing the configuration of an SMS processor](#) on page 157
- [Deleting an SMS processor](#) on page 158

SMS processor states

An SMS Processor maintains the following states for managing functions:

State	Description
Not Running	The server is either stopped or not started yet.
Starting	The server start request is initiated, and is in the process of initialization.
Running	The server is up and functional.
Stopping	The server shutdown is requested.
Need Configuration	The server does not find configuration.
Need Connections	The server has configuration but does not have any connections assigned or configured.
Degraded	The server has configuration and connections. However, some or all connections are not working.
Error	The server data returned has been deemed "stale" (no new data retrieved after a period of 3 minutes), or 2) unexpected return code retrieved from a poll to server.
Stopped	The server is stopped.

Related links

[SMS Processors](#) on page 155

Adding an SMS processor

Procedure

1. Log on to the EPM Web interface.
2. In the EPM main menu, select Home > Multi-Media configuration > SMS > SMS Processors.
3. On the **SMS Processors** page, click **Add**.
4. In the **Name** field, select the name of the server from the drop-down box.
5. Select either the **Yes** or the **No** option for the **Enable** button. In the **Enable** field, select **Yes** or **No**.
6. From the **Categories and Trace Levels** group, select **Custom**.
If you select **Use SMS Settings**, then the trace level buttons are disabled.
7. Set the trace level of SMS Processors by selecting the appropriate button.

The options are:

- Off
- Fine
- Finer

- Finest
8. Set the trace level of the SMS Browser by selecting the appropriate button.
The options are:
 - Off
 - Fine
 - Finer
 - Finest
 9. Click **Save**.

Related links

[SMS Processors](#) on page 155

Changing the configuration of an SMS processor

Procedure

1. Log in to the EPM web interface
2. From the EPM main menu, select Home > Multi-Media configuration > SMS > SMS Processors.
3. Select the check box next to the SMS Processor that you want to change.
4. Click the SMS Processors that you have selected. The system opens the **Change Processor** page.
5. In the **Enable** field, select either the **Yes** or **No** radio button.
6. From the **Categories and Trace Levels** group, select **Customs**.
If you select **Use SMS Settings**, then the trace level buttons are disabled.
7. Select the trace level that you want to set for the SMS Processor.

The options are:

- Off
 - Fine
 - Finer
 - Finest
8. Select the trace level that you want to set for the SMS Browser.
 - Off
 - Fine
 - Finer
 - Finest

9. Click **Save**.

Related links

[SMS Processors](#) on page 155

Deleting an SMS processor

Procedure

1. Log in to the EPM web interface.
2. From the EPM main menu, select Home > Multi-Media configuration > SMS > SMS Processors.
3. Select the check box next to the name of the SMS processors that you want to delete.
4. Click **Delete**.

Related links

[SMS Processors](#) on page 155

Adding an SMS application to Experience Portal

Before you begin

Make sure that SMS processor and required connections are configured in the Experience Portal system.

Procedure

1. Log on to the EPM Web interface using an account with the Administration user role.
2. From the EPM main menu, select **System Configuration > Applications**.
3. On the Applications page, click **Add**.
4. On the Add Application page, enter the appropriate information and click **Save**.

To see descriptions of all the fields on the Add Applications page, click **Help**.

Changing the settings of an SMS application

Procedure

1. Log on to the EPM Web interface using an account with the Administration user role.
2. From the EPM main menu, select **System Configuration > Applications**.
3. On the Applications page, click the application name in the **Name** column.

4. On the Change Application page, enter the appropriate information and click **Save**.
To see descriptions of all the fields on the Change Applications page, click **Help**.

Deleting an SMS application

Procedure

1. Log on to the EPM Web interface using an account with the Administration user role.
2. From the EPM main menu, select **System Configuration > Applications**.
3. On the Applications page, for each application that you want to delete, select the check box to the left of the application name in the applications table.
4. Click **Delete**.

Configuring HTTP and SMPP connections

Adding an HTTP connection

Procedure

1. Log in to the EPM web interface.
2. From the EPM main menu, select Home > Multi-Media configuration > SMS > HTTP Connections.
3. On the **HTTP Connections** page, click **Add**. The system displays the **Add HTTP Connection** page.
4. From the **Zone** field, select the name of the zone.
5. In the **Name** field, type the name of the HTTP connection.
6. From the **Enable** field, select the relevant option.
The options available are **Yes** and **No**.
7. Select the accurate transport protocol.
The available options are **TCP** and **TLS**.
8. Enter the host address of the SMSC.
9. Enter the port number that is used for the SMS connection.
10. Enter the path of the SMSC.
11. Enter the user name.

12. Enter the password.
13. Enter your Application Programming Interface (API) ID to facilitate your connection to the connector.
14. From the **Connector** field, select the type of connector.
The options available are **WebText**, **Clickatell**, **OneWay SMS**, and **AOS**.
15. From the Use **HTTP Proxy** field, select **Yes**.
The available options are **Yes** and **No**. You can configure the subsequent fields only if you select **Yes**.
16. Enter the address of the proxy server.
17. Enter the proxy port number.
The default port number is 8000.
18. Enter the sender ID that can be either a short code or a long number.
19. Select one or more organizations from the **Organization** list.
20. **(Optional)** Click the **Additional Entry** option and enter subsequent short codes or long numbers.
21. Click **Save**.

Changing the configuration of an HTTP connection

Procedure

1. Log in to the EPM web interface.
2. From the EPM main menu, select Home > Multi-Media configuration > SMS > HTTP Connections.
3. In the **Name** field, click the name of the HTTP connection. The system displays the **Change HTTP Connection** page.
4. From the **Zone** field, select the name of the zone.
5. From the **Enable** field, select the relevant option.
The options available are **Yes** and **No**.
6. Select the accurate transport protocol.
The available options are **TCP** and **TLS**.
7. Enter the host address of the SMSC.
8. Enter the port number that is used for the SMS connection.
9. Enter the path of the SMSC.
10. Enter the user name.

11. Enter the password.
12. Enter your Application Programming Interface (API) ID to facilitate your connection to the connector.
13. From the **Connector** field, select the connector.
The options available are **WebText**, **Clickatell**, **OneWay SMS**, and **AOS**.
14. From the Use **HTTP Proxy** field, select **Yes**.
The available options are **Yes** and **No**. You can configure the subsequent fields only if you select **Yes**.
15. Enter the address of the proxy server.
16. Enter the proxy port number.
The default port number is 8000.
17. Enter the sender ID that can be either a short code or a long number.
18. Select one or more organizations from the **Organization** list.
19. **(Optional)** Click the **Additional Entry** option and enter subsequent short codes or long numbers.
20. Click **Save**.

Deleting an HTTP connection

Procedure

1. Log in to the EPM web interface.
2. From the EPM main menu, select Home > Multi-Media configuration > SMS > HTTP Connections.
3. Select the check box next to the HTTP connection that you want to delete.
4. Click **Delete**.

Adding an SMPP connection

Procedure

1. Log in to the EPM Web interface.
2. From the EPM main menu, select Home > Multi-Media configuration > SMS > SMPP Connections.
3. On the **SMPP Connections** page, click **Add**.
The system displays the **Add SMPP Connection** page.
4. In the **Zone** field, select the name of the zone.

5. In the **Name** field, type the name of the SMPP connection.
6. In the **Enable** field, select **Yes**.
7. Enter the host address of the SMS server.
8. In the **Shared** field, select the relevant option.

The options available are **Yes** and **No**. If you select **No**, SMS processor is enabled. Otherwise, SMS processor is disabled.
9. Select the SMS processor from the drop-down box.
10. Enter the port number.
11. In the **Bind Mode** field, select the accurate Bind Mode.

The options are Transceiver, Transmitter, and Receiver.
12. Enter the user name.
13. Enter the password.
14. Enter the address range.
15. Set the **From** field to either Short Code or Blank.
16. Enter the sender ID that can be either a short code or a long number.
17. Select one or more organizations from the **Organization** list.
18. **(Optional)** Click the **Additional Entry** option and enter subsequent short codes or long numbers.
19. Specify the values for the **Advanced Parameters** group.

To know about the **Advanced Parameters**, on the **Add SMPP Connection** page, click **Help**.
20. Click **Save**.

Changing the configuration of an SMPP connection

Procedure

1. Log in to the EPM web interface.
2. From the EPM main menu, select Home > Multi-Media configuration > SMS > SMPP Connections.
3. In the **Name** field, click the name of the SMPP connection that you want to change. The system opens the **Change SMPP Connection** page.
4. From the **Zone** field, select the name of the zone.
5. From the **Enable** field, select the relevant option.

The options available are **Yes** and **No**.

6. Enter the host address of the SMS server.
7. From the **Shared** field, select the relevant option.
The options available are **Yes** and **No**. If you select **No**, SMS processor is required. Otherwise, SMS processor is disabled.
8. Select the SMS processor from the drop-down box.
9. Enter the port number.
10. From the **Bind Mode** field, select the accurate bind mode.
The options are Transceiver, Transmitter, and Receiver.
11. Enter the user name.
12. Enter the password.
13. Enter the address range.
14. Set the From field to either Short Code or Blank.
15. Enter the sender ID that can be either a short code or a long number.
16. Select one or more organizations from the **Organization** list.
17. **(Optional)** Click the **Additional Entry** option and enter subsequent short codes or long numbers.
18. Specify the values for the **Advanced Parameters** group.
To know about the **Advanced Parameters**, on the **Change SMPP Connection** page, click **Help**.
19. Click **Save**.

Testing SMPP connections

About this task

The TestSMPPConnection script can be used to verify that the firewall is open to the SMSC and to verify proper credentials prior to configuring a SMPP connection in the EPM.

Procedure

1. Log in to Linux on the EPM server which is hosting the SMS processor.
If you are an Avaya Services representative, and use Avaya Enterprise Linux or if the Avaya Service accounts are installed on this server:
 - Log on to the local Linux console as sroot.
 - Or log on remotely as a non-root user and then change the user to sroot by entering the `su - sroot` command.
 Otherwise, log on to Linux locally as root, or log in remotely as a non-root user and then change the user to root by entering the `su -` command.

2. Navigate to the `Support/VP-Tools` directory under the Experience Portal installation directory.
3. Enter the `cd $AVAYA_HOME/Support/VP-Tools` command. `$AVAYA_HOME` is an environmental variable pointing to the name of the installation directory specified during the Experience Portal software installation.

The default value is `/opt/Avaya/ExperiencePortal`.

4. Enter the bash `TestSMPPConnection` command followed by the following parameters:

- Host Address
- Port
- UserName
- Password

For example, `bash TestSMPPConnection 255.254.253.252 2775 smppUser smppPass`.

One or more optional parameters may be specified, as provided by the SMSC:

- `-B BindMode` where `BindMode` may be `t` for Transmitter, `r` for Receiver, or `x` for Transceiver. The default is `-B x`.
- `-A AddressRange`
- `-S SystemType`

If the script runs successfully, it returns a message stating that the operation completed without any errors. Otherwise, it returns a message stating the problem that it encountered. This script may take 30 seconds to complete.

Deleting an SMPP connection

Procedure

1. Log in to the EPM web interface.
2. From the EPM main menu, select `Home > Multi-Media configuration > SMS > SMPP Connections`.
3. Select the check box next to the SMPP connection that you want to delete.
4. Click **Delete**.

SMS Browser

An SMS Browser is deployed as a web application on the Multi-Media Tomcat application server. The SMS Browser processes the inbound SMS messages and supports running Orchestration Designer applications for outbound SMS messages.

At startup, the SMS Browser reads the browser configuration data from the configuration DB and initializes the text browser. SMS Browser hosts the Text Browser to analyze TextXML generated by Orchestration Designer.

The SMS Browser monitors the message table for new inbound text messages. New inbound messages are fetched in batches and passed to the text browser. The SMS Browser implements a set of callbacks from the text browser.

Text Browser

The text browser fetches and executes <Textxml> from message applications. The text browser resides on the EPM and is the link between the Message Gateway and the Orchestration Designer application. The text browser only supports running Orchestration Designer applications.

TextXML

TextXML is modeled after VoiceXML, and customized to provide text-processing capabilities. Documents generated by Orchestration Designer for message flow applications conforms to the new TextXML schema for Email and SMS handling. TextXML is modified VoiceXML to handle new challenges for working with text messages. The text browser validates each input document against TextXML schema. TextXML starts with the <TextXML> tag, and follows the same structure as VoiceXML containing forms, vars, blocks and grammars. There are some enhancements made to TextXML.

Related links

[Configuring system parameters for SMS browser settings](#) on page 165

[Configuring system parameters for SMS settings](#) on page 166

Configuring system parameters for SMS browser settings

Procedure

1. Log in to the EPM web interface.
2. From the EPM main menu, select Home > Multi-Media configuration > SMS > SMS Processors > Browser Settings.
3. In the **Fetch Timeout** field, enter the maximum number of seconds that the SMS browser must wait for the application server to return the requested page
4. In the **Proxy Server** field, enter the fully qualified path to the proxy server.
5. In the **Proxy Port** field, enter the port number for the proxy server.
6. In the **Number of Threads** field, enter the maximum number of threads that the SMS browser must use for an asynchronous fetch.

You can enter a number between 1 and 500. The default is 50.

7. Click **Save**.

Related links

[SMS Browser](#) on page 164

Configuring system parameters for SMS settings

Procedure

1. Log in to the EPM web interface.
2. From the EPM main menu, select Home > Multi-Media configuration > SMS > SMS Processors > SMS Settings.
3. Type the maximum message length. The default length is set to 960 bytes.
4. From the **Log Level** field, select the level that you want to set.
The default is **Info**.
5. To enable Call Data records and Session Data records, select the check boxes next to the **Call Data** and **Session Data** fields.
6. Type the number of days for the retention period of the records.

 Note:

The retention period impacts how long CDR and SDR are kept in the operational database used by the processor. The retention period does not impact how long these records are kept in the reporting database.

7. Select the appropriate radio buttons to set the trace levels for **SMS Processor** and **SMS Browser** fields.

If you select the top buttons, the same trace levels are set for both **SMS Processor** and **SMS Browser** fields. The radio buttons next to both the fields are automatically selected.

If you do not select the top buttons, you can set different trace levels for **SMS Processor** and **SMS Browser** fields.

The default is **Fine**.

8. Click **Save**.

Related links

[SMS Browser](#) on page 164

SMS web services

EP provides a Web service that helps any client application, whether EP managed or not, to send SMS messages.

The web service facilitates the sending of an SMS message to a single recipient or a list of recipients.

In addition to sending SMS messages through a web service, EP supports the following capabilities:

- Starting stopping an SMS application.
- User name and password authentication is supported for all SMS Web services.

For information on parameters and return values of the SMS application, refer:

- [LaunchSMS method](#) on page 546
- [SendSMS method](#) on page 557

Reporting filters for SMS

Experience Portal 7.0 and later versions have a new media type filter for SMS that is added to the Contact Detail and Contact Summary reports.

The following are the main filters that are available for SMS:

- SMS
- SMS receipt

Experience Portal 7.0 and later versions support the capability to filter the messages on SMSC. This capability consists of the number of messages sent to one or more SMSCs as well as the number of messages received from one or more SMSCs.

The following information is available in these reports:

- The number of messages sent
- The number of messages received
- The number of delivery receipts requested
- The number of receipts pending
- The number of receipts received

All existing filters for the Contact Detail and Contact Summary reports can be applied to reporting records created by incoming or outbound SMS. This support includes the capability to generate reports for any number of zones defined in the system.

SMS delivery receipt flow sequence

- The client requests for SMS delivery receipt in one of the following ways:
 - The client selects the **RegisteredDelivery=1** option in web service parameter.
 - The client submits a request on a link that is configured for registered delivery.

- The SMS processor sends a request for delivery receipt to SMSC on the basis of the client's request.
- Upon receiving a delivery receipt from SMSC, the server creates a receipt record in the operational database.
- The SMS browser launches the configured delivery receipt application and sends the delivery receipt information to the application.
- Once the browser reads the receipt, the browser deletes the record.
- The application can use the message Id from the obtained receipt and can accordingly correlate the corresponding outbound SMS for processing the receipt.

SMSC success and failure responses

EP handles success and failure responses from all SMSCs. The responses are made available to the application for further evaluation and processing. In case of no connectivity with the SMSC, the SMS processor issues retries. The number of retries is not configurable and retries are infinite. The retry interval is configurable.

Other than the connectivity with the SMSC, the application has the capability of handling failures. The application can trigger a **Resend** or any other action to address the failure.

Chapter 8: HTML management

HTML overview

Avaya Aura® Experience Portal 7.1 and later versions support HTML as an additional communication channel and provide a mechanism to move a self-service interaction from a voice interface to a web interface. HTML applications are always launched by name through the Application Interface web service. As a result, there is no concept of launch criteria, launch order, and default HTML application.

*** Note:**

Experience Portal 7.1 supports HTML applications that are developed using Avaya Aura® Orchestration Designer only.

In this deployment, Experience Portal is completely isolated from the public network while the Orchestration Designer application is partially isolated from the public network by using the customer's HTTP reverse proxy server. An additional security layer is provided by isolating the internal configuration and parameters from the public network. In addition, the system provides a mechanism to make visible only established Orchestration Designer sessions to the public network by session initiation that comes through the HTML Redirector application and Experience Portal.

*** Note:**

You must specify the host address of the reverse proxy if you are using a reverse proxy in front of the redirector or multiple redirectors for added redundancy.

You must configure and use a separate redirector for each zone on zoned systems.

HTML typical flow

The flow of an incoming call and the mechanism to provide an HTML interface to the user is as follows:

- A customer calls.
- The SMS, voice, and email application is launched through the Application Interface web service.
- The application fetches the global and application-specific CAVs.

- The customer and the application interacts with each other. Voice interaction happens through MPP, whereas SMS and email interaction happens through the Primary or Auxiliary EPM.
- The customer opts for a richer interface through HTML.
- The SMS, voice, and email application opts to run the HTML mobile application .
- The customer receives an HTML link based on the interaction:
 - SMS and email applications send a message containing the HTML mobile application link through a prompt.
 - Voice applications send the HTML mobile application link as an SMS or email message.

The reference to the EPM system applies to both the Primary and Auxiliary EPM servers as both support the web services required to launch the mobile HTML application. A Redirector application handles the load balancing of the requests by distributing the incoming requests among the EPM servers. On zoned systems, the Redirector application balances the load requests among the EPM servers within a specific zone.

Data collection

Using Avaya Aura® Experience Portal, you can log report data for an Avaya Aura® Orchestration Designer HTML application session. Once the Orchestration Designer HTML application session ends, Orchestration Designer runtime invokes the web service to log report data. Orchestration Designer runtime invokes the web service irrespective of how the session has ended, either in a normal manner or due to a session timeout.

The report collects usual report data for an application and also collects specific data for an HTML application:

- Count of number of interactions with the mobile application.
- Duration for interactions. This does not include session timeouts.
- Duration for which the application was in session. This includes the application server session timeout.

Adding an HTML application to Experience Portal

Procedure

1. Log on to the EPM Web interface using an account with the Administration user role.
2. In the EPM main menu, click **System Configuration > Applications**.
3. On the Applications page, click **Add**.
4. On the Add Application page:
 - a. Enter the name for the application and select **Type** as **HTML**.

- b. Enter the appropriate information for other fields and click **Save**.

To see descriptions of all the fields on the Add Applications page, click **Help**.

Changing the settings of an HTML application

Procedure

1. Log on to the EPM Web interface using an account with the Administration user role.
2. In the EPM main menu, click **System Configuration > Applications**.
3. On the Applications page, click the application name in the **Name** column.
4. On the Change Application page, make the required changes and click **Save**.

To see descriptions of all the fields on the Change Applications page, click **Help**.

Deleting an HTML application

Procedure

1. Log on to the EPM Web interface using an account with the Administration user role.
2. In the EPM main menu, click **System Configuration > Application**.
3. On the Applications page, for each application that you want to delete, select the check box to the left of the application name in the **Applications** table and click **Delete**.

Configuring HTML Redirector

About this task

The HTML Redirector redirects launch requests for HTML applications. Avaya Aura® Experience Portal stores the Redirector configuration in the database as a global CAV. Avaya Aura® Orchestration Designer runtime gets the configured redirector host address from the global CAVs retrieved from the EPM. Orchestration Designer uses the configured information and the HTML application name to generate a URL to launch an HTML5 application through the redirector.

The Redirector servlet hosts a generic URL that is the initial point of contact in launching an Orchestration Designer HTML5 application. The redirector servlet acts as a wrapper around the web service to provide a layer of security by isolating the EPM servers and hiding any sensitive launch configuration such as application internal IP addresses, confidential parameters, and CAVs from direct exposure to the external browser.

You can set the host address and port number for the Redirector.

Procedure

1. Log on to the EPM web interface.
2. In the EPM main menu, click **Multi-Media configuration** > **HTML**.

The system displays the HTML Redirectors page.

3. Enter the host address and port number for the Redirector.

 Note:

The EPM system is installed with a default zone. Therefore, initially the HTML Redirector page displays only one host address and port that you can configure. However, when an administrator configures zones in Experience Portal, the HTML Redirector page displays a host address and port for each zone that you can configure.

A redirector needs to be configured for each zone that hosts HTML applications.

4. In the **Transport Protocol** field, select the Transport Protocol to send a request to the redirector.

Select either TCP or TLS.

5. Enter the path of the URL to be used for communicating with the redirector in the **Path** field.

The default is “ ”. The path appears after the host address and the port. For example, `http://hostaddress:port/path`.

6. Click **Apply**.

The system saves the configuration.

Chapter 9: Configuring System Manager Single Sign-On

Prerequisites

This chapter describes the prerequisites and procedures required to enable Single Sign-On between Avaya Aura® System Manager and EPM. Customers must read and understand all the considerations and complete all the procedures in this section.

Before enabling the Single Sign-On between System Manager and EPM, you must:

- Import the System Manager certificate to EPM by using the EPM Trusted Certificates webpage, and specify the certificate type as System Manager.

Use the URL `https://<SMGR_FQDN>:443` to import the System Manager certificate.

- Both the System Manager and the primary EPM server requires a fully qualified domain name (FQDN) that can be resolved in the DNS server. The FQDN of the primary EPM server must match a part of the System Manager server's domain name.
- Copy the file `experienceportalWelcome.html` to the System Manager. To perform this task, follow `README.txt` located in the `$AVAYA_HOME/Support/SMGR` directory on the primary EPM.

You must perform this step only once.

- Synchronize the machine date and time between the System Manager and EPM systems.
- Configure the value of the maximum session timeout of System Manager as near to the session timeout configured in EPM.

Configuring the EPM System Manager Settings page

Procedure

1. Log on to the EPM web interface using an account with the User Manager role.
2. In the EPM main menu, click **User Management > Login Options**.
3. On the Login Options page, click **System Manager Settings**.
4. Configure the parameters to enable Single Sign-On between the System Manager and EPM systems.

Related links

[System Manager Settings page field descriptions](#) on page 174

System Manager Settings page field descriptions

Use the fields on this page to establish Single Sign-on with Avaya Aura® System Manager. For more information, see Configuring System Manager Single Sign-On.

Name	Description
Enable Single Sign-On	Allows you to enable or disable Single-Sign on. The options are: • Yes: The Single Sign-On is enabled. • No: The Single Sign-On is disabled.  Note: 1. When you click Save or Apply, Avaya Aura® Experience Portal verifies the System Manager settings only if the Enable Single Sign-On field is set to Yes. If all fields are valid, Experience Portal performs the following actions with System Manager that is configured on this page: - Register Experience Portal Resource Type, Experience Portal system roles, and Experience Portal Resource Instance. - Register navigation link. - Enable SSO client. If the Enable Single Sign-On field is set to No, Experience Portal saves the changes but does not verify the changes if there is no prior configured and enabled System Manager. 2. When you have enabled Single Sign-On, the user can only modify the Navigation Link Display, User Name, and Password. 3. If the user changes the Single Sign-In option from enabled to disabled, EPM tries to communicate with the previous configured System Manager to remove the SSO client and de-register the navigation link and Experience Portal

Name	Description
	Resource Instance. This is possible only if: - Experience Portal is able to access the previous configured System Manager. - System Manager User name and credentials configured are still valid. 4. If Experience Portal cannot access System Manager, the page displays the Force Change check box. Use the check box to disable Single Sign-On with the configured System Manager.

Connection Settings section

Name	Description
System Manager FQDN	The fully qualified host name of the System Manager.  Note: 1. The EPM server must match a part of the System Manager server's domain name. For example, if the FQDN of System Manager server is <code>smgr.us.avaya.com</code>, the FQDN of EPM that can perform Single Sign-On with System Manager can be <code>xx.us.avaya.com</code> or <code>xx.yy.avaya.com</code> or <code>xx.avaya.com</code>. 2. If the System Manager FQDN entered is different than the previous configured System Manager, you must restart EPM to enable Single Sign-On with the new System Manager.
Navigation Link Display	A link display that represents the primary EPM on the System Manager webpage. You can view this Navigation Link Display on the System Manager webpage from: • Home page > Elements > Experience Portal System. • Resource Instance when configuring a role. Valid characters are number, letters, and any of "-", "(", ")", "/", "\", ".", "_", "{", "}".

Table continues...

Name	Description
	 Note: If you have multiple EPMs that are enabled to perform Single Sign-On with the same System Manager, you must configure a unique Navigation Link Display.
User Name	A valid System Manager user who has the System Administrator role and is authorized to register Resource Type and Resource Instance with System Manager.  Note: This user must be a System Manager user and not an EPM user. This System Manager user must be created from the User Management page in the Users tab in System Manager.
Password	The password of the System Manager user.

 Note:

On the primary EPM, if you enable Single Sign-On with a System Manager and if you change the System Manager FQDN to a different System Manager, restart the primary EPM for Single Sign-On with the new System Manager to work properly.

Related links

[Configuring the EPM System Manager Settings page](#) on page 173

Creating a System Manager user

About this task

Avaya recommends that you create a new Avaya Aura® System Manager user with a System Administrator role on the System Manager system.

Use these System Manager user credentials when configuring the System Manager Settings page on the EPM. EPM uses these System Manager credentials to register Experience Portal Resource Type, managed resources, and navigation menu items with System Manager.

 Note:

Do not use the default System Manager user administrator credentials when configuring the System Manager Settings page.

Procedure

Log on to System Manager and navigate to the User Management page .

If a temporary password is assigned to the user, then log in to System Manager by using this user credential and change the password.

Items created on System Manager after enabling Single Sign-on

When you enable Single Sign-on in EPM, the following items are created on Avaya Aura® System Manager:

- Built-in Experience Portal System Roles:
 - Experience Portal Administration
 - Experience Portal User Manager
 - Experience Portal Auditor
 - Experience Portal Maintenance
 - Experience Portal Privacy Manager
 - Experience Portal Reporting
- An **Experience Portal** Resource Type.
- A link **Experience Portal System** in the **Elements** tab on the System Manager home page.
- A navigation link with the name configured in the **Navigation Link Display** on the EPM System Manager Settings page.
- A managed resource with the name configured in the **Navigation Link Display** on the EPM System Manager Settings page.

Note:

If you have installed Intelligent Customer Routing (ICR) Managed App on the Experience Portal system, the system creates the following items on System Manager:

- Built-in Experience Portal ICR System Roles.
 - Experience Portal ICR Administration
 - Experience Portal ICR Reporting
- An **Experience Portal ICR** Resource Type.
- An ICR managed resource with the name configured in the **Navigation Link Display** on the EPM System Manager Settings page.

If you have installed Proactive Outreach Manager (POM) Managed App on the Experience Portal system, the system creates the following items on System Manager:

- Built-in Experience Portal POM System Roles.
 - Experience Portal POM Administration
 - Experience Portal POM Campaign Manager
- An **Experience Portal POM** Resource Type.

- A POM managed resource with the name configured in the **Navigation Link Display** on the EPM System Manager Settings page.

Experience Portal roles and permissions assignment

The Experience Portal permissions assigned to the System Manager user determine the EPM webpages that can be accessed by the System Manager user.

The System Manager administrator can assign any built-in Experience Portal system roles or a custom role that includes the Experience Portal permissions to any valid System Manager user.

- To map permissions to a customer role in System Manager, select **Experience Portal** in the **Element or Resource Type** field.
- In the **Element or Resource instance** field, the **EPM Navigation Link Display** configured on the System Manager Settings page appears in the list.
- Click **Next**. The Permission Mapping page shows all the available Experience Portal permissions that you can select from.

Note:

When the System Manager Administrator selects Experience Portal Resource Type to add permission mapping to a custom role, the **EPM Navigation Link** permission is selected by default. Without this permission, the System Manager user cannot click the **Experience Portal System** link in the **Elements** tab on the System Manager home page.

Single Sign-on

Single Sign-On with System Manager can be accomplished in the following three ways:

Single Sign-On from System Manager

1. Start a Browser and log in to System Manager through System Manager FQDN with a valid System Manager User credentials having Experience Portal permissions.
2. On the System Manager home page, click the **Experience Portal System** link in the **Elements** tab.
3. Expand the left menu, and click the **EPM** link.

The Browser displays the EPM home web page in another tab or in another window without prompting for credentials.

Single Sign-On from System Manager

1. Start a Browser and log in to System Manager through System Manager FQDN with a valid System Manager User credentials having Experience Portal permissions.

2. In the same Browser, start a new Window or a new tab and enter the EPM FQDN in the address bar.

The Browser displays the EPM home web page in the new Window or another tab without prompting for credentials.

Single Sign-On from EPM

1. Start a Browser and log in to EPM through the EPM FQDN.
2. Enter valid System Manager User credentials.

The system displays the EPM home web page.

Note:

Single Sign-On between System Manager and EPM is not supported when accessing through IP address.

To remove all configuration in the System Manager Setting page, disable Single Sign-On.

Logoff

When a Single Sign-On session is active, always click **Log off** to log out from System Manager or EPM.

When a user logs off from System Manager, the system terminates the EPM session. In this release, the EPM webpage does not automatically display the login page unless a user clicks the link on the EPM webpage.

When a user logs off from EPM, the system terminates the System Manager session. The System Manager page displays the login page in a few seconds.

Invalid login scenarios

The following System Manager Users cannot use the Single Sign-On to the EPM feature:

- A disabled System Manager user.
- A password expired System Manager user.
- A System Manager user with the same name as an existing Experience Portal web user.
- An organization System Manager administrator.

Reconfiguring Single Sign-On following a System Manager upgrade

Before you begin

Verify whether you are able to access System Manager using the Single Sign-On feature from EPM.

About this task

Use this procedure to ensure that the Single Sign-On continues to work after a System Manager upgrade.

The Single Sign-On feature allows you to access System Manager and EPM using a Single Sign-on. Following a System Manager upgrade the Single Sign-On will fail if the Experience Portal files on the System Manager are not retained and/or if the System Manager certificate is modified.

Procedure

1. Log on to System Manager as a root user.
2. Verify whether the `experienceportalWelcome.html` file exists at the following location:
`$JBOSS_HOME/server/avmgt/deploy/ROOT.war/
experienceportalWelcome.html`.
3. If the file does not exist, do the following:
 - a. Follow the `Readme.txt` located in the `$AVAYA_HOME/Support/SMGR` directory on the primary EPM.
 - b. Copy the `experienceportalWelcome.html` file to System Manager.
4. If System Manager has a new certificate after the upgrade, do the following:
 - a. Import the new System Manager certificate to the EPM Trusted Certificates Web pages by using the URL `https://<SMGR FQDN>:443`.
 - b. Specify the certificate type as System Manager.
5. Close all existing browsers and start a new browser instance to access System Manager using Single Sign-On.

System Manager Single Sign-On limitations in Experience Portal Release 7.1

The following are the limitations of Single-Sign-on:

- Cannot DELETE EP Resource Type, EP System Roles in System Manager: The Experience Portal Resource Type, ICR Resource Type, POM Resource Type, Experience Portal system roles, POM system roles, and ICR system roles cannot be deleted in System Manager after you have created them from EPM.
- No Locale Support: This includes but is not limited to Experience Portal Resource Type, ICR Resource Type, POM Resource Type, Experience Portal system roles, POM system roles, and ICR system roles, features, and navigation links created in System Manager.
- No Organization Support: Administrators created in Tenant Management cannot access Experience Portal from the System Manager dashboard.

In this release, there is no organizational support for System Manager Single Sign-On. Therefore, an organization System Manager administrator cannot use the Single Sign-On feature to log on to EPM. System Manager also does not support EPM organization roles and features mappings.

- No Notification Mechanism between System Manager and EPM: System Manager does not send out notifications to the EPM when a System Manager session expires, terminates, or logs

out. Similarly, System Manager does not have the ability to receive notifications when the EPM session expires. Sessions are validated when the next request is made.

Chapter 10: Server and database administration

EPM server administration

Changing EPM server settings

The EPM server settings apply to both the primary EPM server and the optional auxiliary EPM server.

Procedure

1. Log on to the EPM Web interface using an account with the Administration user role.
2. From the EPM main menu, select **System Configuration > EPM Server**.
3. On the EPM Servers page, click **EPM Settings**.
4. On the EPM Settings page, enter the appropriate information and click **Save**.

Configuring an auxiliary EPM server

About this task

The auxiliary EPM server:

- Can assign outgoing calls made with the Application Interface web service to an available MPP server. Avaya Aura® Experience Portal does not provide load balancing or failover, however. You must use a third-party product for these purposes.
- Shares Application Logging web service requests when the primary EPM server is in service.

Note:

When using the Application Logging web service, Orchestration Designer 7.1 provides failover and load balancing between the primary and auxiliary EPM servers. Applications written with other tools must provide their own load balancing and failover mechanisms for this web service.

- Handles all requests when the Primary EPM is down
- Does *not* include the EPM Web interface, therefore it cannot be used to administer the system or monitor the status of the MPP servers.

Procedure

1. To reset the password for the vpcommon PostgreSQL account:

- a. Log on to Linux on the Experience Portal Primary EPM server.

If you are an Avaya Services representative, and use Avaya Enterprise Linux or if the Avaya Service accounts are installed on this server:

- Log on to the local Linux console as `sroot`.
- Or log on remotely as a non-root user and then change the user to `sroot` by entering the `su - sroot` command.

Otherwise, log on to Linux locally as `root`, or log in remotely as a non-root user and then change the user to `root` by entering the `su -` command.

- b. Navigate to the `Support/VP-Tools/SetDbPassword` directory by entering the `cd $AVAYA_HOME/Support/VP-Tools/SetDbPassword` command.

`$AVAYA_HOME` is the environment variable pointing to the name of the installation directory specified during the Experience Portal software installation. The default value is `/opt/Avaya/ExperiencePortal`

 Tip:

This script is also available in the `Support/VP-Tools` directory of the Experience Portal installation DVD.

- c. Enter the `bash SetDbPassword.sh update_primary_vpcommon` command.

- d. Type the password for the vpcommon PostgreSQL account and press `Enter`.

2. Install the auxiliary EPM software on the new server as described in the *Optional: Installing the EPM software on the auxiliary EPM server* topic of the *Implementing Avaya Aura® Experience Portal on multiple servers* guide.

When you get to the Database Login Check for Auxiliary EPM installation screen, make sure you specify the password for the vpcommon PostgreSQL database user account.

3. When the installation has finished, add the server to the Experience Portal system:

- a. Log on to EPM Web interface.

If Avaya Services is maintaining this system and you are an Avaya Services representative, log on to the EPM using the init EPM account created during the EPM software installation.

Otherwise, log on to the EPM using an account with the Administrator user role.

- b. From the EPM main menu, select **System Configuration > EPM Server**.
 - c. On the EPM Servers page, click **Add**.
 - d. On the first Add EPM Server page, enter the appropriate information and click **Continue**.
 - e. On the second Add EPM Server page, enter the appropriate information.

If you logged in using the init account, ensure you enter the appropriate LDN number for the server in the **LDN** field. If you do not specify an LDN number, Experience Portal uses the default value (000)000-0000.

- f. Click **OK**.

Changing the configuration information for a EPM server

Procedure

1. Log on to EPM Web interface.

If Avaya Services is maintaining this system and you are an Avaya Services representative, log on to the EPM using the init EPM account created during the EPM software installation.

Otherwise, log on to the EPM using an account with the Administrator user role.

2. From the EPM main menu, select **System Configuration > EPM Server**.
3. On the EPM Servers page, click the name of the EPM server whose settings you want to change.
4. On the Change EPM Server page, enter the appropriate information and click **Save**.

If you logged in using the init account, make sure that the LDN number specified in the **LDN** field matches the information in the Avaya Services database for this server.

Reconnecting the primary and auxiliary EPM servers

Before you begin

Make sure you have reconnected the auxiliary EPM server. The `setup_vpms.php` command is used to reconnect the auxiliary EPM server.

Procedure

1. Log in to the EPM Web interface.

If Avaya Services is maintaining this system and you are an Avaya Services representative, log in to the EPM using the init EPM account created during the EPM software installation.

Otherwise, log in to the EPM using an account with the Administration user role.

2. From the EPM main menu, select **System Configuration > EPM Server**.
3. On the **EPM Servers** page, click the name of the auxiliary EPM server.
4. On the **Change EPM Server** page, enable the **Trust new certificate** check box in the **EPM Certificate** section.
5. If you logged in using the init account, make sure that the LDN number specified in the **LDN** field matches the information in the Avaya Services database for this server.
6. Click **Save**.

Deleting the auxiliary EPM server

Before you begin

You need to delete the managed applications, if any, installed on the auxiliary EPM server. For more information, see the documentation delivered with the managed application.

Procedure

1. Log on to the EPM Web interface using an account with the Administration user role.
2. From the EPM main menu, select **System Configuration > EPM Server**.
3. On the EPM Servers page, click the Selection check box next to the name of the auxiliary EPM server.
4. Click **Delete**.

Stopping the vpms service

You can stop the vpms service if you need to perform maintenance procedures on the server machine.

Procedure

1. Log on to Linux on the Primary or Auxiliary EPM server.

If you are an Avaya Services representative, and use Avaya Enterprise Linux or if the Avaya Service accounts are installed on this server:

- Log on to the local Linux console as sroot.
- Or log on remotely as a non-root user and then change the user to sroot by entering the `su - sroot` command.

Otherwise, log on to Linux locally as root, or log in remotely as a non-root user and then change the user to root by entering the `su -` command.

2. Stop the *vpms* service by entering the `/sbin/service vpms stop` command.

You will see a series of messages as the command starts to shut down EPM components. When the command has successfully stopped all relevant components, the system displays the message: `VPMS Shutdown Status: [ OK ]`.

Next steps

After you finish performing the maintenance procedures, restart the vpms service by entering the `/sbin/service vpms start` command.

Associating Engagement Development Platform with an Experience Portal system

About this task

Avaya Aura® Experience Portal provides a mechanism to associate Engagement Development Platform with an Experience Portal system. The information entered in Experience Portal is stored in global configurable application variables and Avaya Aura® Orchestration Designer uses this information to integrate Orchestration Designer applications with Engagement Development Platform workflows.

Procedure

1. Log on to the EPM Web interface using an account with the Administration user role.
2. In the EPM main menu, click **System Configuration > EPM Servers**.
3. On the EPM Servers page, click **Data Storage Settings**.
4. On the Data Storage Settings page, expand **Engagement Development Platform** and enter information in the fields.

To see descriptions of all the fields on the Data Storage Settings page, click **Help**.

5. Click **Apply > Save**.

Configuring Conversation Repository

About this task

You can use the Conversation Repository feature of Avaya Aura® Experience Portal to store and share conversations in multichannel applications. A conversation is data that a multiturn application stores to remember its state across turns. The feature supports all media types, such as HTML, Email, SMS, and Voice, and provides the option of storing conversation data at alternate locations .

Experience Portal provides the following options for storage of data:

- Local EPM
- Primary EPM
- Context Store

For more information about each location, see Database Storage Settings page field descriptions.

Procedure

1. Log on to the EPM web interface using an account with the Administration user role.
2. In the EPM main menu, click **System Configuration > EPM Servers**.
3. On the EPM Servers page, click **Data Storage Settings**.
4. On the Data Storage Settings page, expand **Conversations** and enter information in the fields.

To see descriptions of fields , click **Help**.

5. Click **Apply** > **Save**.

Moving the Avaya Aura Experience Portal software

Move the Experience Portal software to a different server machine

If required, you can move the Experience Portal software to a different server machine. In all cases, you should make every effort to use the same hostname and IP address on the new server as on the old server. This reduces the number of changes you need to make to the Experience Portal system configuration.

If you want to:

- Move the EPM software to a new server in a system where the EPM and MPP software runs on different servers, see [Move the EPM software to a different server machine](#) on page 187.
- Move the MPP software to a new server in a system where the EPM and MPP software runs on different servers, see [Moving an MPP to a different dedicated server](#) on page 189.
- Move the Experience Portal software in a system where the EPM and the MPP run on the same server, see [Move a single-server Experience Portal system to a different server](#) on page 190.

Move the EPM software to a different server machine

This procedure applies to moving the primary EPM software in a dedicated server configuration. If you need to:

- Move the EPM software in a system where the EPM and the MPP software runs on the same server, see [Move a single-server Experience Portal system to a different server](#) on page 190.
- Move the auxiliary EPM software, simply install the software on the new server as described in [Configuring an auxiliary server](#) on page 182.

Important:

Because these steps build on each other, you must complete them in the order given or you may encounter errors during the procedures.

Step	Description	
1	On the old EPM server, back up the Experience Portal database as described in System Backup Overview on page 207.	

Table continues...

Step	Description	✓
2	If possible, set up the new server so that it has the same IP address and hostname as the old EPM server.	
3	On the new EPM server, install the operating system and the EPM server software as if this was a new installation. If at all possible, the new EPM server should have the same hostname and IP address as the old EPM server in order to minimize the number of manual changes you will need to make. ! Important: Make sure you: • Perform all software prerequisites, such as synchronizing the time between the new EPM server and the MPP servers. • Select the same options you selected for the previous installation. • Go through the same configuration steps after you install the software. For example, if you synchronized the old EPM server with an external time source, make sure you configure the new server to use that time source as well.	
4	On the new EPM server, configure the backup and restore scripts as described in Verifying the backup server mount point on page 218. Make sure that you specify the same mount point and shared directory that you used on the old EPM server.	
5	Restore the Experience Portal database from the backup you made on the old EPM server as described in Database Restore utility and system backup on page 217.	
6	If you could not use the same hostname and IP address for the new EPM server, change the information in the Experience Portal database as described in Changing the hostname or IP address on a dedicated primary EPM server on page 200.	
7	If you could not use the same IP address and hostname for the new server, you need to connect each MPP server with the new EPM server as described in Reconnecting an existing MPP server with the EPM server on page 201.	
8	If your WebLM server ran on the old EPM server, install the Experience Portal license file on the new EPM server as described in the <i>Installing the license file</i> topic in the <i>Implementing Avaya Aura® Experience Portal on multiple servers</i> guide. Otherwise, verify that the new EPM server can contact the WebLM sever by selecting Security > Licensing from the EPM main menu and clicking Verify on the Licensing page.	

Moving an MPP to a different dedicated server

About this task

* Note:

This procedure applies to the Experience Portal system in which the MPP software runs on a dedicated server. If you need to move the MPP in a system where the EPM and the MPP run on the same server, see [Move a single-server Experience Portal system to a different server](#) on page 190.

Procedure

1. If you want to transfer the MPP log files:
 - a. Log into the Media Server Service Menu as described in [Logging in to the Media Server Service Menu](#) on page 280.

+ Tip:

You can also pack the files by running the `getmpplogs.sh` script on the MPP server. For more information, see the *Administrative scripts available on the MPP* topic of the *Troubleshooting Avaya Aura® Experience Portal* guide.

- b. Go to the Diagnostics page and select **Pack Files**.
 - c. On the Pack Files Options page, select **Logs** and **Transcriptions and utterances**.
 - d. Click **Pack**.
 - e. When the process has completed, download the `tar.gz` archive file.
2. If possible, set up the new server so that it has the identical IP address and hostname as the old MPP server. The hostname should match in all respects, including case.
3. Install the MPP software on the new server as described in the *Installing the MPP software interactively* topic of the *Implementing Avaya Aura® Experience Portal on multiple servers* guide.

! Important:

Make sure you select the same options you selected for the previous installation.

4. If you want to transfer the MPP log files, restore them as described in [Restoring packed MPP log files](#) on page 194.
5. If you could not configure the new MPP server to use the same IP address and hostname as the old MPP server:
 - a. Log on to the EPM Web interface using an account with the Administration user role.
 - b. Change the hostname or IP address of the MPP on the Change MPP Server page as described in [Changing an MPP](#) on page 258.
6. Reestablish the link between the EPM and the MPP as described in [Reestablishing the link between the EPM and an MPP](#) on page 190.

Reestablishing the link between the EPM and an MPP

About this task

After you upgrade the Experience Portal software, use this procedure to reestablish the link between the MPP and the EPM by trusting the MPP's security certificate.

Procedure

1. Log on to the EPM Web interface using an account with the Administration user role.
2. From the EPM main menu, select **System Configuration > MPP Servers**.
3. Click the name of the MPP server.
4. On the Change MPP Server page, go to the **MPP Certificate** section and select the **Trust new certificate** check box if that check box is visible.
5. At the bottom of the page, click **Save**.
6. From the EPM main menu, select **System Management > MPP Manager**.
7. On the MPP Manager page, look at the **Mode** column for this server. If it says **Offline**:
 - a. Select the check box next to the name of the MPP.
 - b. In the **Mode Commands** group, click **Online**.
 - c. In a few moments, click **Refresh** to verify that the **Mode** column now says **Online**.
8. Select the check box next to the name of the MPP.
9. In the **State Commands** group, click **Start** and confirm your selection when prompted.
10. In a few minutes, click **Refresh** to verify that the current **State** is **Running**.
11. If desired, make sure that telephony ports were correctly allocated to the MPP server:
 - a. From the EPM main menu, select **Real-Time Monitoring > Port Distribution**.
 - b. On the Port Distribution page, examine the **Current Allocation** column to find the ports allocated to this MPP.
 - c. Look at the **Mode** and **State** columns to make sure the assigned ports are ready to receive calls.

Move a single-server Experience Portal system to a different server

This procedure applies to the Experience Portal system in which the EPM software runs on the same server as the MPP software. If you need to move the EPM or MPP software in a system where the EPM and the MPP run on different servers, see [Move the EPM software to a different server machine](#) on page 187 or [Moving an MPP to a different dedicated server](#) on page 189.

! Important:

Because these steps build on each other, you must complete them in the order given or you may encounter errors during the procedures.

Step	Description
1	On the old Experience Portal server, back up the Experience Portal database. For more information, see System Backup Overview on page 207.
2	If you want to transfer the MPP log files, pack them on the old server as described in Packing MPP logs and transcriptions in a TAR file on page 191.
3	If possible, set up the new server so that it has the same IP address and hostname as the old Experience Portal server.
4	On the new server, install the Experience Portal software. For more information, see <i>Installing the Avaya Aura® Experience Portal software</i> topic in the <i>Implementing Avaya Aura® Experience Portal on a single server</i> guide. ! Important: Make sure you select the same options you selected for the previous installation, and that you go through the same configuration steps after you install the software. For example, if Avaya Services maintains this Experience Portal system, make sure you set up the Avaya Services access requirements as described in the <i>Configuring the Avaya Service accounts</i> topic in the <i>Implementing Avaya Aura® Experience Portal on multiple servers</i> guide.
5	On the new Experience Portal server, configure the backup and restore scripts as described in Verifying the backup server mount point on page 218. Make sure that you specify the same mount point and shared directory that you used on the old sever.
6	Restore the Experience Portal database from the backup you made on the old EPM server as described in Database Restore utility and system backup on page 217.
7	If you archived the MPP log files, restore them by unpacking the TAR archive created by the pack command as described in Restoring packed MPP log files on page 194.
8	If you could not use the same hostname and IP address for the new EPM server, change the information in the Experience Portal database as described in Changing the hostname or IP address on a dedicated primary EPM server on page 200.
9	Reestablish the link between the EPM and the MPP as described in Reestablishing the link between the EPM and an MPP on page 190.
10	If your WebLM server ran on the old EPM server, install the Experience Portal license file on the new EPM server as described in the <i>Installing the license file</i> topic in the <i>Implementing Avaya Aura® Experience Portal on multiple servers</i>. Otherwise, verify that the new EPM server can contact the WebLM sever by selecting Security > Licensing from the EPM main menu and clicking Verify on the Licensing page.

Packing MPP logs and transcriptions in a TAR file

About this task

You can use the Diagnostics in the Media Server Service Menu to pack the logs, transcriptions, and debug files into a single TAR file for further diagnostics and troubleshooting.

*** Note:**

You can use the `getmpplogs.sh` script to customize which files are packed.

Procedure

1. Log into the Media Server Service Menu as described in [Logging in to the Media Server Service Menu](#) on page 280.
2. From the Media Server Service Menu, select **Diagnostics**.
3. On the Diagnostics page, click **Pack Files**.
4. On the Pack Files Options page, select the files you want to pack. You can select any or all of the following:
 - **Select all** check box: Pack all available files.
 - **Logs**: Pack all the MPP log files.
 - **Transcriptions and utterances**: Pack all the transcriptions and utterances saved by the applications running on the MPP.
 - **Debug files**: Pack all the debug (trace) data recorded on the MPP.
5. Click **Pack**.

Experience Portal creates a TAR file with the format `<hostname>_<date and time stamp>_MPP.tar` that contains all of the selected information. In addition, Experience Portal creates a TAR file for each MPP component with the format `<MPP component>_<hostname>_<date and time stamp>_MPP.tar`.

Experience Portal displays the TAR file names at the bottom of the page.

6. To save any TAR file, right-click the file name and select **Save As** from the pop-up menu.

Next steps

If you need to restore the packed log files, use the `restorempplogs.sh` script.

Packing MPP logs and transcriptions using `getmpplogs.sh`

The `getmpplogs.sh` script packs system information files, logs, and transcriptions into one TAR file.

About this task

*** Note:**

You can also pack the log files from the Diagnostics page in the Media Server Service Menu.

Procedure

1. Log on to Linux on the Experience Portal MPP server.

If you are an Avaya Services representative, and use Avaya Enterprise Linux or if the Avaya Service accounts are installed on this server:

- Log on to the local Linux console as `sroot`.
- Or log on remotely as a non-root user and then change the user to `sroot` by entering the `su - sroot` command.

Otherwise, log on to Linux locally as `root`, or log in remotely as a non-root user and then change the user to `root` by entering the `su -` command.

*** Note:**

You can run this script as an `avayagroup` member, but if you run this script while logged in as `root` or `sroot`, it collects additional log files.

2. Navigate to the MPP `bin` directory by entering the `cd $AVAYA_MPP_HOME/bin` command.

`AVAYA_MPP_HOME` is the environment variable pointing to the name of the MPP installation directory specified during the Avaya Aura® Experience Portal software installation.

3. Enter the `getmpplogs.sh` command with the desired options. You can select:

Option	Purpose
--web	Option used when command is run from the MPP Service Menu.
--logs	To export system information and MPP logs, Apache logs, and system event logs. The system information exported is: • hostname • system uptime • system CPU and memory information • network configuration • storage usage • <code>/etc/hosts</code> file • currently running processes • CPU activity information • RPM database information • MPP specific configuration
--transcriptions	To export system information and all the transcriptions and utterances.
--debugfiles	To export only the system information and all the latest core files from each MPP component with libraries and debug symbols.
--help	To display the above <code>getmpplogs.sh</code> commands.

Option	Purpose
	 Note: This parameter cannot be combined with any other parameters.

Except for the `--help` option, you can specify any combination of parameters when you run the `getmpplogs.sh` script. The types of files that are packed in the TAR file depends on the combination of the command options that you use.

For example, to pack all transcriptions, system information, and debug files in a TAR file stored in the `$AVAYA_MPP_HOME/web/admin/AVPSupport` directory, enter the `getmpplogs.sh --web --transcriptions --debugfiles` command.

Next steps

If you need to restore the packed log files, use the `restorempplogs.sh` script.

Restoring packed MPP log files

About this task

You can use the `restorempplogs.sh` script to restore the MPP log files that were packed using either the `getmpplogs.sh` script or the Pack Files Options page available from the Media Server Service Menu.

The `restorempplogs.sh` script:

- Stops the MPP service
- Restores the call data records
- Restores the installation logs
- Restores the process logs, if available
- Restores the transcriptions and utterances, if available
- Restarts the MPP service

Procedure

1. If the MPP was started through the EPM:
 - a. Log on to the EPM Web interface using an account with the Administration or Operations user role.
 - b. From the EPM main menu, select **System Management > MPP Manager**.
 - c. On the MPP Manager page, use the Selection check box in the MPP server table to select which MPPs you want to change.
 - d. Click **Stop** in the **State Commands** group.
 - e. After the grace period expires, click **Refresh** to ensure that the state is now **Stopped**.
 - f. Click **offline** in the **Mode Commands**.
2. Log on to Linux on the Experience Portal MPP server.

If you are an Avaya Services representative, and use Avaya Enterprise Linux or if the Avaya Service accounts are installed on this server:

- Log on to the local Linux console as `sroot`.
- Or log on remotely as a non-root user and then change the user to `sroot` by entering the `su - sroot` command.

Otherwise, log on to Linux locally as `root`, or log in remotely as a non-root user and then change the user to `root` by entering the `su -` command.

3. Restore the log files by entering the `bash restorempplogs.sh <path/file.tar.gz>` command, where `<path/file.tar.gz>` is the fully qualified path and file name of the file created by the `Pack` command or the `getmmplogs.sh` script.

If the script finds the file, it displays the following:

```
This utility will restore records of type:
Records
Installation logs
Process logs
Transcriptions & Utterances
from a tar file generated by the getmmplogs script.
If the directories for these records already exist, then
the directory will be renamed to <directory-YYYYMMDD-HHMM> before
the restore.
Press Enter to continue, or press Control-c to cancel
```

4. Press `Enter` to run the script and restore the log files. The script produces output similar to the following:

```
Extracting files from
'/opt/Avaya/VoicePortal/MPP/tmp/AVPSupport/cl-
mmpplab-02_Apr_24_2007_14_12_17_MPP.tar.gz'...
Depending on the amount of data, this may take several minutes.
Stopping services...
Checking service 'mmp'
- stopping: 'mmp'
- Restoring 'Records'
Moving existing '/opt/Avaya/VoicePortal/MPP/logs/records' to
'/opt/Avaya/VoicePortal/MPP/logs/records-20070424-1419'...
Restoring '/tmp/untar/logs/records' to '/opt/Avaya/VoicePortal/MPP/
logs/records'...
Restoring directory and file permissions...
- Restoring 'Installation logs'
Moving existing '/opt/Avaya/VoicePortal/MPP/logs/install' to
'/opt/Avaya/VoicePortal/MPP/logs/install-20070424-1419'...
Restoring '/tmp/untar/logs/install' to '/opt/Avaya/
VoicePortal/MPP/logs/install'...
Restoring directory and file permissions...
- Restoring 'Process logs'
Moving existing '/opt/Avaya/VoicePortal/MPP/logs/process' to
'/opt/Avaya/VoicePortal/MPP/logs/process-20070424-1419'...
Restoring '/tmp/untar/logs/process' to '/opt/Avaya/
VoicePortal/MPP/logs/process'...
```

```
Restoring directory and file permissions...
- Restoring 'Transcriptions & Utterances'
  Moving existing '/opt/Avaya/VoicePortal/MPP/logs/
transcriptions' to
  '/opt/Avaya/VoicePortal/MPP/logs/
transcriptions-20070424-1419'...
  Restoring '/tmp/untar/transcriptions' to '/opt/Avaya/
VoicePortal/MPP/logs/transcriptions'...
Restoring directory and file permissions...
Log Restoration Complete!
INFO: The service 'mpp' will not be automatically restarted by this
script. If you wish to restart
this service, use the command:
      /sbin/service mpp start
```

5. If the hostname of the current machine is different than the hostname stored in the log files, the `restoremplogs.sh` script displays a warning message alerting you that the names of the log files in the `$AVAYA_MPP_HOME/logs/records` and `$AVAYA_MPP_HOME/logs/transcriptions` directories need to be changed so that the hostname included in the filename matches the server's new hostname.

When you rename these files:

- Use the short name for the server instead of the fully qualified domain name.
- Make sure that the hostname you specify matches the exact server hostname, including case.

 Note:

If you do not change the log file names, then these records will not be accessible to the EPM server and therefore will not be accessible to any reports created through the EPM.

Diagnostics page field descriptions

This page provides you with tools you can use to collect the MPP log files for troubleshooting purposes, and to test the MPP.

To go to the Diagnostics page, log in to the **MPP Service** menu as described in [Logging in to the Media Server Service Menu](#) on page 280.

This page contains the following links:

- **Check connections to servers**, which goes to the Check Server Connections page.
- **Pack files**, which goes to the Pack Files Options page.
- **View process messages**, which goes to the Process Messages page.
- **Version**, which goes to the Version page.

Pack Files Options page field descriptions

Use this page to combine one or more log files into a single compressed file that you can send to Avaya support if you are trying to troubleshoot a problem with the MPP.

Field or Button	Description
Select all check box	Pack all available files.
Logs	Pack all of the MPP log files.
Transcriptions and utterances	Pack all of the transcriptions and utterances saved by the applications running on the MPP.
Debug files	Pack all the debug (trace) data recorded on the MPP.
Pack	When you click Pack, Experience Portal creates a TAR file with the format <code><hostname>_<date and time stamp>_MPP.tar</code> that contains all of the selected information. In addition, Experience Portal creates a TAR file for each MPP component with the format <code><MPP component>_<hostname>_<date and time stamp>_MPP.tar</code>.

Port Distribution Report page field descriptions

Use this page for a real-time view of telephony port distribution across all Media Processing Platform (MPP) servers. You can configure the telephony resources on the VoIP Connections page.

 Note:

If there is a port conflict, the text for a particular port appears in red. For more information, see the **Current Allocation** column.

Column	Description
Zone	The name of the zone within which the MPP server is configured.
Servers	The MPP servers for which you want to see the Port Distribution Report.  Note: This field appears only if you have selected one or more servers from the Port Distribution page. If you select All Servers from the Servers list on the Port Distribution page, the system does not display this field.
Port	The Experience Portal port number associated with the port.  Note: The port distribution report for SIP protocol displays only the highest port distribution record. For detailed port information, click the number of the port to access the Port Information window.

Table continues...

Column	Description
	Click the Up arrow in the column header to sort the ports in ascending order and the Down arrow to sort the ports in descending order.
Mode	The operational mode of the port. The options are: • Online: The port is available for normal inbound and outbound calls and is allocated to an MPP. • Inbound: The port is available for normal inbound calls and is allocated to an MPP. • Test: The port is available for calls made to one of the defined H.323 maintenance stations and is allocated to an MPP in Test mode. • Offline: The port is not available and is not allocated to any MPP. Click the Up arrow in the column header to sort the modes in ascending order and the Down arrow to sort the modes in descending order
State	The state of the port. The options are: • Active: The port has been assigned to an MPP but the MPP does not know the status of the port because the EPM and the MPP are out of sync. • Adding: The port has been assigned to an MPP but the MPP has not taken the port yet. • Alerting: The port is ringing and checking resources. • Available: The port is ready to be assigned to an MPP. • Connected: The port is in service and calls are in progress. • Delete: The port is in the process of being deleted from the system. It is in use until the grace period expires. • Idle: The port is assigned to an MPP but the MPP is not registered with the switch. The port cannot take calls. • In Service: The port is assigned to an MPP and the MPP is registered with the switch. The port is ready to take a call. • None: The assigned port is missing. • Out of Service - Fault: The MPP is trying to register with the port. • Out of Service - Manual: The port is manually taken offline from the MPP. • Proceeding: The port was taken offline but is currently coming back into service. • Removing: The port is being deleted from the MPP. It will soon be available for assignment to another MPP. • Trying: The MPP is trying to register with the port.  Tip: You can hover the mouse over this column to view more information about the state, including any fault information if the port could not be registered.

Table continues...

Column	Description
Port Group	The name of the port group that the port belongs to. Port groups are administered on the System Configuration pages. Click the Up arrow in the column header to sort the groups in ascending order and the Down arrow to sort the groups in descending order
Protocol	The port protocol.  Note: The port distribution data for SIP is consolidated to a single line in each MPP. The port distribution report for SIP protocol displays only the highest port distribution record. Click the Up arrow in the column header to sort the protocols in ascending order and the Down arrow to sort the protocols in descending order.
Current Allocation	The name of the MPP to which the port is currently allocated. If there is a port conflict, you can hover the mouse over this field to view a tooltip containing one of the following error messages: • Unconfigured port currently owned by <MPP Name>. • Port allocated to <MPP1 Name> but currently owned by <MPP2 Name>. • Port not yet allocated but owned by <MPP Name>. • Port allocated to <MPP Name> but not owned by it. • Port allocation not yet sent. • Waiting for confirmation of the port allocation.
Base Allocation	The options are: • " " (blank): The port is currently allocated to the optimal MPP. • An MPP name: The optimal allocation for the port. If the base allocation field is not blank, it probably means that the optimal MPP went out of service and the port was reallocated.

Changing a server hostname or IP address

Hostname or IP address changes for Experience Portal servers

If you need to change the IP address or hostname of any server running the Experience Portal software after that software has been installed, or if you need to move the software to a new server that has a different IP address and hostname, you need to change the information stored in the Experience Portal database to match the new system configuration.

If you want to change the IP address or hostname of:

- The primary EPM server in a dedicated server environment, see [Changing the hostname or IP address on a dedicated primary EPM server](#) on page 200.
- The auxiliary EPM server in a dedicated server environment, see [Changing the hostname or IP address on the auxiliary EPM server](#) on page 203
- An MPP server in a dedicated server environment, see [Changing the hostname or IP address for a dedicated MPP server](#) on page 202.
- The Experience Portal server running the EPM and MPP software in a single server environment, see [Changing the hostname or IP address for the Experience Portal single server system](#) on page 205.

Changing the hostname or IP address on a dedicated primary EPM server

About this task

If you need to change the IP address or hostname of a dedicated primary EPM server after the EPM software is installed, or if you need to move the primary EPM software to a new server that has a different IP address and hostname, you need to change the information stored in the Experience Portal database to match the new system configuration.

Note:

If you want to change the IP address or hostname for a single server Experience Portal system, follow the steps in [Changing the hostname or IP address for the Experience Portal single server system](#) on page 205. If you want to change the IP address or hostname for an auxiliary EPM server, follow the steps in [Changing the hostname or IP address on the auxiliary EPM server](#) on page 203.

Procedure

1. Log on to Linux on the Experience Portal Primary EPM server.

If you are an Avaya Services representative, and use Avaya Enterprise Linux or if the Avaya Service accounts are installed on this server:

- Log on to the local Linux console as `sroot`.
- Or log on remotely as a non-root user and then change the user to `sroot` by entering the `su - sroot` command.

Otherwise, log on to Linux locally as `root`, or log in remotely as a non-root user and then change the user to `root` by entering the `su -` command.

2. Stop the `vpms` service by entering the `/sbin/service vpms stop` command.

You will see a series of messages as the command starts to shut down EPM components. When the command has successfully stopped all relevant components, the system displays the message: `VPMS Shutdown Status: [ OK ]`.

3. If you want to change the hostname or IP address of the current server:
 - a. If you are using Avaya Enterprise Linux, enter the `system-config-network` command and follow the prompts to set the new IP address or hostname.
 - b. If you are using Red Hat Enterprise Linux Server, use the neat tool as described in your Red Hat documentation.
 - c. Open the `/etc/hosts` file in an ASCII editor and change the IP address and hostname to the values you specified with the configuration tool.
 - d. Reboot the EPM server.
 - e. If the `vpms` service starts automatically after the reboot, stop the `vpms` service by entering the `/sbin/service vpms stop` command.
4. Navigate to the `do_UpdateHost` script directory by entering the `$AVAYA_HOME/Support/UpdateHostAddress` command.
5. Enter the `bash do_UpdateHost` command to change the hostname in the database to the hostname of the current server. The system displays a message to confirm whether you want to restart the `vpms` services.
6. Select `Y` to restart EPM and press `Enter`.

After all relevant components are started successfully, the `VPMS Start Status: [ OK ]` message is displayed.

Next steps

Reconnect the existing MPP servers and Auxiliary EPM servers with the Primary EPM server. For more information, see:

- [Reconnecting an existing MPP server with the EPM server](#) on page 201
- [Reconnecting the primary and auxiliary EPM servers](#) on page 184

Reconnecting an existing MPP server with the EPM server

In a dedicated server environment, if the IP address or hostname of the EPM server changes or if you reinstalled the EPM software, you need to reconnect all MPP servers with the EPM server.

Procedure

1. Log on to Linux on the Experience Portal MPP server.

If you are an Avaya Services representative, and use Avaya Enterprise Linux or if the Avaya Service accounts are installed on this server:

- Log on to the local Linux console as `sroot`.
- Or log on remotely as a non-root user and then change the user to `sroot` by entering the `su - sroot` command.

Otherwise, log on to Linux locally as root, or log in remotely as a non-root user and then change the user to root by entering the `su -` command.

2. Navigate to the `$AVAYA_HOME/Support/VP-Tools` directory.
3. Associate this MPP server with the EPM server by entering the `setup_vpms.php myhost` command, where *myhost* is the server name or IP address where the EPM software is installed.
4. Follow the on-screen prompts to install the certificate, restart Apache, and configure Network Time Protocol (NTP).

Next steps

Reestablish the link between the MPP and the EPM by trusting the MPP's security certificate. For more information, see [Reestablishing the link between the and an MPP](#) on page 190.

Changing the hostname or IP address for a dedicated MPP server

About this task

If you need to change the IP address or hostname of a dedicated MPP server after the MPP software has been installed, or if you need to move the MPP software to a new server that has a different IP address and hostname, you need to change the information stored in the Experience Portal database to match the new system configuration.

Note:

If your Experience Portal system consists of a single server, follow the steps in [Changing the hostname or IP address for the Experience Portal single server system](#) on page 205.

Procedure

1. Log on to Linux on the Experience Portal MPP server.
If you are an Avaya Services representative, and use Avaya Enterprise Linux or if the Avaya Service accounts are installed on this server:
 - Log on to the local Linux console as `sroot`.
 - Or log on remotely as a non-root user and then change the user to `sroot` by entering the `su - sroot` command.
 Otherwise, log on to Linux locally as `root`, or log in remotely as a non-root user and then change the user to `root` by entering the `su -` command.
2. Stop the `mpp` service by entering the `service mpp stop` command.
3. If you want to change the hostname or IP address of the current server:
 - a. If you are using Avaya Enterprise Linux, enter the `system-config-network` command and follow the prompts to set the new IP address or hostname.
 - b. If you are using Red Hat Enterprise Linux Server, use the `neat` tool as described in your Red Hat documentation.
 - c. Open the `/etc/hosts` file on the MPP server in an ASCII editor and change the IP address and hostname to the values you specified with the configuration tool.

- d. Log on to Linux on the Experience Portal Primary EPM server.

If you are an Avaya Services representative, and use Avaya Enterprise Linux or if the Avaya Service accounts are installed on this server:

- Log on to the local Linux console as `sroot`.
- Or log on remotely as a non-root user and then change the user to `sroot` by entering the `su - sroot` command.

Otherwise, log on to Linux locally as root, or log in remotely as a non-root user and then change the user to root by entering the `su -` command.

- e. Open the `/etc/hosts` file on the primary EPM server in an ASCII editor and change the IP address and hostname for the MPP to the values you specified with the configuration tool.
- f. Reboot the primary EPM server.
- g. Reboot the MPP server.

4. Log on to EPM Web interface.

If Avaya Services is maintaining this system and you are an Avaya Services representative, log on to the EPM using the `init EPM` account created during the EPM software installation.

Otherwise, log on to the EPM using an account with the Administrator user role.

5. From the EPM main menu, select **System Configuration > MPP Servers**.
6. On the MPP Servers page, click on the name of the MPP whose hostname or IP address you changed.
7. On the Change MPP Server page, make sure that the information in the **Host Address** field matches the new IP address or hostname.

If you logged in using the `init` account, make sure that the LDN number specified in the **LDN** field matches the information in the Avaya Services database for this server.

8. Click **Save**.

Changing the hostname or IP address on the auxiliary EPM server

About this task

To change the IP address or hostname of the auxiliary EPM server after the EPM software has been installed, or to move the auxiliary EPM software to a new server that has a different IP address and hostname, you must change the information stored in the Experience Portal database to match the new system configuration.

Note:

To change the IP address or hostname for the primary EPM server, follow the steps in [Changing the hostname or IP address on a dedicated primary EPM server](#) on page 200.

Procedure

1. Log on to Linux on the Auxiliary EPM server.

If you are an Avaya Services representative, and use Avaya Enterprise Linux or if the Avaya Service accounts are installed on this server:

- Log on to the local Linux console as `sroot`.
- Or log on remotely as a non-root user and then change the user to `sroot` by entering the `su - sroot` command.

Otherwise, log on to Linux locally as `root`, or log in remotely as a non-root user and then change the user to `root` by entering the `su -` command.

2. Stop the `vpms` service by entering the `/sbin/service vpms stop` command.

You will see a series of messages as the command starts to shut down EPM components. When the command has successfully stopped all relevant components, the system displays the message: `VPMS Shutdown Status: [ OK ]`.

3. To change the hostname or IP address of the current server:

- a. If you are using Avaya Enterprise Linux, enter the `system-config-network` command and follow the prompts to set the new IP address or hostname.
- b. If you are using Red Hat Enterprise Linux Server, use the `neat` tool as described in your Red Hat documentation.
- c. Open the `/etc/hosts` file in an ASCII editor and change the IP address and hostname to the values you specified with the configuration tool.
- d. Reboot the auxiliary EPM server.
- e. If the `vpms` service starts automatically after the reboot, stop the `vpms` service by entering the `/sbin/service vpms stop` command.

4. Navigate to the `do_UpdateHost` script directory by entering the `cd $AVAYA_HOME/Support/UpdateHostAddress` command.

5. Enter the `bash do_UpdateHost` command.

The script prompts the following message:

Selection of EPM address update:

(1) Primary EPM (2) auxiliary EPM (local)

- a. To enter a new IP address for the primary EPM server:
 - Select 1
 - Enter the new IP address for the primary EPM server
 - Press Enter
- b. To update the hostname in the database to the hostname of the current (auxiliary EPM) server:
 - Select 2

- Press Enter

- Restart the `vpms` service by entering the `/sbin/service vpms restart` command.

You will see a series of messages as the command starts to shutdown EPM components. When the command has successfully stopped all relevant components, the system displays the message: `VPMS Shutdown Status:[ OK ]`

The command immediately starts the relevant components. When the command is run successfully, the system displays the message: `VPMS Start Status:[ OK ]`.

 Note:

To update the IP address of the primary EPM server as well as the auxiliary EPM server, you must run the `bash do_UpdateHost` command twice and repeat this step.

- Enter the `setup_vpms.php` command to re-authorize the security certificate.

The location of the `setup_vpms` script is `$AVAYA_HOME/Support/VP_Tools/setup_vpms.php`.

- Update the link between the primary and auxiliary EPM servers:

- Log on to EPM Web interface.

If Avaya Services is maintaining this system and you are an Avaya Services representative, log on to the EPM using the init EPM account created during the EPM software installation.

Otherwise, log on to the EPM using an account with the Administrator user role.

- From the EPM main menu, select **System Configuration > EPM Servers**.
- On the EPM Servers page, click the name of the auxiliary EPM server.
- On the Change EPM Server page, update the information in the **Host Address** field.

If you logged in using the init account, make sure that the LDN number specified in the **LDN** field matches the information in the Avaya Services database for this server.

- Click **OK**.

Next steps

Reconnect the Primary EPM server with the Auxiliary EPM server. For more information see, [Reconnecting the primary and auxiliary EPM servers](#) on page 184.

Changing the hostname or IP address for the Experience Portal single server system

About this task

If you need to change the IP address or hostname of the Experience Portal server after the EPM and MPP software has been installed, or if you need to move the Experience Portal software to a new server that has a different IP address and hostname, you need to change the information stored in the Experience Portal database to match the new system configuration.

*** Note:**

If your Experience Portal system consists of one or more dedicated servers, follow the steps in [Changing the hostname or IP address on a dedicated primary EPM server](#) on page 200.

Procedure

1. Log on to Linux on the Primary or Auxiliary EPM server.

If you are an Avaya Services representative, and use Avaya Enterprise Linux or if the Avaya Service accounts are installed on this server:

- Log on to the local Linux console as `sroot`.
- Or log on remotely as a non-root user and then change the user to `sroot` by entering the `su - sroot` command.

Otherwise, log on to Linux locally as root, or log in remotely as a non-root user and then change the user to root by entering the `su -` command.

2. Stop the `vpms` service by entering the `/sbin/service vpms stop` command.

You will see a series of messages as the command starts to shut down EPM components. When the command has successfully stopped all relevant components, the system displays the message: `VPMS Shutdown Status: [ OK ]`.

3. Stop the `mpp` service by entering the `service mpp stop` command.

4. If you want to change the hostname or IP address of the current server:

- a. If you are using Avaya Enterprise Linux, enter the `system-config-network` command and follow the prompts to set the new IP address or host name.
- b. If you are using Red Hat Enterprise Linux, use the `neat` tool as described in your Red Hat documentation.
- c. Open the `/etc/hosts` file in an ASCII editor and change the IP address and hostname to the values you specified with the configuration tool.
- d. Reboot the Experience Portal server.

5. Navigate to the `do_UpdateHost` script directory by entering the `cd $AVAYA_HOME/Support/UpdateHostAddress` command.

6. Enter the `bash do_UpdateHost` command to change the hostname in the database to the hostname of the current server.

7. Restart the `vpms` service by entering the `/sbin/service vpms restart` command.

You will see a series of messages as the command starts to shut down EPM components. When the command has successfully stopped all relevant components, the system displays the message: `VPMS Shutdown Status: [ OK ]`.

The command immediately starts the relevant components. When the command is run successfully, the system displays the message: `VPMS Start Status: [ OK ]`.

8. Start the `mpp` service by entering the `service mpp start` command.

9. If the application server is co-resident with the Experience Portal single server system, verify and/or change the hostname or IP address referenced in the System Configuration > Applications page
 - a. From the EPM main menu, select **System Configuration > Applications**.
 - b. Verify the hostname or IP address

Next steps

Reconnect the existing MPP server with the EPM server. For more information, see [Reconnecting an existing MPP server with the EPM server](#) on page 201.

Local database maintenance

System Backup

System Backup Overview

You can use the System Backup feature in the Experience Portal Manager (EPM) to regularly back up the data in a local Experience Portal database and the associated properties files.

Note:

Before you can use the System Backup feature in EPM, you must complete the tasks in [Database backup prerequisites](#) on page 208.

The System Backup web page in EPM allows you to perform the following backup tasks:

- Configure the backup server and verify the backup server connectivity. For more information, see [Backup Server page field descriptions](#) on page 214.
- Perform on-demand backup directly on the web page or configure backup schedule to perform backup on a periodic basis. For more information, see [Backup Scheduler page field descriptions](#) on page 216.
- Back up Experience Portal database which includes the associated default properties files, and the specified custom files. You can also optionally configure additional files and directories that need to be backed up. For more information, see [User Components page field descriptions](#) on page 216.
- Configure the number of backups to retain in the backup server. You can also retain more than one backup data package and select preferred package for data restore operation. For more information, see [Backup Server page field descriptions](#) on page 214.
- View the backup history.

The System Backup feature verifies the current package list in the backup folder against the set number of backups to retain, and removes the older packages based on the timestamp.

The System Backup copies the Experience Portal database and the property files from the EPM server to the local backup folder, or to a Linux or Windows backup server across the network. Refer to the *Local database configuration for System Backup* section for further information on the backup server.

For information on the backup procedure, see [Backing up an Avaya Aura Experience Portal system from System Backup menu in EPM](#) on page 210.

+ Tip:

You should backup your data at periodic intervals to capture any incremental changes to the database.

Local database configuration

Database backup prerequisites

You must complete the following tasks before you can use the System Backup feature in EPM.

✓	Description
	Make sure that there is enough disk space to store a copy of the database.
	Set up the Linux or Windows backup server. For details, see: • Setting up a Linux backup server on page 208 • Setting up a Windows backup server on page 209

Setting up a Linux backup server

Procedure

1. Log in to Linux on the backup server with the user account that Experience Portal uses while performing the backup operation.
2. Enter the `id` command to obtain the UID of the account with which you are currently logged in.

The system displays the UID. For example: `$>id backupuser uid=500(backupuser) gid=500(backupuser) groups=500(backupuser) context=user_u:system_r:unconfined_t`
3. Create the backup directory where you want to save the backup packages. For example, if you want Experience Portal to store the backups in the `/home/experienceportal/backup` directory, enter the `mkdir /home/experienceportal/backup` command.
4. Enter the `su -` command to gain temporary root level access.
5. Open the `/etc/exports` file in a text editor.
6. Add a new entry for the new directory, to be shared with Experience Portal, using the following format:

```
<BackupDir>
<ExperiencePortalAddress>(rw, sync, all_squash, anonuid=<UID>) where
```

- <BackupDir> is the name of the directory to be shared. For example, /home/experienceportal/backup.
- <ExperiencePortalAddress> is the IP address of the Primary EPM server that accesses the backup directory.
- <UID> is the ID of the user account that Experience Portal uses when accessing the backup directory.

7. Save and close the file.
8. Enter the `#>service nfs restart` command to restart the NFS service.
9. If the backup server is installed on Red Hat Enterprise Linux 5.x, restart the portmap service by entering the `#>service portmap restart` command.

*** Note:**

If the backup server is installed on Red Hat Enterprise Linux 6, you do not need to restart the rpcbind service.

Setting up a Windows backup server

About this task

You can set up shared directories between the main Experience Portal server and a Windows server.

*** Note:**

If the Experience Portal server is installed on Linux, you cannot connect to a Windows server unless you have Samba or other connection utility. For details, see the Red Hat Web site, <http://www.redhat.com>.

Procedure

1. Log into the Windows back up server using an Administrator account.
2. If required, add a new user account that the Experience Portal system uses when backing up files to the server. For more information on adding a new Windows user, see the Microsoft Windows documentation.
3. Create the directory that you want to share with the Experience Portal server.
4. Right-click on the directory in Windows Explorer and select **Sharing and Security** to set the shared permissions.
5. In the <folder name> Properties dialog box, go to the **Sharing** tab.
6. Select **Share this folder**.
7. Click **Permissions**.
8. In the Permissions dialog box, click **Add**.

9. In the **Enter the object names to select** list box, add the appropriate user name in the format `backup_server_name\user_name`, where:

- `backup_server_name` is the name of the Windows backup server.
- `user_name` is the name of a Windows user that currently exists on the backup server.

For example, if the backup server name is `BackupEPMServer` and the Windows user name is `user`, you would enter `BackupEPMServer\user`.

10. Click **OK** to return to the Permissions dialog box.
11. In the **Group or user names** list box, select the user you just added.
12. Enable the **Change** and **Read** check boxes in the **Allow** column for that user. The **Full Control** permission is optional.
13. Click **OK** to save your changes and return to the <folder name> Properties dialog box.
14. Click **OK**.

Backing up an Avaya Aura® Experience Portal system from System Backup menu in EPM

Before you begin

Before you use the System Backup feature in EPM, you must complete the tasks in [Database backup prerequisites](#) on page 208.

Procedure

1. Log in to the EPM web interface.
2. From the EPM main menu, select **System Management > System Backup**.
3. Click the **Backup Server** icon .
4. On the **Backup Server** page, update the configuration details, and click **Verify**.

Important:

Make sure the backup is stored on a server that is not part of the Experience Portal system.

EPM verifies if the backup folder exists and can be mounted using the specified parameters such as server address and backup folder, and displays the details in the Verify Backup Server window.

5. Click **Close Window** on the Verify Backup Server window.
6. Click **Save** on the **Backup Server** page.
7. Click the **Backup Schedule** icon  on the **System Backup** page if you want to specify a schedule for the backup procedure.
8. On the **Backup Scheduler** page, configure the backup schedule, and click **Save**.
9. Click the **User Components** icon .

10. On the **User Components** page, configure user components for the backup operation, and click **Save**.
11. Click **Backup Now** to initiate an on-demand backup.

Result

When the backup is complete, the **System Backup** page displays the backup completed message.

* Note:

Click **Refresh** to check if the backup completed message is displayed.

Next steps

On the **Backup History** section of the **System Backup** page:

- Verify that the package is created
- Verify the Date/Time details of the package

* Note:

The package list is not displayed if the backup server is not configured properly.

System Backup page field descriptions

Use this page to perform the backup operation and configure the backup servers, backup schedule, and the files and folder for backup operation.

This page contains the following sections:

- [Backup Server section](#) on page 211
- [Backup Scheduler section](#) on page 212
- [Backup Components section](#) on page 212
- [Backup History section](#) on page 212
- [Buttons section](#) on page 212

Backup Server section

Field	Description
Server Type	Type of the backup server type. The options are: • PC Windows • RH Linux
Server Address	Network address of the backup server.
Backup Folder	Name of the folder where the backup data is stored.
Number of Backup(s) to Retain	Number of backup data packages to be retained in the backup server.

Table continues...

Field	Description
Backup Server icon 	Opens the Backup Server page for configuring the backup server.

Backup Scheduler section

Field	Description
Backup Schedule	Configured schedule for backup.
Backup Schedule icon 	Opens the Backup Scheduler page for configuring the backup schedule.

Backup Components section

Field	Description
EP Database/ Properties	Experience Portal data that includes the Experience Portal database and the associated properties files.
User Components	Number of files and folders specified for backup.
Backup Components icon 	Opens the User Components page for configuring the backup schedule.

Backup History section

Field	Description
Packages	List of existing backup packages saved in the backup server. The package list is not displayed if the backup server is not configured properly.  Note: The number of maximum packages to be saved is based on the configured Number of Backup(s) to Retain value. Each backup data is formed as a package. The package name follows the <code>pkg<Version>_<Timestamp></code> format, where the time stamp is in milliseconds.
Date/Time	Date and time when each data package was backed up.

Buttons section

Button	Description
Backup Now	Initiates the on-demand backup for the specified components on the configured server.

Table continues...

Button	Description
	 Tip: Verify the backup server details before initiating the on demand backup. Select the Backup Server>Verify web page to verify that the backup folder exists and can be mounted using the specified username and password. For more information, see Verify Backup Server page field descriptions on page 215 On initiating the on-demand backup, the Backup Now button changes to Cancel Backup till the backup operation is in progress.
Cancel Backup	Stops the backup operation in progress.

View System Backup page field descriptions

Use this page to view the backup configuration, backup schedule, and the files and folder for backup operation.

This page contains the following sections:

- [Backup Server section](#) on page 213
- [Backup Scheduler section](#) on page 213
- [Backup Components section](#) on page 214
- [Backup History section](#) on page 214

Backup Server section

Field	Description
Server Type	Type of the backup server type. The options are: • PC Windows • RH Linux
Server Address	Network address of the backup server.
Backup Folder	Name of the folder where the backup data is stored.
Number of Backup(s) to Retain	Number of backup data packages to be retained in the backup server.

Backup Scheduler section

Field	Description
Backup Schedule	Configured schedule for backup.

Backup Components section

Field	Description
EP Database/ Properties	Experience Portal data that includes the Experience Portal database and the associated properties files.
User Components	Number of files and folders specified for backup.

Backup History section

Field	Description
Packages	List of existing backup packages saved in the backup server. The package list is not displayed if the backup server is not configured properly.  Note: The number of maximum packages to be saved is based on the configured Number of Backup(s) to Retain value. Each backup data is formed as a package. The package name follows the <code>pkg<Version>_<Timestamp></code> format, where the time stamp is in milliseconds.
Date/Time	Date and time when each data package was backed up.

Backup Server page field descriptions

Use this page to configure the backup servers, mount point and the authentication information to connect and mount the backup server.

This page contains the following sections:

- [Backup Server section](#) on page 214
- [Number of Backup\(s\) to Retain section](#) on page 215
- [State Commands](#) on page 215

Backup Server section

Field	Description
Server Type	Type of the backup server. The options are: • PC Windows • RH Linux
Server Address	Network address of the backup server. If the backup server is a Windows 7 or Windows 2008 R2 server, enter a valid Fully qualified domain name (FQDN). For all other servers, enter a valid IP address. You can use 127.0.0.1 or localhost as the host/IP address to use the local system as a backup server.
Backup Folder	Name of the folder where the backup data is stored.

Table continues...

Field	Description
	The backup folder name on Linux must have the syntax: <pre>/<Folder name></pre> where, <Folder name> indicates a shared directory that is used to store the backup files in the backup server.  Note: For a local backup, verify that the avayavp and avayavpgroup linux users have the read, write, and execute permissions for the backup folder. The backup folder name on Windows must have the syntax: <pre>/<Folder name> or \<Folder name>.</pre> where, <Folder name> indicates a shared directory that is used to store the backup files in the backup server. For example, the default is C:\Avaya\backup.
Username	The user name used to mount the backup server.
Password	The password used to connect and mount the backup server.
Verify	Verifies that the backup folder exists and can be mounted using the specified parameters such as server address and backup folder.

Number of Backup(s) to Retain section

Field	Description
Number of Backup(s) to Retain	Number of backup data packages to be retained in the backup server. The existing packages are deleted if the limit is exceeded. The maximum limit of backups to retain is 5.

State Commands

Button	Description
Save	Saves the new settings and navigates to the System Backup page.
Apply	Saves the new settings.
Cancel	Cancels the changes and navigates to the System Backup page.

Verify Backup Server page field descriptions

Use this page to verify that the backup folder exists and can be mounted.

Field	Description
Server Type	Type of the backup server. The options are: • PC Windows • RH Linux

Table continues...

Field	Description
Server Address	Network address of the backup server.
Backup Folder	Name of the folder where the backup data is stored.
Username	The user name used to mount the backup server. This field is displayed only when the backup server type selected is PC Windows and the Server Address is not a local server.
<i>Result</i>	Shows whether the backup server was configured successfully or not. For Example: • Backup server was verified successfully. • null mount: mount to NFS server <IP address> failed: System Error: No route to host.

Backup Scheduler page field descriptions

Use this page to schedule the backup operation to run on a periodic or one time basis.

Select Backup Schedule section

Field	Description
None	Disables the backup scheduling.
One time at	Performs backup operation only on the specified date and time.
Daily at	Performs backup operation every day at the specified time.
Weekly on	Performs backup operation every week on the specified day and time.
Monthly on	Performs backup operation every month on the specified day and time.

Note:

If the backup schedule is reached and the previous backup operation is still in progress, the backup action is dropped till its next cycle allowing the backup in progress to complete.

State Commands

Button	Description
Save	Saves the new properties and navigates to the System Backup page.
Apply	Saves the new properties.
Cancel	Cancels the changes and navigates to the System Backup page.

User Components page field descriptions

Use this page to configure user components for the backup operation. You can configure more than one file and folder that you want to backup.

Field	Description
Folder	Name and the path of the folder that you want to backup. The path must be an absolute path.

Table continues...

Field	Description
	For example: For Linux, <code>/opt/coreservices/dss</code>, indicates that you want to backup the contents of <code>dss</code> folder located in the <code>/opt/coreservices</code> directory. For Windows, you can use forward slash (/), back slash (\), as well as the drive name in the path.
File	Name and the path of the file that you want to backup. You can specify the file name with file extension or with asterisk (*). For example, you can specify file names like <code>*.xml</code> or <code>common.*</code>.

*** Note:**

For Linux, verify that the `avayavp` and `avayavpgroup` linux users have the read permission for the folder and file that you want to backup.

If you specify a valid folder name but the file field is empty, all the files from the specified folder are backed up. However, the subfolders are not considered for the back up.

You cannot add duplicate entries. If you try to add the same details suffixed or prefixed with an extra space, that too is treated as a duplicate entry.

State Commands

Button	Description
Save	Saves the new properties and navigates to the System Backup page.
Apply	Saves the new properties.
Cancel	Cancels the changes and navigates to the System Backup page.
Add	Adds the new properties.
Delete	Deletes the new properties.

Database Restore utility

Database Restore utility and system backup

You can use the Database Restore utility to restore your Experience Portal database from a backup created through the **System Backup** web page in EPM.

To restore your Experience Portal database that is installed on Linux:

- Ensure the backup server mount point is updated in the `do_MntDrv` script. For more information, see [Verifying the backup server mount point](#) on page 218.
- Use the `do_RestoreData` script for restoring data. For more information, see [Restoring data backed up from System Backup](#) on page 219.

! Important:

If your primary Experience Portal server fails and cannot be recovered, you must first reinstall the EPM software on a new server. Then you can restore your Experience Portal database using the Database Restore utility.

For details about the **System Backup** feature in EPM, see [System Backup Overview](#) on page 207.

Verifying the backup server mount point

About this task

The Database Backup utility `do_MntDrv` script, used during the restore procedure, creates a shared directory at the mount point on the Experience Portal server and connects that shared directory with the Linux or Windows backup server.

*** Note:**

You cannot connect to a Windows server unless you have Samba or other connection utility. For details, see the Red Hat Web site, <http://www.redhat.com>.

The `do_MntDrv` script is updated automatically with the backup server details configured in the **System Backup>Backup Server** EPM web page.

! Important:

Before you can run this script, you must verify your system details. If the system details are not updated in the script, edit the details as described below.

Procedure

1. Log on to Linux on the Experience Portal Primary EPM server.

If you are an Avaya Services representative, and use Avaya Enterprise Linux or if the Avaya Service accounts are installed on this server:

- Log on to the local Linux console as `sroot`.
- Or log on remotely as a non-root user and then change the user to `sroot` by entering the `su - sroot` command.

Otherwise, log on to Linux locally as root, or log in remotely as a non-root user and then change the user to root by entering the `su -` command.

2. Navigate to the backup directory located in `$AVAYA_HOME` by entering the `cd $AVAYA_HOME/Support/Database/DBbackup` command.
3. Open the `do_MntDrv` script in an ASCII text editor.

This file contains a sample mount drive command.

```
bash MntDrive pc ipAddress backupServerFolder backupUserName where
```

- `[type]` is either `linux` or `pc` based on the type of back up server you are using. Sample command displays `pc` as type.
- `[host address]` is the backup server name or IP address. Sample command displays `ipAddress` as host address.

- `shared_dir` is the name of the shared directory on the backup server. For Linux, this must be the full path. For Windows, this must be the shared directory name. Sample command displays **backupServerFolder** as shared directory.
 - `[Windows_user]` is used only when the backup server is a Windows machine. Replace this parameter with the name of the Windows user that is authorized to access the database. The default is `postgres`. Sample command displays **backupUserName** as Windows user.
4. Verify your backup server details.
 - If you configure the Linux system `voiceportal-linux-backup` as the backup server and set up `/misc/dbbackup` as the shared directory in the **System Backup>Backup Server** EPM web page, verify the `do_MntDrv` script is as follows:


```
bash MntDrive linux voiceportal-linux-backup /misc/dbbackup
```
 - If you configure the Windows XP system `voiceportal-xp-backup` as the backup server and set up `c:\temp\EP_dbbackup` as the shared directory in the **System Backup>Backup Server** EPM web page, verify the `do_MntDrv` script is as follows:


```
bash MntDrive pc voiceportal-xp-backup VP_dbbackup postgres
```

For example: `bash MntDrive pc <IP Address> VP_bu postgres.`
 5. Save and close the file if `do_MntDrv` is updated.

Restoring data backed up from System Backup

Before you begin

The Experience Portal software version must be the same version that was used to create the backup.

Verify the `do_MntDrv` script. For further information, see [Verifying the backup server mount point](#) on page 218.

For more information, see [Backup Server page field descriptions](#) on page 214.

Procedure

1. Log on to Linux on the Experience Portal Primary EPM server.

If you are an Avaya Services representative, and use Avaya Enterprise Linux or if the Avaya Service accounts are installed on this server:

 - Log on to the local Linux console as `sroot`.
 - Or log on remotely as a non-root user and then change the user to `sroot` by entering the `su - sroot` command.

Otherwise, log on to Linux locally as root, or log in remotely as a non-root user and then change the user to root by entering the `su -` command.
2. Stop the `vpms` service by entering the `/sbin/service vpms stop` command.

3. Stop the avpSNMPAgentSvc service by entering the `/sbin/service avpSNMPAgentSvc stop` command.
4. If there is an application server installed on the system, enter the `/sbin/service appserver stop` command to stop the application server.
5. Navigate to the backup directory located in \$AVAYA_HOME by entering the `cd $AVAYA_HOME/Support/Database/DBbackup` command.
6. If the backup package is on a remote server:
 - a. Enter the `bash do_MntDrv` command.
 - b. Restore the database by entering the `bash do_RestoreData` command.

If the backup package is on a local server:

Enter the `do_RestoreData -f <backup file name>` command. For example, enter the `do_RestoreData -f /opt/Avaya/backup` where indicates that you want to restore the contents of *backup* folder located in the `/opt/Avaya` directory.

 Note:

The command will first clean the database .

The list of existing backup packages saved in the backup server is displayed.

7. Select the package for Experience Portal data restore.
 8. Press Enter to continue.
- The script completes the restore process.
9. Perform the following steps if the hostname or IP address of the server running the EPM or MPP software has changed since you created the database backup:
 - a. To navigate to the `do_UpdateHost` script directory, enter the `cd $AVAYA_HOME/Support/UpdateHostAddress` command.
 - b. To change the hostname in the database to the hostname of the current server, enter the `bash do_UpdateHost` command .

10. Restart the `vpms` service by entering the `/sbin/service vpms start` command.
11. Restart the `avpSNMPAgentSvc` service by entering the `/sbin/service avpSNMPAgentSvc start` command.
12. If there is an application server installed on the system, restart the application server by entering the `/sbin/service appserver start` command.
13. Reconnect each MPP server with the EPM server.
14. Reestablish the link between the MPP and the EPM by trusting the MPP's security certificate.
15. Reconnect each auxiliary EPM server with the primary EPM server as described in [Reconnecting the primary and auxiliary EPM servers](#) on page 184.

16. If you are restoring your Experience Portal database to a new server, you need to install a new license file on the server. For further information, see *Installing the license file* section in the *Implementing Experience Portal on multiple servers* or the *Implementing Avaya Aura® Experience Portal on single server* guide.

 Note:

This step is not required if you are using a remote WebLM.

17. To unmount the shared directory, enter the `bash UmntDrive` command.

Purging report data from a local Experience Portal database

About this task

The `PurgeReportDataLocalDB` script purges all report data from the `VoicePortal` database. This data includes all:

- Application Detail Records (ADRs) stored in the `vpapplog` table
- Contact Detail Records (CDRs) stored in the `cdr` table
- Performance records stored in the `vpperformance` table
- Session Detail Records (SDRs) stored in the `sdr` table

 Important:

After you run this script, users cannot generate reports through the EPM until the EPM has downloaded the current report data from the Media Servers.

Procedure

1. Make sure that the EPM is not currently downloading report data from the Media Servers.
 - a. Log on to the EPM Web interface using an account with the Administration user role.
 - b. From the Media Server Service Menu, select **System Configuration > EPM Servers > Report Data**.
 - c. Go to the display text box in the **Download Schedules** group and make sure that no downloads are scheduled for the current time.

2. Log on to Linux on the Primary or Auxiliary EPM server.

If you are an Avaya Services representative and are using Avaya Enterprise Linux, or if the Avaya Service accounts are installed on this server:

- Log on to the local Linux console as `sroot`.
- Or log on remotely as a non-root user and enter the `su - sroot` command to change the user to `sroot`.

Otherwise, log on to Linux locally as `root`, or log in remotely as a non-root user and enter the `su -` command to change the user to `root`.

3. Navigate to the `Support/VP-Tools` directory under the Experience Portal installation directory.
4. Enter the `cd $AVAYA_HOME/Support/VP-Tools` command. `$AVAYA_HOME` is an environmental variable pointing to the name of the installation directory specified during the Experience Portal software installation.

The default value is `/opt/Avaya/ExperiencePortal`.

5. Enter the `bash PurgeReportDataLocalDB` command.

! Important:

The system may take some time to purge the data depending on the amount of data in the database tables.

If the script runs successfully, it returns a message stating that the data was purged from the database. Otherwise, it returns a message stating the problem that it encountered.

External database configuration

Shared external database configuration for multiple Experience Portal systems

If you have multiple Experience Portal systems, you may want to set up a shared external database so that you can log into the EPM for one system and:

- See the status of all systems in the shared database
- Create reports that include data from all systems in the shared database

Once you connect the Experience Portal system to the external database, that system stores all its report data in the external database from that point forward. The report data includes:

- Contact Detail Records (CDRs)
- Session Detail Records (SDRs)
- Application Detail Records (ADRs)
- Performance report records

! Important:

You must back up the external database manually using your database administration tools. You cannot use the Avaya Aura® Experience Portal Database Backup utility to back up an external database.

External database requirements

The performance of the Experience Portal internal database degrades when 5 to 10 million records exist in any table. When you expect the number of calls or number of application-generated report records to exceed these values, you must use an external database.

The external database can be a new or existing database created in:

- Microsoft SQL Server 2010, 2012, and 2014
- MySQL 5.6.x
- Oracle 11g and 12c
- PostgreSQL 9.4.x

Note:

Avaya has tested Experience Portal with Oracle and SQLServer reporting databases containing approximately 50 million total records without any issues. Due to variances in database hardware and network performance, Avaya cannot provide a finite maximum number of records before the database reaches its practical limit. Scheduled reports are not subject to timeouts and can be used when on-demand report generation begins to time out. However, record insertions must be completed within 60 seconds to avoid web service time-outs and perpetual retries. Increasing the web service time-outs is not recommended. When insert time-outs occur regularly, Avaya recommends that you lower the record retention periods in the Report Data Configuration page. Fewer records mean faster insertions and faster report generation.

The administration of the external reporting database and the periodic maintenance of the indexes is a customer responsibility.

Creating the required tables in the external database

In order to create the tables that Experience Portal requires in the shared database, you need to run the scripts provided on the Experience Portal Installation DVD against an Oracle, Postgres, Microsoft SQL Server, or MySQL database.

Before you begin

If you use an existing database, Experience Portal appends its required tables to that database without altering any of the existing data.

The Experience Portal data requires approximately 4 GB of space per million calls handled.

Note:

If you use a Microsoft SQL Server external database that needs to support multibyte characters, you need to create a new Microsoft SQL Server database and select the appropriate collation for the desired language. For instance, for Microsoft SQL Server Management Studio 2008 you need to perform the following steps during database creation:

- Click **Options** under the **Select a page** section.
- Select the appropriate collation for the desired language in the **Collation** field.

- Ensure that the collation you select is of the case-insensitive type. Case-insensitive types contain the letters CI. For example, Japanese_CI_AI.

*** Note:**

Experience Portal adds tables to the database without changing any existing data. Therefore Experience Portal can share an existing external database with other applications as long as the database meets the version requirements.

! Important:

Ensure that the external database is not installed on any Experience Portal server.

Procedure

1. Insert the Experience Portal installation DVD into the DVD device of the server on which you want to create the database.
2. If you are using:
 - Oracle, change to the Oracle support directory `Support/ExternalDB/Oracle/InstallScripts/`.
 - Postgres, change to the Postgres support directory `Support/ExternalDB/Postgres/InstallScripts/`.
 - Microsoft SQL, change to the SQL Server support directory `/Support/ExternalDB/MSSQL/InstallScripts/`.
 - MySQL, change to the MySQL support directory `/Support/ExternalDB/MySQL/InstallScripts/`.
3. Use your database administration tool to run all of the scripts containing the database schema in the appropriate `Support/ExternalDB` directory.

These scripts create the required tables in the external database.

*** Note:**

For Oracle, the database user name for Experience Portal must be assigned CREATE TABLE and CREATE SESSION privileges for the database.

For Microsoft SQL Server, the database user name for Experience Portal must be assigned SELECT, INSERT, UPDATE and DELETE privileges on all tables in the database.

For MySQL, the database user name for Experience Portal must be assigned SELECT, INSERT, UPDATE, DELETE privileges on all tables in the database. The CREATE TEMPORARY TABLE permission is also required. When creating the database, set a collation type of `utf8_unicode_ci`.

Next steps

Connect your Experience Portal systems to the external database as described in [Connecting the Experience Portal system to a shared external database](#) on page 225

Connecting the Experience Portal system to a shared external database

Before you begin

Make sure you have created the required tables in the external database as described in [Creating the required tables in the external database](#) on page 223.

About this task

Once you connect the Experience Portal system to an external database, the system copies all report data currently on all MPPs in that system into the external database. Users can then generate reports that include that data, but they cannot include any data that resides in the local Experience Portal database.

* Note:

The amount of data available on each MPP depends on the settings for the fields in the **Record Handling on MPP** group on the MPP Settings page.

Procedure

1. Log on to the EPM Web interface using an account with the Administration user role.
2. From the EPM main menu, select **System Configuration > EPM Server** and click the **Data Storage Settings** button.
3. On the Data Storage Settings page, select the **External** radio button.
4. Enter the path to the external database in the **URL** field.

A common URL format for Oracle connections is:

`jdbc:oracle:thin:@OracleServerName:1521:DBName`

A common URL format for Postgres is: `jdbc:postgresql://PostgresServerName:5432/DBName`

A common URL format for Microsoft SQL connections is: `jdbc:sqlserver://SQLServerName:1433;databaseName=DBName`

A common URL format for MySQL connections is: `jdbc:mysql://ServerName:3306/DBName`

A format for PDB (portable db) connections is: `jdbc:oracle:thin:@ServerName:1521/pdbName`

5. Enter the name of the Java class that implements the JDBC API to the external database in the **JDBC Driver** field.

For Oracle, the name is `oracle.jdbc.driver.OracleDriver`.

For Postgres, the name is `org.postgresql.Driver`.

For Microsoft SQL Server, the name is `com.microsoft.sqlserver.jdbc.SQLServerDriver`.

For MySQL, the name is `com.mysql.jdbc.Driver`.

6. Enter the user name and password for the external database in the **User Name** and **Password** fields.
7. Click **Apply** at the bottom of the page.

Result

If Experience Portal:

- Can connect to the new database, the system scheduler begins saving all report data currently on all MPPs in that system into the external database.
- Cannot connect to the database, it displays an error message on the page. Experience Portal cannot write to the external database until you fix the error.

Disconnecting the Experience Portal system from a shared external database

When you disconnect the Experience Portal system from a shared external database, the system scheduler begins saving all report data currently on all MPPs in that system into the local Experience Portal database.

About this task

After you disconnect the system, users can generate reports that include the current data that resided on the MPPs along with any older data that previously existed in the local database, but they cannot include any data that resides in the external database.

Note:

The amount of data available on each MPP depends on the settings for the fields in the **Record Handling on MPP** group on the MPP Settings page.

Procedure

1. Log on to the EPM Web interface using an account with the Administration user role.
2. From the EPM main menu, select **System Configuration > EPM Server** and click **Data Storage Settings**.
3. On the Data Storage Settings page, go to the **Report Database** group.
4. On the Report Database Settings page, select the **Local** radio button.
5. Click **Apply** at the bottom of the page.

Result

Experience Portal records all data in the local Experience Portal database from this point forward.

It does not, however, delete any data from the external database. If you reconnect the system later, users can once again access the old data unless it has been purged.

Purging Experience Portal report data from an external database

About this task

The `PurgeReportDataExtDB` script purges the report data from the external database for any inactive Experience Portal system. This data includes all:

- Application Detail Records (ADRs) stored in the `vpapplog` table
- Contact Detail Records (CDRs) stored in the `cdr` table
- Performance records stored in the `vpperformance` table
- Session Detail Records (SDRs) stored in the `sdr` table
- System information such as the unique identifier for each Media Server associated with the Experience Portal system

Procedure

1. Make sure that the Experience Portal system whose data you want to purge is inactive. To do so:
 - a. Log on to the EPM Web interface using an account with the Administration, Operations, or Maintenance user role.
 - b. From the EPM main menu, select **Real-Time Monitoring > System Monitor** and go to the Summary tab.
 - c. Make sure the **State** column says **Inactive**. To change the system status to Inactive, disconnect the system from the shared external database. For more information, see [Disconnecting the Experience Portal system from a shared external database](#) on page 226

2. Log in to Linux on the primary or auxiliary EPM server.

If you are an Avaya Services representative and are using Avaya Enterprise Linux, or if the Avaya Service accounts are installed on this server:

- Log in to the local Linux console as `sroot`.
- Or log in remotely as a non-root user and enter the `su - sroot` command to change the user to `sroot`.

Otherwise, log in to Linux locally as root, or log in remotely as a non-root user and enter the `su -` command to change the user to root.

3. Enter the `cd $AVAYA_HOME/Support/VP-Tools` command. `$AVAYA_HOME` is an environmental variable pointing to the name of the installation directory specified during the Experience Portal software installation.

The default value is `/opt/Avaya/ExperiencePortal`.

4. Enter the `bash PurgeReportDataExtDB "Ext_DB_URL" JDBC_Driver Ext_DB_Username EP_System_Name` command.

Where:

- "*Ext_DB_URL*" is the fully-qualified path to the external database.

 Note:

The quotation marks are used around the first parameter when purging data from an external database. For example, the *Ext_DB_URL* parameter is surrounded with the quotation marks while running the script.

- *JDBC_Driver* is the name of the Java class that implements the JDBC API to the external database.
- *Ext_DB_Username* is the user name for the external database.
- *EP_System_Name* is the name of an **Inactive** Experience Portal system.

 Note:

Database URLs containing semi-colons need to be enclosed within quotes. For example, 'jdbc:sqlserver://<db ip address>:<port>;databaseName=<db name>'.

The values specified for these parameters should match the values specified on the EPM Settings page in the EPM.

 Important:

The system may take some time to purge the data depending on the amount of data in the database tables.

5. Enter the external database password.
6. At the prompt, press **Enter** to continue.

If the script runs successfully, it returns a message stating that the data was purged from the database. Otherwise, it returns a message stating the problem that it encountered. For example, the script will return an error message if you specify the name of an active system or if the system name you specify does not exactly match one of the systems in the external database.

EPM Servers page field descriptions

Use this page to configure the EPM servers on this Experience Portal system.

Column	Description
Selection check box	Indicates which auxiliary EPM servers you want to delete.  Note: You cannot delete the primary EPM server.
Zone	The name of the zone where the EPM server is configured.

Table continues...

Column	Description
 Zones filter icon	To filter zones, click this icon located at the right side of the page. The system opens the Zone filter window for selecting one or more zones. * Note: The Zones filter icon only appears when you create new zones. If you do not create any new zones, you do not see the icon.
Name	The name of the EPM server.
Type	The options are: • Primary: This is the primary EPM server for this system. • Auxiliary: This is the backup EPM server for this system.
Host Address	The hostname or IP address of the EPM server.
Add	Opens the Add EPM Server page so that you can specify the location of the auxiliary EPM server, if one is configured for your system. * Note: You can add one or more auxiliary EPM servers to the Experience Portal system.
Delete	Deletes the selected auxiliary EPM servers.
EPM Settings	Opens the EPM Settings page.
Event Handlers	Opens the Event Handlers page so you can change the global event handlers and prompts for all MPP servers.
Privacy Settings	Opens the Privacy Settings page. * Note: Privacy Settings is available in EPM only when the media server is MPP and when you log in to EPM with a Privacy Manager user role.
Data Storage Settings	Opens the Data Storage Settings page.
Report Data	Opens the Report Data Configuration page.
Alarm Codes	Opens the Alarm Codes page.
Alarm/Log Options	Opens the Alarm/Log Options page.
Syslog Settings	Opens the Syslog Settings page.

EPM Settings page field descriptions

Use this page to set the options that affect the primary EPM server

*** Note:**

If the media server type is MPP, you can also use this page to set the options that affect the optional auxiliary EPM server.

This page contains the:

- [General section](#) on page 230
- [Resource Alerting Thresholds \(%\) group](#) on page 230
- [Web Service Authentication group](#) on page 231
- [Miscellaneous group](#) on page 232

General section

Field	Description
Experience Portal Name	The name of this Experience Portal system. Experience Portal displays this name on the Summary tab of the System Monitor page.
Number of Application Server Failover Logs	The number of backup logs to retain on the application server in case the application server cannot communicate with the Experience Portal database. Each log file can be up to 100MB in size. The number of failover logs determines how much data the server can send to the EPM when the connection is restored. If the number of failover logs is exceeded, the application server deletes the oldest log file and begins recording data in a new file. When that file is full, the application server deletes the oldest log file and opens a new file. This process is repeated until contact with the Experience Portal database is restored and the application server can write its logs to that database.
Commands to Retain in Configuration History	The number of media server configuration changes that Experience Portal should save in the database. This value determines the number of entries on the <Media Server Name> Configuration History page.

Resource Alerting Thresholds (%) group

Field	Description
Disk	The low water threshold determines when the EPM generates an event, warning you, that disk usage is getting high. The high water threshold determines when the EPM generates an alarm, warning you, that disk usage is getting dangerously high. • High Water: Enter a whole number from 0 to 100. The default is 90. • Low Water: Enter a whole number from 0 to 100. The default is 80.
HTML Units	The HTML usage threshold determines when the system approaches the licensed usage limit.

Table continues...

Field	Description
	The administrator can configure the HTML usage threshold that triggers an alarm when the system approaches the licensed usage limit. The threshold is displayed in percentage.

*** Note:**

If the system is configured to use the local postgres database, the Call Data Handler (CDH) scheduler stops downloading report data from media server when the disk space on the EPM is below the configured high water alerting threshold.

Web Service Authentication group

! Important:

If you change the user name or password, there will be a delay of two-minute before these changes propagate across the system. Any request for web services made with the new user name and password will fail until that propagation is complete.

*** Note:**

If these fields are not displayed, click the group heading to expand the group.

Field	Description
Application Reporting section	
User Name	The user name to send to the Application Logging web service for Digest Authentication. * Note: - The user name must not contain the : character. - You cannot use the same user name for both the Application Logging web service and the Application Interface web service.
Password	The password associated with the specified user name.
Verify Password	The associated password again for verification purposes.
Outcall section	
* Note: The Outcall section is available in EPM only if the media server is MPP.	
User Name	The user name to send to the Application Interface web service. * Note: You cannot use the same user name for both the Application Logging web service and the Application Interface web service.
Password	The password associated with the specified user name.
Verify Password	The associated password again for verification purposes.

Miscellaneous group

Field	Description
License Re-allocation Wait Time (minutes)	The number of minutes the system waits before reallocating the licenses from a media server that is out of service to other media servers in the system. Enter a whole number from 0 to 1440. The default is 10.
Operational Grace Period (minutes)	The number of minutes Experience Portal waits for processing to complete before it terminates the remaining EP activities for any of the following Primary EPM, Auxiliary EPM, and MPP commands: • Stop • Reboot • Halt Enter a whole number of minutes between 0 and 999 in this field.  Important: Ensure that the grace period is long enough for the media server to complete any existing activity before it invokes one of the EP Media Server commands mentioned above.
Event Level Threshold to Send to EPM	Besides Fatal alarms, which are always sent, the lowest level of events and alarms to be included in the tracing log that is sent to the EPM. The options are: • Error: Fatal alarms and Error alarms are sent. • Warning: Fatal alarms, Error alarms, and Warning events are sent. • Info: All events and alarms are sent.  Note: Selecting the Info option can cause performance problem as all events and alarms are sent from the media server to EPM.
Multi-Media Server Numeric ID Range	Experience Portal assigns a numeric ID for each MPP in the Experience Portal system from the number range given in this field. This numeric ID identifies the MPP in the Experience Portal database and becomes part of the Universal Call Identifier (UCID) associated with every call processed on that MPP.  Tip: The ID assigned to a specific MPP server is displayed in the Unique ID field on the <MPP name> Details page for that server. Enter a range between 1 and 32,767. The default range is 10,000 to 19,999.  Important: You should only change this value if other components in your call center create Universal Call Identifier (UCID) values that conflict with the default Experience Portal values.

Table continues...

Field	Description
	If you do change the value, ensure that you specify a range that covers all MPP servers in your Experience Portal system.
Maximum Number of Conversations per Server	The maximum number of conversations that can be stored at any given time on either a Primary EPM or an Auxiliary EPM. Enter a range between 0 and 1000000. The default value is 500000.

Avaya Services information

Avaya Services MPPmap.data file

If this Experience Portal system is being maintained by Avaya Services, several of the Experience Portal servers have a Listed Directory Number (LDN) entry in the Avaya Services database.

You associate each server on the Experience Portal system with the corresponding LDN entry using the `$AVAYA_VPMS_HOME/bin/data/MPPmap.data` file.

Avaya Services `MPPmap.data` is found on the primary **EPM** server.

The `MPPmap.data` file should contain an entry for:

- Each dedicated MPP server in a system where the EPM and MPP software resides on different servers.
- Each Automatic Speech Recognition (ASR) server.
- Each Text-to-Speech (TTS) server.
- The auxiliary EPM server, if one is configured for this system.

If you want to:

- Add, delete, or change the IP address of an MPP, ASR, TTS, or auxiliary EPM server in the Experience Portal system, you must also update its entry in the Avaya Services map file through the EPM.
- View the contents of the map file or change an LDN entry in that file, you need to use the `MPPmap.sh` script.

Maintaining the server IP addresses in the MPPmap.data file

Procedure

1. Log on to the EPM using the init EPM account created during the EPM software installation.

2. If you want to add a new server to both the Experience Portal system and the `MPPmap.data` file and the server is:
 - An ASR server, follow the steps in [Adding ASR servers](#) on page 380.
 - An MPP server, follow the steps in [Adding an MPP](#) on page 258.
 - An ASR server, follow the steps in [Adding TTS servers](#) on page 394.
 - The auxiliary EPM server, follow the steps in [Configuring an auxiliary EPM server](#) on page 182.
3. If you want to add or change the IP address or LDN entry for an existing Experience Portal server in the `MPPmap.data` file and the server is:
 - An ASR server, follow the steps in [Changing ASR servers](#) on page 380.
 - An MPP server, follow the steps in [Changing an MPP](#) on page 258.
 - An ASR server, follow the steps in [Changing TTS servers](#) on page 394.
 - The primary or auxiliary EPM server, follow the steps in [Changing the configuration information for a EPM server](#) on page 184.

Using the MPPmap.sh script

About this task

You can use the `MPPmap.sh` script to view the current entries in the `MPPmap.data` file. The `MPPmap.sh` can be found in `$AVAYA_VPMS_HOME/bin`. You cannot change the IP address or LDN values for an existing server or add a new server to this file using the script. You must make those changes using the EPM.

Procedure

1. On the Primary EPM server, log in to Linux locally as root, or log in remotely as a non-root user and then change the user to root by entering the `su -` command.
2. Navigate to the `bin` directory under the EPM installation directory by entering the `cd $AVAYA_VPMS_HOME/bin` command.

`$AVAYA_VPMS_HOME` is the environment variable pointing to the name of the installation directory specified during the EPM software installation. If Linux does not recognize this environment variable, see *Implementing Avaya Aura® Experience Portal on multiple servers* or *Implementing Avaya Aura® Experience Portal on a single server*.
3. If you want to view the contents of the current map file, enter the `bash MPPmap.sh -l` command.
4. If you want to view the online help for this script, enter the `bash MPPmap.sh -h` command.

Logging in to an MPP manually through the MPP map file

If you cannot start a secure shell (SSH) session on an MPP in the MPP map file using the connect2 tool, you can log into the MPP manually using the MPP map file.

About this task

* Note:

This procedure is primarily used by the Avaya services representative.

Procedure

1. On the Primary EPM server, log in to Linux locally as root, or log in remotely as a non-root user and then change the user to root by entering the `su -` command.
2. Navigate to the `bin` directory under the EPM installation directory by entering the `cd $AVAYA_VPMS_HOME/bin` command.

`$AVAYA_VPMS_HOME` is the environment variable pointing to the name of the installation directory specified during the EPM software installation. If Linux does not recognize this environment variable, see *Implementing Avaya Aura® Experience Portal on multiple servers* or *Implementing Avaya Aura® Experience Portal on a single server*.

3. Run the connection script by entering the `bash MPPssh.sh LDN_entry Username` command, where:

- `LDN_entry` is the value stored in the Avaya Services database, including all formatting characters and quotation marks.

* Note:

The LDN entry value must be in the format of a 10 digit telephone number including the formatting characters `(, )`, and `-`. This number must be enclosed in double quotes or a `\` (backslash) must precede the open and close parentheses.

For example, to use the `MPPssh.sh` script that logs on to the LDN entry `(000)555-1212` using the Linux username `"myusername"`, you can enter any of the following:

```
- bash MPPssh.sh "(000)555-1212" myusername
- bash MPPssh.sh \ (000\)555-1212 myusername
```

- `Username` is the initial user name to use when logging into the target system.

Viewing the AF ID for the Experience Portal system

The Avaya Service Account authentication file for each Experience Portal system is assigned a unique ID. After you install the file, you can view the ID using a script installed with Experience Portal.

Before you begin

Install the Avaya Service Account authentication file as described in the *Configuring the Avaya Service accounts* topic in the *Implementing Avaya Aura® Experience Portal on multiple servers* guide or *Implementing Avaya Aura® Experience Portal on a single server* guide.

Procedure

1. Log on to Linux on the Primary or Auxiliary EPM server.

If you are an Avaya Services representative, and use Avaya Enterprise Linux or if the Avaya Service accounts are installed on this server:

- Log on to the local Linux console as `sroot`.
- Or log on remotely as a non-root user and then change the user to `sroot` by entering the `su - sroot` command.

Otherwise, log on to Linux locally as `root`, or log in remotely as a non-root user and then change the user to `root` by entering the `su -` command.

2. Enter the `afview` command.

Chapter 11: SNMP agents and traps

SNMP Agents and Traps

The Avaya Aura® Experience Portal Simple Network Management Protocol (SNMP) network includes agents, traps, and managers.

SNMP agents

You can configure Experience Portal to act as an *SNMP agent* so that a third party network management software can retrieve the Experience Portal system status.

An SNMP agent is a software module that resides on a device, or node, in an SNMP-managed network. The SNMP agent collects and stores management information and makes this information available to *SNMP managers*. SNMP agent communication can be:

- Solicited by an SNMP manager.
- Initiated by the SNMP agent if a significant event occurs. This type of communication is called an *SNMP trap*.

The commands and queries that the SNMP agent can use, along with information about the target objects that the SNMP agent can interact with using these commands and queries, is stored in a Management Information Base (MIB) that resides on the managed device.

SNMP traps

An SNMP trap is an unsolicited notification of a significant event from an SNMP agent to an SNMP manager. When an internal problem is detected, the SNMP agent immediately sends one of the traps defined in the MIB.

Important:

If you configure Experience Portal to send SNMP traps, you must configure the appropriate SNMP managers to receive those traps.

SNMP managers

SNMP managers collect information from SNMP agents. SNMP managers are usually used to display status information in a type of graphical user interface (GUI).

For Experience Portal, the SNMP manager can be an Avaya Services Security Gateway (SSG) or a Network Management System (NMS) station such as HP *OpenView* or IBM *Tivoli*. SNMP traps sent to the Avaya SSG contain specific information that generates Initialization and Administration System (INADS) notifications, which in turn generate customer trouble tickets.

 Note:

You can only configure the Experience Portal SNMP agent and SNMP trap destinations if you are an administrator.

Configuring Avaya Aura[®] Experience Portal as an SNMP agent

Procedure

1. Log on to the EPM Web interface using an account with the Administration user role.
2. From the EPM main menu, select **System Configuration > SNMP**.
3. On the On the SNMP page, click **SNMP Agent Settings**.
4. On the SNMP Agent Settings page, enter the appropriate information and click **Save**.
5. If you changed the port number, restart the SNMP Agent.

Viewing existing SNMP traps

Procedure

1. Log on to the EPM Web interface using an account with the Administration, Operations, or Maintenance user role.
2. From the EPM main menu, select **System Configuration > SNMP**.

The EPM displays the SNMP page. From this page, authorized users can add, change, or delete SNMP trap destinations.

Adding an SNMP trap

Procedure

1. Log on to the EPM Web interface using an account with the Administration user role.
2. From the EPM main menu, select **System Configuration > SNMP**.
3. On the SNMP page, click **Add**.
4. On the Add SNMP Trap Configuration page, enter the appropriate information and click **Save**.

Changing an SNMP trap

Procedure

1. Log on to the EPM Web interface using an account with the Administration user role.
2. From the EPM main menu, select **System Configuration > SNMP**.
3. On the SNMP page, click the SNMP manager IP address or host name in the **Host Address** column.
4. On the Change SNMP Trap Configuration page, enter the appropriate information and click **Save**.

Disabling SNMP traps

If you want a particular SNMP trap to stop sending SNMP notifications but you want to save the configuration information for future reference, you can disable the trap instead of deleting it.

Procedure

1. Log on to the EPM Web interface using an account with the Administration user role.
2. From the EPM main menu, select **System Configuration > SNMP**.
3. On the SNMP page, click the SNMP manager IP address or host tname in the **Host Address** column.
4. On the Change SNMP Trap Configuration page, select **No** in the **Enable** field.
5. Click **Save**.

Testing SNMP traps

Procedure

1. Log on to the EPM Web interface using an account with the Administration user role.
2. From the EPM main menu, select **System Configuration > SNMP**.
3. On the SNMP page, click **Test**.

Experience Portal sends a test message to each SNMP trap configured on the system.

Next steps

When you test your SNMP traps, Experience Portal automatically generates an alarm. You should retire this alarm as soon as possible so that it does not get confused with a real SNMP trap alarm.

Deleting SNMP traps

Procedure

1. Log on to the EPM Web interface using an account with the Administration user role.
2. From the EPM main menu, select **System Configuration > SNMP**.
3. On the SNMP page, click the Selection check box to the left of the destination name in the table for each SNMP trap destination that you want to delete.

 Tip:

To delete all SNMP trap destinations, click the selection check box in the header row of the table. This automatically selects all rows in the SNMP traps table.

4. Click **Delete**.

Configuring IBM Tivoli or HP OpenView with Experience Portal

Procedure

For details about configuring Experience Portal with IBM's *Tivoli* or HP's *OpenView*, see the configuration files on the Experience Portal installation DVD. For:

- IBM Tivoli, see `Support/NMS-Configuration/IBM-Tivoli/ibm-config-steps.txt`
- HP OpenView, see `Support/NMS-Configuration/HP-Openview/hp-config-steps.txt`

SNMP page field descriptions

Use this page to view information about any SNMP trap configurations already administered on the Experience Portal system and to access the SNMP Agent settings. You can also use this page to add or change SNMP traps.

Column or Button	Description
Add	Opens the Add SNMP Trap Configuration page.
Delete	Deletes the selected SNMP traps.
Test	Sends a test alarm notification to all servers so that you can verify the functionality of the traps.
SNMP Agent Settings	Opens the SNMP Agent Settings page.
SNMP Device Notification Settings	Opens the SNMP Device Notification Settings page that lets you change how device notifications are sent.

*** Note:**

The following columns are displayed only if you add an SNMP Trap.

Column or Button	Description
Selection check box	Indicates which SNMP traps you want to delete.
Host Address	The IP address or fully qualified domain name of the SNMP manager that receives the SNMP traps. To change settings for an SNMP trap configuration, click the name or address in this field. Experience Portal opens the Change SNMP Trap Configuration page.
Enable	Whether this SNMP trap is active.
Device	The options are: • SSG/SAL: Experience Portal sends SNMP traps to an Avaya Services Security Gateway (SSG)/Secure Access Link (SAL). * Note: Experience Portal sends only Initialization and Administration System (INADS) traps to the SSG. • NMS: Experience Portal sends SNMP traps to a customer-provided Network Management System (NMS). * Note: The Experience Portal system does not send INADS traps to the NMS.
Transport Protocol	The options are: • UDP: The transport protocol is set to User Datagram Protocol (UDP). • TCP: The transport protocol is set to Transmission Control Protocol (TCP).
Port	The port number the Experience Portal system uses to send SNMP traps.
Notification Type	The options are: • Trap: Experience Portal sends notifications with the SNMP <code>trap</code> command. • Inform: Experience Portal sends notifications with the SNMP <code>inform</code> command.
SNMP Version	The options are: • 1: The SNMP agent uses SNMP Version 1 to send notifications. • 2c: The SNMP agent uses SNMP Version 2c to send notifications. • 3: The SNMP agent uses SNMP Version 3 to send notifications.

Table continues...

Column or Button	Description
Security Name	The character string the Experience Portal SNMP agent uses as the identification name for the configuration.
Authentication Protocol	If the SNMP Version field is set to 3, this can be: • None: The system performs no authentication and you cannot use an Authentication Password. If you select this option, you must also set the Privacy Protocol field to None. • MD5: Authentication is performed using the Message Digest 5 (MD5) protocol. This is the default. • SHA: Authentication is performed using the Secure Hash Algorithm (SHA) protocol.
Privacy Protocol	If the SNMP Version field is set to 3, this can be: • None: The system performs no message encryption and you cannot set a Privacy Password. You must select this option if the Authentication Protocol field is set to None. • DES: The Data Encryption Standard (DES) protocol is used to encrypt SNMP Version 3 messages. • AES128: The Advanced Encryption Standard 128 (AES128) protocol is used to encrypt SNMP Version 3 messages. This is the default. • AES192: The Advanced Encryption Standard 192 (AES192) protocol is used to encrypt SNMP Version 3 messages. • AES256: The Advanced Encryption Standard 256 (AES256) protocol is used to encrypt SNMP Version 3 messages.

SNMP Agent Settings page field descriptions

Use this page to view or configure the SNMP agent settings for this Experience Portal system.

This page contains the:

- [SNMP Version 1 group](#) on page 243
- [SNMP Version 2c group](#) on page 243
- [SNMP Version 3 group](#) on page 243
- [Authorized for SNMP Access group](#) on page 243
- [Transport Protocol group](#) on page 244
- [Port Number group](#) on page 244

SNMP Version 1 group

Field	Description
Enable SNMP Version 1	To configure the Experience Portal SNMP agent to receive and respond to SNMP Version 1 messages, select this check box.
Security Name	If you enabled version 1 messages, enter an alphanumeric name for the Experience Portal SNMP agent in this field. The agent only accepts message strings that include this name. You cannot leave this field blank or use the strings "public" or "private".

SNMP Version 2c group

Field	Description
Enable SNMP Version 2c	To configure the Experience Portal SNMP agent to receive and respond to SNMP Version 2c messages, select this check box.
Security Name	If you enabled version 2c messages, enter an alphanumeric name for the Experience Portal SNMP agent in this field. The agent only accepts message strings that include this name. You cannot leave this field blank or use the strings "public" or "private".

SNMP Version 3 group

Field	Description
Enable SNMP Version 3	To configure the Experience Portal SNMP agent to receive and respond to SNMP Version 3 messages, select this check box.
Security Name	If you enabled version 3 messages, enter an alphanumeric name for the Experience Portal SNMP agent in the Security Name field. The agent only accepts message strings that include this name. You cannot leave this field blank or use the strings "public" or "private".
Authentication Password	Enter a character string to be used as the authentication password for SNMP Version 3 messages. This password must either be blank or contain at least 8 alphanumeric characters. If you leave it blank, then you must also leave the Privacy Password field blank as well.
Privacy Password	Enter a character string to be used as the privacy password for SNMP Version 3 messages. This password must either be blank or contain at least 8 alphanumeric characters.

Authorized for SNMP Access group

Field	Description
Allow All IP Addresses	Allows any SNMP manager access to the Experience Portal SNMP agent. This is the default.
Allow Only the Following	Allows up to five specified SNMP managers access to the Experience Portal SNMP agent.

Table continues...

Field	Description
	If you select this field, specify one or more SNMP managers in the IP Address/Hostname fields.

Transport Protocol group

The only currently supported transportation protocol is the User Datagram Protocol (UDP).

Port Number group

Field	Description
Default Port Number	Specifies that the Experience Portal SNMP agent communicates with SNMP managers using the default port number for UDP, which is 161.
Custom Port Number	Specifies that the Experience Portal SNMP agent communicates with SNMP managers using a non-default port number. If you select this option, enter a port number from 0 to 65535 in the associated text field.

Add SNMP Trap Configuration page field descriptions

Use this page to add a new Simple Network Management Protocol (SNMP) trap.

Column	Description
Enable	Whether this SNMP trap is active. The default is Yes , which means the trap is active.
Device	The options are: • SSG/SAL: Experience Portal sends SNMP traps to an Avaya Services Security Gateway (SSG)/Secure Access Link (SAL).  Note: Experience Portal sends only Initialization and Administration System (INADS) traps to the SSG. • NMS: Experience Portal sends SNMP traps to a customer-provided Network Management System (NMS).  Note: The Experience Portal system does not send INADS traps to the NMS. The default is SSG/SAL.
Transport Protocol	The options are: • UDP: The transport protocol is set to User Datagram Protocol (UDP). • TCP: The transport protocol is set to Transmission Control Protocol (TCP). The default is UDP.

Table continues...

Column	Description
Host Address	The IP address or fully qualified domain name of the SNMP manager that receives the SNMP traps.
Port	The port number the Experience Portal system uses to send SNMP traps. The default is 162.
Notification Type	The options are: • Trap: Experience Portal sends notifications with the SNMP <code>trap</code> command. The receiver does not verify that the command was received. This notification type can be used with all versions of SNMP. • Inform: Experience Portal sends notifications with the SNMP <code>inform</code> command. This option can be used only with SNMP versions 2c and 3. When an SNMP manager receives an SNMP message with the <code>inform</code> command, the SNMP manager sends a response back to the SNMP agent indicating that it received the notification. The default is Trap.
SNMP Version	The options are: • 1: The SNMP agent uses SNMP Version 1 to send notifications. • 2c: The SNMP agent uses SNMP Version 2c to send notifications. • 3: The SNMP agent uses SNMP Version 3 to send notifications. The default is 3.
Security Name	The character string the Experience Portal SNMP agent uses as the identification name for the configuration. For devices configured to use SNMP Version 1 or 2c, this string is used as the <code>Community Name</code>. For devices configured to use SNMP Version 3, this string is used as the <code>Security Name</code>. You cannot leave this field blank or use the strings <code>public</code> or <code>private</code>.
Authentication Protocol	If the SNMP Version field is set to 3, this can be: • None: The system performs no authentication and you cannot use an Authentication Password. If you select this option, you must also set the Privacy Protocol field to None. • MD5: Authentication is performed using the Message Digest 5 (MD5) protocol. This is the default. • SHA: Authentication is performed using the Secure Hash Algorithm (SHA) protocol.
Authentication Password	If the Authentication Protocol field is set to something other than None, the password that the system uses to authenticate SNMP Version 3 messages. The password must contain at least 8 alphanumeric characters.

Table continues...

Column	Description
Privacy Protocol	If the SNMP Version field is set to 3, this can be: • None: The system performs no message encryption and you cannot set a Privacy Password. You must select this option if the Authentication Protocol field is set to None. • DES: The Data Encryption Standard (DES) protocol is used to encrypt SNMP Version 3 messages. • AES128: The Advanced Encryption Standard 128 (AES128) protocol is used to encrypt SNMP Version 3 messages. This is the default. • AES192: The Advanced Encryption Standard 192 (AES192) protocol is used to encrypt SNMP Version 3 messages. • AES256: The Advanced Encryption Standard 256 (AES256) protocol is used to encrypt SNMP Version 3 messages.  Note: For the AES192 or AES256 options, the system must be configured for a high encryption level. These options are not enabled during a standard OS installation and are controlled under U.S. federal export laws. The default is AES128.
Privacy Password	If the Privacy Protocol field is set to something other than None, the password that the system is to use for encrypted SNMP Version 3 messages. The password must contain at least 8 alphanumeric characters.

Change SNMP Trap Configuration page field descriptions

Use this page to change an existing Simple Network Management Protocol (SNMP) trap.

Column	Description
Enable	Whether this SNMP trap is active. The default is Yes, which means the trap is active.
Device	The options are: • SSG/SAL: Experience Portal sends SNMP traps to an Avaya Services Security Gateway (SSG)/Secure Access Link (SAL).  Note: Experience Portal sends only Initialization and Administration System (INADS) traps to the SSG. • NMS: Experience Portal sends SNMP traps to a customer-provided Network Management System (NMS).

Table continues...

Column	Description
	 Note: The Experience Portal system does not send INADS traps to the NMS. The default is SSG/SAL.
Transport Protocol	The options are: • UDP: The transport protocol is set to User Datagram Protocol (UDP). • TCP: The transport protocol is set to Transmission Control Protocol (TCP). The default is UDP.
Host Address	The IP address or fully qualified domain name of the SNMP manager that receives the SNMP traps.
Port	The port number the Experience Portal system uses to send SNMP traps. The default is 162.
Notification Type	The options are: • Trap: Experience Portal sends notifications with the SNMP <code>trap</code> command. The receiver does not verify that the command was received. This notification type can be used with all versions of SNMP. • Inform: Experience Portal sends notifications with the SNMP <code>inform</code> command. This option can be used only with SNMP versions 2c and 3. When an SNMP manager receives an SNMP message with the <code>inform</code> command, the SNMP manager sends a response back to the SNMP agent indicating that it received the notification. The default is Trap.
SNMP Version	The options are: • 1: The SNMP agent uses SNMP Version 1 to send notifications. • 2c: The SNMP agent uses SNMP Version 2c to send notifications. • 3: The SNMP agent uses SNMP Version 3 to send notifications. The default is 3.
Security Name	The character string the Experience Portal SNMP agent uses as the identification name for the configuration. For devices configured to use SNMP Version 1 or 2c, this string is used as the <code>Community Name</code>. For devices configured to use SNMP Version 3, this string is used as the <code>Security Name</code>. You cannot leave this field blank or use the strings <code>public</code> or <code>private</code>.

Table continues...

Column	Description
Authentication Protocol	If the SNMP Version field is set to 3, this can be: • None: The system performs no authentication and you cannot use an Authentication Password. If you select this option, you must also set the Privacy Protocol field to None. • MD5: Authentication is performed using the Message Digest 5 (MD5) protocol. This is the default. • SHA: Authentication is performed using the Secure Hash Algorithm (SHA) protocol.
Authentication Password	If the Authentication Protocol field is set to something other than None, the password that the system uses to authenticate SNMP Version 3 messages. The password must contain at least 8 alphanumeric characters.
Privacy Protocol	If the SNMP Version field is set to 3, this can be: • None: The system performs no message encryption and you cannot set a Privacy Password. You must select this option if the Authentication Protocol field is set to None. • DES: The Data Encryption Standard (DES) protocol is used to encrypt SNMP Version 3 messages. • AES128: The Advanced Encryption Standard 128 (AES128) protocol is used to encrypt SNMP Version 3 messages. This is the default. • AES192: The Advanced Encryption Standard 192 (AES192) protocol is used to encrypt SNMP Version 3 messages. • AES256: The Advanced Encryption Standard 256 (AES256) protocol is used to encrypt SNMP Version 3 messages.  Note: For the AES192 or AES256 options, the system must be configured for a high encryption level. These options are not enabled during a standard OS installation and are controlled under U.S. federal export laws. The default is AES128.
Privacy Password	If the Privacy Protocol field is set to something other than None, the password that the system is to use for encrypted SNMP Version 3 messages. The password must contain at least 8 alphanumeric characters.

View SNMP Device Notification Settings page field descriptions

Use this page to view how SNMP notifications are sent on the Avaya Aura® Experience Portal system

This page contains the following groups:

- [NMS group](#) on page 249
- [SSG/SAL group](#) on page 249
- [Last Time All Alarms Retired group](#) on page 250

NMS group

Section or Field	Description
Notification options	The SNMP notifications that Avaya Aura® Experience Portal sends to the Network Management System (NMS) . The options are: • All Minor, Major, and Critical notifications will be sent. • First Minor will be sent. All Major and Critical notifications will be sent. • First Minor and Major will be sent. All Critical notifications will be sent. • First Minor, Major, and Critical notifications will be sent.
Highest severity notification sent	If any option except All Minor, Major, and Critical notifications will be sent. is selected in the Notification options section, this field displays: • " " (blank) if no notification has been sent since the last time the old alarms were retired. • The highest notification that has been sent to this system since the last time the status of all alarms was set to Retired. No more notifications below this level will be sent to the NMS until the status of all current alarms has been set to Retired.

SSG/SAL group

Section or Field	Description
Notification options	The SNMP notifications that Avaya Aura® Experience Portal sends to the Service Selection Gateway (SSG). The options are: • All Minor, Major, and Critical notifications will be sent. • First Minor will be sent. All Major and Critical notifications will be sent. • First Minor and Major will be sent. All Critical notifications will be sent. • First Minor, Major, and Critical notifications will be sent.
Highest severity notification sent	If any option except All Minor, Major, and Critical notifications will be sent. is selected in the Notification options section, this field displays: • " " (blank) if no notification has been sent since the last time the old alarms were retired. • The highest notification that has been sent to this system since the last time the status of all alarms was set to Retired.

Table continues...

Section or Field	Description
	No more notifications below this level will be sent to the SSG until the status of all current alarms has been set to Retired.

Last Time All Alarms Retired group

Displays the last time that the status of all alarms was set to Retired, thereby resetting the notification triggers.

Chapter 12: Media Processing Platforms

Media Processing Platform server overview

A Media Processing Platform (MPP) server is a server machine running the Avaya Aura® Experience Portal MPP software.

The MPP software:

- Runs on Avaya Enterprise Linux or Red Hat Enterprise Linux 6.4 or later, but not RHEL 7.x.
- Uses Voice over IP (VoIP) protocols to communicate with the telephone network.
- Uses the Media Resource Control Protocol (MRCP) protocol to communicate with the speech servers.
- Runs Voice eXtensible Markup Language (VoiceXML) speech applications deployed on the application server.
- Runs Call Control eXtensible Markup Language (CCXML) applications

 Note:

Experience Portal uses the Oktopous™ ccXML Interpreter.

Multiple MPP servers

When a system is configured with multiple MPP servers:

- An individual MPP server is not aware of any other MPP servers in the system, nor can it communicate directly with them.
- The Experience Portal Manager (EPM) web interface allows administrators to control any MPP server in the system.

Data storage

The Experience Portal system is designed so that all persistent data is stored on the primary EPM server. For example, all configuration information is stored on the primary EPM server and downloaded to the MPP when required.

Any persistent data created on the MPP server is uploaded to the EPM either on-demand or through scheduled jobs. For example:

- The EPM regularly polls the MPP server's status.
- Event and alarm data is delivered to the EPM on demand.
- Report data, including Contact Detail Records (CDRs) and Session Detail Records (SDRs), are delivered to the EPM according to a schedule that you administer.

The MPP has additional data that can be used for debugging, but is not required to be persistent. For example:

- Trace data and MPP-specific log files.
- Session transcriptions and utterances.

MPP server components

The MPP server consists of the following components:

- System Manager
- Web services
- Session Manager
- Avaya Voice Browser
- CCXML Browser
- Speech proxies
- Telephony
- Event Manager

Related links

[System Manager component](#) on page 252

[The Web services component](#) on page 253

[The Session Manager component](#) on page 254

[The Avaya Voice Browser component](#) on page 254

[The CCXML Browser component](#) on page 255

[Speech proxy component](#) on page 255

[The Telephony component](#) on page 255

System Manager component

The System Manager component works in conjunction with the EPM to keep the MPP functioning in an optimal state. In addition, System Manager provides the following functions:

Function	Description
State management	Starts and stops all processes in response to start or stop commands from the EPM. Monitors the health of the processes and attempts to restart any processes that exit prematurely, appear deadlocked, have stopped responding.
Configuration management	The EPM downloads configuration information to the MPP during startup. Configuration updates can also be downloaded to the MPP while it is running. The System Manager transfers the information to the other MPP components of the change, if needed.

Table continues...

Function	Description
License management	The EPM manages port licensing for each MPP and passes that information during MPP startup and later if licenses need to be redistributed. The EPM downloads all licensing changes to the MPP.
Resources monitor	The EPM monitors CPU usage, memory usage, and disk usage for each MPP. The EPM checks the state of these resources at predetermined intervals during EPM polling operations. If at any time the use of these resources crosses thresholds set on the EPM, Resource monitor issues an alert. The System Manager also monitors for network errors between the MPP and the EPM.

Related links

[Media Processing Platform server overview](#) on page 251

The Web services component

The EPM accesses the web services of the MPP to monitor and control the MPP. The Apache Web server implements the web services and ensures that communication between the EPM and the web services is secure. The MPP web services are:

Service name	Description
Call Data Handler (CDH) service	The EPM uses the CDH service to transfer Application Detail Records (ADRs), Contact Detail Records (CDRs), and Session Detail Records (SDRs) from the MPP. The EPM stores the record data in the Experience Portal database and uses this information to generate the call and session reports.
MPP Management Service (MMS)	The EPM uses the MMS to send heartbeat requests, configuration changes, and commands. The MMS then forwards these requests to the System Manager for execution.
Application Interface web service	Also known as the “Outcall web service”, using this Web services the developers can: • Start a CCXML or VoiceXML application that has been added to Experience Portal. • Send an event to a specific application session running on an MPP. • Query the system for the total number of: - Used and unused outbound resources available - Unused SIP outbound resources - Unused H.323 outbound resources • Send an SMS or Email message using Experience Portal resources. • Start an SMS or Email application that has been added to Experience Portal.
TransService	This process uploads any transcription data to the Experience Portal database.

Related links

[Media Processing Platform server overview](#) on page 251

The Session Manager component

A *session* covers the time between the start of the inbound or outbound call and the completion of that call.

When the MPP initiates a call or is assigned a call, the Session Manager:

1. Starts a new session.
2. Assigns the session a unique ID.
3. Associates the call with the appropriate Call Control eXtensible Markup Language (CCXML) or Voice eXtensible Markup Language (VoiceXML) application.
4. Depending on the MPP settings, the administrator selects for the MPP, records all or some of the following data during the session:
 - Contact Detail Records (CDRs)
 - Application Detail Records (ADRs)
 - Session transcriptions
 - Performance trace information

The MPP Session Manager also coordinates all interactions between the MPP and:

- Any Automatic Speech Recognition (ASR) servers
- Any Text-to-Speech (TTS) servers
- Any telephony components
- The Avaya Voice Browser.
- The CCXML Browser

Related links

[Media Processing Platform server overview](#) on page 251

The Avaya Voice Browser component

The Avaya Voice Browser is a Voice eXtensible Markup Language (VoiceXML) interpreter that communicates with the application servers to interpret the VoiceXML documents of a speech application.

For each incoming call:

1. Session Manager starts a new Avaya Voice Browser session and passes the Universal Resource Indicator (URI) of the VoiceXML application to the new session.

2. The Avaya Voice Browser contacts the application server and waits for the VoiceXML page to be returned.
3. After the application starts, the Avaya Voice Browser is responsible for:
 - Interpreting the VoiceXML page returned by the application server.
 - Managing the user interaction including playing prompts and interpreting input from the caller through Dual-tone multi-frequency (DTMF) or Automatic Speech Recognition (ASR).

Related links

[Media Processing Platform server overview](#) on page 251

The CCXML Browser component

The CCXML Browser component is responsible for providing low level call control support including the setup, monitoring, and tear-down of telephone calls.

For VoiceXML applications, Experience Portal includes a default CCXML application that provides the basic call control functionality. If you want to use advanced features such as call merging and all conferencing, you need to create a custom CCXML application.

Related links

[Media Processing Platform server overview](#) on page 251

Speech proxy component

The MPP speech proxy component integrates third-party media resources, such as Automatic Speech Recognition (ASR) and Text-to-Speech (TTS) speech servers, into the Experience Portal system by employing Media Resource Control Protocol (MRCP).

When a speech application requests ASR or TTS resources, the speech proxy component communicates with the speech servers and selects the appropriate server to provide those resources. The MRCP proxy reports the state of the speech servers to the MPP System Manager.

If directed by the EPM, the speech proxy component can also add or remove communication ports between an MPP and any speech server in the system.

Related links

[Media Processing Platform server overview](#) on page 251

The Telephony component

The MPP Telephony component provides all telephony services required by the Experience Portal system, including call control and media processing.

The telephony subsystem can be connected to:

- Direct connection to Communication Manager, a VoIP-based PBX gateway, using either the International Standard for Multimedia Communication Over Packet-switched Networks (H.323) or Session Initiation Protocol (SIP) for signaling and Real-time Transport Protocol (RTP) to transport the actual audio data stream in a connection.
- Proxied SIP connection through Avaya Aura Session Manager to Communication Manager, Communication Server 1000, the Avaya G860 Media Gateway or Third-party SIP gateways.

Related links

[Media Processing Platform server overview](#) on page 251

Setting the global grace period and trace level parameters

Procedure

1. Log on to the EPM Web interface using an account with the Administration user role.
2. To set the global trace period:
 - a. From the EPM main menu, select **System Configuration > EPM Servers**.
 - b. On the EPM Servers page, click EPM Settings.
 - c. On the EPM Settings page, go to the Miscellaneous group and do the following
 - In the Operational Grace Period (minutes) field, enter the number of minutes Experience Portal waits for the processing to complete before it terminates all the remaining EP activities and begins changing the following states of the Primary EPM, Auxiliary EPM, and MPP:
 - Halting
 - Rebooting
 - Restarting
 - Stopping
 - In the Event Level Threshold to Send to EPM drop-down list, select the lowest level of events to be included in the performance tracing log that is sent to the EPM.
3. To set the trace level parameters:
 - a. From the EPM main menu, select System Configuration > MPP Servers.
 - b. On the MPP Servers page, click MPP Settings.
 - c. On the MPP Settings page, click the Categories and Trace Levels section header to view the complete table of options.
 - d. Select the performance trace level you want to use as the default for each component. You can select Off, Fine, Finer, or Finest.

! Important:

Performance tracing is a valuable troubleshooting tool, but it can adversely impact Experience Portal system performance if you set all categories to Finest on a busy production system. If you need to troubleshoot a particular area, you must set specific categories to Fine and examine the resulting output to see if you can locate the issue. If not, set the level to Finer and repeat the process. If you still need more data, then set the level to Finest and keep a close watch on system resource usage.

Viewing all MPP servers

Procedure

1. Log on to the EPM Web interface using an account with the Administration, Operations, or Maintenance user role.
2. To view the:
 - Current status of all MPP servers and get detailed information about any alarms they have generated, select **Real-Time Monitoring > System Monitor** and go to the <System name> Details tab. The information on this page refreshes automatically if you leave the browser window open.
 - MPP configuration, select **System Configuration > MPP Servers** to access the MPP Servers page.

In general, the MPP servers shown on these pages should be identical. Occasionally, however, there may be more MPP servers on the <System name> Details tab on the System Monitor page. For example, when an administrator deletes an MPP server, Experience Portal immediately removes it from the MPP Servers but leaves it on the <System name> Details tab until the ports allocated to the MPP server can be reassigned.

Viewing details for a specific MPP

Procedure

1. Log on to the EPM Web interface using an account with the Administration, Operations, or Maintenance user role.
2. From the EPM main menu, select **Real-Time Monitoring > System Monitor** and go to the appropriate <System name> Details tab.
3. In the **Server Name** column, click the name of the MPP whose details you want to view.
4. On the <MPP name> Details page, if you want to view the configuration history of the MPP, click the **History** link next the **Configuration** group at the top of the second column.

*** Note:**

If you are logged in with the Administration user role, you can access the Media Server Service Menu for the MPP by clicking the **Service Menu** link in the **Miscellaneous** group at the bottom of the second column.

Adding an MPP

Procedure

1. Log on to EPM Web interface.

If Avaya Services is maintaining this system and you are an Avaya Services representative, log on to the EPM using the init EPM account created during the EPM software installation.

Otherwise, log on to the EPM using an account with the Administrator user role.

2. From the EPM main menu, select **System Configuration > MPP Servers**.
3. On the Add MPP Server page, click **Add**.
4. On the first Add MPP Server page, enter the appropriate information and click **Continue**.
5. On the second Add MPP Server page, enter the appropriate information and click **Save**.

If you logged in using the init account, ensure you enter the appropriate LDN number for the server in the **LDN** field. If you do not specify an LDN number, Experience Portal uses the default value (000)000-0000.

*** Note:**

Make sure you verify the security certificate displayed in the click the **MPP Certificate** section and then check the **Trust new certificate** check box. You cannot save the MPP unless this check box has been selected.

Changing an MPP

About this task

You can change all MPP options except the name of the MPP.

Procedure

1. Log on to EPM Web interface.

If Avaya Services is maintaining this system and you are an Avaya Services representative, log on to the EPM using the init EPM account created during the EPM software installation.

Otherwise, log on to the EPM using an account with the Administrator user role.

2. From the EPM main menu, select **System Configuration > MPP Servers**.
3. On the MPP Servers page, click the name of the MPP you want to reconfigure in the **Name** column.
4. On the Change MPP Server page, enter the appropriate information and click **Save**.

If you logged in using the init account, make sure that the LDN number specified in the **LDN** field matches the information in the Avaya Services database for this server.

MPP server capacity

The number of telephony ports and the maximum number of simultaneous calls that an MPP server can handle depend on many factors, including the hardware characteristics of the MPP server and the complexity of the applications that the Avaya Aura® Experience Portal system is running. For assistance in sizing your MPP server capacity and setting the correct value for the **Maximum Simultaneous Calls** parameter for each MPP server, contact your Avaya Services representative or Avaya Business Partner.

When configuring your Avaya Aura® Experience Portal system, make sure that you have enough MPP servers to handle the telephony ports that you purchase. Ideally, you should have enough reserve capacity so that when one MPP server goes out of service, all of your telephony ports can be handled by the remaining MPP servers. You must have enough MPP servers so that the sum of the maximum simultaneous calls is larger than the number of configured ports.

For example, if your Avaya Aura® Experience Portal system needs to handle 400 simultaneous calls, you must purchase 400 telephony port licenses and configure a sufficient number of MPP servers to run that many simultaneous calls.

If your Avaya Services representative or Avaya Business Partner determines that each one of your MPP servers can handle a maximum of 100 simultaneous calls, you could configure:

- 4 MPP servers, each with the **Maximum Simultaneous Calls** parameter set to 100. When Avaya Aura® Experience Portal initializes, it distributes the 400 available telephony ports across the 4 servers so that each server is running at the maximum capacity of 100 calls each and the entire system can process 400 simultaneous calls. In this configuration there is no failover capability. If an MPP goes out of service, Avaya Aura® Experience Portal cannot reassign the ports because the other 3 servers are already running 100 simultaneous calls. This means that the total number of simultaneous calls the system can handle drops to 300.
- 5 MPP servers, each with the **Maximum Simultaneous Calls** parameter set to 100. When Avaya Aura® Experience Portal initializes, it distributes the 400 available telephony ports across the 5 servers so that each server is assigned 80 telephony ports and the entire system can process 400 simultaneous calls. In this configuration, if an MPP goes out of service, Avaya Aura® Experience Portal can reassign the 80 ports to the other 4 servers, bringing those 4 servers up to their maximum capacity of 100 ports. The entire system remains capable of processing 400 simultaneous calls.

For more information about capacity and scalability specification, see *Avaya Aura® Experience Portal Overview and Specification*.

MPP operational modes

Mode	Description
Offline	The MPP is unavailable to handle customer calls or test calls. It is not currently being polled, but its last known status is displayed on the MPP Manager page. The MPP will <i>not</i> respond to state change commands issued through the EPM, but you can change the mode to Online or Test.
Online	The MPP is available to handle customer calls. It is being polled, and its updated status is displayed on the MPP Manager page. The MPP will respond to state change commands issued through the EPM.
Test	The MPP is <i>not</i> available to handle customer calls but is available to handle test calls made using an H.323 connection that has at least one maintenance station defined. If your site does not have any configured H.323 connections or has no defined maintenance stations, then an MPP in Test mode will not respond to any VoIP requests. The MPP will respond to state change commands issued through the EPM.

Related links

[Changing the operational mode of an MPP](#) on page 260

Changing the operational mode of an MPP

Procedure

1. Log on to the EPM Web interface using an account with the Administration or Operations user role.
2. From the EPM main menu, select **System Management > MPP Manager**.
3. On the MPP Manager page, use the Selection check box in the MPP server table to select which MPP you want to change.
4. Click the desired operational state button in the **Mode Commands** group. You can select:
 - **Offline** if the MPP server is currently in Online or Test mode.
 - **Test** if the MPP server is currently in Offline mode.
 - **Online** if the MPP server is currently in Offline mode.
5. When you have finished setting the operational mode, click **Refresh** to ensure the mode is now what you expect.

Related links

[MPP operational modes](#) on page 260

MPP operational states

State	Description
Booting	The MPP is in the process of restarting and is not yet ready to take new calls. It is not responding to heartbeats and last MPP state was Rebooting. If the MPP remains in this state for more than 10 minutes, the state changes to Not Responding.
Degraded	The MPP is running but it is not functioning at full capacity. This usually means that: • Some of the H.323 or SIP telephony resources assigned to the MPP are not registered with the switch. For more information on viewing telephony port distribution, see <i>Administering Avaya Aura® Experience Portal</i>. • Enough ports have gone out of service to trigger a fatal alarm. The percentage of out of service ports that trigger such an alarm is specified in the Out of Service Threshold group on the VoIP Settings page. • A critical process has stopped on the MPP server. If an MPP has issued a fatal event and remains in that state for three minutes, Experience Portal automatically restarts the MPP in an attempt to fix the problem. If the problem persists after the restart, Experience Portal tries to restart the MPP up to two more times. If after three restarts the MPP is still encountering fatal errors, the state changes to Error.
Error	The MPP has encountered a severe problem and cannot recover.
Halted	The MPP is no longer responding to heartbeats because it received a Ha1t command. The MPP cannot be restarted until its server machine has been manually restarted.
Halting	The MPP is responding to heartbeats but is not taking new calls. Experience Portal shuts down the corresponding server machine after all calls in progress are completed or the grace period ends, whichever comes first. Once an MPP has halted, you must manually turn on the corresponding server machine before the MPP can be restarted.
Never Used	The MPP has never successfully responded to a heartbeat request. New MPPs start to receive heartbeat requests during the next polling interval after they have been configured. This state occurs when an MPP has either not yet been sent a heartbeat request after it was added or the MPP did not respond to the heartbeat request.
Not Responding	The MPP is not responding to heartbeat requests and it has not received a Restart or Ha1t command. You should manually check the MPP server machine.
Rebooting	The MPP is responding to heartbeats but is not taking new calls. Experience Portal reboots the corresponding server machine after all calls in progress are completed or the grace period ends, whichever comes first.
Recovering	The MPP has encountered a problem and is attempting to recover.

Table continues...

State	Description
Restart Needed	This state is most often reached when the MPP has encountered a problem that it cannot recover from and it requires a manual restart. However, it may also appear for an MPP when the EPM software has been upgraded and the MPP software has not. In that case, the state should update automatically when you upgrade the MPP software.
Running	The MPP is responding to heartbeat requests and is accepting new calls.
Starting	The MPP is responding to heartbeats but not taking new calls because it is transitioning from the Stopped state to the Running state.
Stopped	The MPP is responding to heartbeats but is not taking new calls. The MPP enters this state while it initializes after it restarts or when a <code>stop</code> command is received. Experience Portal will restart the MPP automatically if the MPP: • Stopped unexpectedly and the Auto Restart option is selected for that MPP. In this case, Experience Portal restarts the MPP immediately. • Has a specified restart schedule. In this case, Experience Portal restarts the MPP when the scheduled restart time arrives whether the MPP stopped because of an explicit <code>stop</code> command or because the MPP encountered a problem and was not configured to restart automatically.
Stopping	The MPP is responding to heartbeats but is not taking new calls. Experience Portal stops the corresponding server machine after all calls in progress are completed or the grace period ends, whichever comes first.

Related links

[Checking the operational state for one or more MPPs](#) on page 262

[Changing the operational state for one or more MPPs](#) on page 263

[Setting the license reallocation time](#) on page 264

Checking the operational state for one or more MPPs

Procedure

1. Log on to the EPM Web interface using an account with the Administration or Operations user role.
2. From the EPM main menu, select **System Management > MPP Manager**.
3. On the MPP Manager page, look at the **State** column for the MPPs whose state you want to check.

The options are:

- **Booting:** The Media Server is in the process of restarting and is not yet ready to take new calls.
- **Degraded:** The Media Server is running but it is not functioning at full capacity.
- **Error:** The Media Server has encountered a severe problem and cannot recover.

- **Halted:** The Media Server is no longer responding to heartbeats because it received a `halt` command.
- **Halting:** The Media Server is responding to heartbeats but is not taking new calls.
- **Need Configuration:** An Email or SMS processor residing on the Media Server has not yet been configured.
- **Need Connections:** No connections (SMPP or HTTP) have been configured or assigned to an Email/SMS processor residing on the Media Server.
- **Never Used:** The Media Server has never successfully responded to a heartbeat request.
- **Not Installed:** The Media Server is missing files required for heartbeat requests to occur.
- **Not Responding:** The Media Server is not responding to heartbeat requests and it has not received a `Restart` or `halt` command.
- **Partially Running:** (EPM only) The Media Server is in the process of starting up, and not all individual components of the service, for example: Tomcat, SL, ActiveMQ, have come up yet.
- **Rebooting:** The Media Server is responding to heartbeats but is not taking new calls.
- **Recovering:** The Media Server has encountered a problem and is attempting to recover.
- **Restart Needed:** This state is most often reached when the Media Server has encountered a problem that it cannot recover from and it requires a manual restart. However, it can also appear for an MPP when the EPM software has been upgraded and the MPP software has not. In that case, the state should update automatically when you upgrade the MPP software.
- **Running:** The Media Server is responding to heartbeat requests and is accepting new calls.
- **Starting:** The Media Server is responding to heartbeats but not taking new calls because it is transitioning from the Stopped state to the Running state.
- **Stopped:** The Media Server is responding to heartbeats but is not taking new calls. The Media Server enters this state while it initializes after it restarts or when a `stop` command is received.
- **Stopping:** The Media Server is responding to heartbeats but is not taking new calls.
- **Unknown:** The Media Server is in the Offline mode.

Related links

[MPP operational states](#) on page 261

Changing the operational state for one or more MPPs

Procedure

1. Log on to the EPM Web interface using an account with the Administration or Operations user role.

2. From the EPM main menu, select **System Management > MPP Manager**.
3. On the MPP Manager page, use the Selection check box in the MPP server table to select which MPP servers you want to change.
4. If you selected multiple servers and you plan to either restart or reboot them, in the **Restart/Reboot Options** group, select either **One server at a time** or **All selected servers at the same time**.
5. Click the desired operational state button in the **State Commands** group and confirm your selection when prompted. You can select:
 - Start
 - Stop
 - Restart
 - Reboot
 - Halt
 - Cancel
6. When you have finished setting the operational state, click **Refresh** to ensure that the state is now what you expect.

 Tip:

You can also verify the state change by selecting **Real-Time Monitoring > System Monitor** from the EPM main menu and going to the <System name> Details tab. The information on this page refreshes automatically if you leave the browser window open.

Related links

[MPP operational states](#) on page 261

Setting the license reallocation time

About this task

When you stop or restart an MPP, the EPM waits for the specified license reallocation time before taking the telephony ports away from that MPP and redistributing them to the other MPPs in the Experience Portal system. The reallocation time needs to be longer than the MPP grace period so that the MPP has time to finish any active calls, stop, and then restart.

Procedure

1. Log on to the EPM Web interface using an account with the Administration user role.
2. From the EPM main menu, select **System Configuration > EPM Servers**.
3. On the EPM Servers page, click the **EPM Settings** button.
4. On the EPM Settings page, go to the **Miscellaneous** group.
5. Enter the number of minutes to wait in the **License Re-allocation Wait Time** field.
6. Click **Save**.

Related links

[MPP operational states](#) on page 261

MPP processes

The following table provides an overview of the processes that run on the MPP.

Process Name	Descriptive Name	Notes
ccxml	CCXML Interpreter	Controls all call handling behavior for each VoiceXML application that runs on the MPP. CCXML Interpreter also controls each request to obtain or release a telephony resource for a given VoiceXML application.
CdhService	Call Data Handler (CDH)	A web service that runs when the EPM is downloading Contact Detail Records (CDRs) and Session Detail Records (SDRs).
EventMgr	Event Manager	Collects events from other MPP processes and sends them to the network log web service on the EPM.
httpd	Apache Web Server	Enables the other web services running on the MPP. The first Apache Web Server process started by the daemon runs as root. The root process starts nine other processes that run as the <code>avayavp</code> user in the <code>avayavp</code> group.
MmsServer	MPP Management Service (MMS)	With a Web service interface, the EPM server sends commands to the MPP server. MMS runs only when the EPM is polling or sending commands to the MPP.
mppmaint	MPP Maintenance Utility	The <code>cron</code> process runs the MPP Maintenance Utility daily at 4 am to purge CDRs, SDRs, and transcriptions data based on the retention period specified in the EPM.
mppmon	MPP Monitor	Runs as root and monitors the <code>httpd</code> service, restarting them if necessary.
mppsismgr	System Manager	Handles the majority of tasks required to manage the MPP. For example, this process monitors system resources such as CPU usage, memory usage, and disk usage. If any of these values exceed the baseline set in the EPM, the System Manager issues an alarm message. When instructed by the EPM, the System Manager starts or stops all MPP processes and distributes EPM configuration updates to all MPP processes as updates occur.
SessionManager	Session Manager	Runs as root and integrates and controls the interaction between the MPP and media resources, as well as between the speech application and the ASR, TTS, and telephony components.

Table continues...

Process Name	Descriptive Name	Notes
TransService		Uploads any transcription data to the Experience Portal database.
vxlmgr	VoiceXML Manager	Works with the Session Manager to run multiple VoiceXML dialog sessions. VoiceXML Manager also interfaces with the CCXML, telephony, ASR, and TTS subsystems. The VoiceXML Manager and the Session Manager communicates through messages. The Session Manager is responsible for interpreting these messages and routing the calls to the appropriate platform subsystems on behalf of the VoiceXML Manager.

Software Upgrade

Software Upgrade overview

The Software Upgrade page in Experience Portal allows you to upgrade the software version of the MPPs running on your Experience Portal system. The Software Upgrade page lists only those software versions which have the .iso image set in the `$AVAYA_IA_HOME/download` directory. Before you start the upgrade process from the Software Upgrade page in EP, make sure you:

- Execute the `/opt/Avaya/InstallAgent/bin/DownloadPK.bash <EPM_Hostname, or EPM IP address>` command on the MPPs to authorize the software upgrades through EPM. For more information see the *Authorizing the EPM to upgrade the MPP* section in the *Implementing Avaya Aura® Experience Portal on multiple servers* guide.
- Copy the .iso image of the updated software versions in the `$AVAYA_IA_HOME/download` directory.
- Have a corresponding .sig for every .iso image.



Note:

Delete files from the `$AVAYA_IA_HOME/download` directory when they are not required.

Software Upgrade page field descriptions

Use this page to upgrade the software version of the MPPs running on your Experience Portal system.

This page contains the:

- [Software Upgrade server table](#) on page 267
- [Upgrade Commands group](#) on page 269

Software Upgrade server table

Field	Version Description
Selection check box	Indicates the MPPs you want to upgrade. To select all MPPs, click the check box in the header row. * Note: If there is no Selection check box next to an MPP, it can be because: • The user does not have the permission to upgrade an MPP. • There is no .iso image available in the \$AVAYA_IA_HOME/download directory. • An MPP is already being upgraded. • The MPP version is not Experience Portal 6.0 or higher. • The MPP is on the same server as the primary EPM. If you select all MPPs, the upgrade process skips MPPs which meet any of the conditions mentioned above.
Zone	The zone where the MPPs are configured.
 Zones filter icon	To filter zones, click this icon located at the right side of the page. The system opens the Zone filter window for selecting one or more zones. * Note: The Zones filter icon only appears when you create new zones. If you do not create any new zones, you do not see the icon
Server Name	The name of the MPP.
Mode	The MPP operational mode. The options are: • Online: The Media Server is available. • Offline: The Media Server is unavailable and is not being polled by the EPM server. • Test: (MPP only) The Media Server is available to handle calls made to one of the defined H.323 maintenance stations. + Tip: To view the date and time that this mode was first reached, hover the mouse over this column.
State	The operational state of the MPP. + Tip: To view the date and time that this state was first reached, hover the mouse over this column.

Table continues...

Field	Version Description
Config	The MPP configuration state. The options are: • Need ports: The MPP has been configured and is waiting for ports to be assigned • None: The MPP has never been configured • OK: The MPP is currently operating using the last downloaded configuration • Restart needed: The MPP must be restarted to enable the downloaded configuration • Reboot needed: The MPP must be rebooted to enable the downloaded configuration
Active Calls	This field displays: • In: The number of active incoming calls in the system • Out: The number of active outgoing calls in the system
Current Version	The MPP version.
Upgrade Status	The MPP upgrade status. The options are: • Upgrade Pending: The MPP is selected for an upgrade and is waiting for the upgrade process to start. • Upgrade Not Needed: The current version of the MPP is higher than the requested upgrade version. • Upgrade Not Requested: The MPP is not selected for upgrade. • Upgrade Not Possible: Requested version of upgrade is not supported. • Downloading: The requested upgrade version is in the process of downloading. During this process, the MPP continues to be in the Running state. • Downloaded: Download process is complete and the MPP is waiting for upgrade. • Recovery Needed: The upgrade process is interrupted before completion.  Note: This upgrade status is typically displayed when the EPM server reboots while the MPP is being upgraded. The upgrade of this MPP continues while the EPM is out of service. However, you must restart the upgrade process for any other MPPs that still needs to be upgraded.

Table continues...

Field	Version Description
	• Upgrade In Progress: The MPP upgrade is in progress. Once this process starts: - The MPP State changes to Stopped - The MPP is out of service and the MPP mode changes to Upgrading • Completed Successfully: The MPP upgrade is completed successfully. • Failed: The MPP upgrade process is unsuccessful.  Note: If there is a problem in upgrading an MPP, the upgrade for all MPPs is stopped. The other MPPs continue to run the software version they had prior to the start of the upgrade. For more information on the upgrade error, you can use the Log Viewer page. • Cancelled: The MPP upgrade process is cancelled.
Certificate Algorithm	The Certificate Signing Algorithm of the MPP server certificate.

Upgrade Commands group

Note:

These buttons are greyed out until you select one or more MPPs using the Selection check box in the MPP server table.

Button	Description
New Version	The new versions available for upgrade.  Note: • Only those versions are available for selection which have the .iso image set in the \$AVAYA_IA_HOME/download directory. • Ensure that each .iso has a corresponding .sig in the \$AVAYA_IA_HOME/download directory. • Manually delete files from the \$AVAYA_IA_HOME/download directory when they are no longer needed.
Upgrade	Starts the upgrade for the selected MPPs.  Note: When selected, the button is greyed out until the upgrade is complete.
Cancel	Stops the upgrade for the selected MPPs. It allows an ongoing download or upgrade process to complete before cancelling the upgrade command.

Upgrading all MPP servers

Before you begin

Execute the `/opt/Avaya/InstallAgent/bin/DownloadPK.bash <EPM_Hostname, or EPM IP address>` command on the MPPs to authorize the software upgrades through EPM.

For more information, see the *Authorizing the EPM to upgrade the MPP* section in the *Implementing Avaya Aura® Experience Portal on multiple servers* guide.

Procedure

1. Log on to EPM Web interface.

If Avaya Services is maintaining this system and you are an Avaya Services representative, log on to the EPM using the init EPM account created during the EPM software installation.

Otherwise, log on to the EPM using an account with the Administrator user role.

2. From the EPM main menu, select **System Management > Software Upgrade**.
3. Click the Selection check box in the first column header of the MPP server table to select all MPP servers.

 Note:

The upgrade process skips an MPP if:

- The user does not have the permission to upgrade an MPP.
- There is no .iso image available in the `$AVAYA_IA_HOME/download` directory.
- An MPP is already being upgraded.
- The MPP version is not Experience Portal 6.0 or higher.
- The MPP is on the same server as the primary EPM.

4. Select the required upgrade version in the **New Version** field.

 Note:

Only those versions are available for selection which have the .iso image set in the directory `$AVAYA_IA_HOME/download` (default = `/opt/Avaya/InstallAgent/download`).

5. Click **Upgrade** in the **State Commands** group and confirm your selection when prompted.

Experience Portal upgrades the MPP servers. This process can take several minutes depending on how many servers there are in your system.

 Note:

The selection boxes are greyed out and you cannot start another upgrade until the current one completes.

6. After a few minutes, click **Refresh** and verify that, for all MPP servers, the:

- **Mode** is **Online**.
- **State** is **Running**.
- **Config** is **OK**.

 Note:

If there is an error, you can use the **Log Viewer** page to view the details.

7. Check that the version numbers are correctly allocated to the MPP servers by verifying the **Current Version** column.

Upgrading an MPP server

Procedure

1. Log on to EPM Web interface.

If Avaya Services is maintaining this system and you are an Avaya Services representative, log on to the EPM using the init EPM account created during the EPM software installation.

Otherwise, log on to the EPM using an account with the Administrator user role.

2. From the EPM main menu, select **System Management > Software Upgrade**.

3. Click the Selection check box next to the MPP server you want to upgrade.

 Note:

If there is no Selection check box next to an MPP, it can be because:

- The user does not have the permission to upgrade an MPP.
- There is no .iso image available in the `$AVAYA_IA_HOME/download` directory.
- An MPP is already being upgraded.
- The MPP version is not Experience Portal 6.0 or higher.
- The MPP is on the same server as the primary EPM.

4. Select the required upgrade version in the **New Version** field.

 Note:

Only those versions are available for selection which have the .iso image set in the directory `$AVAYA_IA_HOME/download` (default = `/opt/Avaya/InstallAgent/download`).

5. Click **Upgrade** in the **State Commands** group and confirm your selection when prompted.

Experience Portal upgrades the MPP server. This process can take several minutes depending on how many servers there are in your system.

*** Note:**

The selection boxes are greyed out and you cannot start another upgrade until the first one completes.

6. After a few minutes, click **Refresh** and verify that the:
 - **Mode** is **Online**.
 - **State** is **Running**.
 - **Config** is **OK**.
7. Check that the version number is correctly allocated to the MPP server by verifying the **Current Version** column.

Starting all MPP servers

Procedure

1. From the EPM main menu, select **System Management > MPP Manager**.
2. On the MPP Manager page, make sure that the **Mode** column says **Online** for all servers. If any are shown as **Offline**:
 - a. Click the Selection check box next to each Offline MPP server.
 - b. Click the **Online** button in the **Mode Commands** group and confirm your selection when prompted.
3. Click the Selection check box in the first column header of the MPP server table to select all MPP servers.
4. Click **Start** in the **State Commands** group and confirm your selection when prompted.

Experience Portal starts the MPP servers. This process can take several minutes depending on how many servers there are in your system.
5. After a few minutes, click **Refresh** and verify that, for all MPP servers, the:
 - **Mode** is **Online**.
 - **State** is **Running**.
 - **Config** is **OK**.
6. If desired, make sure that all licensed telephony ports were correctly allocated to the MPP servers:
 - a. From the EPM main menu, select **Real-Time Monitoring > Port Distribution**.
 - b. On the Port Distribution page, examine the **Mode** and **State** columns.

Starting an MPP server

Procedure

1. From the EPM main menu, select **System Management > MPP Manager**.
2. On the MPP Manager page, make sure that the **Mode** column says **Online** for the server you want to start. If the mode is **Offline**:
 - a. Click the Selection check box next to the Offline MPP server.
 - b. Click the **Online** button in the **Mode Commands** group and confirm your selection when prompted.
3. Click the Selection check box next to the MPP server you want to start.
4. Click **Start** in the **State Commands** group and confirm your selection when prompted.
5. After a few minutes, click **Refresh** and verify that the:
 - **Mode** is **Online**.
 - **State** is **Running**.
 - **Config** is **OK**.
6. If desired, make sure that all licensed telephony ports were correctly allocated to the MPP server:
 - a. From the EPM main menu, select **Real-Time Monitoring > Port Distribution**.
 - b. On the Port Distribution page, examine the **Mode** and **State** columns.

Restarting one or more MPP servers

Procedure

1. Log on to the EPM Web interface using an account with the Administration or Operations user role.
 2. From the EPM main menu, select **System Management > MPP Manager**.
 3. On the MPP Manager page, use the Selection check box in the MPP server table to select the MPP servers you want to restart.
-  **Tip:**
- To restart all MPP servers, click the Selection check box in the header row of the MPP server table.
4. If you selected multiple servers, in the **Restart/Reboot Options** group, select either **One server at a time** or **All selected servers at the same time**.
 5. Click **Restart** in the **State Commands** group.
 6. Confirm that you want to restart the selected MPP servers when prompted.

7. After the grace period for the MPP servers has expired, click **Refresh** to ensure that the servers are restarting.

Setting the restart options for an MPP

Procedure

1. Log on to the EPM Web interface using an account with the Administration or Operations user role.
2. From the EPM main menu, select **System Management > MPP Manager**.
3. On the MPP Manager page, if you want to:
 - Change the action Experience Portal takes if an MPP stops unexpectedly, click the pencil icon in the **Auto Restart** column and enter the appropriate information in the Auto Restart <MPP Name> page.
 - Schedule a one time restart during the current day, click the pencil icon under **Restart Today** in the **Restart Schedule** column and enter the appropriate information in the Restart <MPP Name> Today page.
 - Specify that the MPP should be automatically restarted on a regular basis, click the pencil icon under **Recurring** in the **Restart Schedule** column and enter the appropriate information in the Restart Schedule for <MPP Name> page.
4. When you have specified the required information, click **Save** to return to the MPP Manager page.

Viewing MPP configuration history

Procedure

1. Log on to the EPM Web interface using an account with the Administration, Operations, or Maintenance user role.
2. From the EPM main menu, select **Real-Time Monitoring > System Monitor**.
3. On the <System name> Details tab of the System Monitor page, in the **Server Name** column of the system status table, click the name of the MPP whose configuration history you want to view.
4. On the <MPP name> Details page, click the **History** link next the **Configuration** group.
5. On the <MPP Name> Configuration History page, if you want to view or save an XML document detailing a specific configuration change, click the link in the **Configuration** column for that change and follow the prompts.

 Note:

The number of configuration changes displayed depends on the setting for the **Commands to Retain in Configuration History** field on the EPM Settings page.

6. If you want to view or save an XML document showing the complete current configuration for the MPP, click **Export** in the top right corner of the page and follow the prompts.

Configuring Experience Portal to use the Test operational mode

You can test any MPP in the Experience Portal system if there is at least one maintenance station assigned to an H.323 connection and a speech application is available to handle a call made from the maintenance station.

Before you begin

If desired, on the Communication Manager PBX for the system, create a special hunt group for maintenance numbers. For information about setting up the hunt group on the Communication Manager, see *Avaya Configuration Note 3910* on the Avaya online support Web site, <http://support.avaya.com>.

Make sure that at least one H.323 station has been defined as a maintenance number as described in [Defining maintenance stations for an H.323 connection](#) on page 55.

Procedure

1. Log on to the EPM Web interface using an account with the Administration user role.
2. From the EPM main menu, select **System Configuration > Applications**.
3. On the Applications page, look at the **Launch** column and make sure that at least one speech application is specifically associated with the maintenance stations defined for the H.323 connection.
4. If no application is assigned to handle the maintenance stations:
 - Add a new application as described in [Adding a speech application to Experience Portal](#) on page 320, making sure that you specify the maintenance stations in the **Application Launch** group on the Add Application page.
 - Change an existing application so that it is specifically associated with the maintenance station as described in [Changing speech application settings through Avaya Aura Experience Portal](#) on page 321, making sure that you specify the maintenance stations in the **Application Launch** group on the Change Application page.

Related links

[Using the Test operational mode](#) on page 276

Using the Test operational mode

The Test operational mode allows you to send a test call to one or more MPPs in the Experience Portal system.

Before you begin

Configure one or more H.323 connections to use the Test operational mode as described in [Configuring Experience Portal to use the Test operational mode](#) on page 275.

Procedure

1. Log on to the EPM Web interface using an account with the Administration or Operations user role.
2. From the EPM main menu, select **System Management > MPP Manager**.
3. On the MPP Manager page, use the Selection check box in the MPP server table to select the MPPs you want to test.

If you select multiple MPPs, keep in mind that the number of available test ports is equal to the number of defined maintenance numbers. If you put more MPPs into Test mode than you have defined maintenance numbers, some of the MPPs will not be assigned a port and therefore will not be tested.

4. If any of the MPPs are running:
 - a. In the **State Commands** group, click **Stop** and confirm your selection when prompted.
 - b. After allowing the MPP to finish processing, click **Refresh** to ensure that the state is Stopped.
 - c. Use the appropriate Selection check boxes to reselect the MPPs you want to test.
5. In the **Mode Commands** group, click **Test**.
6. Click **Refresh** to ensure the **Mode** is now **Online**.
7. Use the appropriate Selection check boxes to reselect the MPPs you want to test.
8. In the **State Commands** group, click **Start** or **Restart** and confirm your selection when prompted.

Experience Portal assigns a Test mode port to each MPP as soon as it starts. If the number of MPPs currently in Test mode is:

- Less than or equal to the number of defined maintenance stations, Experience Portal assigns one Test mode port to each MPP.
 - Greater than the number of defined maintenance stations, Experience Portal randomly assigns the associated Test mode ports to a subset of the selected MPPs. To determine which MPPs were selected, see [Viewing telephony port distribution](#) on page 47.
9. Initiate a call using a unique maintenance station for each MPP you placed in Test mode.
 10. Verify the results of each call using the Experience Portal reports and MPP logs for additional information if needed.

11. When you have finished testing:

- a. Use the appropriate Selection check boxes to reselect the MPPs you want to put into Online mode.
- b. In the **State Commands** group, click **Stop** and confirm your selection when prompted.
- c. After allowing the MPP to finish processing, click **Refresh** to ensure that the **State** is **Stopped**.
- d. Use the appropriate Selection check boxes to reselect the MPPs.
- e. In the **Mode Commands** group, click **Online**.
- f. Use the appropriate Selection check boxes to reselect the MPPs.
- g. In the **State Commands** group, click **Start** or **Restart** and confirm your selection when prompted.
- h. Click **Refresh** to ensure the **Mode** is now **Online** and the **State** is **Running**.

Related links

[Configuring Experience Portal to use the Test operational mode](#) on page 275

You can test any MPP in the Experience Portal system if there is at least one maintenance station assigned to an H.323 connection and a speech application is available to handle a call made from the maintenance station.

Reestablishing the link between the EPM and an MPP

About this task

After you upgrade the Experience Portal software, use this procedure to reestablish the link between the MPP and the EPM by trusting the MPP's security certificate.

Procedure

1. Log on to the EPM Web interface using an account with the Administration user role.
2. From the EPM main menu, select **System Configuration > MPP Servers**.
3. Click the name of the MPP server.
4. On the Change MPP Server page, go to the **MPP Certificate** section and select the **Trust new certificate** check box if that check box is visible.
5. At the bottom of the page, click **Save**.
6. From the EPM main menu, select **System Management > MPP Manager**.
7. On the MPP Manager page, look at the **Mode** column for this server. If it says **Offline**:
 - a. Select the check box next to the name of the MPP.
 - b. In the **Mode Commands** group, click **Online**.
 - c. In a few moments, click **Refresh** to verify that the **Mode** column now says **Online**.

8. Select the check box next to the name of the MPP.
9. In the **State Commands** group, click **Start** and confirm your selection when prompted.
10. In a few minutes, click **Refresh** to verify that the current **State** is **Running**.
11. If desired, make sure that telephony ports were correctly allocated to the MPP server:
 - a. From the EPM main menu, select **Real-Time Monitoring > Port Distribution**.
 - b. On the Port Distribution page, examine the **Current Allocation** column to find the ports allocated to this MPP.
 - c. Look at the **Mode** and **State** columns to make sure the assigned ports are ready to receive calls.

Deleting MPP servers

Procedure

1. Log on to the EPM Web interface using an account with the Administration user role.
2. From the EPM main menu, select **System Configuration > MPP Servers**.
3. On the MPP Servers page, for each MPP that you want to delete, click the Selection check box to the left of the MPP name in the MPP server table.

 Tip:

To delete all MPPs, click the Selection check box in the header row of the MPP server table.

4. Click **Delete**.

Experience Portal removes the MPP from the MPP Servers page, but leaves the MPP on the <System name> Details tab of the System Monitor page until the association between the MPP and all H.323 ports and SIP channels has been removed.

MPPServiceMenu

The Media Server Service Menu provides details about the status of an MPP and of the calls running on that MPP.

 Note:

You must be logged into the EPM as a user with the Administration user role to access the Media Server Service Menu.

Name	Description
Home	Displays the MPP Service Menu home page, which shows an overview of the MPP status.
Activity	Displays the Page Activity page, which shows details about call and telephony activity currently taking place on the MPP.
Calls	Displays the Active Calls page, which shows details about all calls running on the MPP.
Sessions	Displays the Active Sessions page, which shows details about all sessions running on the MPP.
Applications	Displays the Applications page, which shows details about all applications running on the MPP.
Statistics	Displays the Application Statistics page, which shows statistics for all applications running on the MPP.
Certificates	Displays the Certificates page, which displays a list of the certificates available on the MPP.
Configuration	Displays the Configuration page, which shows the configuration file for this MPP.
Diagnostics	Displays the Diagnostics page, which lets you: • Check the connectivity between the MPP and the other servers in the Experience Portal system. • Create a compressed file containing the logs stored on this MPP. • View process messages. • View the current and previous version of the MPP software installed on this server.
Logs	Displays the Log Directories page, which shows the logs created on the MPP.
Resources	Displays the Resources page, which shows a summary of the Automatic Speech Recognition (ASR), Text-to-Speech (TTS), and telephony resources are being used by the applications running on the MPP.
ASR	Displays the ASR Resources page, which displays details about the ASR resources being used by the MPP.
TTS	Displays the TTS Resources page, which displays details about the TTS resources being used by the MPP.
Speech Servers	Displays the Speech Servers page, which displays the status of the speech servers available to the MPP.
Telephony	Displays the Telephony Resources page, which displays details about the telephony resources being used by the MPP.
Networking	Displays the Networking page, which displays details about the telephony resources being used by the MPP.

Table continues...

Name	Description
Users	Displays the Users page, which shows the EPM user accounts that have the Administration user role and are therefore authorized to access the Media Server Service Menu.

Related links

[Logging in to the Media Server Service Menu](#) on page 280

If you are logged in to the EPM with the Administration user role, you can also log in to the Media Server Service Menu for a specific MPP.

[Using the Media Server Service Menu with a proxy server](#) on page 280

Logging in to the Media Server Service Menu

If you are logged in to the EPM with the Administration user role, you can also log in to the Media Server Service Menu for a specific MPP.

Procedure

1. Log on to the EPM Web interface using an account with the Administration user role.
2. From the EPM main menu, select **Real-Time Monitoring > System Monitor**.
3. Go to the <System name> Details tab on the System Monitor page, where <System Name> matches the name of the Experience Portal system that contains the MPP whose Media Server Service Menu you want to access.
4. Click the name of an MPP in the **Server Name** column.
5. On the <MPP name> Details page, click **Service Menu** in the **Miscellaneous** group at the bottom of the second column.

If the EPM does not automatically open the Media Server Service Menu, there may be a problem with the proxy server settings. For details, see [Using the Media Server Service Menu with a proxy server](#) on page 280.

Related links

[MPPServiceMenu](#) on page 278

The Media Server Service Menu provides details about the status of an MPP and of the calls running on that MPP.

Using the Media Server Service Menu with a proxy server

About this task

If your browser uses a proxy server, you need to add the host address of the MPP to the list of addresses for which a proxy server is not required. You should then be able to access the Media Server Service Menu from the appropriate <MPP name> Details page.

Procedure

1. Open Internet Explorer.
2. Select **Tools > Internet Options > Connections**.
3. Click **LAN Settings**, then click **Advanced**.
4. In the **Exceptions** text box, enter the host addresses of the MPP whose Media Server Service Menu you want to access. You can use the * (asterisk) wildcard to specify multiple MPPs with similar addresses.

Tip:

To determine the host address of a particular MPP, look at the <MPP name> Details for that MPP. To view the host addresses for all MPPs, from the EPM main menu, select **System Configuration > MPP Servers**.

5. When you are done, click **OK** three times to close the Proxy Settings dialog, the LAN Settings dialog, and the Internet Options dialog.

Next steps

Log into the Media Server Service Menu as described in [Logging in to the Media Server Service Menu](#) on page 280.

Related links

[MPPServiceMenu](#) on page 278

The Media Server Service Menu provides details about the status of an MPP and of the calls running on that MPP.

Moving the MPP logs to a different location

About this task

If you need to free up space on an MPP server, you can use the `mppMoveLogs.sh` script to create a new directory and move the MPP logs to that directory.

Procedure

1. Install the target drive or create the target partition as described in your operating system documentation.

Important:

Do *not* create the new directory on this drive or partition, as the script will fail if the directory already exists.

The drive or partition must be local to the MPP server and it must contain either 2 GB of free space or be at least as large as the current `$AVAYA_MPP_HOME/logs` directory, whichever value is greater.

+ Tip:

For a good tutorial about creating a partition, see http://tldp.org/HOWTO/html_single/Partition/.

2. If you created a new partition, add an entry for the partition in the `/etc/fstab` file so that it is automatically mounted when the system is booted.

If the partition for the directory will only host the Experience Portal log directory, you can improve security by setting its properties in the `/etc/fstab` file to `rw,nosuid,noexec,auto,nouser,async,noatime,nodev`. For more information about these options, refer to Man pages on Linux for the **Mount** command

3. Log on to the EPM Web interface using an account with the Administration or Operations user role.
4. Stop the MPP whose logs you want to move:
 - a. From the EPM main menu, select **System Management > MPP Manager**.
 - b. On the MPP Manager page, click the Selection check box next to the name of the MPP you want to stop.
 - c. Click **Stop** in the **State Commands** group.
 - d. Wait until the operational state becomes Stopped. To check this, click **Refresh** and look at the **State** field.

*** Note:**

The operational state changes when the last active call completes or the grace period expires, whichever comes first.

5. Log on to Linux on the Experience Portal MPP server.

If you are an Avaya Services representative, and use Avaya Enterprise Linux or if the Avaya Service accounts are installed on this server:

- Log on to the local Linux console as `sroot`.
- Or log on remotely as a non-root user and then change the user to `sroot` by entering the `su - sroot` command.

Otherwise, log on to Linux locally as `root`, or log in remotely as a non-root user and then change the user to `root` by entering the `su -` command.

6. Enter the `bash mppMoveLogs.sh [-logdir directory_name]` command, where `-logdir directory_name` is an optional parameter specifying the directory name that you want to use.

If you do not specify this parameter on the command line, the script prompts you for the directory name during execution. If the directory you specify already exists, the script returns an error message and fails. This ensures that no existing files will be overwritten by the script.

When the script completes successfully, all of the current logs will reside in the new location, and all future logs will be stored in the new location.

7. Restart the MPP:

- From the EPM main menu, select **System Management > MPP Manager**.
- On the MPP Manager page, click the Selection check box next to the name of the MPP you want to start.
- Click **Restart** in the **State Commands** group
- Wait until the operational state becomes Running. To check this, click **Refresh** and look at the **State** field.

Related links

[Add MPP Server page field descriptions](#) on page 283

Add MPP Server page field descriptions

Use these pages to add a new Media Processing Platform (MPP) to the Experience Portal system.

Add MPP Server page (page 1 of 2)

Field	Description
Zone	The name of the zone where the MPP server is configured. Select the name of the zone from the drop-down box.  Note: The Zone drop-down box appears only if you have created zones on your Experience Portal system. If you do not create any new zones, you do not see the drop-down box.
Name	The unique identifier for the MPP server on the Experience Portal system. This name is used only in the EPM Web interface and cannot be changed after you save the new MPP.
Host Address	The network address, or location, of the computer on which the MPP server resides. The EPM uses this address to communicate with the MPP server. This address can be a fully qualified domain name or an IP address, but the address must be unique on this Experience Portal system and the machine must already have the MPP software installed on it. You cannot use any of the following hostnames: 127.0.0.1, localhost, or localhost.local.domain.
Continue	Submits the name and host address to Experience Portal for verification. Experience Portal verifies the host address by attempting to download the Secure Sockets Layer (SSL) certificate from the designated MPP. If the SSL certificate fails to download, Experience Portal prompts you to correct the Host Address field entry and try again. When the SSL certificate downloads successfully, Experience Portal displays the second Add MPP Server page.

Add MPP Server page (page 2 of 2)

This page contains the:

- [General section](#) on page 284
- [MPP Certificate section](#) on page 285
- [Categories and Trace Levels section](#) on page 285

General section

Field	Description
Name	The name you entered on the first Add MPP page.  Note: This field cannot be changed.
Host Address	The network address, or location, of the computer on which the MPP server resides. The EPM uses this address to communicate with the MPP server. This address can be a fully qualified domain name or an IP address, but the address must be unique on this Experience Portal system and the machine must already have the MPP software installed on it. You cannot use any of the following hostnames: 127.0.0.1, localhost, or localhost.local.domain.  Important: If you entered an incorrect host address on the first Add MPP page, Experience Portal displays an error message in red next to this field. You must correct this error before you can save the new MPP.
Network Address (VoIP)	The IP address the telephony servers must use to communicate with the MPP.
Network Address (MRCP)	The IP address the speech proxy servers must use to communicate with the MPP when processing ASR and TTS requests.  Tip: This address is usually the same as the host IP address.
Network Address (AppSvr)	The IP address the application servers must use to communicate with the MPP.  Tip: This address is usually the same as the host IP address.
Maximum Simultaneous Calls	The maximum number of calls that this MPP can handle at any one time. It is equivalent to the maximum number of ports that Experience Portal will allocate to this MPP. Enter an integer in this field.  Note: For assistance in sizing your MPP server capacity and setting the correct value for the Maximum Simultaneous Calls parameter for each MPP server, contact your Avaya Services representative or Avaya Business Partner. For more information, see

Table continues...

Field	Description
	<i>Avaya Aura® Experience Portal Overview and Specification</i> on http://support.avaya.com .
Restart Automatically	The options are: • Yes: If the MPP stops unexpectedly, Experience Portal brings it back online automatically. • No: If the MPP stops, it must be manually restarted.  Note: This option also affects an MPP that has received an explicit Reboot or Halt command. For details about issuing a Halt command and changing the operational state of one or more MPPs, see <i>Administering Avaya Aura® Experience Portal</i> on http://support.avaya.com.
Listed Directory Number (LDN)	This field is only shown when you are logged into the EPM using the Avaya Services init account created when the Avaya Service accounts were configured. If you are logged into the EPM using the init account, enter the LDN number for this server as it appears in the Avaya Services database. If an LDN number is not specified for this server, Experience Portal uses the default value (000)000-0000.

MPP Certificate section

Field	Description
Certificate display box	The SSL certificate issued by the MPP. The displayed certificate must exactly match the certificate that was established when the MPP was first installed.
Trust new certificate	If this MPP has just been installed or upgraded, this check box is displayed in this section. If you see this check box, make sure the certificate is valid and then select the check box. You cannot save the MPP until the certificate is accepted.

Categories and Trace Levels section

Performance tracing is a valuable troubleshooting tool, but it can adversely impact Experience Portal system performance if you set all categories to **Finest** on a busy production system. If you need to troubleshoot a particular area, you must set specific categories to **Fine** and examine the resulting output to see if you can locate the issue. If not, set the level to **Finer** and repeat the process. If you still need more data, then set the level to **Finest** and keep a close watch on system resource usage.

 Note:

If these fields are not displayed, click the group heading to expand the group.

Field or Radio Button	Description
Trace level settings radio buttons	The options are: • Use MPP Settings: The MPP uses the default settings for all MPPs set on the MPP Settings page.

Table continues...

Field or Radio Button	Description
	• Custom: The MPP uses the trace level settings in the table in this section.  Note: If you want to set any of the trace levels, you must select the Custom radio button first.
Off	Sets trace logging for all categories to off.
Fine	Sets trace logging for all categories to fine.
Finer	Sets trace logging for all categories to finer.
Finest	Sets trace logging for all categories to finest.
ASR	The amount of trace logging done on the Automatic Speech Recognition (ASR) server. Select Off , Fine , Finer , or Finest .
CCXML Browser	The amount of trace logging done for Call Control eXtensible Markup Language (CCXML). Select Off , Fine , Finer , or Finest .
Event Manager	The amount of trace logging for the Event Manager. This component collects events from other MPP processes and sends them to the network log web service on the EPM. Select Off , Fine , Finer , or Finest .
Media Endpoint Manager	The amount of trace logging done for the Media End Point Manager. This trace component controls the logging for the media endpoint interface in the MediaManager process. The media endpoint interface controls the RTP (audio, video) flow through the MediaManager and to the external servers. Select Off , Fine , Finer , or Finest .
Media Manager	The amount of trace logging done for the Media Manager. This trace component controls the logging for the start and shutdown of the MediaManager process. Select Off , Fine , Finer , or Finest .
Media Video Manager	The amount of trace logging done for the Media Video Manager. This trace component controls the logging for the video interface in the MediaManager process. The video interface handles: • Downloading of any files (.txt, .jpg, .3pg and so on.) referenced in the Synchronized Multimedia Integration Language (SMIL) from the application server • Rendering video based on the video configuration from EPM and commands from SessionManager  Note: SMIL parsing is done in SessionManager and low level video commands are sent to this component.

Table continues...

Field or Radio Button	Description
	Select Off , Fine , Finer , or Finest .
MPP System Manager	The amount of trace logging done for the MPP System Manager. Select Off , Fine , Finer , or Finest .
MRCP	The amount of trace logging done on the speech proxy server. Select Off , Fine , Finer , or Finest .
Reporting	The amount of trace logging done for the Call Data Handler (CDH). Select Off , Fine , Finer , or Finest .
Session Manager	The amount of trace logging done for the MPP Session Manager. Select Off , Fine , Finer , or Finest .
SIP Messages Tracing	The amount of trace logging done for the SIP Messages. Select Off , Fine , Finer , or Finest . This component logs the Global Session ID (GSID) in the trace files when you set the tracing level to Finest .
Telephony	The amount of trace logging done on the telephony server. Select Off , Fine , Finer , or Finest .
Trace Logger	The amount of trace logging done for the Web Service Trace. The Trace Logger uploads the MPP traces requested by the trace client that runs on EPM. This trace component controls the logging for the activities of trace retrieval in the Trace Web Service. Select Off , Fine , Finer , or Finest .
TTS	The amount of trace logging done on the Text-to-Speech (TTS) server. Select Off , Fine , Finer , or Finest .
Voice Browser Client	The amount of trace logging done for the Avaya Voice Browser (AVB) client. This component connects the Voice eXtensible Markup Language (VoiceXML) interpreter to the MPP. Its logs: • Indicate the progress of VoiceXML execution and any exceptions or errors from VoiceXML documents • Contain the status and errors from platform initialization and interpreter initialization Select Off , Fine , Finer , or Finest .
Voice Browser INET	The amount of trace logging done for the AVB INET. This component manages: • Downloading content such as VoiceXML and prompts from the application server • Storing this content in the local VoiceXML interpreter cache Select Off , Fine , Finer , or Finest .

Table continues...

Field or Radio Button	Description
Voice Browser Interpreter	The amount of trace logging done for the AVB interpreter. This component parses and interprets the VoiceXML commands and controls the flow of the application based on Dual-tone multi-frequency (DTMF) or recognition results. Select Off, Fine, Finer, or Finest.
Voice Browser Java Script Interface	The amount of trace logging done for the AVB Javascript Interface. This component perform the ECMAScript execution from the VoiceXML documents. Its logs contain the status of script execution and any ECMAScript semantic errors. Select Off, Fine, Finer, or Finest.
Voice Browser Object	The amount of trace logging done for the AVB. This component is the interface to the platform module that performs VoiceXML element execution. Select Off, Fine, Finer, or Finest.
Voice Browser Platform	The amount of trace logging done for the AVB. This component handles messages from the MPP <code>vxxmlmgr</code> process, the wrapper for the VoiceXML interpreter. Select Off, Fine, Finer, or Finest.
Voice Browser Prompt	The amount of trace logging done for the AVB prompt. This component controls queuing, converting, and playing prompts. Select Off, Fine, Finer, or Finest.
Voice Browser Recognition	The amount of trace logging done for the AVB recognition function. This component controls queuing, loading, and unloading grammars. Select Off, Fine, Finer, or Finest.
Voice Browser Telephony	The amount of trace logging done for the AVB telephony interface. This component is the interface to the telephony system of the MPP. It handles features such as features as disconnect, blind transfer, and bridge transfer. In addition, its log also contains any channel initialization errors that the system encounters. Select Off, Fine, Finer, or Finest.

Related links

[Moving the MPP logs to a different location](#) on page 281

Restart Automatically <MPP Name> page field descriptions

Field	Description
Restart Automatically	Determines whether Experience Portal automatically restarts an MPP if it stops unexpectedly. If this check box is: • Selected, Experience Portal brings the MPP back online automatically • Not selected, you must manually restart the MPP if it stops  Note: This option also affects an MPP that has received an explicit Reboot or Halt command. For details about issuing a Halt command and changing the operational state of one or more MPPs, see <i>Administering Avaya Aura® Experience Portal</i> on http://support.avaya.com.

Change MPP Server page field descriptions

Use this page to change an existing Media Processing Platform (MPP).

This page contains the:

- [General section](#) on page 289
- [MPP Certificate section](#) on page 291
- [Categories and Trace Levels section](#) on page 291

General section

Field	Description
Zone	The name of the zone where the MPP server is configured. Select the name of the zone from the drop-down box.  Note: The Zone drop-down box appears only if you have created zones on your Experience Portal system. If you do not create any new zones, you do not see the drop-down box.
Name	The unique identifier for the MPP server on the Experience Portal system.  Note: This field cannot be changed.
Host Address	The network address, or location, of the computer on which the MPP server resides. The EPM uses this address to communicate with the MPP server.

Table continues...

Field	Description
	This address can be a fully qualified domain name or an IP address, but the address must be unique on this Experience Portal system and the machine must already have the MPP software installed on it. You cannot use any of the following hostnames: 127.0.0.1, localhost, or localhost.local.domain.  Note: This field cannot be changed.
Network Address (VoIP)	The IP address the telephony servers must use to communicate with the MPP. To use the IP address associated with the address in the Host Address field, enter <Default> in this field.
Network Address (MRCP)	The IP address the speech proxy servers must use to communicate with the MPP when processing ASR and TTS requests.  Tip: This address is usually the same as the host IP address. To use the IP address associated with the address in the Host Address field, enter <Default> in this field.
Network Address (AppSvr)	The IP address the application servers must use to communicate with the MPP.  Tip: This address is usually the same as the host IP address. To use the IP address associated with the address in the Host Address field, enter <Default> in this field.
Maximum Simultaneous Calls	The maximum number of calls that this MPP can handle at any one time. It is equivalent to the maximum number of ports that Experience Portal will allocate to this MPP. Enter an integer in this field.  Note: For assistance in sizing your MPP server capacity and setting the correct value for the Maximum Simultaneous Calls parameter for each MPP server, contact your Avaya Services representative or Avaya Business Partner. For more information, see <i>Avaya Aura® Experience Portal Overview and Specification</i> on http://support.avaya.com.
Restart Automatically	The options are: • Yes: If the MPP stops unexpectedly, Experience Portal brings it back online automatically. • No: If the MPP stops, it must be manually restarted.  Note: This option also affects an MPP that has received an explicit Reboot or Halt command. For details about issuing a Halt command and changing the operational

Table continues...

Field	Description
	state of one or more MPPs, see <i>Administering Avaya Aura® Experience Portal</i> on http://support.avaya.com .
Listed Directory Number (LDN)	This field is only shown when you are logged into the EPM using: - The Avaya Services init account created when the Avaya Service accounts were configured. In this case, you can enter a value in this field. - Any other EPM user account and an Avaya Services representative has previously set the LDN value. In this case, the field is read only. If you are logged into the EPM using the init account, enter the LDN number for this server as it appears in the Avaya Services database. If an LDN number is not specified for this server, Experience Portal uses the default value (000)000-0000.

MPP Certificate section

Field	Description
Certificate display box	The SSL certificate issued by the MPP. The displayed certificate must exactly match the certificate that was established when the MPP was first installed.  Note: The MPP certificate cannot be edited on this page.
Trust new certificate	If this MPP has just been installed or upgraded, this check box is displayed in this section. If you see this check box, make sure the certificate is valid and then select the check box. You cannot save the MPP until the certificate is accepted.

Categories and Trace Levels section

Performance tracing is a valuable troubleshooting tool, but it can adversely impact Experience Portal system performance if you set all categories to **Finest** on a busy production system. If you need to troubleshoot a particular area, you must set specific categories to **Fine** and examine the resulting output to see if you can locate the issue. If not, set the level to **Finer** and repeat the process. If you still need more data, then set the level to **Finest** and keep a close watch on system resource usage.

 Note:

If these fields are not displayed, click the group heading to expand the group.

Field or Radio Button	Description
Trace level settings radio buttons	The options are: Use MPP Settings: The MPP uses the default settings for all MPPs set on the MPP Settings page. Custom: The MPP uses the trace level settings in the table in this section.

Table continues...

Field or Radio Button	Description
	 Note: If you want to set any of the trace levels, you must select the Custom radio button first.
Off	Sets trace logging for all categories to off.
Fine	Sets trace logging for all categories to fine.
Finer	Sets trace logging for all categories to finer.
Finest	Sets trace logging for all categories to finest.
ASR	The amount of trace logging done on the Automatic Speech Recognition (ASR) server. Select Off , Fine , Finer , or Finest .
CCXML Browser	The amount of trace logging done for Call Control eXtensible Markup Language (CCXML). Select Off , Fine , Finer , or Finest .
Event Manager	The amount of trace logging for the Event Manager. This component collects events from other MPP processes and sends them to the network log web service on the EPM. Select Off , Fine , Finer , or Finest .
Media Endpoint Manager	The amount of trace logging done for the Media End Point Manager. This trace component controls the logging for the media endpoint interface in the MediaManager process. The media endpoint interface controls the RTP (audio, video) flow through the MediaManager and to the external servers. Select Off , Fine , Finer , or Finest .
Media Manager	The amount of trace logging done for the Media Manager. This trace component controls the logging for the start and shutdown of the MediaManager process. Select Off , Fine , Finer , or Finest .
Media Video Manager	The amount of trace logging done for the Media Video Manager. This trace component controls the logging for the video interface in the MediaManager process. The video interface handles: • Downloading of any files (.txt, .jpg, .3pg and so on.) referenced in the Synchronized Multimedia Integration Language (SMIL) from the application server • Rendering video based on the video configuration from EPM and commands from SessionManager  Note: SMIL parsing is done in SessionManager and low level video commands are sent to this component. Select Off, Fine, Finer, or Finest.

Table continues...

Field or Radio Button	Description
MPP System Manager	The amount of trace logging done for the MPP System Manager. Select Off , Fine , Finer , or Finest .
MRCP	The amount of trace logging done on the speech proxy server. Select Off , Fine , Finer , or Finest .
Reporting	The amount of trace logging done for the Call Data Handler (CDH). Select Off , Fine , Finer , or Finest .
Session Manager	The amount of trace logging done for the MPP Session Manager. Select Off , Fine , Finer , or Finest .
SIP Messages Tracing	The amount of trace logging done for the SIP Messages. Select Off , Fine , Finer , or Finest . This component logs the Global Session ID (GSID) in the trace files when you set the tracing level to Finest .
Telephony	The amount of trace logging done on the telephony server. Select Off , Fine , Finer , or Finest .
Trace Logger	The amount of trace logging done for the Web Service Trace. The Trace Logger uploads the MPP traces requested by the trace client that runs on EPM. This trace component controls the logging for the activities of trace retrieval in the Trace Web Service. Select Off , Fine , Finer , or Finest .
TTS	The amount of trace logging done on the Text-to-Speech (TTS) server. Select Off , Fine , Finer , or Finest .
Voice Browser Client	The amount of trace logging done for the Avaya Voice Browser (AVB) client. This component connects the Voice eXtensible Markup Language (VoiceXML) interpreter to the MPP. Its logs: • Indicate the progress of VoiceXML execution and any exceptions or errors from VoiceXML documents • Contain the status and errors from platform initialization and interpreter initialization Select Off , Fine , Finer , or Finest .
Voice Browser INET	The amount of trace logging done for the AVB INET. This component manages: • Downloading content such as VoiceXML and prompts from the application server • Storing this content in the local VoiceXML interpreter cache Select Off , Fine , Finer , or Finest .

Table continues...

Field or Radio Button	Description
Voice Browser Interpreter	The amount of trace logging done for the AVB interpreter. This component parses and interprets the VoiceXML commands and controls the flow of the application based on Dual-tone multi-frequency (DTMF) or recognition results. Select Off, Fine, Finer, or Finest.
Voice Browser Java Script Interface	The amount of trace logging done for the AVB Javascript Interface. This component perform the ECMAScript execution from the VoiceXML documents. Its logs contain the status of script execution and any ECMAScript semantic errors. Select Off, Fine, Finer, or Finest.
Voice Browser Object	The amount of trace logging done for the AVB. This component is the interface to the platform module that performs VoiceXML element execution. Select Off, Fine, Finer, or Finest.
Voice Browser Platform	The amount of trace logging done for the AVB. This component handles messages from the MPP <code>vxxmlmgr</code> process, the wrapper for the VoiceXML interpreter. Select Off, Fine, Finer, or Finest.
Voice Browser Prompt	The amount of trace logging done for the AVB prompt. This component controls queuing, converting, and playing prompts. Select Off, Fine, Finer, or Finest.
Voice Browser Recognition	The amount of trace logging done for the AVB recognition function. This component controls queuing, loading, and unloading grammars. Select Off, Fine, Finer, or Finest.
Voice Browser Telephony	The amount of trace logging done for the AVB telephony interface. This component is the interface to the telephony system of the MPP. It handles features such as features as disconnect, blind transfer, and bridge transfer. In addition, its log also contains any channel initialization errors that the system encounters. Select Off, Fine, Finer, or Finest.

<MPP name> Details page field descriptions

Use this page to view detailed information about the Media Processing Platform (MPP) <MPP Name>.

Note:

This page is called the <EPM Name>/<MPP Name> Details page if the EPM and MPP server are installed on the same machine.

General Information group

Field	Description
Zone	The name of the zone within which the MPP is configured.
Server Name	The unique name for this MPP.
Unique ID	The ID number used for this MPP in the database. Experience Portal selects this number from the range given in the MPP Numeric ID Range field on the MPP Settings page.
Host Address	The hostname of the MPP.
IP Address	The IP address of the MPP.
Version	The version number of the MPP software.
Last Successful Poll	The last date and time that the EPM polled the MPP successfully.

Operational State group

Field or Button	Description
Current State	The operational state of the Media Server. The options are: • Booting: The Media Server is in the process of restarting and is not yet ready to take new calls. • Degraded: The Media Server is running but it is not functioning at full capacity. • Error: The Media Server has encountered a severe problem and cannot recover. • Halted: The Media Server is no longer responding to heartbeats because it received a Halt command. • Halting: The Media Server is responding to heartbeats but is not taking new calls. • Need Configuration: An Email or SMS processor residing on the Media Server has not yet been configured. • Need Connections: No connections (SMPP or HTTP) have been configured or assigned to an Email/SMS processor residing on the Media Server. • Never Used: The Media Server has never successfully responded to a heartbeat request. • Not Installed: The Media Server is missing files required for heartbeat requests to occur. • Not Responding: The Media Server is not responding to heartbeat requests and it has not received a Restart or Halt command. • Partially Running: (EPM only) The Media Server is in the process of starting up, and not all individual components of the service, for example: Tomcat, SL, ActiveMQ, have come up yet. • Rebooting: The Media Server is responding to heartbeats but is not taking new calls.

Table continues...

Field or Button	Description
	• Recovering: The Media Server has encountered a problem and is attempting to recover. • Restart Needed: This state is most often reached when the Media Server has encountered a problem that it cannot recover from and it requires a manual restart. However, it can also appear for an MPP when the EPM software has been upgraded and the MPP software has not. In that case, the state should update automatically when you upgrade the MPP software. • Running: The Media Server is responding to heartbeat requests and is accepting new calls. • Starting: The Media Server is responding to heartbeats but not taking new calls because it is transitioning from the Stopped state to the Running state. • Stopped: The Media Server is responding to heartbeats but is not taking new calls. The Media Server enters this state while it initializes after it restarts or when a Stop command is received. • Stopping: The Media Server is responding to heartbeats but is not taking new calls. • Unknown: The Media Server is in the Offline mode.
Requested State	If the MPP is in the process of changing states, this field shows the state that the user requested and the time at which the request was made.

Operational Mode group

Field or Button	Description
Current Mode	The operational mode of the MPP. The options are: • Online: The Media Server is available. • Offline: The Media Server is unavailable and is not being polled by the EPM server. • Test: (MPP only) The Media Server is available to handle calls made to one of the defined H.323 maintenance stations.
Configure	Opens the Change MPP Server page so you can change the MPP configuration.

Configuration group

Field or Link	Description
History	Click this link to view the MPP configuration history.
Current State	The current configuration state.
Last Modified	The date and time when the MPP configuration was last changed.

Call Status group

Field	Description
Current Capacity	The number of calls that the system is ready to accept.

Table continues...

Field	Description
Licenses Allocated	The number of licenses allocated to the MPP.
Maximum Call Capacity	The maximum call capacity for the MPP.
Active Calls	The number of calls that are currently active on the MPP.
Calls Today	The number of calls handled by the MPP today.

Resource Status group

Field	Description
CPU	The percentage of CPU utilization for the MPP.
Memory	The percentage of memory utilization for the MPP.
Disk	The percentage of hard disk utilization for the MPP.

Miscellaneous group

This group contains a link to the Media Server Service Menu. To access this menu, click **Service Menu**.

MPP Manager page field descriptions

Use this page to change the operational state and mode of the MPPs running on your Experience Portal system.

The page contains the:

- [MPP server table](#) on page 297
- [State Commands group](#) on page 299
- [Restart/Reboot Options group](#) on page 300
- [Mode Commands group](#) on page 301

MPP server table

Field	Description
Selection checkbox	Indicates the MPPs whose operational state or mode you want to change. To select all MPPs, click the check box in the header row.
Zone	The name of the zone where the MPP is configured.
	To filter zones, click this icon located at the right side of the page. The system opens the Zone filter window for selecting one or more zones.

Table continues...

Field	Description
Zones filter icon	 Note: The Zones filter icon only appears when you create new zones. If you do not create any new zones, you do not see the icon
Server Name	The name of the MPP.
Mode	The MPP operational mode and the date and time that mode took effect. The options are: • Online: The MPP is available to handle normal call traffic. • Offline: The MPP is unavailable to handle any calls and is not being polled by the Experience Portal server. • Test: The MPP is available to handle calls made to one of the defined H.323 maintenance stations. • Upgrading: The MPP upgrade is in process and the MPP is temporarily unavailable.  Tip: To view the date and time that this mode was first reached, hover the mouse over this column.
State	The operational state of the MPP.  Tip: To view the date and time that this state was first reached, hover the mouse over this column.
Active Command	This column is displayed if one or more MPPs are currently in transition from their current state to a new user-requested state. For each transitional MPP, this column displays the requested, or final, state. For any other MPPs in the system, this field displays None .
Config	The MPP configuration state. The options are: • Need certificates: The Primary EPM certificate must be downloaded to the MPP by running the <code>setup_vpms.php</code> script on the MPP • Need ports: The MPP has been configured and is waiting for ports to be assigned • None: The MPP has never been configured • OK: The MPP is currently operating using the last downloaded configuration • Restart needed: The MPP must be restarted to enable the downloaded configuration • Reboot needed: The MPP must be rebooted to enable the downloaded configuration
Auto Restart	The options are: • Yes if the MPP will restart automatically if it fails • No if the MPP must be manually restarted if it fails

Table continues...

Field	Description
Restart Schedule	This field displays: • Today: Displays Yes at time if the MPP is administered to restart today. Displays No otherwise. To change this, click the pencil icon. • Recurring: Displays the recurring restart schedule, or None if there is no schedule defined. To change this, click the pencil icon.
Active Calls	This field displays: • In: The number of active incoming calls in the system • Out: The number of active outgoing calls in the system

State Commands group

 Note:

These buttons are greyed out until you select one or more MPPs using the Selection check box in the MPP server table.

 Important:

Ensure that the Operational Grace Period is long enough for the MPP to complete any existing calls before it stops, restarts, reboots, or halts. Calls are terminated when the Operational Grace Period is reached. For more information on the Operational Grace Period, see [Setting the global grace period and trace level parameters](#) on page 256.

Button	Description
Start	Starts the MPP. The operational state changes to Starting until the MPP is back online, after which the state changes to Running.  Important: When you start an MPP, the Experience Portal system experiences a brief disruption in service while it reallocates the licensed ports. To avoid the disruption, start MPPs during off-peak hours.
Stop	Stops the MPP. The operational state changes to Stopping until all active calls have disconnected or the grace period expires, whichever comes first. At that time, the state changes to Stopped. Experience Portal will only restart the MPP if: • You issue an explicit Start command • The MPP has a specified restart schedule  Note: For more information, see Setting the global grace period and trace level parameters on page 256.
Restart	Restarts the MPP software, but does not affect the server machine. The operational state changes to Stopping until all active calls have disconnected or the grace period expires, whichever comes first.

Table continues...

Button	Description
	After the MPP stops, it starts again automatically, and the operational state changes to Starting until the MPP is ready to take calls again. At that point, the state changes to Running.  Important: Before you click this button, make sure you select the appropriate option in the Restart/Reboot Options group.
Reboot	Reboots the MPP server machine. The operational state changes to Rebooting until all active calls have disconnected or the grace period expires, whichever comes first. At that time, the MPP server machine shuts down and automatically restarts. The state changes to Starting until the MPP is ready to take calls again. At that point, the state changes to Running.  Note: If the EPM resides on the same server as the MPP, it will be rebooted as well. In that case, you need to wait several minutes after the system has rebooted for Tomcat to restart and reinitialize its web applications before you can log back into the Experience Portal.  Important: Before you click this button, make sure you select the appropriate option in the Restart/Reboot Options group.
Halt	Halts the MPP and turns off the server machine on which the MPP is running. The operational state changes to Halting until all active calls have disconnected or the grace period expires, whichever comes first. After that, the state changes to Halted when the MPP server machine has powered down.  Important: If the EPM resides on the same server as the MPP, it will be halted as well. The MPP cannot be restarted until after the MPP server machine is restarted. Once the server machine has finished booting, the MPP software is automatically started and the MPP enters the Stopped state. At that point: • If the Auto Restart option is enabled, Experience Portal automatically starts the MPP. • You can manually restart the MPP using the Start button on this page.
Cancel	If you have issued a restart or reboot request and selected One server at a time in the Restart/Reboot Options group, you can cancel that request for any MPP servers that have not yet been restarted or rebooted. You cannot cancel a restart or reboot request that is already in process.

Restart/Reboot Options group

The options are:

- **One server at a time.** If you select this option, Experience Portal restarts or reboots one of the selected MPPs and waits until that MPP has completely restarted and been assigned its ports before it goes on to restart or reboot the next MPP on the list.
- **All selected servers at the same time.**

Mode Commands group

* Note:

These buttons are grayed out until you select one or more MPPs using the Selection check box in the MPP server table.

Button	Description
Offline	Sets the operational mode to Offline. No further polling is done.
Test	Sets the operational mode to Test. Once you start or restart the MPP, only calls made to one of the defined H.323 maintenance stations will be accepted. For details, see Using the Test operational mode on page 276.
Online	Sets the operational mode to Online. Once you start or restart the MPP, it will be ready to handle normal call traffic.

MPP Servers page field descriptions

Use this page to view, add, change, and delete the Media Processing Platform (MPP) servers currently administered on the Experience Portal system.

+ Tip:

To sort the servers by any column, click the up arrow (sort ascending) or down arrow (sort descending) in the column header.

Field	Description
Selection check box	Indicates which MPP servers you want to delete.
Zone	The name of the zone where the MPP servers are configured.
 Zones filter icon	To filter zones, click this icon located at the right side of the page. The system opens the Zone filter window for selecting one or more zones. * Note: The Zones filter icon only appears when you create new zones. If you do not create any new zones, you do not see the icon.
Name	The unique identifier for the MPP server on the Experience Portal system.
Host Address	The network address, or location, of the computer on which the MPP server resides. The EPM uses this address to communicate with the MPP server.
Network Address (VoIP)	The IP address the telephony servers must use to communicate with the MPP. The options are: • <Default>: The servers use the IP address specified in the Host Address field.

Table continues...

Field	Description
	• A specific IP address.
Network Address (MRCP)	The IP address the speech proxy servers must use to communicate with the MPP when processing ASR and TTS requests. The options are: • <Default>: The servers use the IP address specified in the Host Address field. • A specific IP address.
Network Address (AppSvr)	The IP address the application servers must use to communicate with the MPP. The options are: • <Default>: The servers use the IP address specified in the Host Address field. • A specific IP address.
Maximum Simultaneous Calls	The maximum number of calls that this MPP can handle at any one time. It is equivalent to the maximum number of ports that Experience Portal will allocate to this MPP.
Trace Level	The options are: • Use MPP Settings: The MPP uses the default trace settings specified on the MPP Settings page. • Custom: The MPP uses the trace settings specified for the specific MPP. To view these settings, click the server name in the Name column.
Add	Opens the Add MPP Server page so that you can add a new MPP server.
Delete	Deletes the selected MPP servers.
MPP Settings	Opens the MPP Settings page so you can change the global settings for all MPP servers.
Browser Settings	Opens the Browser Settings page so you can change the global Avaya Voice Browser settings for all MPP servers.
Video Settings	Opens the Video Settings page to configure system parameters that affect video.
VoIP Settings	Opens the VoIP Settings page so you can change the global Voice over IP settings for all MPP servers.

MPP Settings page field descriptions

Use this page to configure options that affect all MPPs on the Experience Portal system.

Resource Alerting Thresholds group

Field	Description
CPU	The low water threshold determines when the MPP generates an event warning you that CPU usage is getting high. The high water threshold determines when the MPP generates an alarm warning you that CPU usage is getting dangerously high. • High Water: Enter a whole number from 0 to 100. The default is 70. • Low Water: Enter a whole number from 0 to 100. The default is 60.
Memory	The low water threshold determines when the MPP generates an event warning you that RAM usage is getting high. The high water threshold determines when the MPP generates an alarm warning you that RAM usage is getting dangerously high. • High Water: Enter a whole number from 0 to 100. The default is 80. • Low Water: Enter a whole number from 0 to 100. The default is 70.
Disk	The low water threshold determines when the MPP generates an event warning you that disk usage is getting high. The high water threshold determines when the MPP generates an alarm warning you that disk usage is getting dangerously high. • High Water: Enter a whole number from 0 to 100. The default is 80. • Low Water: Enter a whole number from 0 to 100. The default is 60.

Trace Logger group

Field	Description
Log File Maximum Size	The maximum size, in megabytes, that the log file can be. Once the log file reaches this size, the system starts a new log file. If starting a new log file causes the number of logs to exceed the Number of Logs to Retain setting, the system deletes the oldest file before it starts the new file. Enter a whole number from 1 to 100. The default is 10.  Note: Due to the volume of trace messages from the following components, the number of log files retained by the system are set higher than the number you specify in this field. The actual size is as follows: • Endpoint Manager (\$AVAYA_MPP_HOME/logs/process/MediaMgr/EndPointMgr): 5x • Media Manager (\$AVAYA_MPP_HOME/logs/process/MediaMgr/MediaManager): 2x • Session Manager (\$AVAYA_MPP_HOME/logs/process/SessMgr/*): 2x
Number of Logs to Retain	The maximum number of log files the system can retain, including the current one. Once this number of log files exists, the system deletes the oldest log file before starting a new one. Enter a whole number from 1 to 5. The default is 2.

Table continues...

Field	Description
	 Note: Due to the volume of trace messages from the following components, the number of log files retained by the system are set higher than the number you specify in this field. The actual size is as follows: • Endpoint Manager (\$AVAYA_MPP_HOME/logs/process/MediaMgr/EndPointMgr): 5x • Media Manager (\$AVAYA_MPP_HOME/logs/process/MediaMgr/MediaManager): 2x • Session Manager (\$AVAYA_MPP_HOME/logs/process/SessMgr/*): 2x

Transcription group

Field	Description
Transcriptions Retention Period	How long an MPP keeps detailed session transcriptions for the sessions that it handles. Enter a whole number from 0 to 999. The default is 14.

Record Handling on MPP group

Field	Description
Session Data	Whether an MPP keeps detailed records about the sessions that it handles. Experience Portal uses this data to create the Session Detail report and Session Summary report. • Enable: Select this check box to record session data on all MPPs. • Retention Period: The number of days to retain the session data. Enter a whole number from 0 to 999. The default is 14.
Call Data	Whether an MPP keeps detailed records about the calls that it handles. Experience Portal uses this data to create the Contact Detail report and Contact Summary report. • Enable: Select this check box to record call data on all MPPs. • Retention Period: The number of days to retain the session data. Enter a whole number from 0 to 999. The default is 14.
VoiceXML/CCXML Log Tags	Whether an MPP keeps the CCXML and VoiceXML Log tag data from the application sessions transacted on that server. If desired, Experience Portal can download the Log tag data and display it in the Application Detail report and Application Summary report. • Enable: Select this check box to record application on all MPPs. • Retention Period: The number of days to retain the session data. Enter a whole number from 0 to 999. The default is 14.

Categories and Trace Levels section

Performance tracing is a valuable troubleshooting tool, but it can adversely impact Experience Portal system performance if you set all categories to **Finest** on a busy production system. If you need to troubleshoot a particular area, you must set specific categories to **Fine** and examine the

resulting output to see if you can locate the issue. If not, set the level to **Finer** and repeat the process. If you still need more data, then set the level to **Finest** and keep a close watch on system resource usage.

*** Note:**

If these fields are not displayed, click the group heading to expand the group.

Field or Radio Button	Description
Off	Sets trace logging for all categories to off.
Fine	Sets trace logging for all categories to fine.
Finer	Sets trace logging for all categories to finer.
Finest	Sets trace logging for all categories to finest.
ASR	The amount of trace logging done on the Automatic Speech Recognition (ASR) server. Select Off , Fine , Finer , or Finest .
CCXML Browser	The amount of trace logging done for Call Control eXtensible Markup Language (CCXML). Select Off , Fine , Finer , or Finest .
Event Manager	The amount of trace logging for the Event Manager. This component collects events from other MPP processes and sends them to the network log web service on the EPM. Select Off , Fine , Finer , or Finest .
Media Endpoint Manager	The amount of trace logging done for the Media End Point Manager. This trace component controls the logging for the media endpoint interface in the MediaManager process. The media endpoint interface controls the RTP (audio, video) flow through the MediaManager and to the external servers. Select Off , Fine , Finer , or Finest .
Media Manager	The amount of trace logging done for the Media Manager. This trace component controls the logging for the start and shutdown of the MediaManager process. Select Off , Fine , Finer , or Finest .
Media Video Manager	The amount of trace logging done for the Media Video Manager. This trace component controls the logging for the video interface in the MediaManager process. The video interface handles: • Downloading of any files (.txt, .jpg, .3pg and so on.) referenced in the Synchronized Multimedia Integration Language (SMIL) from the application server • Rendering video based on the video configuration from EPM and commands from SessionManager

Table continues...

Field or Radio Button	Description
	 Note: SMIL parsing is done in SessionManager and low level video commands are sent to this component. Select Off, Fine, Finer, or Finest.
MPP System Manager	The amount of trace logging done for the MPP System Manager. Select Off, Fine, Finer, or Finest.
MRCP	The amount of trace logging done on the speech proxy server. Select Off, Fine, Finer, or Finest.
Reporting	The amount of trace logging done for the Call Data Handler (CDH). Select Off, Fine, Finer, or Finest.
Session Manager	The amount of trace logging done for the MPP Session Manager. Select Off, Fine, Finer, or Finest.
SIP Messages Tracing	The amount of trace logging done for the SIP Messages. Select Off, Fine, Finer, or Finest. This component logs the Global Session ID (GSID) in the trace files when you set the tracing level to Finest.
Telephony	The amount of trace logging done on the telephony server. Select Off, Fine, Finer, or Finest.
Trace Logger	The amount of trace logging done for the Web Service Trace. The Trace Logger uploads the MPP traces requested by the trace client that runs on EPM. This trace component controls the logging for the activities of trace retrieval in the Trace Web Service. Select Off, Fine, Finer, or Finest.
TTS	The amount of trace logging done on the Text-to-Speech (TTS) server. Select Off, Fine, Finer, or Finest.
Voice Browser Client	The amount of trace logging done for the Avaya Voice Browser (AVB) client. This component connects the Voice eXtensible Markup Language (VoiceXML) interpreter to the MPP. Its logs: • Indicate the progress of VoiceXML execution and any exceptions or errors from VoiceXML documents • Contain the status and errors from platform initialization and interpreter initialization Select Off, Fine, Finer, or Finest.
Voice Browser INET	The amount of trace logging done for the AVB INET.

Table continues...

Field or Radio Button	Description
	This component manages: • Downloading content such as VoiceXML and prompts from the application server • Storing this content in the local VoiceXML interpreter cache Select Off, Fine, Finer, or Finest.
Voice Browser Interpreter	The amount of trace logging done for the AVB interpreter. This component parses and interprets the VoiceXML commands and controls the flow of the application based on Dual-tone multi-frequency (DTMF) or recognition results. Select Off, Fine, Finer, or Finest.
Voice Browser Java Script Interface	The amount of trace logging done for the AVB Javascript Interface. This component perform the ECMAScript execution from the VoiceXML documents. Its logs contain the status of script execution and any ECMAScript semantic errors. Select Off, Fine, Finer, or Finest.
Voice Browser Object	The amount of trace logging done for the AVB. This component is the interface to the platform module that performs VoiceXML element execution. Select Off, Fine, Finer, or Finest.
Voice Browser Platform	The amount of trace logging done for the AVB. This component handles messages from the MPP <code>vxmlmgr</code> process, the wrapper for the VoiceXML interpreter. Select Off, Fine, Finer, or Finest.
Voice Browser Prompt	The amount of trace logging done for the AVB prompt. This component controls queuing, converting, and playing prompts. Select Off, Fine, Finer, or Finest.
Voice Browser Recognition	The amount of trace logging done for the AVB recognition function. This component controls queuing, loading, and unloading grammars. Select Off, Fine, Finer, or Finest.
Voice Browser Telephony	The amount of trace logging done for the AVB telephony interface. This component is the interface to the telephony system of the MPP. It handles features such as features as disconnect, blind transfer, and bridge transfer. In addition, its log also contains any channel initialization errors that the system encounters. Select Off, Fine, Finer, or Finest.

Restart <MPP Name> Today page field descriptions

Use this page to schedule a one time restart for the MPP.

Field	Description
Restart Today	Indicates that you want the MPP to restart today. When the specified time is reached, the EPM restarts the MPP and clears this check box. The EPM only restarts the MPP again if a regular restart schedule is defined on the Restart Schedule for <MPP Name> page.
Time	After you select the Restart Today check box, enter the time at which you want the MPP to restart using a 24 hour clock. For example, to have the MPP restart at midnight, enter 00:00. To have it restart at 10:30 p.m., enter 22:30.

Restart Schedule for <MPP Name> page field descriptions

Use this page to set up a restart schedule if you want Experience Portal to periodically stop and then restart the MPP.

 Note:

The Restart MPP schedule option is available only on the **MPP Manager** page.

Field	Description
None	If you do not want to set up a schedule for restarting the MPP, select this button.
Daily at	If you want the MPP to restart each day, select this button and enter the time you want the MPP to restart using the 24 hour time format hh:mm. For example, to have the MPP restart at midnight, enter 00:00. To have it restart at 10:30 p.m., enter 22:30.
Weekly on	If you want the MPP to restart once a week, select this button, select a day of the week from the drop-down list, and enter the time you want the MPP to restart using the 24 hour time format hh:mm.
Monthly on	If you want the MPP to restart once a month, select this button, select a day of the month from the drop-down list, and enter the time you want the MPP to restart using the 24 hour time format hh:mm. If you select a day that does not occur in a given month, Experience Portal takes the number of days between the end of the month and the restart date and restarts the MPP that many days into the next month. For example, if you select 31 for this field and there are only 28 days in February, Experience Portal actually restarts the MPP three days after the end of the month, on the 3rd of March. It will restart the MPP again on the 31st of March. Similarly, April only has 30 days, so Experience Portal will restart the MPP on the 1st of May and again on the 31st of May.

<System name> Details tab on the System Monitor page field descriptions

Use this tab for a detailed view of the health and status of the EPM and each MPP in the Experience Portal system named in <System Name>. The information on this page refreshes automatically if you leave the browser window open.

*** Note:**

If the EPM server needs to be restarted, Experience Portal displays the message "EPM needs to be restarted." in red text just above the system status table.

Column	Description
 Zones filter icon	To filter zones, click this icon located at the right side of the page. The system opens the Zone filter window for selecting one or more zones. * Note: The Zones filter icon only appears when you create new zones. If you do not create any new zones, you do not see the icon.
Zone	The zone where the EPM and the MPP servers are configured.
Server Name	The options are: • The name of the EPM server. Click this name to view the <EPM Name> Details page. • The name of an MPP running on the system. Click this name to view the <MPP name> Details page. • <EPM Name>/<MPP Name>, if an MPP resides on the same server as the EPM. Click this name to view the <MPP name> Details page.
Type	The options are: • EPM: The Experience Portal Manager • MPP: A Media Processing Platform + Tip: To verify whether the associated server is a primary or auxiliary EPM server, hover the mouse over the EPM field.
Mode	The operational mode of the Media Server. The options are: • Online: The Media Server is available. • Offline: The Media Server is unavailable and is not being polled by the EPM server. • Test: (MPP only) The Media Server is available to handle calls made to one of the defined H.323 maintenance stations.

Table continues...

Column	Description
	 Tip: To view the date and time that this mode was first reached, hover the mouse over this column.
State	The operational state of the Media Server. The options are: • Booting: The Media Server is in the process of restarting and is not yet ready to take new calls. • Degraded: The Media Server is running but it is not functioning at full capacity. • Error: The Media Server has encountered a severe problem and cannot recover. • Halted: The Media Server is no longer responding to heartbeats because it received a <code>HaLt</code> command. • Halting: The Media Server is responding to heartbeats but is not taking new calls. • Need Configuration: An Email or SMS processor residing on the Media Server has not yet been configured. • Need Connections: No connections (SMPP or HTTP) have been configured or assigned to an Email/SMS processor residing on the Media Server. • Never Used: The Media Server has never successfully responded to a heartbeat request. • Not Installed: The Media Server is missing files required for heartbeat requests to occur. • Not Responding: The Media Server is not responding to heartbeat requests and it has not received a <code>Restart</code> or <code>HaLt</code> command. • Partially Running: (EPM only) The Media Server is in the process of starting up, and not all individual components of the service, for example: Tomcat, SL, ActiveMQ, have come up yet. • Rebooting: The Media Server is responding to heartbeats but is not taking new calls. • Recovering: The Media Server has encountered a problem and is attempting to recover. • Restart Needed: This state is most often reached when the Media Server has encountered a problem that it cannot recover from and it requires a manual restart. However, it can also appear for an MPP when the EPM software has been upgraded and the MPP software has not. In that case, the state should update automatically when you upgrade the MPP software. • Running: The Media Server is responding to heartbeat requests and is accepting new calls. • Starting: The Media Server is responding to heartbeats but not taking new calls because it is transitioning from the Stopped state to the Running state.

Table continues...

Column	Description
	• Stopped: The Media Server is responding to heartbeats but is not taking new calls. The Media Server enters this state while it initializes after it restarts or when a stop command is received. • Stopping: The Media Server is responding to heartbeats but is not taking new calls. • Unknown: The Media Server is in the Offline mode.  Tip: To view the date and time that this state was first reached, hover the mouse over this column.
Active Command	This column is displayed if one or more Media Servers are currently in transition from their current state to a new user-requested state. For each transitional Media Server, this column displays the requested, or final, state. For any other Media Servers in the system, this field displays None.
Config	The configuration state of the Auxiliary EPM/MPP. The options are: • Need certificates: The Primary EPM certificate must be downloaded to the Auxiliary EPM/MPP by running the <code>setup_vpms.php</code> script on the Auxiliary EPM/MPP. • Need ports: The MPP has been configured and is waiting for ports to be assigned. • None: The MPP has never been configured. • OK: The Auxiliary EPM/MPP is currently operating using the last downloaded configuration. • Restart needed: The MPP must be restarted to enable the downloaded configuration. • Reboot needed: The MPP must be rebooted to enable the downloaded configuration. • Upgrade needed: The Auxiliary EPM must be upgraded to the same version of the software as on the Primary EPM. • Unknown: The MPP is either not responding or is in the Offline mode.
Call Capacity	This field displays: • Current: The number of calls that can be currently handled by the system. • Licensed: The number of licenses allocated to this system. • Maximum: The maximum number of simultaneous calls that the MPPs in this system can handle. This value is obtained by adding together the maximum number of calls set for each of the MPPs in the system.  Note: This value can be larger than the number of licenses allocated to the system, but it should never be smaller. If it is smaller, then some of your licenses will never be used.

Table continues...

Column	Description
Active Calls	This field displays: • In: The number of active incoming calls in the system. • Out: The number of active outgoing calls in the system. Clicking the number displayed under the Active Calls In column displays all the active incoming calls for the media servers. Clicking the number displayed under the Active Calls Out column displays all the active outgoing calls for the media servers.
Calls Today	The number of calls handled during the current day.
Alarms	The alarm status indicators for the EPM, each MPP, and the overall Experience Portal system. The options are: • Green: There are no active major or critical alarms • Yellow: There are one or more active minor alarms • Red: There are one or more active major or critical alarms  Tip: You can click any red or yellow alarm indicator to view the Alarm report for that system.
Summary	The total number of calls based on Contact Summary and Active Calls. On the Summary line, clicking the number displayed under the Active Calls In column displays all the active incoming calls for the media servers. On the Summary line, clicking the number displayed under the Active Calls Out column displays all the active outgoing calls for the media servers.

Email, HTML and SMS processors section

Column	Description
Zone	The zone where the Email and SMS processors are configured. The summary reports within a zone are: • Email Summary: Summary of the incoming and outgoing email messages in the last 24 hours. • SMS Summary: Summary of the incoming and outgoing SMS messages in the last 24 hours. • HTML Summary: Summary of the incoming HTML messages in the last 24 hours.
Server Name	The name of the EPM on which the Email, SMS and HTML processors are configured.
Type	The options are: • Email processor • HTML processor

Table continues...

Column	Description
	• SMS processor
State	The operational state of the email/SMS/HTML processors. The options are: • Not Running: The server is either stopped or not started yet. • Starting: The server start request is initiated, and is in the process of initialization. • Running: The server is up and functional. • Stopping: The server shutdown is requested. • Need Configuration: The server does not find configuration. • Need Connections: The server has configuration but does not have any connections assigned or configured. • Degraded: The server has configuration and connections. However, some or all connections are not working. • Error: The server data returned has been deemed "stale" (no new data retrieved after a period of 3 minutes), or 2) unexpected return code retrieved from a poll to server. • Stopped: The server is stopped.
Usage (Today)	Displays the number of messages processed during the current day. The Summary row also shows the maximum number of messages allowed per day.
Messages (Last 24 hours)	The options are: • Incoming: The number of incoming messages processed in the last 24 hours. • Outgoing: The number of outgoing messages processed in the last 24 hours.  Note: Clicking on the Last 24 hours text, lets the user to change the number of messages displayed for the following time frames: • Last hour • Last 3 hours • Last 6 hours • Last 12 hours • Last 24 hours
Timeline Graph 	Displays a graph icon. Clicking this graph icon displays the number of messages processed in a graphical form.

Related links

[Viewing Avaya Aura Experience Portal system status](#) on page 425

Summary tab on the System Monitor page field descriptions

Use this tab for a consolidated view of the health and status of the Experience Portal system. The information on this page refreshes automatically if you leave the browser window open.

*** Note:**

If the EPM server needs to be restarted, Experience Portal displays the message "EPM needs to be restarted." in red text just above the system status table.

Column	Description
 Zones filter icon	To filter zones, click this icon located at the right side of the page. The system opens the Zone filter window for selecting one or more zones. * Note: The Zones filter icon only appears when you create new zones. If you do not create any new zones, you do not see the icon.
System Name	The name of the Experience Portal system, as specified in the Avaya Aura Experience Portal Name field on the EPM Settings page. If your installation consists of multiple Experience Portal systems that share a common external database, this column contains: - The name of the local system that you currently logged into. The Type for this system will always be EP. - The name of the another Experience Portal system in the shared external database. The Type will always be Remote EP. Click the system name to log into the EPM Web interface for the remote system.
Type	If your installation consists of a single Experience Portal system, the type will always be EP. If your installation consists of multiple Experience Portal systems that share a common external database, this column contains: EP: This type indicates that you are currently logged into the EPM for this system. Any system commands you issue will affect this EPM and any media servers assigned to this system. The <System name> Details tab for this system shows the assigned media servers. Remote EP: This type indicates that this is an active Experience Portal system, but it is <i>not</i> the system you are currently logged into. To affect the EPM or media servers assigned to a remote system, you must first log into that system by clicking the remote system name in the System Name column.
State	Displays the operational state of the Experience Portal system.

Table continues...

Column	Description
	The options are: • Active: This Experience Portal system is updating its information in the database on a regular basis. • Inactive: A remote Experience Portal system of Type is Remote EP is no longer updating information in the shared database. Click the system name to log into the EPM on that system and troubleshoot the problem locally. • Stale: It has been over an hour since this Experience Portal system has updated its summary information in the database. Create an Alarm report to view the error messages generated by the system.  Note: If you are using an external database, the time difference between your Experience Portal systems is too great. For more information, see the <i>Time Synchronization between external database and EPM servers</i> topic in the <i>Troubleshooting Avaya Aura® Experience Portal</i> guide.  Tip: To view the date and time that this state was first reached and on which it was last changed, hover the mouse over this column.
Call Capacity	This field displays: • Current: The number of calls that can be currently handled by the system. • Licensed: The number of licenses allocated to this system. • Maximum: The maximum number of simultaneous calls that the media servers in this system can handle. This value is obtained by adding together the maximum number of calls set for each of the media servers in the system. This value can be larger than the number of licenses allocated to the system, but it should never be smaller. If it is smaller, then some of your licenses will never be used.
Active Calls	When the number of active calls (In or Out) is greater than zero, the number displayed on the System Monitor is displayed as a link. Clicking on this link takes the user to the Active Calls web page.
Alarms	This field displays one of the following alarm status indicators: • Green: There are no active major or critical alarms • Yellow: There are one or more active minor alarms • Red: There are one or more active major or critical alarms For a system whose Type is EP, you can click any red or yellow alarm indicator to view an associated Alarm report. To view the alarms for a system whose Type is Remote EP, you must first log into the remote system by clicking the name in the System Name column.

Related links

[Viewing Avaya Aura Experience Portal system status](#) on page 425

<Media server Name> Configuration History page field descriptions

Use this page to view information about the history of configuration changes for the media server installed on the server.

Column	Description
Time	The date and time the media server configuration change occurred.
Command	A summary of the media server configuration change.
Configuration	Click the link to open or save an XML file with detailed information about media server configuration changes.

Chapter 13: Speech applications in Avaya Aura Experience Portal

Speech applications in Avaya Aura® Experience Portal

Speech applications are the “directors” of Avaya Aura® Experience Portal system operations. When a caller dials in to the system, the Media Processing Platform (MPP) accesses the appropriate speech application to control the call. From that point on, the speech application directs the flow of the call until the caller hangs up or the application is finished.

Experience Portal systems can have more than one application active and available at a time. The MPP that takes the call accesses the appropriate application based on the Dialed Number Identification Service (DNIS).

 Note:

An application does not have to have a DNIS assigned to it. In this case, such an application handles any call that comes in to the system by means of a DNIS that is not assigned to any other application on the system. However, you can only have one such application on the system. If you attempt to configure a second application without a DNIS, the system generates an error.

In addition, if the speech application requires Automatic Speech Recognition (ASR) or Text-to-Speech (TTS) resources, the MPP contacts the appropriate ASR or TTS server through an Media Resource Control Protocol (MRCP) proxy server.

Call flow example

This call flow example shows how the Experience Portal system interacts with other systems to handle an automated telephone transaction.

1. A caller from the Public Switched Telephone Network (PSTN) dials a telephone number.
2. The PSTN routes the call to the Private Branch Exchange (PBX) associated with that number.
3. Using Voice over IP (VoIP), the PBX breaks the voice data into packets and sends them over the LAN to a Media Processing Platform (MPP) server in the Experience Portal system.

4. The MPP server looks at the Dialed Number Identification Service (DNIS) for the incoming call and uses the configuration information downloaded from the EPM server to match the number to a speech application that has been added to Experience Portal.
5. The System Manager starts an Avaya Voice Browser session and passes it the Universal Resource Indicator (URI) specified for the selected speech application.
6. The Avaya Voice Browser contacts the application server and passes it the URI.
7. The application server returns a VoiceXML page to the Avaya Voice Browser.
8. Based on instructions on the VoiceXML page, the MPP uses prerecorded audio files, Text-to-Speech (TTS), or both to play a prompt to start interaction with the caller.
9. If the caller responds by:
 - Entering Dual-tone multi-frequency (DTMF) digits, the MPP establishes a connection to a TTS server and the ASCII text in the speech application is forwarded for processing. The TTS server renders the text as audio output in the form of synthesized speech which the MPP then plays for the caller.

*** Note:**

This connection requires one TTS license, which is released as soon as processing is complete.

- Speaking, the MPP establishes a connection to an Automatic Speech Recognition (ASR) server and sends the caller's recorded voice response to the ASR server for processing. The ASR server then returns the results to the application for further action.

*** Note:**

This connection requires one ASR license, which is *not* released until the entire call is complete.

10. If errors are encountered during the call, how these errors are handled depend on the type of grammar used by the application. If the application grammar is:
 - Dynamic, or In-line, the speech server gets the grammar directly from Experience Portal and any error messages are passed back to Experience Portal.
 - External or static, the speech server asks for the grammar using the URL specified in the application. If the URL points to an application server, the speech server interacts directly with that application server. Because Experience Portal is not involved in this communication, any error messages passed back by the application server may not be passed back to Experience Portal.
11. The application terminates the call when it finishes execution or when the caller hangs up.
12. When the call ends, the PSTN clears the call from the PBX and releases the ASR license if one was required.

Deploying a speech application

About this task

You must deploy a speech application to an application server connected to your Experience Portal system before you can add it to Experience Portal.

Procedure

1. Create the speech application.

For design guidelines, see [Design for user experience](#) on page 325.

2. Package the application for deployment.

For more information about packaging applications for deployment on Apache Tomcat or IBM WebSphere, see [Tomcat and WebSphere speech application deployment guidelines](#) on page 319.

3. Copy the speech application package file to the Application server from which the application will run.

Security alert:

Remember to exercise and observe appropriate security measures when transporting application package files to the application server.

4. If necessary, take steps to deploy the application on the application server.

Some application server environments require that you take additional steps to deploy the speech application after the application files have been copied to the application server. This might include installing any run-time support files that the application requires. For more information about support files required by your application server, see the documentation for your server.

Related links

[Tomcat and WebSphere speech application deployment guidelines](#) on page 319

Tomcat and WebSphere speech application deployment guidelines

You can deploy Orchestration Designer speech applications on a Tomcat or WebSphere application server. If you want to use a different application server, consult your server documentation for deployment requirements.

Apache Tomcat deployment guidelines

To deploy a speech application to an Apache Tomcat application server, you must package the application within a standard Web Archive (WAR) file. A WAR file is a compressed set of files, similar to a ZIP file. The WAR file format is specified by the J2EE specification and all J2EE-compliant application servers should support this format. The Tomcat servlet engine is optimized to

handle WAR files. For more information about WAR file requirements for speech applications on your Apache Tomcat system, see the documentation for your system.

When you transport the WAR files to your Apache Tomcat application server, copy them to the directory `TomcatHome\webapps\`, where `TomcatHome` is the directory in which your Apache Tomcat application server software is installed.

Then, when you next start Tomcat, Tomcat automatically installs and deploys the application.

! Important:

If you are redeploying an existing application, make sure the original application is not running before you deploy the new version on the server. If the original application is running, there could be conflicts with the log files.

IBM WebSphere deployment guidelines

In order to deploy a speech application on an IBM WebSphere or WebSphere Express application server, you must package the application within a standard Enterprise ARchive (EAR) file or Web ARchive (WAR) file with the JDK source level set to 15. These files are compressed sets of files, similar to a ZIP file. IBM WebSphere servlet engines can use either EAR or WAR file formats. For more information about EAR or WAR file requirements for speech applications on your IBM WebSphere system, see the documentation for your system.

When you transport the EAR or WAR files to your IBM WebSphere application server, make note of the directory to which you copy them. Then later, use the WebSphere Administrative Console to actually deploy the application from this location. For more information, see your IBM WebSphere documentation.

! Important:

If you are redeploying an existing application, make sure the original application is not running before you deploy the new version on the server. If the original application is running, there could be conflicts with the log files.

Related links

[Deploying a speech application](#) on page 319

Adding a speech application to Experience Portal

Before you begin

Make sure that the:

- Required speech servers are added to the Experience Portal system. For more information, see [Speech servers in Avaya Aura Experience Portal](#) on page 378.
- Speech application is deployed to the application server.

Procedure

1. Log on to the EPM Web interface using an account with the Administration user role.
2. From the EPM main menu, select **System Configuration > Applications**.

3. On the Applications page, click **Add**.
4. On the Add Application page, enter the appropriate information and click **Save**.

Changing speech application settings through Avaya Aura® Experience Portal

Procedure

1. Log on to the EPM Web interface using an account with the Administration user role.
2. From the EPM main menu, select **System Configuration > Applications**.
3. On the Applications page, click the application name in the **Name** column.
4. On the Change Application page, enter the appropriate information and click **Save**.

Viewing speech applications added to the Experience Portal system

Procedure

1. Log on to the EPM Web interface using an account with the Administration, Operations, or Maintenance user role.
2. From the EPM main menu, select **System Configuration > Applications**.

The EPM displays the Applications page, which lists all of the speech applications added to Experience Portal. The options displayed on this page depend on your user role.

Deleting speech applications from Avaya Aura® Experience Portal

Procedure

1. Log on to the EPM Web interface using an account with the Administration user role.
2. From the EPM main menu, select **System Configuration > Applications**.
3. On the Applications page, for each application that you want to delete, select the check box to the left of the application name in the applications table.

+ Tip:

To delete all applications, click the Selection check box in the header row of the table, which automatically selects all rows in the applications table.

4. Click **Delete**.
5. If desired, remove the application from the Application server as well.

Speech application priority

Because you can specify wildcards in the **Called URI** field for an application, you could end up with a situation in which an incoming call could match more than one application. In this case, Experience Portal uses the first application listed on the Applications page to handle an incoming call from that URI. If you want Experience Portal to use a different application for given URI, you must change that application's priority by changing its position in the list.

For example, if you have the following:

Application name	Specified Called URI value
all_555	\+1-212-555-xxxx
1212_specific	\+1-212-555-1212

When you get a call from 1-212-555-1212, that call matches both applications because of the wildcards specified in `all_555`. If `all_555` is above `1212_specific` in priority, then Experience Portal will always run `all_555` and never run `1212_specific`.

Related links

[Changing speech application priority](#) on page 322

Changing speech application priority

Procedure

1. Log on to the EPM Web interface using an account with the Administration user role.
2. From the EPM main menu, select **System Configuration > Applications**.
3. On the Applications page, click the **Change Launch Order** link above the right-most column of the table.
4. In the Application Launch Order window, click the name of the application whose priority you want to change, then click:
 - The up arrow to the right of the list box to move the application up in priority.
 - The down arrow to the right of the list box to move the application down in priority.
5. Click **Save**.

Related links

[Speech application priority](#) on page 322

Specifying the default application for inbound calls

You can specify a default application for Experience Portal to use when the system receives a call from a telephone number that is not associated with any other application.

Procedure

1. Log on to the EPM Web interface using an account with the Administration user role.
2. From the EPM main menu, select **System Configuration > Applications**.
3. On the Applications page, if you want to:
 - Add a new application and designate it as the default, click **Add** and enter the appropriate information in all sections of the Add Application page *except* the **Application Launch** group.
 - Designate an existing application as the default, click the application name in the **Name** column. The EPM displays the Change Application page.
4. On the Add Application or Change Application page, go to the **Application Launch** group.
5. Select the **Inbound Default** radio button in the **Type** field.
6. Click **Save** at the bottom of the page.

Accessing VoiceXML and CCXML Log tag data through Experience Portal

If you include VoiceXML or CCXML Log tags in an application and you want to view that information in the Experience Portal application reports, you need to make sure that the data is being collected on the MPP and downloaded to the Experience Portal database.

Procedure

1. Log on to the EPM Web interface using an account with the Administration user role.
2. To specify that the MPP servers should collect and store Log tag data:
 - a. From the EPM main menu, select **System Configuration > MPP Servers**.
 - b. On the MPP Servers page, click **MPP Settings**.
 - c. On the MPP Settings page, make sure that the **Enable** check box is checked for the **VoiceXML/CCXML Log Tags** option in the **Record Handling on MPP** group.
 - d. Click **Apply**.

3. To download the Log tag data to the Experience Portal database:
 - a. From the EPM main menu, select **System Configuration > EPM Servers > Report Data**.
 - b. On the Report Data Configuration page, make sure that the following fields are set to **Yes**:
 - **Download VoiceXML Log Tags**
 - **Download CCXML Log Tags**
 - c. Click **Apply**.
4. To view the Log tag data available in the Experience Portal database:
 - a. Log on to the EPM Web interface using an account with the Administration, Operations, or Maintenance user role.
 - b. From the EPM main menu, select **Reports > Standard** or **Reports > Application Detail**.
 - c. Click **more >>** to expand the **Optional Filters** group.
 - d. In the **Activity Type** field, make sure that the check boxes for **VoiceXML Log Tag** and **CCXML Log Tag** are selected.
 - e. Click **OK**.

Viewing application transcription data

Procedure

1. Log on to the EPM Web interface using an account with the Administration, Operations, or Maintenance user role.
2. From the EPM main menu, select **Reports > Standard > Session Detail**.
3. On the Session Detail page, the **more >>** link to display the rest of the optional filters.
4. Enter the criteria you want to use for the report.

 Tip:

If you want to limit the report to those sessions that have transcription information, select **Yes** in the **Session Transcription** field.

5. When you are finished, click **OK**.

The EPM displays the Session Detail Report page.

6. Locate the particular session for which you want to view the transcription data and click the **View Session Details** icon at the end of the appropriate row.

Experience Portal displays the Session Details page, which shows both the session and transcription data grouped by information category.

Speech application design guidelines

Best practices for speech application design

Sound files

High quality stereo sound files may appear to be the perfect way to communicate with your customers, but you must remember that these files will be played over a telephone line which has only 8 KHz bandwidth. Most of the higher frequencies are lost when a recording is played over the telephone.

When you record sound files:

- Record monaural rather than stereo.
- Record at and even multiple of 8 KHz. For example, you could record at 8 KHz, 16 KHz, or 24 KHz,.
- Use 16 bit-depth A-to-D conversion.
- Use a quality audio editing program to normalize the amplitude of your various phrases and convert to mu-LAW or A-LAW PCM.

When you have finished recording, listen to each recording in its final format. If you use the above guidelines, the way they sound at this point will be very close to how they sound over the telephone.

Design for user experience

The best first step in planning an application is to envision exactly what you want the caller to experience when calling in to your system. Do not consider how to set up the application. Simply ask and try to answer as many questions as you can.

For example, ask and try to answer the following questions:

- What options do you want to offer callers?
- Do you want to offer callers the opportunity to interact in more than one language?
- What means do you want to offer callers to respond to options? By voice? By using touchtone keys on the telephone? By recording their answers or other short messages?
- What voice gender do you want to use in presenting your prompts?
- Do you need to use Text-to-Speech (TTS) technology to provide the caller a way to hear text-based information?
- What about hearing- or speech-impaired callers? How do you want to provide for their special needs?

Again, the idea is to ask as many questions as you possibly can. Create sample scenarios for the various situations you think callers might require help with. Try to be as comprehensive as possible.

Design for potential problems

One of the most important steps in planning a good speech application is to plan for any potential problem and error condition you can think of and to include error handlers that can deal with these issues. For example, how should the system respond when one of these problem situations arises?

- Technical or hardware limitations. What if the caller does not have a touchtone telephone? How does your system respond to TTY or TDD requests?
- Accessibility for callers with physical limitations. Have you allowed for the extra time it can take for callers with physical handicaps or other limitations?
- Language limitations. Is it likely that a caller will need to interact using a different language than the primary language? Do you have the necessary Automatic Speech Recognition (ASR) and Text-to-Speech (TTS) servers and software to accommodate them?
- Personal preferences. Have you allowed for the personal preferences of your callers? Some people would rather interact with the system verbally, while others can prefer to use touchtone, or Dual-tone multi-frequency (DTMF) , responses. Other people prefer to interact with a live attendant no matter how good your Interactive Voice Response (IVR) speech application is. How easy is it for such users to get to a live attendant?

If an application encounters an error that is not handled by its own error handlers, or if an application cannot be started due to problems with the application server or the speech servers, Experience Portal uses the error handlers installed on the MPP server. In addition to designing the speech applications, you should also design the error handlers that Experience Portal uses in these cases.

For example, you want your default event handler to:

1. Play a prompt explaining that there was a problem and that the customer is being redirected to an agent immediately.
2. Transfer the call to a special number reserved for such issues.

A call coming in on this special number alerts the agent that the caller has encountered an error in Experience Portal, and that the agent should find out what the customer was doing when the error occurred. The call center can then track these exceptions and fix areas that encounter frequent problems.

For more information, see [Experience Portal event handlers](#) on page 326.

Related links

[Experience Portal event handlers](#) on page 326

Experience Portal event handlers

When a CCXML speech application tries to access an HTML page that cannot be found or a VoiceXML application encounters an unexpected event, the application responds with an exception error message. A well-designed speech application includes exception handlers that deal with these messages and help the application recover so that it can continue processing the call.

Experience Portal uses the error handlers defined in the application whenever possible. However, if an exception error message occurs that is not handled by the application, or if there is a problem running the application due to issues with the application server or the speech servers, Experience Portal uses one of the event handlers installed on the MPP server.

The event handler Experience Portal uses depends on the state of the speech application. If an application:

- Was successfully started and there is a call in progress, Experience Portal uses the event handler associated with that application when it was added to the Experience Portal system.
- Could not be started, Experience Portal looks at the type of application that was requested and uses the appropriate default CCXML or VoiceXML event handler.

When you install the software, Experience Portal automatically installs default event handlers for CCXML and VoiceXML, as well as an event handler prompt that is played by the default event handlers.

If you want to customize the way Experience Portal reacts to a problem, you can add your own event handlers and prompts and then designate which ones Experience Portal should use as the default.

For example, you want your default event handler to:

1. Play a prompt explaining that there was a problem and that the customer is being redirected to an agent immediately.
2. Transfer the call to a special number reserved for such issues.

A call coming in on this special number alerts the agent that the caller has encountered an error in Experience Portal, and that the agent should find out what the customer was doing when the error occurred. The call center can then track these exceptions and fix areas that encounter frequent problems.

Related links

[Design for potential problems](#) on page 326

Design for application flow

You have envisioned the experience you want your callers to have. You have tried to foresee and plan for any problem contingency that might arise. Now you are ready to start actually mapping the flow of your speech application. A number of methods can serve you well in this effort, but here are a couple of the more common approaches:

- Describe the flow verbally. Talk through each of your scenarios verbally. Make sure you take note of where the prompts occur and what you want callers to say or do. Record these verbal "walkthroughs".
- Use a flow diagram. As you work through your scenarios, you can create a flow diagram to show the major points in the call flow. Use this diagram to show such things as:
 - Where you want to offer options to callers
 - Where you want them to listen to the entire prompt and where they can interrupt, or "barge in", and cut the prompt off
 - Where you require a response from callers and what the valid responses will be
 - Where you want or need to access databases to retrieve or record customer data
 - How and where you want to access a Web service to respond to a customer request

Again, the idea is to be as complete and comprehensive as possible. Try and foresee every eventuality, and map how the system will respond.

Design for modularity

When you are planning your speech application, be alert to places where you can reuse parts of the application in two or more places. Then, when designing and building the application, you can create these parts as modules that you can reuse wherever you need that functionality.

If you plan for these modules ahead of time, you can also develop them before developing your main application project file. That way, they are already available when you create your main application.

For example, you might want to collect bank account or credit card numbers from callers at several points in the call flow. You have figured out that it is the same basic process each time you need to collect such numbers. Therefore, you might want to create a speech project module that you can reuse in your master application whenever you need to collect this type of information from callers.

Using this modular approach to application design has several advantages:

- You can "develop once, use many times." This can be a tremendous advantage, especially if you have certain actions or options you want to offer in several places to your callers.
- It is easier to maintain the overall application, even if you are not reusing much of the code. When you use a modular approach, you can change one part of the application without necessarily having to rebuild the entire application.
- It can make it easier to debug your applications, by making it possible to isolate the trouble spots where errors are occurring.

A team of developers can work on separate pieces of an application separately and then merge their efforts.

Design for application resources

As a final step in planning your speech application, you must attempt to identify and list all the application resources you will need to develop the application. Application resources include components such as Automatic Speech Recognition (ASR) and Text-to-Speech (TTS) servers, prerecorded phrases that the system plays back as prompts, and so on.

If you have planned the flow completely, keeping in mind all the resources you will need, you can list those application resources before you actually start to develop the application. Then you can create or import those resources before creating the call flow.

In the case of phrases, for example, if you know exactly what phrases you want to use, and if you plan to have those phrases recorded by a professional talent, you can list all the phrases and have them recorded as WAV files before you start to develop the actual application. Then, when you get to the points in the application where you need the phrases, you can import the prerecorded files.

CCXML and VoiceXML considerations

Keeping CCXML application sessions active until the MPP grace period expires

About this task

When you stop, restart, or halt an MPP, any CCXML application currently running on that MPP is sent a `ccxml.kill` event. This event notifies the application that the MPP is shutting down when the grace period expires.

If you do not define an error handler for this event in your CCXML application, the application exits immediately, even if it still processing a call.

Procedure

To keep the CCXML application active until the grace period has expired or until the application encounters an `</exit>` tag, add the following event handler to your CCXML application:

```
<transition event="ccxml.kill">
<!-- Do nothing. Platform will kill session
after grace period-->
</transition>
```

Restrictions for dialogs attached to CCXML conference calls

Dialogs attached to conference calls may only play audio or text-to-speech prompts. If an attached dialog attempts to perform speech recognition processing, each attempt will result in a `no resource error`.

If you need speech recognition capabilities, you must attach the dialog to one of the calls that is part of the conference. In this case, however, the dialog can only process the speech that comes from the call to which it is attached.

Speech recognition results and VoiceXML applications

VoiceXML provides shadow variables accessible within a page to access recognition results such as `application.lastresult$`. While this includes a mechanism for presenting multiple possible semantic matches (n-best results whose presence can be determined by inspecting `application.lastresult$.length`), unfortunately the specification does not describe how to present a result that contains multiple interpretations for a given semantic match.

Avaya Aura® Experience Portal addresses the issue of a result containing multiple interpretations for a given semantic match by exposing the shadow variable `application.lastresult$.interpretation$`. To test for the presence of multiple interpretations in a result, examine `application.lastresult$.interpretation$.length`.

If the VoiceXML page containing that grammar uses the `maxnbest` property of 2, then the recognition results arising from a caller saying “star gazer” would be accessed as follows in the VoiceXML specification:

```
application.lastResult$.length      2
application.lastResult$[0].confidence 0.83
application.lastResult$[0].utterance  Stargazer
application.lastResult$[0].interpretation eyes
application.lastResult$[1].confidence 0.12
application.lastResult$[1].utterance  starchaser
application.lastResult$[1].interpretation legs
```

Even though the recognition results contain the additional interpretations “look” and “run”, the VoiceXML specification makes no provisions for making those additional interpretations available to the application. To accomplish this, Avaya Aura® Experience Portal extends this list of shadow variables as:

```
application.lastResult$[0].interpretation$.length 2
application.lastResult$[0].interpretation$[0]     eyes
application.lastResult$[0].interpretation$[1]     look
application.lastResult$[1].interpretation$.length 2
application.lastResult$[1].interpretation$[0]     legs
application.lastResult$[1].interpretation$[1]     run
```

Privacy feature support for VoiceXML applications

In VoiceXML applications, you can declare a form or field to be private using the following property statement:

```
<property name="private" value="true"/>
```

While a private form or field is executing, Experience Portal does not write any speech recognition results, DTMF results, or TTS strings into the session transcription logs or into any alarms that may be generated during execution. Once the private form or field has finished executing, Experience Portal resumes logging these items as normal.

* Note:

If tracing is turned on for the MPP, Experience Portal ignores the privacy property and writes the requested debugging information into the MPP trace logs.

DTMF digits sending by a VoiceXML application

A new feature that was introduced in Experience Portal 7.0 is the ability of VoiceXML applications running on an MPP to request that the system send DTMF digits. This feature is most commonly used when an application running on Experience Portal communicates with an automated system and not with a human being. Previously, the only way for Experience Portal applications to send DTMF digits was to play an audio file that contained a recording of the digits to be sent.

Example

The following is a sample VoiceXML application that demonstrates how to send the digits 1 2 3 4:

```
<?xml version="1.0" encoding="UTF-8"?>
<vxml version="2.1"
```

```

xmlns="http://www.w3.org/2001/vxml"
xmlns:xsi="http://www.w3.org/2001/XMLSchema-instance"
xsi:schemaLocation="http://www.w3.org/2001/vxml
http://www.w3.org/TR/2007/REC-voicexml21-20070619/vxml.xsd">
<form>
  <field>
    <prompt>
      <audio src="builtin://senddigit/1234"/>
    </prompt>
  </field>
</form>
</vxml>

```

CCXML elements and attributes

Elements	Attributes	Supporting information on Limitations and Extensions
<accept>	• connectionid • hints	For each specific instance of the hints attribute, go to http://dd-linux.sv.avaya.com:8080/SageWiki/Wiki.jsp?page=CCXMLHints .
<assign>	• name • expr	If the CCXML compliance flag is set to true , the session variables like session* is checked for read only .
<cancel>	sendid	
<ccxml>	• version • xml:base • xsi:schemaLocation	For more information on the xsi:schemaLocation attribute, visit the following websites: • http://www.w3.org/2002/09/ccxml. • http://www.w3.org/TR/ccxml/ccxml.xsd.
<createcall>	• dest • connectionid • aai • callerid • hints • timeout • joinid • joindirection	For each specific instance of the hints attribute, go to http://dd-linux.sv.avaya.com:8080/SageWiki/Wiki.jsp?page=CCXMLHints .
<createccxml>	• next	

Table continues...

Elements	Attributes	Supporting information on Limitations and Extensions
	• namelist • fetchparam • parameters • method • sessionid • timeout • maxage • maxstale • enctype	
<createconference>	• conferenceid • confname • reservedtalkers • reservedlisteners • hints	
<destroyconference>	• conferenceid • hints	
<dialogprepare>	• src • type • namelist • parameters • dialogid • connectionid • conferenceid • mediadirection • maxage • maxstale • enctype • method • hints	For each specific instance of the hints attribute, go to http://dd-linux.sv.avaya.com:8080/SageWiki/Wiki.jsp?page=CCXMLHints .
<dialogstart>	• src • preparedialogid • type • namelist	• If the compliance flag is set to true, the flag checks if maxage is used with preparedialogid. In

Table continues...

Elements	Attributes	Supporting information on Limitations and Extensions
	- parameters - dialogid - connectionid - conferenceid - mediadirection - maxage - maxstale - enctype - method - hints	such a case, an error event is generated. - If the compliance flag is set to true, the flag checks if maxstale is used with preparedialogid. In such a case, an error event is generated. - If the compliance flag is set to true, the flag checks if enctype is used with preparedialogid. In such a case, an error event is generated. - If the compliance flag is set to true, the flag checks if method is used with preparedialogid. In such a case, an error event is generated. For each specific instance of the hints attribute, go to http://dd-linux.sv.avaya.com:8080/SageWiki/Wiki.jsp?page=CCXMLHints.
<dialogterminate>	- dialogid - immediate - hints	EP does not support the hints attribute.
<disconnect>	- connectionid - reason - hints	
<else>		
<elseif>	cond	
<eventprocessor>	statevariables	
<exit>	- expr - namelist	For EPM reporting, the following namelists are used: - avayaExitReason - avayaExitInfo1 - avayaExitInfo2 - avayaExitInfo5 - avayaExitInfo6

Table continues...

Elements	Attributes	Supporting information on Limitations and Extensions
		• avayaExitInfo7 • avayaExitInfo8 • avayaExitInfo9 • avayaExitPreferredPath • avayaExitCustomerId • avayaExitTopic
<fetch>	• next • type • namelist • method • fetchid • timeout • maxage • maxstale • timeout • mode	
<goto>	fetchid	
<if>	cond	
<join>	• id1 • id2 • duplex • hints • entertone • exittone • autoinputgain • autooutputgain • dtmfclamp • toneclamp	The hints attribute is not used in EP.
<log>	• label • expr	
<merge>	• connectionid1 • connectionid2	<Merge> is only supported by SIP, not by H.323.

Table continues...

Elements	Attributes	Supporting information on Limitations and Extensions
	hints	
<meta>	- name - http-equiv - content	
<metadata>		
<move>	- source - event - sessionid	
<redirect>	- connectionid - dest - reason - hints	For each specific instance of the hints attribute, go to http://dd-linux.sv.avaya.com:8080/SageWiki/Wiki.jsp?page=CCXMLHints .
<reject>	- connectionid - reason - hints	For each specific instance of the hints attribute, go to http://dd-linux.sv.avaya.com:8080/SageWiki/Wiki.jsp?page=CCXMLHints .
<script>	- src - fetchid - timeout - maxage - maxstale - charset	- If the compliance flag is set to true, the src string should not include a single quote. In all other cases, the single quote is required. The following is an example of a noncompliant src string: <pre><script src="'http://<IP Address>:8080/ FetchTestCCXML/jsp/ updateaccount.js'"/></pre> The following is an example of a compliant src string: <pre>script src="'http://<IP Address>:8080/ FetchTestCCXML/jsp/ updateaccount.js'"/></pre> - If the compliance flag is set to true, the charset string should not include a single quote. In all

Table continues...

Elements	Attributes	Supporting information on Limitations and Extensions
		other cases, the single quote is required. The following is an example of a noncompliant charset string: <pre><script src="script_utf_8.es"cha rset="'UTF-8'"/></pre> The following is an example of a compliant charset string: <pre><script src="script_utf_8.es"cha rset="'UTF-8'"/></pre>
<send>	- target - targettype * Note: The extra Avaya types are: - avaya_platform - avaya_plaform.web_service - SIPEndpoint - sendid - delay - name * Note: If name is avaya.launchresponse, then status and failed_status can be used. The values for status and failed_status are: - success - no resource - busy - no answer - invalid telephony uri - network refuse - invalid application uri	For each specific instance of the hints attribute, go to http://dd-linux.sv.avaya.com:8080/SageWiki/Wiki.jsp?page=CCXMLHints.

Table continues...

Elements	Attributes	Supporting information on Limitations and Extensions
	- application server failure - fax detected - network failed before connect - near end disconnect before connect - far end disconnect before connect - transferred before connect - unknown failure before connect - call disconnected before application started • namelist • hints	
<transition>	• state • event • cond	
<unjoin>	• id1 • id2 • hints	
<var>	• name • expr	

VoiceXML elements and attributes

Tag	Attributes	Available in VoiceXML 2	Available in VoiceXML 2.1	Limitation or Extensions, Supporting information
<assign>	• name • expr	Yes	Yes	Supports all attributes.

Table continues...

Tag	Attributes	Available in VoiceXML 2	Available in VoiceXML 2.1	Limitation or Extensions, Supporting information
<audio>	• src • fetchtimeout • fetchhint • maxage • maxstale • expr	Yes	Yes	Supports all other attributes except fetchhint .
<block>	• name • expr • cond	Yes	Yes	Supports all attributes.
<catch>	• event • count • cond	Yes	Yes	Supports all attributes.
<choice>	• dtmf • accept • next • expr • event • eventexpr • message • messageexpr • fetchaudio • fetchhint • fetchtimeout • maxage • maxstale	Yes	Yes	Supports all attributes except message , messageexpr , and fetchhint .
<clear>	• namelist	Yes	Yes	Supports the namelist attribute.
<initial>	• name • expr • cond	Yes	Yes	Supports all attributes.

Table continues...

Tag	Attributes	Available in VoiceXML 2	Available in VoiceXML 2.1	Limitation or Extensions, Supporting information
<disconnect>	• namelist	No	Yes	Supports the namelist attribute.
<else>	• name • expr • cond	Yes	Yes	Supports all attributes.
<error>	count cond	Yes	Yes	Supports all attributes.
<exit>	expr namelist	Yes	Yes	Supports all attributes.
<field>	• name • expr • cond • type • slot • modal	Yes	Yes	Supports all attributes.
<filled>	• mode • namelist	Yes	Yes	Supports all attributes.
<form>	• id • scope	Yes	Yes	Supports all attributes.
<goto>	• next • expr • nextitem • expritem • fetchaudio • fetchhint • fetchtimeout • maxage • maxstale	Yes	Yes	Supports all attributes.
<grammar>	• version • xml:lang • mode • root	Yes	Yes	Supports all attributes except fetchhint .

Table continues...

Tag	Attributes	Available in VoiceXML 2	Available in VoiceXML 2.1	Limitation or Extensions, Supporting information
	- tag-format - xml:base - src - scope - type - weight - fetchhint - fetchtimeout - maxage - maxstale - srcexpr			
<help>	- count - cond	Yes	Yes	Supports all attributes.
<if> (optional <else> and <elseif> elements)		Yes	Yes	Supports the if element.
<link>	- next - expr - eventexpr - message - messageexpr - dtmf - fetchaudio - fetchhint - fetchtimeout - maxage - maxstale	Yes	Yes	Supports all attributes except fetchhint .
<log>	- label - expr	Yes	Yes	Supports all attributes.
<mark> (an SSML element)	- name - nameexpr - markname	- name — Yes - nameexpr — No - markname — No	Yes	Supports name and nameexpr only.

Table continues...

Tag	Attributes	Available in VoiceXML 2	Available in VoiceXML 2.1	Limitation or Extensions, Supporting information
	marktime	marktime — No		 Note: In VoiceXML 2.0, the ,<mark> element was ignored by VoiceXML platforms.
<menu>	- id - scope - dtmf - accept	Yes	Yes	Supports all attributes.
<meta>	- name - content - http-equiv	Yes	Yes	Currently inactive.
<metadata>	- creator - rights - subject	Yes	Yes	Currently inactive.
<noinput>	- count - cond	Yes	Yes	Supports all attributes.
<nomatch>	- count - cond	Yes	Yes	Supports all attributes.
<object>	- name - expr - cond - classid - codebase - codetype - data - type - archive - fetchhint - fetchtimeout - maxage	Yes	Yes	Currently inactive.

Table continues...

Tag	Attributes	Available in VoiceXML 2	Available in VoiceXML 2.1	Limitation or Extensions, Supporting information
	maxage			
<option>	- dtmf - accept - value	Yes	Yes	Currently inactive.
<param>	- name - expr - value - valuetype - type	Yes	Yes	- Currently inactive — valuetype and type. - Supports all the other attributes.
<prompt>	- bargein - bargeintype - cond - count - timeout - xml:lang - xml:base	Yes	Yes	Supports all attributes.
<property>	- name - value	Yes	Yes	Supports all attributes.
<record>	- name - expr - cond - modal - beep - maxtime - finalsilence - dtmfterm - type	Yes	Yes	Supports all attributes.
<reprompt>		Yes	Yes	Supports the <reprompt> element.
<return>	- event - eventexpr	Yes	Yes	Supports all attributes.

Table continues...

Tag	Attributes	Available in VoiceXML 2	Available in VoiceXML 2.1	Limitation or Extensions, Supporting information
	• message • messageexpr • namelist			
<script>	• src • charset • fetchhint • fetchtimeout • maxage • maxstale • srcexpr	• srcexpr — No • Rest of the attributes— Yes	Yes	Supports all attributes except fetchhint .
<subdialog>	• name • expr • cond • namelist • srcexpr • method • enctype • fetchaudio • fetchtimeout • maxage • maxstale	Yes	Yes	Supports all attributes.
<submit>	• next • expr • namelist • method • enctype • fetchaudio • fetchhint • fetchtimeout • maxage • maxstale	Yes	Yes	Supports all attributes except fetchhint .

Table continues...

Tag	Attributes	Available in VoiceXML 2	Available in VoiceXML 2.1	Limitation or Extensions, Supporting information
<throw>	- event - eventexpr - message - messageexpr	Yes	Yes	Supports all attributes.
<transfer>	- name - expr - cond - dest - destexpr - bridge - connecttimeout - maxtime - transferaudio - aai - aaiexpr - type	- type — No - Rest of the attributes — Yes	Yes	Supports all attributes.
<value>	expr	Yes	Yes	Supports the attribute.
<var>	- name - expr	Yes	Yes	Supports all attributes.
<vxml>	- version - xmlns - xml:base - xml:lang_d - application	Yes	Yes	Supports all attributes.
<data>	- src - name - srcexpr - method - namelist - enctype - fetchaudio	No	Yes	Supports all attributes except fetchhint.

Table continues...

Tag	Attributes	Available in VoiceXML 2	Available in VoiceXML 2.1	Limitation or Extensions, Supporting information
	• fetchhint • fetchtimeout • maxage • maxstale			
<foreach>	• array • item	No	Yes	Supports all attributes.
<receive>	• fetchaudio • fetchaudioexpr • maxtime • maxtimeexpr			
<send>	• async • asyncexpr • body • bodyexpr • contenttype • contenttypeexpr • event • eventexpr • fetchaudio • fetchaudioexpr • namelist • target • targetexpr • timeout • timeoutexpr			

Call classification in speech applications

Call classification overview

Call classification, or call progress, is a method for determining who or what is on the other end of a call by analyzing the audio stream. When the analysis determines a probable match, the CCXML page receives a `connection.signal` event which contains the result in the `event $.info.callprogress` variable. Depending on the results of the analysis, call classification may continue for the duration of the call. In that case, the CCXML page will may receive multiple `connection.signal` events.

Call classification falls into two categories:

- Tone-based classification. This category has a high degree of accuracy because it is easy for the system to detect busy signals or fax machine signals.
- Speech-based classification. This category has a much lower degree of accuracy because it can be difficult to tell a human being's speech from an answering machine's recorded message.

Experience Portal uses speech-based classification when it detects an amount of energy in a frequency consistent with human speech. When it detects human speech, it differentiates between a live human being and an answering machine based on the length of the utterance. Generally, if a live human being answers, the utterance is relatively short while answering machine greetings are usually much longer.

For example, a live human might just say "Hello." while an answering machine message might say "Hello. I can't come to the phone right now. Please leave your message after the beep."

However, some people may answer the phone with a much longer greeting while others have recorded a very short answering machine greeting. In both of these cases, the call classification algorithm will incorrectly identify the call and assume the long greeting is a recorded message while the short greeting is a live human being.

To use call classification in your applications, make sure you design the application so that it takes such mistakes into account.

If you configure Experience Portal system to use H.323 connections and outcall applications, you must have Communication Manager with the SA8874 feature to detect that the call has been answered. Without the SA8874 feature, Experience Portal incorrectly detects that the call is answered even if the call is not answered.

If you configure Experience Portal system to use outcall applications, and want the Experience Portal system to differentiate human vs. answering machine, you require the Enhanced Call Classification license.

Call classification analysis results

When Experience Portal classifies the call, it sends a `connection.signal` event to the CCXML page. This event includes the results of the classification in the `event$.info.callprogress` variable.

Value of event <code>\$.info.callprogress</code>	Applies to	Description
<code>start_of_voice</code>	Outbound calls only	The call is answered and Experience Portal detects a voice on the line. EP determines whether the voice is from a human being or from an answering machine. A <code>Start_of_voice</code> classification is followed by either a <code>live_voice</code> or <code>recorded_msg</code> classification.
<code>live_voice</code>	Outbound calls only	The call is probably connected to a human being. No further classifications will be sent for this call.
<code>busy_tone</code>	Outbound calls only	A busy tone was received. This is commonly referred to as the “slow busy” tone. No further classifications will be sent for this call.
<code>reorder</code>	Outbound calls only	A switch error, such as all circuits being busy, has occurred. This is commonly referred to as the “fast busy” tone. No further classifications will be sent for this call.
<code>sit_tone</code>	Outbound calls only	A special information tone was received which indicates that the call could not be completed. This is the three frequency tone that is often followed by a spoken message. No further classifications will be sent for this call.
<code>sit_tone_reorder</code>		A call-disposition category for a call processing failure. (Incomplete digits, internal office or feature failure – local office) and (Call failure, no wink or partial digits received – distant office).
<code>sit_tone_vacant</code>		A call-disposition category for a call attempt to an unassigned NPA (numbering plan area) or NXX (Central Office exchange code).
<code>sit_tone_no_circuit</code>		A SIT (special information tone) classification for call attempts that fail to find an available Local/long distance. Service Provider outgoing trunk. (All circuits busy – local office).
<code>sit_tone_ineffective</code>		General misdialing, coin deposit required, or other failure.
<code>sit_tone_intercept</code>		Number changed or disconnected.
<code>recorded_msg</code>	Outbound calls only	An answering machine was detected and a recorded message has just started.

Table continues...

Value of event <code>\$.info.callprogress</code>	Applies to	Description
		A <code>recorded_msg</code> classification will always be followed by either a <code>msg_end</code> or <code>timeout</code> classification. No further classifications will be sent for this call.
<code>msg_end</code>	Outbound calls only	The end of a recorded message, such as that played by an answering machine, was detected. No further classifications will be sent for this call.
<code>fax_calling_tone</code>	Inbound calls only	A fax machine was detected as the initiator of an inbound call. No further classifications will be sent for this call.
<code>fax_answer_tone</code>	Outbound calls only	A fax machine was detected as the recipient of an outbound call. No further classifications will be sent for this call.
<code>ringing</code>	Outbound calls only	A “ring back” tone was detected. One or more of these classifications may be received by the application, but they are always followed by one of the other applicable classifications.
<code>timeout</code>	Inbound and outbound calls	The classification algorithm failed to classify the call before the allotted time ran out. By default, the allotted time is 20 seconds (or 20000 milliseconds). The default value can be overridden for outbound calls by setting the <code>call_classification_timeout</code> parameter in the <code>hints</code> attribute on the <code><createcall></code> tag to the desired number of milliseconds before call classification analysis should time out. No further classifications will be sent for this call.
<code>error</code>	Inbound and outbound calls	An internal error occurred during the classification analysis and the call could not be properly classified. No further classifications will be sent for this call.
<code>early_media</code>	Outbound calls only	Early media refers to media that is exchanged before a particular session is accepted by the called user. For example, for outbound calls the color ring tone will be detected as <code>early_media</code> by call classification.

Call classification for inbound calls

The only call classification provided for inbound calls is the ability to detect an incoming fax. It is extremely difficult to differentiate between a live human being and a recorded message for an incoming call because you cannot assume the initial greeting will be as short for an incoming call as

it is for an outgoing call. Therefore, any classification for an incoming call other than `fax_calling_tone` should be treated as if a live human being was detected.

If fax tone is detected when using VoiceXML applications, Experience Portal kills the application and transfers the call to a fax machine.

If fax tone is detected when using CCXML applications, Experience Portal sends the `fax_calling_tone` event to the application. The call treatment is then decided by the rules which the application designer has configured on the application.

When you add an application to Experience Portal using the EPM Web interface, the following parameters in the **Advanced Parameters** group on the Add Application page determine what happens when an incoming fax machine call is detected:

Parameter	Description
Fax Detection Enabled	The options are: • Yes: The application should attempt to identify whether the caller is a fax machine and route any fax machine calls to the telephone number specified in Fax Phone Number. • No: The application should not attempt to identify whether the caller is a fax machine. The default is No.
Fax Phone Number	If Fax Detection Enable is set to Yes , this is the telephone number or URI to which fax machines calls should be routed.

Call classification for outbound calls

Classification of human vs. answering machine for outbound call is done by Experience Portal. The classification is based on the length of the voice energy that is detected after the call is answered. You require the Enhanced Call Classification license on the Experience Portal system to differentiate human vs. answering machine. The classification is done only if the application sends a classification request to Experience Portal.

Note:

In the VoiceXML <TRANSFER> outcall method, the human vs. answering machine classification is never done.

Detection of answer, busy, RNA, and so on classification is done by Communication Manager and not by Experience Portal. Communication Manager needs the SA8874 feature to detect this classification. The detection is done on all outcalls except for blind transfers.

The application designer needs to enable call classification for outbound calls. If the call is going to be invoked by the Application Interface web service `LaunchVXML` method, you can specify the call classification parameters when you invoke the web service, as described in [Call classification with the LaunchVXML method](#) on page 551.

Otherwise, the application designer has to set `enable_call_classification=true` in the `hints` attribute of the `<createcall>` tag.

When call classification is enabled, a call will receive one or more `connection.signal` events containing the `event$.info.callprogress` field. This field will have one of the values described in [Call classification for outbound calls](#) on page 349.

*** Note:**

Remember that the page may receive `connection.signal` events that do *not* contain the `callprogress` field. It is up to the page to determine if the `callprogress` field exists and to take the appropriate course of action based on the value of this field.

The default timeout for outbound call classification is 20 seconds (or 20000 milliseconds). The default value can be overridden for outbound calls by setting the `call_classification_timeout` parameter in the `hints` attribute on the `<createcall>` tag to the desired number of milliseconds before call classification analysis should time out.

The following example shows a simple `connection.signal` handler page that first determines whether this is a `connection.signal` event bearing classification data. If it is, the handler assesses the data to determine what action to take. If the classification is `live_voice`, then it returns a status of `success` and the page continues to run. Otherwise, it returns the failure status `no answer`.

```
<transition event="connection.signal">
  <if cond="typeof(event$.info) != 'undefined'">
    <if cond="typeof(event$.info.callprogress) != 'undefined'">
      <var name="call_classification" expr="event$.info.callprogress"/>
      <var name="status"/>
      <if cond="call_classification == 'live_voice'">
        <assign name="status" expr="'success'"/>
        <send name="'avaya.launchresponse'" targettype="'avaya_platform'"
              target="session.id" namelist="status"/>
      </if>
    </if>
    <assign name="status" expr="'no answer'"/>
    <send name="'avaya.launchresponse'" targettype="'avaya_platform'"
          target="session.id" namelist="status"/>
  </if>
</transition>
```

Call classification with the LaunchVXML method

Call classification allows the VoiceXML application to return the appropriate status code based on whether a human, an answering machine, or a fax machine answers an outbound call.

Call classification parameters for the LaunchVXML method

The following call classification name-value pairs can be passed as parameters with the `LaunchVXML` method. For both parameters the default is `false`, which means that you must specify the name-value pair in order to enable the associated functionality.

Name-value pair	Description
<code>enable_call_classification=true</code>	This required parameter enables call classification.
<code>detect_greeting_end=true</code>	This optional parameter instructs the VoiceXML application to identify the end of a recorded greeting if an answering machine answers the outbound call.
<code>call_classification_recorded_msg_timeout = in mili secs (e.g. 30000 is 30 sec)</code>	This Optional parameter is to set wait timeout for “end of recorded greeting”, if an answering machine answers the outbound call. Default is 30 sec.
<code>call_classification_connectWhen = (OnConnect or OnProgress)</code>	This optional parameter is to start the CPA engine (call classification) on either OnConnect or OnProgress. By default it is set to OnProgress. In case the engine is started before connect, early media will also be captured for call classification.
<code>call_classification_timeout=value</code>	This optional parameter indicates how long the call classification function will run if it is unable to determine the classification. The value specified should be in milliseconds. If the value is not provided, the default timeout is 20 sec.
<code>call_classification_timeout = in mili secs (e.g. 20000 is 20 sec)</code>	Timeout for outbound call classification from engine. Default is 20 sec.

Call classifications

If you enable call classification, the VoiceXML application sends one of the following classifications to the application server using the query arguments on the URL:

Classification	Description
<code>live_voice</code>	If a human being answers the call, the application starts the previously-prepared VoiceXML dialog.  Note: This is the default classification assigned to the VoiceXML session before the call is placed. If a human being does not answer the call, this classification must be changed.
<code>recorded_msg</code>	If the <code>LaunchVXML</code> method was invoked with <code>detect_greeting_end=false</code> or if the <code>detect_greeting_end</code> parameter was not specified and an answering machine answers the call, the application terminates the previously-prepared VoiceXML dialog and starts a new dialog by sending the classification <code>recorded_msg</code> to the application server.
<code>msg_end</code>	If the <code>LaunchVXML</code> method was invoked with <code>detect_greeting_end=true</code> and an answering machine answers the call, the application terminates the previously-prepared VoiceXML dialog and starts a new dialog by sending the classification <code>msg_end</code> to the application server.

Table continues...

Classification	Description
fax_answer_tone	If a fax machine answers the call, the application terminates and returns the error code <code>fax detected (8206)</code> to the Application Interface web service.
timeout	If the VoiceXML application does not send a classification change message to the CCXML page within a given period of time, the CCXML applications assumes that a live person has answered the phone and it starts the previously-prepared VoiceXML dialog.
*	All other classifications result in the status code for <code>no answer ()</code> being returned the Application Interface web service.

SIP application support

User-to-User Interface (UII) data passed in SIP headers

When you add an application to Experience Portal using the EPM Web interface, you also specify how User-to-User Interface (UII) information will be passed to the application if it uses a SIP connection using the **Operation Mode** field in the **Advanced Parameters** group on the Add Application page.

The options are:

- Service Provider: Experience Portal passes the UII data along as a single block to the application without making any attempt to interpret data.

If you select this option, the application must handle the UII data on its own.

- Shared UII: Experience Portal takes the UII data and parses it into an array of IDs and their corresponding values. It then passes the application both the fully encoded UII data and the parsed array with only the values still encoded..

If you select this option, the UII data must conform to the Avaya UII specifications listed below.

UII data format in CCXML applications

For a CCXML application, the UII data is organized in a tree format. For example:

```
avaya.ucid = '#####'
avaya.uii.mode = "shared ui"
avaya.uii.shared[0].id = "FA"
avaya.uii.shared[0].value = "#####"
avaya.uii.shared[1].id = "BG"
avaya.uii.shared[1].value = "#####"
```

Each connection has its own tree associated with it, and the values for that connection can be accessed using the format

```
session.connections['connection_number'].avaya.element_name.
```

For example, if you want to declare two variables called `ucid` and `mode`, and you wanted to set those variables to be equal to the corresponding values for connection 1234, you would specify:

```
<var name="ucid" expr="session.connections['1234'].avaya.ucid"/>
<var name="mode" expr="session.connections['1234'].avaya.uui.mode"/>
```

UII data format in VoiceXML applications

In VoiceXML, there is only one active call so the UII information is organized into a similar tree format and placed into a session variable at the start of the dialog. The tree structure looks like this:

```
session.avaya.ucid
session.avaya.uui.mode
session.avaya.uui.shared[]
```

With the Shared UII mode, you must send UII/AAI data as name-value pairs in the following format:

```
<id0>,<value0>;<id1>,<value1>;<id2>,<value2>; ...
```

When you specify the name-value pairs:

- Each name must be set to the hexadecimal encoded ID stored in the `shared[]` array.
- Each value must be set to the encoded value stored in the `shared[]` array.
- Each name in the pair must be separated from its value by a `,` (comma).
- Each name-value pair must be separated from the next name-value pair by a `;` (semi-colon).

For example, if you wanted to send a UCID using UII/AAI, you might specify: `aa1 = "FA, 2901000246DEE275"`

Related links

[Universal Call Identifier \(UCID\) values included in UII data](#) on page 353

[Experience Portal application parameters affecting the UII data](#) on page 354

Universal Call Identifier (UCID) values included in UII data

The Universal Call Identifier (UCID) is an Avaya-proprietary call identifier used to help correlate call records between different systems. This identifier can either be generated by the Experience Portal MPP server or it can be passed to Experience Portal through an application's SIP headers if the application uses a SIP connection and the application's **Operation Mode** is set to **Shared UII**.

Note:

If the application uses an H.323 connection, Experience Portal can receive UCID from Communication Manager. This feature is supported in Communication Manager 5.2.

To enable this feature, you need to administer `ucid-info` on button 10 on the 7434ND stations used by Experience Portal.

A UCID consists of 20 decimal digits in three groups. Before the UCID is added to the UII data, Experience Portal encodes each group as a hexadecimal value and concatenates the three groups together. The:

- First group of 5 digits represents a 2 byte network node identifier assigned to the Communication Manager. In the UII data, this group is encoded as 4 hexadecimal digits.

- Second group of 5 digits represents a 2 byte sequence number. This group is encoded as 4 hexadecimal digits.
- Third group of 10 digits represents a 4 byte timestamp. This group is encoded as 6 hexadecimal digits.

For example, the UCID 00001002161192633166 would be encoded as 000100D84716234E.

When Experience Portal passes the UCID 00001002161192633166 to the application, it would look like this:

```
avaya.ucid = '00001002161192633166'
avaya.uui.mode = 'shared uui'
avaya.uui.shared[0].id = 'FA'
avaya.uui.shared[0].value = '000100D84716234E'
```

 Note:

The identifier for the UCID is always 250, which becomes FA in hexadecimal in the UUI shared[] array.

Related links

[User-to-User Interface \(UUI\) data passed in SIP headers](#) on page 352

Experience Portal application parameters affecting the UUI data

When you add an application to Experience Portal using the EPM Web interface, the following parameters in the **Advanced Parameters** group on the Add Application page affect the contents of the SIP UUI data:

Parameter	Description
Generate UCID	The Universal Call Identifier (UCID) is an Avaya-proprietary call identifier used to help correlate call records between different systems. The options are: • Yes: If the CM does not pass a UCID to Experience Portal, the MPP server generates a UCID. • No: The MPP does not generate a UCID.
Operation Mode	The SIP header for each call can contain User-to-User Interface (UUI) information that the switch can either pass on as a single block or attempt to parse so that the information can be acted on. This field determines how Experience Portal treats the UUI data. The options are: • Service Provider: Experience Portal passes the UUI data as a single block to the application without making any attempt to interpret data. If you select this option, the application must handle the UUI data on its own. • Shared UUI: Experience Portal takes the UUI data and parses it into an array of IDs and their corresponding values. It then passes the application both the fully encoded UUI data and the parsed array with only the values still encoded.

Table continues...

Parameter	Description
	If you select this option, the UUI data must conform to the Avaya UUI specifications described in User-to-User Interface (UUI) data passed in SIP headers on page 352. • Service Provider: Experience Portal passes the UUI data as a single block to the application without making any attempt to interpret data. If you select this option, the application must handle the UUI data on its own. • Shared UUI: Experience Portal takes the UUI data and parses it into an array of IDs and their corresponding values. It then passes the application both the fully encoded UUI data and the parsed array with only the values still encoded. If you select this option, the UUI data must conform to the Avaya UUI specifications described in User-to-User Interface (UUI) data passed in SIP headers on page 352.
Transport UCID in Shared Mode	If Operation Mode is set to Shared UUI and Generate UCID is set to Yes, this field determines whether Experience Portal encodes the Experience Portal-generated UCID and adds it to the UUI data for all outbound calls. The default is No, which means that a UCID is only passed as part of the UUI information if that UCID was passed to Experience Portal by the application.
Maximum UUI Length	The maximum length of the UUI data that can be passed in the SIP header. If this length is exceeded and Experience Portal generated a UCID for the call, the UCID is removed from the UUI data. If the result still exceeds this value, or if the UCID was passed to Experience Portal by the application, Experience Portal does <i>not</i> send any UUI data. Instead, it leaves the entire field blank because it has no way to determine what can be left out.

Related links

[User-to-User Interface \(UUI\) data passed in SIP headers](#) on page 352

SIP header support for CCXML and VoiceXML applications

Session Initiation Protocol (SIP) headers can provide additional information about a call that a CCXML or VoiceXML application can use to determine what processing needs to be done for that call. Experience Portal uses a collection of session variables to present this information to the application. However, not all SIP headers are accessible and many accessible headers are read only.

The following table lists the session variables that may accompany an inbound SIP INVITE. In the table, `<sip>` is the variable access string used to access the variables in a particular context. The valid strings are:

Variable access string	Description
<code>session.connection.protocol.sip</code>	This access string can be used by either CCXML or VoiceXML applications.

Table continues...

Variable access string	Description
<code>event\$.info.protocol.sip</code>	This access string can be used when variables arrive in the <code>info</code> map for a transition. These variables are only valid within the transition in which they arrived.
<code>session.connections['SessionID'].protocol.sip</code> where <i>SessionID</i> is the session ID.	This access string can be used to retrieve the variables from the connection object in the session variable space. The variables exist between transitions but can be overwritten by new data at any time.

If you want to use a variable in your application, you must use the complete text in your code.

For example, if you want to access the `<sip>.callid` variable in a session with the session ID `1234`, you would code one of the following, depending on the context in which you want to access the variable:

- `session.connection.protocol.sip.callid`
- `event$.info.protocol.sip.callid`
- `session.connections['1234'].protocol.sip.callid`

Session Variable	SIP Header	Notes
<code><sip>.callid</code>	Call-ID	Uniquely identifies a particular invitation or all registrations of a particular client.
<code><sip>.contact[array].displayname</code> <code><sip>.contact[array].uri</code>	Contact	Provides the display name, a URI with URI parameters, and header parameters.
<code><sip>.from.displayname</code> <code><sip>.from.uri</code> <code><sip>.tag</code>	From	The initiator of the request.
<code><sip>.historyinfo[array].displayname</code> <code><sip>.historyinfo[array].user</code> <code><sip>.historyinfo[array].host</code> <code><sip>.historyinfo[array].opaque</code>	History-Info	This field is typically used to inform proxies and User Agent Clients and Servers involved in processing a request about the history or progress of that request.
<code><sip>.passertedid[array].displayname</code> <code><sip>.passertedid[array].uri</code>	P-asserted Identity	The verified identity of the user sending the SIP message. This field is typically used among trusted SIP intermediaries to prove that the initial message was sent by an authenticated source.

Table continues...

Session Variable	SIP Header	Notes
<sip>.require	Require	The options that the User Agent Client (UAC) expects the User Agent Server (UAS) to support in order to process the request.
<sip>.supported[array].option	Supported	All extensions supported by the UAC or UAS.
<sip>.to.displayname <sip>.to.host <sip>.to.uri <sip>.to.user	To	The logical recipient of the request.
<sip>.unknownhdr[array].name <sip>.unknownhdr[array].value	Unknown	All headers not understood by Avaya Aura® Experience Portal are passed to the application through this array.
<sip>.useragent[array]	User-Agent	Contains information about the UAC originating the request.
<sip>.via[array].sentaddr <sip>.via[array].sentport <sip>.via[array].protocol <sip>.via[array].branch	Via	The path taken by the request to this point along with the path that should be followed in routing responses.
<sip>.name		This variable returns “sip” when the SIP protocol is used.
<sip>.version		This variable returns the SIP protocol version when the SIP protocol is used.
<sip>.requestmethod <sip>.requestversion <sip>.requesturi <sip>.request.user <sip>.request.host <sip>.requestparams[array].name <sip>.requestparams[array].value	“request”	The various components of the request URI (INVITE). For example, this variable includes the parameters, user and host part of the URI, and the request method.
<sip>.respcode		The results of a transaction. The actual contents varies by transaction type.
<sip>.resptext		The results of a transaction. The actual contents varies by transaction type.

Sample VoiceXML page logging SIP headers

The following VoiceXML page logs various SIP headers using the Experience Portal session variables.

```
<?xml version="1.0"?>
<vxml version="2.0" xmlns="http://www.w3.org/2001/vxml" xml:lang="en-us">
<property name="promptgender" value="female"/>
<property name="timeout" value="4s"/>
<property name="maxspeechtimeout" value="15s"/>
<form id="form0">
  <block>
    <log>session.connection.protocol.sip <value
      expr="session.connection.protocol.sip"/></log>
    <log>session.connection.protocol.name: <value
      expr="session.connection.protocol.name"/></log>
    <log>session.connection.protocol.version: <value
      expr="session.connection.protocol.version"/></log>
    <log>session.connection.protocol.sip.requesturi: <value
      expr="session.connection.protocol.sip.requesturi"/></log>
    <log>session.connection.protocol.sip.requestmethod: <value
      expr="session.connection.protocol.sip.requestmethod"/></log>
    <log>session.connection.protocol.sip.requestversion: <value
      expr="session.connection.protocol.sip.requestversion"/></log>
    <log>session.connection.protocol.sip.request.user: <value
      expr="session.connection.protocol.sip.request.user"/></log>
    <log>session.connection.protocol.sip.request.host: <value
      expr="session.connection.protocol.sip.request.host"/></log>
    <log>session.connection.protocol.sip.requestparams[0].name: <value
      expr="session.connection.protocol.sip.requestparams[0].name"/></log>
    <log>session.connection.protocol.sip.requestparams[0].value: <value
      expr="session.connection.protocol.sip.requestparams[0].value"/></log>
    <log>session.connection.protocol.sip.to.uri: <value
      expr="session.connection.protocol.sip.to.uri"/></log>
    <log>session.connection.protocol.sip.to.displayname: <value
      expr="session.connection.protocol.sip.to.displayname"/></log>
    <log>session.connection.protocol.sip.to.user: <value
      expr="session.connection.protocol.sip.to.user"/></log>
    <log>session.connection.protocol.sip.to.host: <value
      expr="session.connection.protocol.sip.to.host"/></log>
    <log>session.connection.protocol.sip.from.uri: <value
      expr="session.connection.protocol.sip.from.uri"/></log>
    <log>session.connection.protocol.sip.from.displayname: <value
      expr="session.connection.protocol.sip.from.displayname"/></log>
    <log>session.connection.protocol.sip.from.tag: <value
      expr="session.connection.protocol.sip.from.tag"/></log>
    <log>session.connection.protocol.sip.from.user: <value
      expr="session.connection.protocol.sip.from.user"/></log>
    <log>session.connection.protocol.sip.from.host: <value
      expr="session.connection.protocol.sip.from.host"/></log>
    <log>session.connection.protocol.sip.useragent[0]: <value
      expr="session.connection.protocol.sip.useragent[0]"/></log>
    <log>session.connection.protocol.sip.contact[0].displayname: <value
      expr="session.connection.protocol.sip.contact[0].displayname"/></log>
    <log>session.connection.protocol.sip.contact[0].uri: <value
      expr="session.connection.protocol.sip.contact[0].uri"/></log>
    <log>session.connection.protocol.sip.via[0].sentaddr: <value
      expr="session.connection.protocol.sip.via[0].sentaddr"/></log>
    <log>session.connection.protocol.sip.via[0].protocol: <value
      expr="session.connection.protocol.sip.via[0].protocol"/></log>
    <log>session.connection.protocol.sip.via[0].sentport: <value
      expr="session.connection.protocol.sip.via[0].sentport"/></log>
```



```

<log>session.connection.protocol.sip.via[1].sentaddr: <value
expr="session.connection.protocol.sip.via[1].sentaddr"/></log>
<log>session.connection.protocol.sip.via[1].protocol: <value
expr="session.connection.protocol.sip.via[1].protocol"/></log>
<log>session.connection.protocol.sip.via[1].sentport: <value
expr="session.connection.protocol.sip.via[1].sentport"/></log>
<log>session.connection.protocol.sip.supported: <value
expr="session.connection.protocol.sip.supported"/></log>
<log>session.connection.protocol.sip.require: <value
expr="session.connection.protocol.sip.require"/></log>
</block>
</form>
</vxml>

```

Support for unknown headers

If Experience Portal receives an INVITE with a header it does not recognize, it saves the name and value of the header in the `session.connection.protocol.sip.unknownhdr` session variable array.

For example, if Experience Portal receives an INVITE with the following unknown headers:

```

new_header: "helloworld"
another_new_header: "howareyou"

```

Experience Portal adds the following entries to the `session.connection.protocol.sip.unknownhdr` array:

```

session.connection.protocol.sip.unknownhdr.unknownhdr[0].name = "new_header"
session.connection.protocol.sip.unknownhdr.unknownhdr[0].value = "helloworld"
session.connection.protocol.sip.unknownhdr.unknownhdr[1].name = "another_new_header"
session.connection.protocol.sip.unknownhdr.unknownhdr[1].value = "howareyou"

```

RFC 3261 SIP headers

You can set a limited number of SIP headers independently for applications that initiate an outbound call with one of the following:

- A REFER as a result of a blind or consultative transfer
- An INVITE as a result of bridged transfer or a CCXML outbound call

 Note:

Not all headers that are available to be set on an INVITE are available to be set on a REFER.

You can set the following headers with the VoiceXML `<property>` element before `<transfer>` element. In the table, `<sip_prop>` represents

AVAYA_SIPHEADER.session.connection.protocol.sip.

*** Note:**

If you want to set a header in your application, you must use the complete text in your code. For example, code `<sip_prop>.callid` as `AVAYA_SIPHEADER.session.connection.protocol.sip.callid`.

SIP Header	<property>	Notes
Call-Info	<code><sip_prop>.callinfo</code>	Provides additional information about the source or target of the call, depending on whether it is found in a request or response.
To.displayname	<code><sip_prop>.to.displayname</code>	Displays the name of the call's target.
From.displayname	<code><sip_prop>.from.displayname</code>	Displays the name of the call's source.
P-asserted Identity	<code><sip_prop>.passertedid.displayname</code> <code><sip_prop>.passertedid.uri</code>	The unique identifier of the source sending the SIP message. This identifier is used for authentication purposes if your SIP configuration requires trusted connections. * Note: If you define the P-Asserted-Identity parameter for the SIP connection through the EPM, Experience Portal ignores any attempt by an application to change this identity.
Subject	<code><sip_prop>.subject</code>	A summary of the call.
Organization	<code><sip_prop>.organization</code>	The name of the organization to which the SIP element issuing the request or response belongs.
Priority	<code><sip_prop>.priority</code>	The priority of the request.

Creating a custom header

Procedure

To create a custom header, store a name and value pair in `thesession.connection.protocol.sip.unknownhdr` session variable array.

Example

To create a custom header with the name as `new_header` and value as `mycustomheader`, add the following to the `session.connection.protocol.sip.unknownhdr` array:

```
AVAYA_SIPHEADER.session.connection.protocol.sip.unknownhdr[0].name = "new_header"
AVAYA_SIPHEADER.session.connection.protocol.sip.unknownhdr[0].value = "mycustomheader"
```

Sample VoiceXML page setting SIP headers in a VoiceXML application

The following VoiceXML page sets various SIP headers on a bridged transfer.

```
<?xml version="1.0" ?>
<vxml version="2.0" xmlns="http://www.w3.org/2001/vxml" xml:lang="en-us" >
<form id="form0">
  <property name="AVAYA_SIPHEADER.session.connection.protocol.sip.from.displayname"
    value="kong, king"/>
  <property name="AVAYA_SIPHEADER.session.connection.protocol.sip.to.displayname"
    value="godzilla"/>
  <property
name="AVAYA_SIPHEADER.session.connection.protocol.sip.passertedid.displayname"
    value="authority"/>
  <property name="AVAYA_SIPHEADER.session.connection.protocol.sip.passertedid.uri"
    value="sip:1234@123.321.123.321"/>
  <property name="AVAYA_SIPHEADER.session.connection.protocol.sip.unknownhdr[0].name"
    value="Random"/>
  <property name="AVAYA_SIPHEADER.session.connection.protocol.sip.unknownhdr[0].value"
    value="This is an unknown header"/>
  <transfer name="t1" type="bridge" dest="tel:1234"/>
</form>
</vxml>
```

SIP UPDATE method

The SIP UPDATE method, as per RFC 3311, allows you to update parameters of a session. While a call is in a queue, Experience Portal allows the SIP UPDATE method to update the following parameter of the call:

- User-to-User Interface data

You can send multiple UPDATE messages after the initial INVITE is established and before the final response to the INVITE.

Note:

Experience Portal supports SIP UPDATE method only if the Allow header indicates support.

Related links

[Sample SIP UPDATE Method](#) on page 361

Sample SIP UPDATE Method

The following is an example of the SIP UPDATE method:

```
Via: SIP/2.0/UDP pc33.<domain_name>.com;branch=<branch id>
;received=<ip address>
To: <sip: email id>;tag=<tag number>
From: <name>
<sip:email id>;tag= <tag number>
Call-ID: <call_id>
CSeq: 63104 OPTIONS
Contact: <sip: email id>
```

```
Contact: <mailto: email id>
Allow: INVITE, ACK, CANCEL, OPTIONS, BYE, UPDATE
Accept: application/sdp
Accept-Encoding: gzip
Accept-Language: en
Supported: foo
Content-Type: application/sdp
Content-Length: 274
```

Related links

[SIP UPDATE method](#) on page 361

Experience Portal event handlers

When a CCXML speech application tries to access an HTML page that cannot be found or a VoiceXML application encounters an unexpected event, the application responds with an exception error message. A well-designed speech application includes exception handlers that deal with these messages and help the application recover so that it can continue processing the call.

Experience Portal uses the error handlers defined in the application whenever possible. However, if an exception error message occurs that is not handled by the application, or if there is a problem running the application due to issues with the application server or the speech servers, Experience Portal uses one of the event handlers installed on the MPP server.

The event handler Experience Portal uses depends on the state of the speech application. If an application:

- Was successfully started and there is a call in progress, Experience Portal uses the event handler associated with that application when it was added to the Experience Portal system.
- Could not be started, Experience Portal looks at the type of application that was requested and uses the appropriate default CCXML or VoiceXML event handler.

When you install the software, Experience Portal automatically installs default event handlers for CCXML and VoiceXML, as well as an event handler prompt that is played by the default event handlers.

If you want to customize the way Experience Portal reacts to a problem, you can add your own event handlers and prompts and then designate which ones Experience Portal should use as the default.

For example, you want your default event handler to:

1. Play a prompt explaining that there was a problem and that the customer is being redirected to an agent immediately.
2. Transfer the call to a special number reserved for such issues.

A call coming in on this special number alerts the agent that the caller has encountered an error in Experience Portal, and that the agent should find out what the customer was doing when the error occurred. The call center can then track these exceptions and fix areas that encounter frequent problems.

Related links

[Adding application event handlers and prompts](#) on page 363

You can install custom event handlers and prompts that you can use either as the system default or as the event handler for a specific application.

[Setting the default application event handlers](#) on page 364

You can define a default CCXML and VoiceXML event handler, along with a default event handler prompt, for Experience Portal to use if an application encounters a problem and no specific event handler has been associated with that application.

Adding application event handlers and prompts

You can install custom event handlers and prompts that you can use either as the system default or as the event handler for a specific application.

Before you begin

Make sure you test all event handlers thoroughly before you add them to the system.

Important:

Experience Portal does not validate the code in an uploaded event handler. If the event handler has a syntax error, it will not be detected until Experience Portal tries to use the event handler to process a call.

Procedure

1. Log on to the EPM Web interface using an account with the Administration user role.
2. From the EPM main menu, select **System Configuration > EPM Servers** and click **Event Handlers**.
3. To add a VoiceXML event handler:
 - a. Go to the VXML tab.
 - b. Verify that an event handler with the filename you intend to use does not already exist.
If you install an event handler with the same filename as an existing event handler, Experience Portal overwrites the old event handler with the new file without requiring confirmation.
 - c. Click **Add**.
 - d. On the Add VoiceXML Event Handler page, enter the appropriate information and click **Install**.
You can specify any file with the extension VXML.
4. To add a CCXML event handler:
 - a. Go to the CCXML tab.
 - b. Verify that an event handler with the filename you intend to use does not already exist.

If you install an event handler with the same filename as an existing event handler, Experience Portal overwrites the old event handler with the new file without requiring confirmation.

- c. Click **Add**.
- d. On the Add CCXML Event Handler page, enter the appropriate information and click **Install**.

You can specify any file with the extension CCXML.

5. To add an event handler prompt:

- a. Go to the Prompts tab.
- b. Verify that an event handler prompt with the filename you intend to use does not already exist.

If you install an event handler prompt with the same filename as an existing prompt, Experience Portal overwrites the old prompt with the new file without requiring confirmation.

- c. Click **Add**.
- d. On the Add Event Handler Prompt page, enter the appropriate information and click **Install**.

You can specify any file with the extension WAV, ALAW, or ULAW. After you add a prompt, it can be used by any of the installed VoiceXML or CCXML event handlers.

Related links

[Experience Portal event handlers](#) on page 362

Setting the default application event handlers

You can define a default CCXML and VoiceXML event handler, along with a default event handler prompt, for Experience Portal to use if an application encounters a problem and no specific event handler has been associated with that application.

Procedure

1. Log on to the EPM Web interface using an account with the Administration user role.
2. From the EPM main menu, select **System Configuration > MPP Servers** and click **Event Handlers**.
3. To specify the default VoiceXML event handler:
 - a. Go to the VXML tab.
 - b. In the **Default** column, click the **Default** link associated with the VoiceXML handler you want to use as the default.
4. To specify the default CCXML event handler:
 - a. Go to the CCXML tab.

- b. In the **Default** column, click the **Default** link associated with the CCXML handler you want to use as the default.

Related links

[Experience Portal event handlers](#) on page 362

Avaya Voice Browser overview

A voice browser is a web browser that presents an interactive voice user interface to the user. In addition, it typically provides an interface to the PSTN or a PBX. Just as a visual web browser works with HTML pages, a voice browser operates on pages that specify voice dialogues. These pages are usually written in VoiceXML, but other proprietary voice dialogue languages remain in use.

The Avaya Voice Browser is a VoiceXML interpreter. The Avaya Voice Browser performs the following functions:

- Fetches VoiceXML and ECMA script documents.
- Parses, translates, and stores VoiceXML documents. Stores parsed VoiceXML pages in memory.
- Loads and switches Execution context.
- Loads, activates, and unloads Grammars. Supports SRGS 1.0 and simple JSFG 1.0.
- Browses through VoiceXML elements and interprets them.
- Translates <Prompt> elements to SSML 1.0 format and collects user inputs.
- Reports events (throws exceptions) according to VoiceXML specification.

Related links

[Setting Avaya Voice Browser options](#) on page 365

[AVB-specific VoiceXML events](#) on page 366

[Browser Settings page field descriptions](#) on page 367

[INET and cache Interface](#) on page 371

[Cache control mechanisms](#) on page 372

[ETag Directives](#) on page 372

[Component details of a request](#) on page 372

[Cache performance factors](#) on page 376

Setting Avaya Voice Browser options

Procedure

1. Log on to the EPM Web interface using an account with the Administration user role.
2. From the EPM main menu, select **System Configuration > MPP Servers**.
3. On the MPP Servers page, click **Browser Settings**.

4. On the AVB Settings page, enter the appropriate information and click **Save**.

Related links

[Avaya Voice Browser overview](#) on page 365

AVB-specific VoiceXML events

The Avaya Voice Browser may issue any of the following Experience Portal-specific VoiceXML events:

AVB event name	Description
<code>error.badfetch.applicationuri</code>	The targeted application could not be found.
<code>error.badfetch.baddialog</code>	The targeted dialog could not be found. For example, it cannot match the specified <code><form></code> id or <code><field></code> name.
<code>error.badfetch.baduri</code>	A bad URI was encountered during a fetch attempt.
<code>error.grammar</code>	An unknown grammar was received from a speech server.
<code>error.grammar.choice</code>	An unknown grammar error was received from a speech server while processing a <code><choice></code> statement.
<code>error.grammar.inlined</code>	An unknown grammar was received from a speech server while processing inline grammars for <code><field></code> or <code><link></code> .
<code>error.grammar.option</code>	An unknown grammar error was received from a speech server while processing an <code><option></code> statement.
<code>error.internalerror</code>	An internal error was encountered.
<code>error.max_loop_count_exceeded</code>	The maximum number of document pages allowed for a session has been exceeded.  Note: This is usually an indication of an infinite loop detected in an application execution path.
<code>error.noresource.asr</code>	No ASR resources are currently available.
<code>error.noresource.tts</code>	No TTS resources are currently available.
<code>error.recognition</code>	An unknown recognition error was received from a speech server.
<code>error.semantic.ecmascript</code>	A semantic error was encountered while processing a ECMA script.
<code>error.semantic.no_event_in_throw</code>	An empty "event" attribute was encountered. For example, a <code><throw></code> was defined with no associated event.
<code>error.semantic.recordparameter</code>	A semantic error was encountered while processing recording-related parameters.
<code>error.transfer</code>	An unknown error was encountered during a transfer attempt.

Related links

[Avaya Voice Browser overview](#) on page 365

Browser Settings page field descriptions

Use this page to configure the Browser settings that affect all MPPs in the Experience Portal system.

This page contains the:

- [VoiceXML Properties group](#) on page 367
- [VoiceXML Browser Properties group](#) on page 369
- [CCXML Browser Properties group](#) on page 371

*** Note:**

Click the group heading to expand or collapse the group.

To restore the default settings for all the fields, click **Reset All to Default**.

VoiceXML Properties group

*** Note:**

Most of these default values can be overridden either in the VoiceXML application itself or in the application parameters when you add the application to Experience Portal.

Field	Description
Language	The default application language. The available choices depend on the ASR application languages installed on your Experience Portal system.
Confidence Threshold	The default confidence level below which the ASR engine rejects the input from the caller. This value is mapped to whatever scale the ASR engine uses to compute the confidence level. In the case of ASR engines that use MRCP, this value is mapped in a linear fashion to the range 0 to 100. Enter a number in the range 0.0 to 1.0. The default is 0.5.
Sensitivity Level	How loud an utterance must be for the ASR engine to start speech recognition. The higher the sensitivity level, the lower the input volume required to start speech recognition. This value is mapped to whatever scale the ASR engine uses to compute the sensitivity level for speech recognition. Enter a number in the range 0.0 to 1.0. The default is 0.5.
Speed vs. Accuracy	The balance between speed of recognition and accuracy of recognition.

Table continues...

Field	Description
	This value is mapped to whatever scale the ASR engine uses to compute the balance between speed and accuracy of recognition. Enter a number in the range 0.0 to 1.0. The default is 0.5. If you are using ASR servers <i>without</i> MRCP and want to: • Decrease the time it takes to recognize an utterance at the expense of recognition accuracy, enter a lower number in this field. • Increase the likelihood that an utterance is correctly recognized at the expense of recognition speed, enter a higher number in this field. If you are using ASR servers <i>with</i> MRCP and want to: • Decrease the time it takes to recognize an utterance at the expense of recognition accuracy, enter a higher number in this field. • Increase the likelihood that an utterance is correctly recognized at the expense of recognition speed, enter a lower number in this field.
N Best List Length	The maximum number of recognition results that the ASR engine can return. Enter a number in the range 1 to 100. The default is 1.
Fetch Timeout	The maximum number of seconds that the VoiceXML browser should wait for the application server to return the requested page.
Output Modes	Select the output mode for a media track. The options are: • Audio—Selects the audio track for playback. • Video—Selects the video track for playback. • Audio/Video—Selects the audio and video tracks for playback.
Maximum Recording Duration	The maximum recording time allowed. If recording time exceeds the limit, event message containing this information is sent. Enter a number in the range 0 to 65535. The default is 10800.
Alarm Event Interval	The interval, in seconds, that determines the number of times the same type of error is logged to Log Viewer. If the same type of error occurs more than once in the specified interval, the error is logged to Log Viewer only once. This functionality ensures that the number of repetitive errors logged to Log Viewer are reduced. Enter a value in the range 0 to 999999. The default is 3600.
Maximum Cache Age section	
Document	The maximum length of time that a document can be in the cache before the application considers it to be stale and forces the MPP to download the document again. Enter a whole number of seconds in this field. The default is 3600.

Table continues...

Field	Description
Grammar	The maximum length of time that an utterance can be in the cache before the application considers it to be stale and forces the MPP to download the utterance again. Enter a whole number of seconds in this field. The default is 3600.  Note: This value is the same as the Maximum Grammar Cache Age application parameter, and Experience Portal uses it in conjunction with the Maximum Grammar Staleness and Minimum Grammar Freshness Time application parameters in order to determine whether to force the MPP to download the utterance again.
Audio	The maximum length of time that an audio file can be in the cache before the application considers it to be stale and forces the MPP to download the audio file again. Enter a whole number of seconds in this field. The default is 3600.
Script	The maximum length of time that a script can be in the cache before the application considers it to be stale and forces the MPP to download the script again. Enter a whole number of seconds in this field. The default is 3600.
Data	The maximum length of time that data can be in the cache before the application considers it to be stale and forces the MPP to download the data again. Enter a whole number of seconds in this field. The default is 3600.

VoiceXML Browser Properties group

Field	Description
Maximum Branches	Maximum number of JavaScript branches for each JavaScript evaluation, that are used to interrupt infinite loops from (possibly malicious) scripts. Enter a value in the range 1 to 999999. The default is 100000.
Cache section	
Total Size	The maximum size for the AVB cache. Once this size is reached, Experience Portal cleans the cache until size specified in the Low Water field is reached. The default is 40.
Low Water	The size that you want the AVB cache to be after it is cleaned. The default is 10.
Maximum Entry Size	The maximum individual file size to cache. This field has to be less than Total Size value. File that exceeds the size limit is not fetched. Enter a value in the range 0 to 65535. The default is 4 MB.

Table continues...

Field	Description
Entry Expiration Time	You should obtain the lock before reading or writing files in the cache. If the lock is not available, the entry expiration time is used to periodically check its availability. Enter a value in the range 0 to 65535. The default is 5 seconds.
Interpreter section	
Maximum Documents	The maximum number of pages that the AVB can access in a single session. Enter a number between 250 and 10000. The default is 500.
Maximum Execution Context Stack Depth	The maximum number of scripting context threads that can be stored simultaneously in the AVB. Enter a number between 1 and 128. The default is 10.  Tip: If you set this value too high, your system could run out of memory if the applications initiate an unexpectedly large number of threads. You should specify the highest number of threads that can run simultaneously without seriously taxing the resources available on the MPP server.
Maximum Loop Iterations	Prevents voice browser from entering into an infinite loop while handling VXML events. If number of entries to event handling function exceeds the limit, the application exits. Enter a number between 1 and 2000. The default is 1000.
INET section	
Proxy Server	If your site uses an INET Proxy server, the fully qualified path to the proxy server.
Proxy Port	If your site uses an INET Proxy server, the port number for the proxy server. The default is 8000.
SSL Verify	The options are: • Yes: If an application is configured to use https and this option is set to Yes, Experience Portal verifies the connection from the MPP to the application server using the appropriate application certificate.  Important: If a suitable certificate cannot be found, the connection to the application server will fail and the application will not run. • No: Experience Portal does not verify the connection from the MPP to the application server regardless of the specified application protocol.
Connection Persistent	Whether a new connection is established for each HTTP request. The options are: • Yes: Same connection is used for each HTTP request.

Table continues...

Field	Description
	• No: A new connection is used for each HTTP request. The default is Yes.

CCXML Browser Properties group

Field	Description
Fetch Timeout	The maximum number of seconds that the CCXML browser should wait for the application server to return the requested page. If this time elapses with no response from the application server, the CCXML browser cancels the request and runs the application's default error page. Enter a number between 1 and 65535. The default is 15.
Number of Threads for Asynchronous Fetch	The maximum number of threads that the CCXML browser should use for an asynchronous fetch. Enter a number between 1 and 500. The default is 5.
Maximum Branches	Maximum number of JavaScript branches for each JavaScript evaluation, that are used to interrupt infinite loops from (possibly malicious) scripts. Enter a value in the range 1 to 999999. The default is 100000.

Related links

[Avaya Voice Browser overview](#) on page 365

INET and cache Interface

The INET and Cache modules provide the interface for fetching resources from the internet and control the caching scheme based on the configuration of several elements. Attributes of the INET and Cache interface include:

- Supports HTTP, HTTPS and FILE protocols.
- Caches responses to GET requests.
- Supports HTTPS through OpenSSL.
- Supports Cookies to enable sessions in the web server.
- Provides caching based on server caching policy.
- Validates cache based on maxage and maxstale setting in the application.
- Configures cache folder, size and low watermark level.

Related links

[Avaya Voice Browser overview](#) on page 365

Cache control mechanisms

There are three basic mechanisms for controlling caches: freshness, validation, and invalidation.

- **Freshness** allows a response to be used without rechecking it on the original server, and can be controlled by both the server and the client. For example, the Expires response header gives a date when the document becomes stale, and the max-age directive tells the cache how many seconds the response is fresh for.
- **Validation** can be used to check whether a cached response is still good after it becomes stale. For example, if the response has a Last-Modified header, a cache can make a conditional request using the If-Modified-Since header to see if it has changed. The ETag (entity tag) mechanism also allows for both strong and weak validation.
- **Invalidation** is usually a side effect of another request that passes through the cache. For example, if a URL associated with a cached response subsequently gets a **POST**, **PUT** or **DELETE** request, the cached response will be invalidated.

Related links

[Avaya Voice Browser overview](#) on page 365

ETag Directives

An ETag or entity tag is one of several mechanisms that HTTP provides for cache validation. ETags are used by servers and browsers to validate cached components. ETags enable a client to make conditional requests.

An ETag is an identifier assigned by a web server or a browser to a specific version of a resource. If the resource content ever changes, a new and different ETag is assigned. Used in this manner, ETags are similar to fingerprints and can be compared to determine if two versions of a resource are the same or not.

The use of ETags in the HTTP header is optional.

Avaya Voice Browser supports the use of ETags. For information on disabling ETag directives, see <http://www-01.ibm.com/support/docview.wss?uid=swg21566450>.

Related links

[Avaya Voice Browser overview](#) on page 365

Component details of a request

HTTP Header Setting (Request Headers)

Requests can be made using the GET or POST HTTP method. A **GET** command checks if an updated version of a document exists using the configuration settings to determine whether to fetch the document or use the cached version. A **POST** command forces a new fetch of the document irrespective of the configuration settings and bypasses the Cache Validator step. The header

settings can be controlled from within the application (for a given document), at the application server level, and at the ASR speech server level for grammars. Common headers include the following:

- **Host:** Host information.
- **Accept:** Acceptable media types.
- **Referrer:** Referring URL.
- **Connection:** Connection type, persistent or non-persistent, use close for non-persistent.
- **Cache-Control:** maxage, maxstale, no-cache, no-store.
- **Cookie:** If Cookies are enabled.
- **If-Modified-Since:** Last-Modified from pervious fetch (**GET** only).
- **Expect:** Waiting for continue (**POST** only).
- **Content-Length:** Media size that is used to allocate buffer for fetching documents. Memory allocation is done block by block, if not set.
- **Content-Type:** Media type that is used to decide the MIME type of the audio and is set according to the extension/MIME type mapping on the server.

POST requests support multipart or form-data to submit audio to the application server.

Example

```
accept: */*
host: avb-linux.sv.avaya.com:8080
user-agent: AvayaVXI/2.0
referrer: http://avb-linux.sv.avaya.com:8080/test_promptFile.vxml
connection: close
cache-control: max-age=3600
method=GET
protocol=HTTP/1.1
```

URL Parsing

In this step, the protocol, the machine name, the port number, and the absolute path of the requested document is determined. This is setup through the IR or EP Administration interface when deploying the application.

Fetch versus Cache

A fetch will be performed rather than using the cache under the following conditions:

- No maxage configured
- No cache validator present
- Validator has expired (or no expiration time is set)
- An error encountered when reading the cache

The default maxage and maxstale values are configured through the EPM for Experience Portal. The expiration of the cache or the validator is configured on the application server. If expiration is not sent from the application server, the entry expires.

HTTP Header Settings (Response Headers)

- **Pragma:** no cache — Do not cache

- Cache-Control:
 - no-cache, no-store or private — Do not cache
 - maxage, s-maxage — use the max age given in the header
 - must-revalidate — Do not cache
- Expires:
 - When does this entry expire — no conditional gets before the entry expires
- Last-Modified
- Date

Example

In this example, the expiration date is later than the current date, so the cache entry is still valid and will be used. If the “Expires” header is absent, AVB will send conditional HTTP GET with If-Modified-Since and If-None-Match headers to check if the resources has been updated.

```
HTTP/1.1 200 OK
Date: Tue, 23 May 2006 22:30:45 GMT
Server: Apache/2.0.46 (Red Hat)
Last-Modified: Tue, 28 Feb 2006 17:43:35 GMT
ETag: "6090ec-29b-5dd53fc0"
Accept-Ranges: bytes
Content-Length: 667
Cache-Control: max-age=86400
Expires: Wed, 24 May 2006 22:30:45 GMT
Keep-Alive: timeout=15, max=100
Connection: Keep-Alive
Content-Type: text/xml
```

Example

In this example due to the no-cache settings and 0 value for expiration, no entry will be added to the cache for future requests thus forcing a fetch of the document for each request.

```
HTTP/1.1 200 OK
Server: Apache-Coyote/1.1
Set-Cookie: JSESSIONID=65F51939A8D2D86E2D31919FFF5A2DED; Path=/pizza
Cache-Control: no-cache
Pragma: no-cache
Expires: 0
Content-Type: text/xml;charset=UTF-8
Date: Tue, 23 May 2006 23:14:53 GMT
Connection: close
```

Cache Validation

If a document has previously been fetched and the header response information indicates that the document should be cached, the next time this document is requested, a cache entry will be found and evaluated. The cache validation logic is as follows and uses the maxage and maxstale values. These values can be specified for each individual cacheable resource such as document page, prompt and grammar in the application or on the EP and IR systems (defaults are provided). For EP, they are configured through the EPM and on IR, they are configured by editing the defaults.xml file.

Note:

The maxage and maxstale defined for speech grammars are used by speech servers and the speech server can define and override the behavior of the settings.

Freshness Life Time = maxage from header or “Expires” – “Date”

Staleness = Current Age – Freshness Life Time

Must Revalidate = “must-revalidate” from “Cache-Control”

If Current Age > maxage then the document is Expired

If Staleness < 0 then the document is Not Expired

If Must Revalidate is set then the document is treated as Expired

If Staleness is > maxstale then the document has Expired

If No Freshness Life Time is less than or equal to 0 then the document has Expired

Connections

The method of configuring connections impact performance. Persistent connections saves the time spent in parsing the URL and resolves the hostname using DNS. Configurations that use load balancers or any mechanism that changes host name to IP address mapping of application servers may not use persistent connections. Make sure persistent connections works in your environment before utilizing this option.

Persistent versus Non-Persistent

- Persistent connections reuses existing sockets within the same call instance.
- Non-Persistent will open a new socket connection for every request.
- This is configurable at the process level with the default being persistent.
- Persistent mode uses a connection table to get a Connection for a host.
- Persistent and Non-persistent modes resolve host names using DNS and support multiple IPs.

Secured versus Non-Secured

- Based on the protocol specified in the URL (HTTP or HTTPS)
- Trusted client certificates are supported
- OpenSSL is used for Secured Connections

Cookie Support

The AVB supports the use of Cookies as follows:

- Can be enabled and disabled at the process level
- Can not be shared across sessions
- Collects cookies from the server
- Ensures Expires, Domain and Path cookie attribute matches
- Does not match request port number

Example

```
Client requests a document, and receives in the response:
- Set-Cookie: CUSTOMER=WILE_E_COYOTE; path=/; expires=Wednesday, 09-Nov-99 23:12:40
  GMT
When client requests a URL in path "/" on this server, it sends:
- Cookie: CUSTOMER=WILE_E_COYOTE
Client requests a document, and receives in the response:
```

```
Set-Cookie: PART_NUMBER=ROCKET_LAUNCHER_0001; path=/
When client requests a URL in path "/" on this server, it sends:
Cookie: CUSTOMER=WILE_E_COYOTE; PART_NUMBER=ROCKET_LAUNCHER_0001
Client receives:
Set-Cookie: SHIPPING=FEDEX; path=/foo
When client requests a URL in path "/foo" on this server, it sends:
Cookie: CUSTOMER=WILE_E_COYOTE; PART_NUMBER=ROCKET_LAUNCHER_0001; SHIPPING=FEDEX
```

Related links

[Avaya Voice Browser overview](#) on page 365

Cache performance factors

There are several factors to consider when making decisions on the configuration settings for a given application or customer environment. These include:

- **Security:** The connections between the Application Server and the AVB (platform) and the Application Server and the server hosting the secured resources must be secure.
- **Persistent Connections:** If you use persistent connections, you save the time spent on parsing the URL and resolving the host name using DNS.

 Note:

Configurations that use load balancers or any mechanism that changes host name to IP address mapping of application servers may not lend themselves to using persistent connections. So make sure persistent connections work properly in your environment before utilizing this option.

- **Dynamic URLs:** Pages that use dynamic URLs should not be cached.
- **Cache Size:** The browser cache size should be configured to ensure all cacheable files from an application (or set of applications) can be stored in the cache. The number and size of cacheable resources will determine the correct size of the cache. The default is set to 40 megabytes and can be configured through the EPM for EP or by editing the defaultsx.cfg file on IR(where x is the VXi instance number). This may need to be adjusted if you are running multiple applications, if the length of the prompts is measured in minutes, or if there are an unusually large number of prompts, pages and grammars in the application. The quickest way to size it is to run through the application (or set of applications that will coreside) a few times and cover as many application execution paths as possible, and then check the cache folder size.
- **Expiration frequency:** If feasible, a 24-hour or longer expiration timeframe is recommended. The AVB will still use the cached copy if it has exceeded its expiration time by no more than maxstale seconds. A shorter expiration timeframe will cause more conditional GETs to be performed by AVB given the same maxage or maxstale settings. Use the HTTP Expires header to set the expiration time.
- When a load balancer is used it is essential to keep ETags and last modified records the same across all servers, otherwise AVB performs many unnecessary cache updates. The AVB generates f-Match/If-None-Match headers while refreshing a resource with an ETag that was previously retrieved.

- The **POST** method should be used in cases where caching is not useful to prevent unnecessary overhead.
- Understand the default and tunable parameters for your application server. For example, Tomcat does not set the HTTP Expires header for static files such as audio files and grammar files. The absence of the HTTP Expires header will force the browser to do a conditional get to the server on every access to the static file. It is possible to use Tomcat in combination with an http server, such as Apache or IIS, which then allows the server to generate the HTTP Expires header setting.

Related links

[Avaya Voice Browser overview](#) on page 365

Using a secure connection between the MPP and the application server

About this task

You can require that the MPP running a particular application uses a secure connection to the application server.

Procedure

1. Log on to the EPM Web interface using an account with the Administration user role.
2. From the EPM main menu, select **System Configuration > Applications**.
3. For each application that you want to use a secure connection, verify that the URL in the **URL** column starts with `https`.

If it does not, click the application name to open the Change Application page and specify a URL that begins with `https`.
4. From the EPM main menu, select **Security > Certificates** and go to the Application Certificates tab.
5. Verify that a security certificate exists for each application server that Experience Portal can trust.

Important:

If Experience Portal cannot find a suitable application certificate, it will not be able to establish a secure connection to the application server, and all `https` applications will fail.

6. Click **Add** to install a security certificate using the Add Application Certificate page.
7. From the EPM main menu, select **System Configuration > MPP Servers** and click **Browser Settings**.
8. On the Browser Settings page, make sure that **SSL Verify** is set to **Yes**.

Chapter 14: Speech servers in Avaya Aura Experience Portal

Speech servers in Avaya Aura® Experience Portal

The Avaya Aura® Experience Portal system integrates with two types of third-party speech servers:

- Automatic Speech Recognition (ASR): This technology enables an interactive voice response (IVR) system to collect verbal responses from callers.
- Text-to-Speech (TTS): This technology enables an IVR system to render text content into synthesized speech output according to algorithms within the TTS software.

For more information, see *Avaya Aura® Experience Portal Overview and Specification*.

Mixed Protocols for configuring speech servers

When the Media Processing Platform (MPP) software receives a call, the MPP software uses the Media Resource Control Protocol (MRCP) protocol to communicate with the speech servers. Experience Portal allows you to configure multiple MRCP options for each speech server depending upon which protocols are supported by the speech vendor.

For example, Experience Portal enables you to configure the following MRCP protocols for the Nuance speech server in the Experience Portal system:

- MRCP V1
- MRCP V2 TCP
- MRCP V2 TLS

In such a configuration, the MPP software uses the speech servers in a round robin way. For example, if you configure a Nuance Vocalizer to use MRCPV1 and a Nuance Recognizer server to use MRCPv2 w/ TLS, the MPP software uses the Nuance Vocalizer MRCPv1 server for the first call, the Nuance Recognizer MRCPv2 w/ TLS for the second call, and so on.

Important:

- Although EPM allows you to configure various MRCP options for different types of speech servers, you need to contact your speech server vendor for information on the MRCP

options supported by each speech server. For example, Nuance Recognizer server supports all options (MRCPv1, MRCPv2+TCP, and MRCPv2+TLS).

- To configure TLS on any ASR or TTS speech server, you must restart the MPP server to reauthorize the certificates.

ASR servers in Avaya Aura Experience Portal

ASR servers in Avaya Aura® Experience Portal

The Automatic Speech Recognition (ASR) technology enables an Interactive Voice Response (IVR) system to collect verbal responses from callers. The IVR system then interprets these verbal responses according to algorithms within the ASR software. Avaya Aura® Experience Portal integrates with third-party ASR servers to provide this capability in speech applications.

When the Experience Portal Media Processing Platform (MPP) software receives a call, MPP starts the associated speech application that controls the call flow. If the speech application uses ASR resources, MPP also starts a session with an ASR server that is configured to use *all* the languages defined in the speech application.

 Note:

You can switch languages within a single speech application, provided all the required languages are configured on the same ASR server. If a speech application is configured to use more languages than are configured for any single ASR server, Experience Portal sends a `No ASR Resource` exception to the application. What happens then depends on the event handler that the application uses.

As the call progresses, MPP directs any requests for speech recognition from the application to the designated ASR server. The ASR server processes the input collected from the caller and returns the results to the speech application for further action.

 Note:

You need one ASR license for each call that requires ASR resources. The license is unavailable until the call is complete.

Viewing existing ASR servers

Procedure

1. Log on to the EPM Web interface using an account with the Administration, Operations, or Maintenance user role.
2. From the EPM main menu, select **System Configuration > Speech Servers**.

3. Click the ASR tab.

The options displayed on this page depend on your user role.

Adding ASR servers

Procedure

1. Log on to EPM Web interface.

If Avaya Services is maintaining this system and you are an Avaya Services representative, log on to the EPM using the init EPM account created during the EPM software installation.

Otherwise, log on to the EPM using an account with the Administrator user role.

2. In the EPM main menu, select **System Configuration > Speech Servers**.
3. On the **ASR** tab of the Speech Servers page, click **Add**.
4. On the Add ASR Server page, enter the appropriate information and click **Save**.

If you logged in using the init account, ensure you enter the appropriate LDN number for the server in the **LDN** field. If you do not specify an LDN number, Experience Portal uses the default value (000)000-0000.

After you save the changes, the **System Monitor** webpage and the **MPP Manager** webpage on EPM display the **Restart Required** configuration status for MPPs that are in the **Running** state.

5. Restart only the MPP servers that belong to the affected zone.

Changing ASR servers

Procedure

1. Log on to EPM Web interface.

If Avaya Services is maintaining this system and you are an Avaya Services representative, log on to the EPM using the init EPM account created during the EPM software installation.

Otherwise, log on to the EPM using an account with the Administrator user role.

2. In the EPM main menu, select **System Configuration > Speech Servers**.
3. On the ASR tab of the Speech Servers page, click the server name in the **Name** column.
4. On the Change ASR Server page, enter the appropriate information and click **Save**.

If you logged in using the init account, make sure that the LDN number specified in the **LDN** field matches the information in the Avaya Services database for this server.

After you save the changes, the **System Monitor** webpage and the **MPP Manager** webpage on EPM display the **Restart Required** configuration status for MPPs that are in the **Running** state.

- Restart only the MPP servers that belong to the affected zone.

Deleting ASR servers

Before you begin

Important:

All ASR-enabled applications on the Experience Portal system have associated ASR languages. Before you delete a server, look at the **Languages** column. Ensure that all the languages that the server supports are also supported by at least one other ASR server. If the server you plan to delete is the only one that supports a given language, you must assign that language to another ASR server. You can also change any applications that use the old language.

Procedure

- Log on to the EPM Web interface using an account with the Administration user role.
- In the EPM main menu, select **System Configuration > Speech Servers**.
- On the Speech Servers page, click the **ASR** tab .
- For each ASR server that you want to delete, select the **Selection** check box to the left of the server name in the table.

Tip:

To delete all servers, select the **Selection** check box in the header row of the table. The system automatically selects all rows in the table.

- Click **Delete**.

If the server is currently in use, Experience Portal deletes it after the server finishes processing any active calls.

After you save the changes, the **System Monitor** webpage and the **MPP Manager** webpage on EPM display the **Restart Required** configuration status for MPPs that are in the **Running** state.

- Restart only the MPP servers that belong to the affected zone.

ASR tab on the Speech Servers page field descriptions

Use this tab to view information about the Automatic Speech Recognition (ASR) servers currently administered on the Experience Portal system, add a new ASR server, or change an existing server, and add or delete different languages and language codes.

Note:

Any modifications to the speech servers requires the MPP(s) to be restarted for the affected zone(s).

+ Tip:

To sort the servers by any column, click the up arrow (sort ascending) or down arrow (sort descending) in the column header.

Column or Button	Description
Selection check box	Use this Selection check box to select which ASR servers you want to delete.
Zone	The name of the zone where the ASR servers are configured.
 Zones filter icon	To filter zones, click this icon located at the right side of the page. The system opens the Zone filter window for selecting one or more zones. * Note: The Zones filter icon only appears when you create new zones. If you do not create any new zones, you do not see the icon.
Name	The unique identifier for this ASR server on the Experience Portal system. To change the parameters for an ASR server, click the name of the server in the table. Experience Portal opens the Change ASR Server page.
Enable	Whether this ASR server is available for use by the Experience Portal system.
Network Address	The network address, or location, of the ASR server.
Engine Type	The type of ASR software engine the server uses.
MRCP	The MRCP protocol used for allocating the media processing server resources (ASR).
Base Port	The port number on the ASR server to which requests for ASR services are sent. The ASR server must be configured to receive and process requests through this port.
Total Number of Licensed ASR Resources	The total number of licensed ASR resources that will be used by the Experience Portal system. Experience Portal uses this information to determine the total number of ASR resources available to the Experience Portal system.
Languages	The languages that the ASR server can recognize.
Add	Opens the Add ASR Server page.
Delete	Deletes the ASR servers whose Selection check box has been checked. After you delete the servers, the System Monitor web page and the MPP Manager web page on EPM display the Restart needed configuration status for affected MPPs that are in the Running state. You must restart affected MPPs before the deleted ASR servers will be removed from the MPP's configuration.
Customize	Opens the ASR Custom Languages page. Using this page you can add custom languages and their respective language codes to the Automatic Speech Recognition (ASR) servers currently administered on the Experience Portal system. You can also delete the existing custom configured languages and their respective codes.

Add ASR Server page field descriptions

Use this page to add a new Automatic Speech Recognition (ASR) server to the Experience Portal system.

After you save the changes, the **System Monitor** web page and the **MPP Manager** web page on EPM display the **Restart needed** configuration status for the affected MPPs that are in the **Running** state. You must restart the affected MPPs before the applications can use the new ASR server.

This page contains the:

- [General Section](#) on page 383
- [MRCP Section](#) on page 385
- [SRTP Section](#) on page 386
- [Configured SRTP List group](#) on page 387

*** Note:**

The SRTP and the Configured SRTP List sections are available only if the Transport Protocol field is set to TLS.

General Section

Field	Description
Zone	The name of the zone where the ASR servers are configured. Select the name of the zone from the drop-down box. * Note: The Zone drop-down box appears only if you have created zones on your Experience Portal system. If you do not create any new zones, you do not see the drop-down box.
Name	The unique identifier for this ASR server on the Experience Portal system. If you are using a Nuance server, this name must be between 1 and 32 characters. * Note: Once you save the ASR server, this name cannot be changed.
Enable	Whether this ASR server is available for use by the Experience Portal system. The default is Yes, which means the server is available. * Note: Even if this field is set to No, you must restart the MPPs so that the system is prepared for this server. You do not need to restart the MPPs for the second time when the server is enabled.
Engine Type	The type of ASR software engine the server uses.

Table continues...

Field	Description
	The options are: • IBM WVS (permissive use only as per the Avaya End of Sales notice for IBM Websphere Voice Server (WSVS 5)) • Loquendo • Nuance The selection of an engine type in this field affects what the EPM displays as the defaults in the Base Port, New Connection per Session, Languages and RTSP URL fields.  Note: Once you save the ASR server, this type cannot be changed.
Network Address	The network address, or location, of the ASR server. This must be a valid network address in the form of a fully qualified hostname or an IP address. When you enter an address in this field, the EPM automatically inserts the address as part of the RTSP URL field.
Base Port	The port number on the ASR server to which requests for ASR services are sent. The default value for this field depends on which engine type and MRCP protocol you select: • For IBM WebSphere, the default is port 554 • For Loquendo, the default is 554 • For Nuance, the default is port 4900 The default port value changes to 5060 if you select MRCPV2 (TCP) protocol and to 5061 for MRCPV2 (TLS) protocol.  Important: These values are set to the default port numbers on the respective ASR servers. Unless you have manually changed the default settings on the ASR server, you should not have to change them here.
Total Number of Licensed ASR Resources	The total number of licensed ASR resources that will be used by the Experience Portal system. Experience Portal uses this information to determine the total number of ASR resources available to the Experience Portal system.
New Connection per Session	Whether Experience Portal opens a new connection for each call session. If you are using: • IBM WVS (permissive use only as per the Avaya End of Sales notice for IBM Websphere Voice Server (WSVS 5)), the default is Yes • Loquendo, the default is No • Nuance, the default is No

Table continues...

Field	Description
	 Important: You must use the above settings for this parameter.
Languages	Displays all the languages that ASR servers can use on this system. The selected languages are the ones that this ASR server can recognize. Select an individual entry in this list by clicking on it, or use Ctrl+Click and Shift+Click to select multiple entries. This list is prepopulated with the list of the languages that were available for the designated ASR engine type when Experience Portal was released. It is maintained in a special file on the Experience Portal system and is not automatically updated. You must verify that the languages you select here are actually installed and available on the target ASR server. You can add more languages to this list by clicking Configuration>Speech Servers from the EPM menu and selecting Customize in the ASR tab.  Note: If a speech application is configured to use more languages than are configured for any single ASR server, Experience Portal sends a <code>No ASR Resource</code> exception to the application. What happens then depends on the event handler that the application uses.
Listed Directory Number (LDN)	This field is only shown when you are logged into the EPM using the Avaya Services init account created when the Avaya Service accounts were configured. If you are logged into the EPM using the init account, enter the LDN number for this server as it appears in the Avaya Services database. If an LDN number is not specified for this server, Experience Portal uses the default value (000)000-0000.

MRCP Section

Field	Description
Ping Interval	When a speech application requires ASR resources, the MPP establishes a connection to the ASR server at the beginning of a session. Experience Portal sends periodic "heartbeat" messages to the ASR server to make sure the connection is not terminated prematurely. This field specifies the number of seconds the Experience Portal system waits between heartbeat messages. Enter an integer in this field. The default is 15.
Response Timeout	The number of seconds to allow for the ASR server to respond to a request for ASR resources before timing out. Enter an integer in this field. The default is 4.
Protocol	The MRCP protocol used for allocating the media processing server resources (ASR). The options are: • MRCP V1

Table continues...

Field	Description
	• MRCP V2 — This option is shown only when you select Nuance or Loquendo in the Engine Type field  Note: If you have installed Avaya Aura® Media Server on the system, the only option available is MRCP V1. The default is MRCP V1.
RTSP URL	The URL of the Real-Time Streaming Protocol (RTSP) server. The RTSP server is the network remote control for the Experience Portal multimedia servers. The default path depends on: • The network address as set in the Network Address field. If you change the network address, the default RTSP URL updates to reflect the change. • Which ASR engine type you have selected in the Engine Type field. If you change the engine type, the default RTSP URL updates to reflect the change.  Tip: If you want to change the default URL, make sure you specify the network address and select the ASR engine type first. Otherwise, Experience Portal will overwrite your changes when you enter a new network address or change the engine type.
Transport Protocol	This field is only shown when you select the MRCP V2 protocol under the MRCP section. The transport protocol used for transporting the real-time data. The options are: • TCP • TLS The default is TCP. The TLS option is shown only when you select Nuance in the Engine Type field.  Important: • If you select TLS, ensure the TLS certificate is installed on the EPM server. From the EPM main menu, select Security > Certificates > Trusted Certificates to view any currently installed certificates if one is available, or to install a new certificate. • Select System Maintenance > Log Viewer to check for speech server connection errors.
Listener Port	This field is only shown when you select the MRCP V2 protocol under the MRCP section. Enter an integer value in the range 1 – 65535. The default is 5060 if you select MRCPV2 (TCP) protocol and 5061 for MRCPV2 (TLS) protocol.

SRTP Section

 Note:

This group only appears if the **Transport Protocol** field is set to **TLS**.

Field	Description
Enable	The options are: • Yes : This connection uses SRTP. • No : This connection does not use SRTP.
Encryption Algorithm	The options are: • AES_CM_128: This connection uses 128 key encryption. • None: Messages sent through this connection are not encrypted.
Authentication Algorithm	The options are: • HMAC_SHA1_80: Authentication is done with HMAC SHA-1 which uses 80 bit key for the authentication. • HMAC_SHA1_32: Authentication is done with HMAC SHA-1 which uses 32 bit key for the authentication.
RTCP Encryption Enabled	The options are: • Yes: This connection uses RTP Control Protocol encryption. • No: This connection does not use RTP Control Protocol encryption.
RTP Authentication Enabled	The options are: • Yes: This connection uses Real-time Transport Protocol authentication. • No: This connection does not use Real-time Transport Protocol authentication.
Add	Adds the SRTP configuration to the Configured SRTP List .

Configured SRTP List group

This group displays any SRTP configurations defined for the connection.

 Note:

This group only appears if the Transport Protocol field is set to TLS.

Field	Description
Display list box	Displays the SRTP configurations for this connection.
Remove	Removes the association between the SRTP configuration selected in the display text box and the SIP connection.

Change ASR Server page field descriptions

Use this page to change an existing Automatic Speech Recognition (ASR) server to the Experience Portal system.

For all ASR changes except for Enable/Disable, after you save the changes, the **System Monitor** web page and the **MPP Manager** web page on EPM display the **Restart needed** configuration

status for affected MPPs that are in the **Running** state. You must restart the affected MPPs before applications can use the modified configuration.

*** Note:**

You do not need to restart the MPPs if the only change that you have made is to enable or disable the speech server.

This page contains the:

- [General Section](#) on page 388
- [MRCP Section](#) on page 390
- [SRTP Section](#) on page 392
- [Configured SRTP List group](#) on page 393

General Section

Field	Description
Zone	The name of the zone where the ASR servers are configured. Select the name of the zone from the drop-down box. * Note: The Zone drop-down box appears only if you have created zones on your Experience Portal system. If you do not create any new zones, you do not see the drop-down box.
Name	The unique identifier for this ASR server on the Experience Portal system. If you are using a Nuance server, this name must be between 1 and 32 characters. * Note: Once you save the ASR server, this name cannot be changed.
Enable	Whether this ASR server is available for use by the Experience Portal system. The default is Yes, which means the server is available. * Note: When you change this value from Yes to No, no new calls will use this server. However, any calls in progress may continue to use the speech server. You must let the ongoing calls to complete before taking the speech server out of service to avoid application errors.
Engine Type	The type of ASR software engine the server uses. The options are: • IBM WVS (permissive use only as per the Avaya End of Sales notice for IBM Websphere Voice Server (WSVS 5)) • Loquendo • Nuance The selection of an engine type in this field affects what the EPM displays as the defaults in the Base Port, New Connection per Session, Languages and RTSP URL fields.

Table continues...

Field	Description
	 Note: Once you save the ASR server, this type cannot be changed.
Network Address	The network address, or location, of the ASR server. This must be a valid network address in the form of a fully qualified hostname or an IP address. When you enter an address in this field, the EPM automatically inserts the address as part of the RTSP URL field.
Base Port	The port number on the ASR server to which requests for ASR services are sent. The default value for this field depends on which engine type and MRCP protocol you select: • For IBM WebSphere, the default is port 554 • For Loquendo, the default is 554 • For Nuance, the default is port 4900 The default port value changes to 5060 if you select MRCPV2 (TCP) protocol and to 5061 for MRCPV2 (TLS) protocol.  Important: These values are set to the default port numbers on the respective ASR servers. Unless you have manually changed the default settings on the ASR server, you should not have to change them here.
Total Number of Licensed ASR Resources	The total number of licensed ASR resources that will be used by the Experience Portal system. Experience Portal uses this information to determine the total number of ASR resources available to the Experience Portal system.
New Connection per Session	Whether Experience Portal opens a new connection for each call session. If you are using: • IBM WVS (permissive use only as per the Avaya End of Sales notice for IBM Websphere Voice Server (WSVS 5)), the default is Yes • Loquendo, the default is No • Nuance, the default is No  Important: You must use the above settings for this parameter.
Languages	Displays all the languages that ASR servers can use on this system. The selected languages are the ones that this ASR server can recognize. Select an individual entry in this list by clicking on it, or use Ctrl+Click and Shift+Click to select multiple entries.

Table continues...

Field	Description
	This list is prepopulated with the list of the languages that were available for the designated ASR engine type when Experience Portal was released. It is maintained in a special file on the Experience Portal system and is not automatically updated. You must verify that the languages you select here are actually installed and available on the target ASR server. You can add more languages to this list by clicking Configuration>Speech Servers from the EPM menu and selecting Customize in the ASR tab.  Note: If a speech application is configured to use more languages than are configured for any single ASR server, Experience Portal sends a <code>No ASR Resource</code> exception to the application. What happens then depends on the event handler that the application uses.
Listed Directory Number (LDN)	This field is only shown when you are logged into the EPM using the Avaya Services init account created when the Avaya Service accounts were configured. If you are logged into the EPM using the init account, enter the LDN number for this server as it appears in the Avaya Services database. If an LDN number is not specified for this server, Experience Portal uses the default value (000)000-0000.

MRCP Section

Field	Description
Ping Interval	When a speech application requires ASR resources, the MPP establishes a connection to the ASR server at the beginning of a session. Experience Portal sends periodic "heartbeat" messages to the ASR server to make sure the connection is not terminated prematurely. This field specifies the number of seconds the Experience Portal system waits between heartbeat messages. Enter an integer in this field. The default is 15.
Response Timeout	The number of seconds to allow for the ASR server to respond to a request for ASR resources before timing out. Enter an integer in this field. The default is 4.
Protocol	The MRCP protocol used for allocating the media processing server resources (ASR). The options are: • MRCP V1 • MRCP V2 — MRCPv2 option is shown only when you select Nuance or Loquendo in the Engine Type field.

Table continues...

Field	Description
	 Note: If you have installed Avaya Aura® Media Server on the system, the only option available is MRCP V1. The default is MRCP V1.
RTSP URL	The URL of the Real-Time Streaming Protocol (RTSP) server. The RTSP server is the network remote control for the Experience Portal multimedia servers. The default path depends on: • The network address as set in the Network Address field. If you change the network address, the default RTSP URL updates to reflect the change. • Which ASR engine type you have selected in the Engine Type field. If you change the engine type, the default RTSP URL updates to reflect the change.  Tip: If you change the default URL, make sure you specify the network address and select the ASR engine type first. Otherwise, Experience Portal will overwrite your changes when you enter a new network address or change the engine type.
Transport Protocol	This field is only shown when you select the MRCP V2 protocol under the MRCP section. The transport protocol used for transporting the real-time data. The options are: • TCP • TLS The default is TCP. The TLS option is shown only when you select Nuance in the Engine Type field.  Important: • If you select TLS, ensure the TLS certificate is installed on the EPM server. From the EPM main menu, select Security > Certificates > Speech Server Certificates to view any

Table continues...

Field	Description
	currently installed certificates if one is available, or to install a new certificate. • Select System Maintenance > Log Viewer to check for speech server connection errors.
Listener Port	This field is only shown when you select the MRCP V2 protocol under the MRCP section. Enter an integer value in the range 1 – 65535. The default is 5060 if you select MRCPV2 (TCP) protocol and 5061 for MRCPV2 (TLS) protocol.

SRTP Section

* Note:

This group only appears if the **Transport Protocol** field is set to **TLS**.

Field	Description
Enable	The options are: • Yes: This connection uses SRTP. • No: This connection does not use SRTP.
Encryption Algorithm	The options are: • AES_CM_128: This connection uses 128 key encryption. • None: Messages sent through this connection are not encrypted.
Authentication Algorithm	The options are: • HMAC_SHA1_80: Authentication is done with HMAC SHA-1 which uses 80 bit key for the authentication.. • HMAC_SHA1_32: Authentication is done with HMAC SHA-1 which uses 32 bit key for the authentication..
RTCP Encryption Enabled	The options are: • Yes: This connection uses RTP Control Protocol encryption. • No: This connection does not use RTP Control Protocol encryption.
RTP Authentication Enabled	The options are: • Yes: This connection uses Real-time Transport Protocol authentication.

Table continues...

Field	Description
	• No: This connection does not use Real-time Transport Protocol authentication.
Add	Adds the SRTP configuration to the Configured SRTP List .

Configured SRTP List group

This group displays any SRTP configurations defined for the connection.

*** Note:**

This group only appears if the Transport Protocol field is set to TLS.

Field	Description
Display list box	Displays the SRTP configurations for this connection.
Remove	Removes the association between the SRTP configuration selected in the display text box and the SIP connection.

TTS servers in Avaya Aura Experience Portal

TTS servers in Experience Portal

The Text-to-Speech (TTS) technology enables an Interactive Voice Response (IVR) system to render text content into synthesized speech output, according to algorithms within the TTS software. Avaya Aura® Experience Portal integrates with third-party TTS servers to provide this capability in speech applications.

When the Experience Portal Media Processing Platform (MPP) software receives a call, MPP starts the associated speech application that controls the call flow. If the speech application uses TTS resources, MPP also starts a session with a TTS server that is configured to use *all* the language and voice combinations defined in the speech application.

*** Note:**

You can switch languages within a single speech application, provided all the required languages are configured on the same TTS server. If a speech application is configured to use more language/voice combinations than are configured for any single TTS server, Experience Portal sends a `No TTS Resource` exception to the application. What happens then depends on the event handler that the application uses.

As the call progresses, MPP directs any requests for speech synthesis from the application to the designated TTS server. The TTS server then renders the text content as audible speech output.

 Note:

You need one TTS license for each call that requires TTS resources. The license is unavailable until the call is complete and becomes available to other calls after the current call ends.

Viewing existing TTS servers

Procedure

1. Log on to the EPM Web interface using an account with the Administration, Operations, or Maintenance user role.
2. From the EPM main menu, select **System Configuration > Speech Servers**.
3. Click the TTS tab.

The options displayed on this page depend on your user role.

Adding TTS servers

Procedure

1. Log on to EPM Web interface.

If Avaya Services is maintaining this system and you are an Avaya Services representative, log on to the EPM using the init EPM account created during the EPM software installation.

Otherwise, log on to the EPM using an account with the Administrator user role.
2. In the EPM main menu, select **System Configuration > Speech Servers**.
3. On the **TTS** tab of the Speech Servers page, click **Add**.
4. On the Add TTS Server page, enter the appropriate information and click **Save**.

If you logged in using the init account, ensure you enter the appropriate LDN number for the server in the **LDN** field. If you do not specify an LDN number, Experience Portal uses the default value (000)000-0000.

After you save the changes, the **System Monitor** webpage and the **MPP Manager** webpage on EPM display the **Restart Required** configuration status for MPPs that are in the **Running** state.

5. Restart only the MPP servers that belong to the affected zone.

Changing TTS servers

Procedure

1. Log on to EPM Web interface.

If Avaya Services is maintaining this system and you are an Avaya Services representative, log on to the EPM using the init EPM account created during the EPM software installation.

Otherwise, log on to the EPM using an account with the Administrator user role.

2. In the EPM main menu, select **System Configuration > Speech Servers**.
3. On the **TTS** tab on the Speech Servers page, click the server name in the **Name** column.
4. On the Change TTS Server page, enter the appropriate information and click **Save**.

If you logged in using the init account, make sure that the LDN number specified in the **LDN** field matches the information in the Avaya Services database for this server.

After you save the changes, the **System Monitor** webpage and the **MPP Manager** webpage on EPM display the **Restart Required** configuration status for MPPs that are in the **Running** state.

5. Restart only the MPP servers that belong to the affected zone.

Deleting TTS servers

Before you begin

Important:

All TTS-enabled applications on the Experience Portal system have associated TTS languages and voices. Before you delete a server, look at the **Voices** column. Ensure that all the languages or voices that the server supports are also supported by at least one other TTS server. If the server you plan to delete is the only one that supports a given language or voice, you must assign that language or voice to another TTS server. You can also change any applications that use the old language or voice.

Procedure

1. Log on to the EPM Web interface using an account with the Administration user role.
2. In the EPM main menu, select **System Configuration > Speech Servers**.
3. On the Speech Servers page, click the **TTS** tab.
4. For each TTS server that you want to delete, select the **Selection** check box to the left of the server name in the table.

Tip:

To delete all servers, select the **Selection** check box in the header row of the table. The system automatically selects all rows in the table.

5. Click **Delete**.

If the server is currently in use, Experience Portal deletes it after the server finishes processing any active calls.

After you save the changes, the **System Monitor** webpage and the **MPP Manager** webpage on EPM display the **Restart Required** configuration status for MPPs that are in the **Running** state.

- Restart only the MPP servers that belong to the affected zone.

Custom RealSpeak TTS dictionaries

Adding custom dictionaries for Nuance Vocalizer

An application that uses the Nuance Vocalizer server can use a custom dictionary. You can create as many custom dictionaries as you require. You can pass the dictionary as a vendor specific parameter `swtts.ssfrs_dict_enable` or define the dictionary using parameter dictionaries in the Nuance Vocalizer configuration file *baseline.xml*.

Procedure

- Create the custom dictionaries, as described in the Nuance Vocalizer documentation. Nuance Vocalizer doesn't support text-based dictionary format (DCT or TDC files) anymore, only binary user dictionary format, BDC or DCB files, is supported. The binary dictionary format has also changed.
- Convert the old text format dictionary (.dct or .tdc) to the new Vocalizer text format dictionary (.txt) with the following command:

```
dictmigrate -i <old-dictionary> -o <new_dictionary>
```

For example:

```
dictmigrate -i DictionaryName.dct -o DictionaryName.txt
```

Note:

Skip this step if you've already created a new text format dictionary.

- Compile text format dictionary (.txt) to binary format dictionary, .bdc or .dcb, with the following command:

```
dictcpl -o <BinaryFilename.bdc> <TextName.txt>
```

For example:

```
dictcpl -o DictionaryName.bdc DictionaryName.txt
```

If the user dictionary will be accessed from the application server through HTTP, you must map the dictionary extensions that you are using to the appropriate MIME type.

- On each Nuance Vocalizer HTTP server, open the *mime.types* file.

The default file location on Linux is in the `/etc/` directory. The default locations on Windows are:

- For a 32 bit system:

C:\Program Files\Apache Software Foundation\Apache2.2\conf

- For a 64 bit system:

C:\Program Files (x86)\Apache Software Foundation\Apache2.2\conf

5. Add the following lines to mime.types to associate text and binary dictionaries with the correct file extensions:

application/octet-stream bdc

application/octet-stream dcb

application/octet-stream dct

application/octet-stream tdc

6. Save and close the file.
7. Upload the custom dictionaries as described in the Nuance Vocalizer documentation.

Next steps

Associate the dictionary with the application.

Related links

[Associating a custom dictionary with an application through Experience Portal](#) on page 397

[Associating a custom dictionary with an application using the lexicon tag](#) on page 398

Associating a custom dictionary with an application through Experience Portal Procedure

1. Follow the steps described in [Adding a speech application to Experience Portal](#) on page 320 or [Changing speech application settings through Avaya Aura Experience Portal](#) on page 321.
2. When you get to the **TTS** section in the **Speech Parameters** group, go to the **TTS** field and:
 - If your Vocalizer server is on Linux, add the `switts.ssfters_dict_enable="file:///opt/ttsdict/<dictionary name>.<extension>"` parameter.
 - If your Vocalizer server is on Windows, add the `switts.ssfters_dict_enable="file://<drive>/<full path>/<dictionary name>.<extension>"` parameter.
3. Click **Save**.

Example

On Windows, if your dictionary is stored in a file called C:/custom/ttsdict/my_dictionary.bdc, specify the following:

`switts.ssfters_dict_enable="file://C:/custom/ttsdict/my_dictionary.bdc"`

Related links

[Adding custom dictionaries for Nuance Vocalizer](#) on page 396

Associating a custom dictionary with an application using the lexicon tag

About this task

Avaya Orchestration Designer does not currently support the `lexicon` tag, but if you want to use it in your custom application, place it within the `prompt` tag.

Procedure

If you are using:

- Linux, add the tag using the format `<lexicon uri="file:///<fully qualified file path>/<filename>.<extension>/">`
- Windows, add the tag using the format `<lexicon uri="file://<drive>/<full path>/<filename>.<extension>/">`

Example

On Windows you could specify:

```
<prompt bargin="false">
<lexicon uri="file://c:/mydictionary.dct/">
Welcome to Avaya Inc.
</prompt>
```

Related links

[Adding custom dictionaries for Nuance Vocalizer](#) on page 396

Sample custom dictionary for Vocalizer

The following shows a sample text-base dictionary for US English:

```
[Header]

[SubHeader]
Language = ENU
Content=EDCT_CONTENT_ORTHOGRAPHIC
Representation=EDCT_REPR_SZ_STRING
[Data]
DLL      "Dynamic Link Library"
Hello    "Welcome to the demonstration of the American English Text-to-Speech system."
TTS      "Text To Speech."
info     Information
```

```
[SubHeader]
Language = ENU
Content = EDCT_CONTENT_BROAD_NARROWS
Representation = EDCT_REPR_SZZ_STRING
[Data]
addr     // '@.dR+Es
avaya    // $. 'v@.j$
```

The `[Data]` sections contain the abbreviations or phonetic expressions you want to add to your custom dictionary.

Phonetic expressions allowed in a custom dictionary

Phonetic Symbols	Orthographic Example	Phonetic Example
i	f(ee)l	'fil
l	f(i)ll	'fll
E	f(e)ll	'fEl
@	c(a)t	'k@t
A	g(o)t	'gAt
^	c(u)t	'k^t
O	f(a)ll	'fOl
U	f(u)ll	'fUl#\
u	f(oo)l	'ful
E0	c(u)rt	'kE0R+t
e&l	f(ai)l	'fe&ll
O&l	f(oi)l	'fO&ll
a&l	f(i)le	'fa&ll
a&U	f(ou)l	'fa&Ul
o&U	g(oa)l	'go&Ul
j	(y)es	'jEs
w	(wh)y	'wa&l
R+	(r)ip	'R+lp
l	(l)ip	'llp
p	(p)it	'plt
t	(t)op	'tAp
k	(c)at	'k@t
b	(b)it	'blt
d	(d)ig	'dlg
g	(g)ot	'gAt
?	(i)llness	'?ll.nls
f	(f)at	'f@t
T	(th)in	'Tln
s	(s)eal	'sil
S	(sh)ip	'Slp
v	(v)at	'v@t
D	(th)en	'DEn
z	(z)eal	'zil
Z	lei(s)ure	'li.Z\$R+”

Table continues...

Phonetic Symbols	Orthographic Example	Phonetic Example
h	(h)at	'h@t
t&S	ca(tch)	'k@t&S
d&Z	(j)ourney	'd&ZE0R+.ni
m	(m)an	'm@n
n	(n)ut	'n^t
nK	ri(ng)	'R+InK
.	syllable break	
'	primary stress	
'2	secondary stress	
“	sentence accent	
#	silence (pause)	
_	word delimiter	
*.	end of declarative	
*,	comma	
*!	end of exclamation	
*?	end of question	
*.	semicolon	
*:	colon	
\$	(a)llow	\$. 'la&U
l%)	batt(le)	'b@.r6l%)
n%)	did(n')t	'dl.dn%)t
r6	bu(tt)er	'b^ .r6\$R+

TTS tab on the Speech Servers page field descriptions

Use this tab to view information about the Text-to-Speech (TTS) servers currently administered on the Experience Portal system, add a new TTS server, or change an existing server, and add or delete different voices and voice codes.

Note:

Any modifications to the speech servers requires the MPP(s) to be restarted for the affected zone(s).

Tip:

To sort the servers by any column, click the up arrow (sort ascending) or down arrow (sort descending) in the column header.

Column or Button	Description
Selection check box	Use this Selection check box to select which servers you want to delete.
Zone	The name of the zone where the TTS server is configured.
 Zones filter icon	To filter zones, click this icon located at the right side of the page. The system opens the Zone filter window for selecting one or more zones. * Note: The Zones filter icon only appears when you create new zones. If you do not create any new zones, you do not see the icon.
Name	The unique identifier for this TTS server on the Experience Portal system. To change the parameters for a TTS server, click the name of the server in the table. Experience Portal opens the Change TTS Server page.
Enable	Whether this TTS server is available for use by the Experience Portal system.
Network Address	The network address, or location, of the TTS server you want to use.
Engine Type	The type of TTS software engine the server uses.
MRCP	The MRCP protocol used for allocating the media processing server resources (TTS).
Base Port	The port number on the TTS server to which requests for TTS services are to be sent. The TTS server must be configured to receive and process requests through this port.
Total Number of Licensed TTS Resources	The total number of licensed TTS resources that is used by the Experience Portal system. Experience Portal uses this information to determine the total number of TTS resources available to the Experience Portal system.
Voices	The voices that this TTS server is configured to use.
Add	Opens the Add TTS Server page.
Delete	Deletes the TTS servers whose Selection check box has been checked. After you delete the servers, the System Monitor web page and the MPP Manager web page on EPM display the Restart needed configuration status for affected MPPs that are in the Running state. You must restart affected MPPs before the deleted TTS servers will be removed from the MPP's configuration.
Customize	Opens the TTS Custom Voices page. Using this page you can add custom voices and their respective language codes to the Text-to-Speech (TTS) servers currently administered on the Experience Portal system. You can also delete the existing custom configured voices and their respective language codes.

Add TTS Server page field descriptions

Use this page to add a new Text-to-Speech (TTS) server to the Experience Portal system.

After you save the changes, the **System Monitor** web page and the **MPP Manager** web page on EPM display the **Restart needed** configuration status for affected MPPs that are in the **Running** state. You must restart the affected MPPs before the applications can use the new TTS server.

This page contains the:

- [General Section](#) on page 402
- [MRCP Section](#) on page 404
- [SRTP Section](#) on page 405
- [Configured SRTP List group](#) on page 406

*** Note:**

The SRTP and the Configured SRTP List sections are available only if the Transport Protocol field is set to **TLS**.

General Section

Field	Description
Zone	The name of the zone where the TTS server is configured. Select the name of the zone from the drop-down box. * Note: The Zone drop-down box appears only if you have created zones on your Experience Portal system. If you do not create any new zones, you do not see the drop-down box.
Name	The unique identifier for this TTS server on the Experience Portal system. If you are using a Nuance server, this name must be between 1 and 32 characters. * Note: You cannot change this name once you save the TTS server.
Enable	Whether this TTS server is available for use by the Experience Portal system. The default is Yes, which means the server is available. * Note: Even if this field is set to No, you must restart the MPPs so that the system is prepared for this server. You do not need to restart the MPPs for the second time when the server is enabled.
Engine Type	The type of TTS software engine the server uses. The options are: • IBM WVS (permissive use only as per the Avaya End of Sales notice for IBM Websphere Voice Server (WSVS 5)) • Loquendo • Nuance The selection of an engine type in this field affects what the EPM displays as the defaults in the Base Port, New Connection per Session, Voices and RTSP URL fields as well.

Table continues...

Field	Description
	 Note: Once you save the TTS server, this engine type cannot be changed.
Network Address	The network address, or location, of the TTS server you want to use. This must be a valid network address in the form of a fully qualified hostname or an IP address. When you enter a network address in this field, the EPM automatically inserts the address as part of the RTSP URL field.
Base Port	The port number on the TTS server to which requests for TTS services are to be sent. The value for this field depends on the selected engine type and the MRCP protocol: • For IBM WebSphere, the default is port 554 • For Loquendo, the default is 554 • For Nuance, the default is port 4900 The default port value changes to 5060 if you select MRCPV2 (TCP) protocol and to 5061 for MRCPV2 (TLS) protocol.  Important: These values are set to the default port numbers on the respective TTS servers. Unless you have manually changed the default settings on the TTS server, you should not have to change them here.
Total Number of Licensed TTS Resources	The total number of licensed TTS resources that is used by the Experience Portal system. Experience Portal uses this information to determine the total number of TTS resources available to the Experience Portal system.
New Connection per Session	Whether Experience Portal establishes a new connection on the TTS server for each call session. If you are using: • IBM WVS (permissive use only as per the Avaya End of Sales notice for IBM Websphere Voice Server (WSVS 5)), set this to Yes • Loquendo, set this to No • Nuance, set this to No
Voices	Displays all the voices that TTS servers can use on this system. The selected voices are the ones that this TTS server is configured to use. Select an individual entry in this list by clicking on it, or use Ctrl+Click and Shift+Click to select multiple entries. This list is prepopulated with the list of the voices that were available for the designated TTS engine type when Experience Portal was released. It is maintained in a special file on the Experience Portal system and is not automatically updated. You must verify that the voices you select here are actually installed and available on the target TTS server.

Table continues...

Field	Description
	You can add more voices to this list by clicking Configuration>Speech Servers from the EPM menu and selecting Customize in the TTS tab.  Note: If a speech application is configured to use more language/voice combinations than are configured for any single TTS server, Experience Portal sends a No TTS Resource exception to the application. What happens then depends on the event handler that the application uses.
Listed Directory Number (LDN)	This field is only shown when you are logged into the EPM using the Avaya Services init account created when the Avaya Service accounts were configured. If you are logged into the EPM using the init account, enter the LDN number for this server as it appears in the Avaya Services database. If an LDN number is not specified for this server, Experience Portal uses the default value (000)000-0000.

MRCP Section

Field	Description
Ping Interval	When a speech application requires TTS rendering, the MPP establishes a connection to the TTS server at the beginning of a session. Experience Portal sends periodic "heartbeat" messages to the TTS server to make sure the connection is not terminated prematurely. This field specifies the number of seconds the Experience Portal system waits between the heartbeat messages. Enter an integer in this field. The default is 15.  Note: The value specified in this field does not affect TTS timeout.
Response Timeout	An integer value specifying the number of seconds to wait for the TTS server to respond to a request for TTS before timing out. The default is 4.
Protocol	The MRCP protocol used for allocating the media processing server resources (TTS). The options are: • MRCP V1 • MRCP V2 — MRCPv2 option is shown only when you select Nuance or Loquendo in the Engine Type field.  Note: If you have installed Avaya Aura® Media Server on the system, the only option available is MRCP V1. The default is MRCP V1.

Table continues...

Field	Description
RTSP URL	The URL of the Real-Time Streaming Protocol (RTSP) server. The RTSP server is the network remote control for the Experience Portal multimedia servers. The default path depends on which TTS engine type you select in the Engine Type field. If you change the Engine Type, this field also changes to a new default. To change the default path, first select the TTS engine type and then overwrite the default value in this field.
Transport Protocol	This field is only shown when you select the MRCP V2 protocol under the MRCP section. The transport protocol used for transporting the real-time data. The options are: • TLS • TCP The default is TCP. The TLS option is shown only when you select Nuance in the Engine Type field.  Important: • If you select TLS, ensure the TLS certificate is installed on the EPM server. From the EPM main menu, select Security > Certificates > Trusted Certificates to view any currently installed certificates if one is available, or to install a new certificate. • Select System Maintenance > Log Viewer to check for speech server connection errors.
Listener Port	This field is only shown when you select the MRCP V2 protocol under the MRCP section. Enter an integer value in the range 1 – 65535. The default is 5060 if you select MRCPV2 (TCP) protocol and 5061 for MRCPV2 (TLS) protocol.

SRTP Section

Note:

This group only appears if the **Transport Protocol** field is set to **TLS**.

Field	Description
Enable	The options are: • Yes : This connection uses SRTP. • No : This connection does not use SRTP.
Encryption Algorithm	The options are: • Yes : AES_CM_128: This connection uses 128 key encryption. • No : None: Messages sent through this connection are not encrypted.

Table continues...

Field	Description
Authentication Algorithm	The options are: • HMAC_SHA1_80: Authentication is done with HMAC SHA-1 which uses 80 bit key for the authentication. • HMAC_SHA1_32: Authentication is done with HMAC SHA-1 which uses 32 bit key for the authentication.
RTCP Encryption Enabled	The options are: • Yes: This connection uses RTP Control Protocol encryption. • No: This connection does not use RTP Control Protocol encryption.
RTP Authentication Enabled	The options are: • Yes: This connection uses Real-time Transport Protocol authentication. • No: This connection does not use Real-time Transport Protocol authentication.
Add	Adds the SRTP configuration to the connection.

Configured SRTP List group

This group displays any SRTP configurations defined for the connection.

 Note:

This group only appears if the Transport Protocol field is set to TLS.

Field	Description
Display list box	Displays the SRTP configurations for this connection.
Remove	Removes the association between the SRTP configuration selected in the display text box and the SIP connection.

Change TTS Server page field descriptions

Use this page to change an existing Text-to-Speech (TTS) server.

For all TTS changes except for Enable/Disable, after you save the changes, the **System Monitor** web page and the **MPP Manager** web page on EPM display the **Restart needed** configuration status for affected MPPs that are in the **Running** state. You must restart the affected MPPs before the applications can use the modified configuration.

*** Note:**

You do not need to restart the MPPs if the only change that you have made is to enable or disable the speech server.

This page contains the:

- [General Section](#) on page 407
- [MRCP Section](#) on page 409
- [SRTP Section](#) on page 411
- [Configured SRTP List group](#) on page 411

General Section

Field	Description
Zone	The name of the zone where the TTS server is configured. Select the name of the zone from the drop-down box. * Note: The Zone drop-down box appears only if you have created zones on your Experience Portal system. If you do not create any new zones, you do not see the drop-down box.
Name	The unique identifier for this TTS server on the Experience Portal system. If you are using a Nuance server, this name must be between 1 and 32 characters. * Note: You cannot change this name once you save the TTS server.
Enable	Whether this TTS server is available for use by the Experience Portal system. The default is Yes, which means the server is available. * Note: When you change this value from Yes to No, no new calls will use this server. However, any calls in progress may continue to use the speech server. You must let the ongoing calls to complete before taking the speech server out of service to avoid application errors.
Engine Type	The type of TTS software engine the server uses. The options are: • IBM WVS IBM WVS (permissive use only as per the Avaya End of Sales notice for IBM Websphere Voice Server (WSVS 5)) • Loquendo • Nuance The selection of an engine type in this field affects what the EPM displays as the defaults in the Base Port, New Connection per Session, Voices and RTSP URL fields as well.

Table continues...

Field	Description
	 Note: Once you save the TTS server, this engine type cannot be changed.
Network Address	The network address, or location, of the TTS server you want to use. This must be a valid network address in the form of a fully qualified hostname or an IP address. When you enter a network address in this field, the EPM automatically inserts the address as part of the RTSP URL field.
Base Port	The port number on the TTS server to which requests for TTS services are to be sent. The value for this field depends on the selected engine type and the MRCP protocol: • For IBM WebSphere, the default is port 554 • For Loquendo, the default is 554 • For Nuance, the default is port 4900 The default port value changes to 5060 if you select MRCPV2 (TCP) protocol and to 5061 for MRCPV2 (TLS) protocol.  Important: These values are set to the default port numbers on the respective TTS servers. Unless you have manually changed the default settings on the TTS server, you should not have to change them here.
Total Number of Licensed TTS Resources	The total number of licensed TTS resources that is used by the Experience Portal system. Experience Portal uses this information to determine the total number of TTS resources available to the Experience Portal system.
New Connection per Session	Whether Experience Portal establishes a new connection on the TTS server for each call session. If you are using: • IBM WVS IBM WVS (permissive use only as per the Avaya End of Sales notice for IBM Websphere Voice Server (WSVS 5)), set this to Yes • Loquendo, set this to No • Nuance, set this to No  Important: You must use the above settings for this parameter.
Voices	Displays all the voices that TTS servers can use on this system. The selected voices are the ones that this TTS server is configured to use. Select an individual entry in this list by clicking on it, or use <code>Ctrl+Click</code> and <code>Shift+Click</code> to select multiple entries. This list is prepopulated with the list of the voices that were available for the designated TTS engine type when Experience Portal was released. It is maintained in a special file on

Table continues...

Field	Description
	the Experience Portal system and is not automatically updated. You must verify that the voices you select here are actually installed and available on the target TTS server. You can add more voices to this list by clicking Configuration>Speech Servers from the EPM menu and selecting Customize in the TTS tab.  Note: If a speech application is configured to use more language/voice combinations than are configured for any single TTS server, Experience Portal sends a <code>No TTS Resource</code> exception to the application. What happens then depends on the event handler that the application uses.
Listed Directory Number (LDN)	This field is only shown when you are logged into the EPM using the Avaya Services init account created when the Avaya Service accounts were configured. If you are logged into the EPM using the init account, enter the LDN number for this server as it appears in the Avaya Services database. If an LDN number is not specified for this server, Experience Portal uses the default value (000)000-0000.

MRCP Section

Field	Description
Ping Interval	When a speech application requires TTS rendering, the MPP establishes a connection to the TTS server at the beginning of a session. Because there is no way to know when the connection will be used during the session, Experience Portal sends periodic "heartbeat" messages to the TTS server to make sure the connection is not terminated prematurely. This field specifies the number of seconds the Experience Portal system waits between the heartbeat messages. Enter an integer in this field. The default is 15.  Note: The value specified in this field does not affect TTS timeout.
Response Timeout	An integer value specifying the number of seconds to wait for the TTS server to respond to a request for TTS before timing out. The default is 4.
Protocol	The MRCP protocol used for allocating the media processing server resources (TTS). The options are: • MRCP V1

Table continues...

Field	Description
	• MRCP V2 — MRCPv2 option is shown only when you select Nuance or Loquendo in the Engine Type field.  Note: If you have installed Avaya Aura® Media Server on the system, the only option available is MRCP V1. The default is MRCP V1.
RTSP URL	The URL of the Real-Time Streaming Protocol (RTSP) server. The RTSP server is the network remote control for the Experience Portal multimedia servers. The default path depends on which TTS engine type you select in the Engine Type field. If you change the Engine Type, this field also changes to a new default. To change the default path, first select the TTS engine type and then overwrite the default value in this field.
Transport Protocol	This field is only shown when you select the MRCP V2 protocol under the MRCP section. The transport protocol used for transporting the real-time data. The options are: • TCP • TLS The default is TCP. The TLS option is shown only when you select Nuance in the Engine Type field.  Important: • If you select TLS, ensure the TLS certificate is installed on the EPM server. From the EPM main menu, select Security > Certificates > Speech Server Certificates to view any currently installed certificates if one is available, or to install a new certificate. • Select System Maintenance > Log Viewer to check for speech server connection errors.
Listener Port	This field is only shown when you select the MRCP V2 protocol under the MRCP section. Enter an integer value in the range 1 – 65535. The default is

Table continues...

Field	Description
	5060 if you select MRCPV2 (TCP) protocol and 5061 for MRCPV2 (TLS) protocol.

SRTP Section

* Note:

This group only appears if the **Transport Protocol** field is set to **TLS**.

Field	Description
Enable	The options are: • Yes : This connection uses SRTP. • No : This connection does not use SRTP.
Encryption Algorithm	The options are: • AES_CM_128: This connection uses 128 key encryption. • None: Messages sent through this connection are not encrypted.
Authentication Algorithm	The options are: • HMAC_SHA1_80: Authentication is done with HMAC SHA-1 which uses 80 bit key for the authentication. • HMAC_SHA1_32: Authentication is done with HMAC SHA-1 which uses 32 bit key for the authentication.
RTCP Encryption Enabled	The options are: • Yes : This connection uses RTP Control Protocol encryption. • No : This connection does not use RTP Control Protocol encryption.
RTP Authentication Enabled	The options are: • Yes : This connection uses Real-time Transport Protocol authentication. • No : This connection does not use Real-time Transport Protocol authentication.
Add	Adds the SRTP configuration to the Configured SRTP List .

Configured SRTP List group

This group displays any SRTP configurations defined for the connection.

* Note:

This group only appears if the **Transport Protocol** field is set to **TLS**.

Field	Description
Display list box	Displays the SRTP configurations for this connection.
Remove	Removes the association between the SRTP configuration selected in the display text box and the SIP connection.

Chapter 15: Application Server Manager

Application Server Manager in Avaya Aura® Experience Portal

The Application Server web page in the Experience Portal Manager (EPM) allows you to start and stop the Application server co-resident with the primary EPM.

You can also use this page to navigate to the Tomcat Manager web interface that allows users to deploy, undeploy, start and stop applications on the Application server.

To access the Tomcat Manager web interface from EPM, you need a Tomcat user name which is created during the Tomcat application installation.

 Important:

The Application Server page is displayed only when Avaya Aura® Experience Portal is installed on a single server and has a Tomcat application server installed on it. For details, see the *Optional: Installing a Tomcat application server* topic in the *Implementing Avaya Aura® Experience Portal on a single server* guide.

Application Server page field descriptions

Use this page to start and stop the application server co-resident with the primary Experience Portal Manager (EPM). You can also use this page to navigate to the Tomcat Manager web page which allows users to deploy, undeploy, start and stop applications on the application server.

 Important:

The Application Server page is displayed only when Experience Portal is installed on a single server and has a Tomcat application server installed on it. For details, see the *Optional: Installing a Tomcat application server* topic in the *Implementing Avaya Aura® Experience Portal on a single server* guide.

This page contains the:

- [Application Server table](#) on page 414
- [State Commands group](#) on page 414

Application Server table

Field	Description
Selection check box	Indicates the application servers in the Experience Portal system. To select all application servers, click the check box in the header row.
Host Address	The application server host address. To access the Tomcat Manager web page, click the host address of the server. Experience Portal displays the Tomcat Manager web page in a separate window.  Note: The link to the Tomcat Manager web page is enabled only when the application server state is Running.
State	The operational state of the application server.

State Commands group

 Note:

These buttons are greyed out until you select one or more application servers using the Selection check box in the Application Server table.

Button	Description
Start	Starts the application server and changes the operational state to Running.
Stop	Stops the application server and changes the operational state to Stopped.  Note: All applications available on the application server are stopped.

Starting Application server

Procedure

1. From the EPM main menu, select **System Management > Application Server**.
2. Click the Selection check box next to the Application server you want to start.
3. Click **Start** in the **State Commands** group and confirm your selection when prompted.
4. After a few minutes, click **Refresh** and verify that the **State** is **Running**.

Logging in to the Tomcat Manager web interface from Avaya Aura® Experience Portal

The Experience Portal Manager (EPM) web interface allows you to navigate to the *Tomcat Web Application Manager* page which allows users to deploy, remove, start and stop applications on the application server.

About this task

The login account for accessing the Tomcat Manager web interface is different from your EPM user name.

Procedure

1. Log into the EPM web interface.
2. From the EPM main menu, select **System Management > Application Server**.
3. Click the host address of the server.
Opens a new browser window and displays the login dialog box for the Tomcat Manager web interface.
4. On the **Tomcat Manager** login page, enter your Tomcat user name in the **User Name** field.
The user name must match an existing Tomcat account name exactly, including case.
5. In the **Password** field, enter your login password.
The password must match the password assigned to the specified user name exactly, including case.
6. Click **OK**.
If your user name and password:
 - Match an authorized Tomcat user account, the Tomcat Web Application Manager page is displayed in a new browser window.
 - Do not match an authorized Tomcat user account, the login dialog box is displayed again.

Chapter 16: Managed Applications in Avaya Aura Experience Portal

Managed applications in Avaya Aura® Experience Portal overview

Managed applications are special classes of applications which derive the licensing, administration framework, manageability and accessibility from the Avaya Aura® Experience Portal management system (EPM).

Experience Portal is the single point of management for managed applications.

For example, Avaya Proactive Outreach Manager is a managed application which runs on Experience Portal. Avaya Proactive Outreach Manager uses the Experience Portal platform to create and deliver automated campaigns to support Finance, Marketing, and Healthcare needs for automation.

Note:

For more information, see the documentation delivered with the managed applications.

Experience Portal provides the following capabilities for managed applications:

- [Acquire and maintain licenses](#) on page 417
- [Add managed application to EPM](#) on page 417
- [Role-based access](#) on page 418
- [Multi-tenancy](#) on page 418
- [Logging and Alarming](#) on page 418
- [Reports related to managed applications](#) on page 419

Managed applications related menus, web pages and associated online help are installed and integrated into the EPM by the managed application installer.

Acquire and maintain licenses

The managed application installer adds the licensing information to the licensing tables in the Experience Portal database. Experience Portal retrieves this information from the database and acquires the licenses for the managed applications from the license server.

Experience Portal also handles the license expiry and grace period for the managed application licenses. Experience Portal provides a thirty day grace period under the following conditions:

- Managed application is installed and the managed application license is not available on the license server. The licensed values allowed during the grace period are specified by the managed application during installation.
- License server is no longer available or accessible from the EPM.
- Managed application license has expired.

 Note:

Experience Portal generates appropriate alarms for these conditions.

Experience Portal generates an alarm, seven days prior to the managed application license expiry.

Once a grace period is initiated, EPM generates an alarm every day till the issue is resolved or the grace period expires.

Managed applications periodically retrieve the license information from the EPM and take appropriate actions based on the licensed values.

When the grace period expires:

- The licensed features of the managed application are reset to zero.
- The configuration and management web pages of managed application are still available in EPM but they do not function.

You can view and configure the license details of the managed application from the Licensing web page in EPM.

For more information, see the documentation delivered with the managed application.

Add managed application to EPM

The managed application installer adds additional pages and fields to the EPM. The user roles determine which pages and fields the user can see and what actions the user can perform. A managed application may add additional fields to existing EPM pages, or new pages with new fields.

A managed application may also add an additional application type during installation. This application type will be available in the **EPM>Add Application** page as an option in the **Type** field.

For more information about the pages and fields related to managed application, see the documentation delivered with the managed application.

*** Note:**

You must log in to the EPM web interface on the primary EPM server to perform any managed application related administrative tasks.

Role-based access

The managed application installer may add new features to existing roles or additional roles and features to the EPM.

Experience Portal enables you to create custom roles which are based on existing roles and managed application roles. The user roles determine which pages the user can see and what actions the user can perform in EPM.

You can create new users and assign them managed application based roles as well as Experience Portal based roles.

For more information on roles and features related to managed application, see the documentation delivered with the managed application.

*** Note:**

The EPM administrator role can access managed application features when the managed application is installed on Experience Portal.

Multi-tenancy

The multi-tenancy feature in Experience Portal allows the configuration data and reports maintained by the Experience Portal Manager (EPM) to be segmented for multiple organizations. Managed applications can take advantage of the multi-tenancy feature and segment their data for multiple organizations.

For more information on multi-tenancy, see [Organization level access in Avaya Aura Experience Portal](#) on page 126.

For more information on multi tenancy feature related to managed applications, see the documentation delivered with the managed application.

Logging and Alarming

Avaya Aura® Experience Portal enables you to view audit logs, event logs, and alarms generated by managed applications.

The managed application installer may add the following additional categories:

- Audit log categories. These categories are available in the **Audit Log Viewer** EPM web page along with the EPM audit log categories and can be used for filtering the audit logs.
- Event log categories. These categories are available in the **Log Viewer** EPM web page along with the EPM event log categories and can be used for filtering the event logs.
- Alarm categories. These categories are available in the **Alarm Manager** EPM web page along with the EPM alarm categories and can be used for filtering the alarms.

 Note:

The retention of the audit logs, event logs, and alarms is based on the purge and retention settings specified in the **Alarm/Log Options** EPM web page.

For more information, see the documentation delivered with the managed application.

Reports related to managed applications

The managed application installer adds additional standard reports to Experience Portal. These additional standard reports are available in the **Standard Reports** EPM web page. You can create and schedule custom reports based on these standard reports.

For more information about standard reports related to managed applications, see the documentation delivered with the managed application.

Chapter 17: Intelligent Customer Routing (ICR) functionality in Avaya Aura Experience Portal

Intelligent Customer Routing overview

Intelligent Customer Routing (ICR) derives the licensing, administration framework, manageability and accessibility from Avaya Aura® Experience Portal.

ICR uses the Experience Portal platform to identify and determine caller intent through simple, intelligent, customer conversations using speech and self service, and, when necessary, routes the call to a relevant call center across applicable geographic locations. Using Avaya Call Center Best Services Routing (BSR) infrastructure, ICR routes calls to the most preferred resource available. Once a route decision is made, the call is either transferred directly to the selected location, or a virtual call is placed and parked on the Experience Portal and enhanced wait treatment is performed.

 Note:

For more information, see the ICR documentation library posted on the Avaya support site at <http://support.avaya.com> under the appropriate release in the Intelligent Customer Routing product category.

Experience Portal provides the following capabilities for ICR:

- [Acquire and maintain licenses](#) on page 421
- [Configure ICR in EPM](#) on page 421
- [Role-based access](#) on page 422
- [Multi-tenancy](#) on page 422
- [Database Backup and Restore](#) on page 422
- [Logging and Alarming](#) on page 423
- [Reports related to ICR](#) on page 423
- SIP connection configuration: ICR leverages existing SIP connection configuration available in EPM.

ICR related menus, web pages and associated online help are installed and integrated into the EPM by the ICR installer.

Acquire and maintain licenses

The ICR installer adds the licensing information to the licensing tables in the Experience Portal database. Experience Portal retrieves this information from the database and acquires the licenses for ICR from the license server.

Experience Portal also handles the license expiry and grace period for the ICR licenses. Experience Portal provides a thirty day grace period under the following conditions:

- ICR is installed and the ICR license is not available on the license server. The licensed values allowed during the grace period are specified by ICR during installation.
- License server is no longer available or accessible from the EPM.
- ICR license has expired.

 Note:

Experience Portal generates appropriate alarms for these conditions.

Experience Portal generates an alarm, seven days prior to the ICR license expiry.

Once a grace period is initiated, EPM generates an alarm every day till the issue is resolved or the grace period expires.

ICR periodically retrieve the license information from the EPM and take appropriate actions based on the licensed values.

When the grace period expires:

- The licensed features of ICR are reset to zero.
- The configuration and management web pages of ICR are still available in EPM but they do not function.

You can view and configure the license details of ICR from the Licensing web page in EPM.

 Note:

For more information, see the ICR documentation library posted on the Avaya support site at <http://support.avaya.com> under the appropriate release in the Intelligent Customer Routing product category.

Configure ICR in EPM

The ICR installer adds new pages and fields to the EPM. The user roles determine which pages and fields the user can see and what actions the user can perform.

ICR adds an additional application type during installation. This application type is available in the **EPM > System Configuration > Applications > Add Application** page as an option in the **Type** field.

You must log in to the EPM web interface on the primary EPM server to perform any ICR related administrative tasks.

*** Note:**

For more information, see the ICR documentation library posted on the Avaya support site at <http://support.avaya.com> under the appropriate release in the Intelligent Customer Routing product category.

Role-based access

The ICR installer adds new features to existing roles and an additional role to the EPM.

Experience Portal enables you to create custom roles which are based on existing roles and managed application roles. The user roles determine which pages the user can see and what actions the user can perform in EPM.

You can create new users and assign them ICR based roles as well as Experience Portal based roles.

*** Note:**

For more information, see the ICR documentation library posted on the Avaya support site at <http://support.avaya.com> under the appropriate release in the Intelligent Customer Routing product category.

The EPM administrator role can access ICR features when ICR is installed on Experience Portal.

Multi-tenancy

The multi-tenancy feature in Experience Portal allows the configuration data and reports maintained by the Experience Portal Manager (EPM) to be segmented for multiple organizations. ICR can take advantage of the multi-tenancy feature and segment the data for multiple organizations.

For more information on multi-tenancy, see [Organization level access in Avaya Aura Experience Portal](#) on page 126.

Database Backup and Restore

The System Backup feature in EPM enables you to regularly back up the data in a local Experience Portal database and the associated properties files. The System Backup feature takes the EP and ICR database backup

For more information, see [System Backup Overview](#) on page 207.

The Database Restore utility enables you to restore the Experience Portal database, that includes ICR data, from a backup created through the System Backup web page in EPM.

For more information, see [Database Restore utility and system backup](#) on page 217.

Logging and Alarming

Experience Portal enables you to view audit logs, event logs, and alarms generated by ICR.

The ICR installer adds the following additional categories:

- Audit log categories. These categories are available in the **Audit Log Viewer** EPM web page along with the EPM audit log categories and can be used for filtering the audit logs.
- Event log categories. These categories are available in the **Log Viewer** EPM web page along with the EPM event log categories and can be used for filtering the event logs.
- Alarm categories. These categories are available in the **Alarm Manager** EPM web page along with the EPM alarm categories and can be used for filtering the alarms.

 Note:

The retention of the audit logs, event logs, and alarms is based on the purge and retention settings specified in the **Alarm/Log Options** EPM web page.

 Note:

For more information, see the ICR documentation library posted on the Avaya support site at <http://support.avaya.com> under the appropriate release in the Intelligent Customer Routing product category.

Reports related to ICR

The ICR installer adds additional standard reports to Experience Portal. These additional standard reports are available in the **Standard Reports** EPM web page. You can create and schedule custom reports based on these standard reports.

 Note:

For more information, see the ICR documentation library posted on the Avaya support site at <http://support.avaya.com> under the appropriate release in the Intelligent Customer Routing product category.

Chapter 18: Integrated Voice and Video Response

The Integrated Voice and Video Response (IVVR) is an extension to the voice support capabilities of the Avaya Aura® Experience Portal system. It combines the standard Experience Portal audio processing with video streaming between two endpoints.

IVVR uses the 3G video enabled devices and SIP-based video phones to deliver the multi-modal communication capabilities to the end users. IVVR supports video streaming in addition to static and dynamic menu creation and audio prompting.

You can use following VoiceXML tags when designing a video enabled application:

- `<media>`: This tag enables you to specify new definition of non-audio media content such as video.
- `<seq>`: This is a control tag used to queue up media files for playback in a sequential order.
- `<para>`: This is a control tag used to queue up items to be played in parallel.

 Note:

The video is supported only in SIP based deployments.

The video server that supports the IVVR is available on the MPP. However, to use the IVVR feature, you must have the **Video Server Connections** license. This license enables or disables the support for the video server.

You can configure the IVVR feature by specifying the **Video Enable** option value to **Yes** or **No** while configuring the applications. You must set the license value to a non-zero number to enable the video server and to zero to disables it.

Chapter 19: Avaya Aura Experience Portal system events

Viewing Avaya Aura® Experience Portal system status

Procedure

1. Log on to the EPM Web interface using an account with the Administration, Operations, or Maintenance user role.
2. From the EPM main menu, select **Real-Time Monitoring > System Monitor**.
3. On the System Monitor page, if you want to:
 - View the overall status for all Avaya Aura® Experience Portal systems in the network, go to the Summary tab.
 - View the status for the EPM and all MPPs in the local Experience Portal system, go to the <System name> Details tab.
 - View detailed information for an MPP, go to the <System name> Details tab and click the name of the MPP in the **Server Name** column.
 - View detailed alarm information, click any yellow or red alarm indicator.

Tip:

The information on this page refreshes automatically if you leave the browser window open.

4. If desired, check the resources being used by all current applications in the system by selecting **Real-Time Monitoring > Active Calls** from the EPM main menu.

Related links

[Summary tab on the System Monitor page field descriptions](#) on page 314

[<System name> Details tab on the System Monitor page field descriptions](#) on page 309

Summary tab on the System Monitor page field descriptions

Use this tab for a consolidated view of the health and status of the Experience Portal system. The information on this page refreshes automatically if you leave the browser window open.

*** Note:**

If the EPM server needs to be restarted, Experience Portal displays the message "EPM needs to be restarted." in red text just above the system status table.

Column	Description
 Zones filter icon	To filter zones, click this icon located at the right side of the page. The system opens the Zone filter window for selecting one or more zones. * Note: The Zones filter icon only appears when you create new zones. If you do not create any new zones, you do not see the icon.
System Name	The name of the Experience Portal system, as specified in the Avaya Aura Experience Portal Name field on the EPM Settings page. If your installation consists of multiple Experience Portal systems that share a common external database, this column contains: - The name of the local system that you currently logged into. The Type for this system will always be EP. - The name of the another Experience Portal system in the shared external database. The Type will always be Remote EP. Click the system name to log into the EPM Web interface for the remote system.
Type	If your installation consists of a single Experience Portal system, the type will always be EP. If your installation consists of multiple Experience Portal systems that share a common external database, this column contains: EP: This type indicates that you are currently logged into the EPM for this system. Any system commands you issue will affect this EPM and any media servers assigned to this system. The <System name> Details tab for this system shows the assigned media servers. Remote EP: This type indicates that this is an active Experience Portal system, but it is <i>not</i> the system you are currently logged into. To affect the EPM or media servers assigned to a remote system, you must first log into that system by clicking the remote system name in the System Name column.
State	Displays the operational state of the Experience Portal system. The options are: Active: This Experience Portal system is updating its information in the database on a regular basis. Inactive: A remote Experience Portal system of Type is Remote EP is no longer updating information in the shared database. Click the system name to log into the EPM on that system and troubleshoot the problem locally. Stale: It has been over an hour since this Experience Portal system has updated its summary information in the database. Create an Alarm report to view the error messages generated by the system.

Table continues...

Column	Description
	 Note: If you are using an external database, the time difference between your Experience Portal systems is too great. For more information, see the <i>Time Synchronization between external database and EPM servers</i> topic in the <i>Troubleshooting Avaya Aura® Experience Portal</i> guide.  Tip: To view the date and time that this state was first reached and on which it was last changed, hover the mouse over this column.
Call Capacity	This field displays: • Current: The number of calls that can be currently handled by the system. • Licensed: The number of licenses allocated to this system. • Maximum: The maximum number of simultaneous calls that the media servers in this system can handle. This value is obtained by adding together the maximum number of calls set for each of the media servers in the system. This value can be larger than the number of licenses allocated to the system, but it should never be smaller. If it is smaller, then some of your licenses will never be used.
Active Calls	When the number of active calls (In or Out) is greater than zero, the number displayed on the System Monitor is displayed as a link. Clicking on this link takes the user to the Active Calls web page.
Alarms	This field displays one of the following alarm status indicators: • Green: There are no active major or critical alarms • Yellow: There are one or more active minor alarms • Red: There are one or more active major or critical alarms For a system whose Type is EP, you can click any red or yellow alarm indicator to view an associated Alarm report. To view the alarms for a system whose Type is Remote EP, you must first log into the remote system by clicking the name in the System Name column.

Related links

[Viewing Avaya Aura Experience Portal system status](#) on page 425

<System name> Details tab on the System Monitor page field descriptions

Use this tab for a detailed view of the health and status of the EPM and each MPP in the Experience Portal system named in <System Name>. The information on this page refreshes automatically if you leave the browser window open.

*** Note:**

If the EPM server needs to be restarted, Experience Portal displays the message "EPM needs to be restarted." in red text just above the system status table.

Column	Description
 Zones filter icon	To filter zones, click this icon located at the right side of the page. The system opens the Zone filter window for selecting one or more zones. * Note: The Zones filter icon only appears when you create new zones. If you do not create any new zones, you do not see the icon.
Zone	The zone where the EPM and the MPP servers are configured.
Server Name	The options are: • The name of the EPM server. Click this name to view the <EPM Name> Details page. • The name of an MPP running on the system. Click this name to view the <MPP name> Details page. • <EPM Name>/<MPP Name>, if an MPP resides on the same server as the EPM. Click this name to view the <MPP name> Details page.
Type	The options are: • EPM: The Experience Portal Manager • MPP: A Media Processing Platform + Tip: To verify whether the associated server is a primary or auxiliary EPM server, hover the mouse over the EPM field.
Mode	The operational mode of the Media Server. The options are: • Online: The Media Server is available. • Offline: The Media Server is unavailable and is not being polled by the EPM server. • Test: (MPP only) The Media Server is available to handle calls made to one of the defined H.323 maintenance stations. + Tip: To view the date and time that this mode was first reached, hover the mouse over this column.
State	The operational state of the Media Server. The options are: • Booting: The Media Server is in the process of restarting and is not yet ready to take new calls. • Degraded: The Media Server is running but it is not functioning at full capacity. • Error: The Media Server has encountered a severe problem and cannot recover.

Table continues...

Column	Description
	• Halted: The Media Server is no longer responding to heartbeats because it received a halt command. • Halting: The Media Server is responding to heartbeats but is not taking new calls. • Need Configuration: An Email or SMS processor residing on the Media Server has not yet been configured. • Need Connections: No connections (SMPP or HTTP) have been configured or assigned to an Email/SMS processor residing on the Media Server. • Never Used: The Media Server has never successfully responded to a heartbeat request. • Not Installed: The Media Server is missing files required for heartbeat requests to occur. • Not Responding: The Media Server is not responding to heartbeat requests and it has not received a Restart or halt command. • Partially Running: (EPM only) The Media Server is in the process of starting up, and not all individual components of the service, for example: Tomcat, SL, ActiveMQ, have come up yet. • Rebooting: The Media Server is responding to heartbeats but is not taking new calls. • Recovering: The Media Server has encountered a problem and is attempting to recover. • Restart Needed: This state is most often reached when the Media Server has encountered a problem that it cannot recover from and it requires a manual restart. However, it can also appear for an MPP when the EPM software has been upgraded and the MPP software has not. In that case, the state should update automatically when you upgrade the MPP software. • Running: The Media Server is responding to heartbeat requests and is accepting new calls. • Starting: The Media Server is responding to heartbeats but not taking new calls because it is transitioning from the Stopped state to the Running state. • Stopped: The Media Server is responding to heartbeats but is not taking new calls. The Media Server enters this state while it initializes after it restarts or when a stop command is received. • Stopping: The Media Server is responding to heartbeats but is not taking new calls. • Unknown: The Media Server is in the Offline mode.  Tip: To view the date and time that this state was first reached, hover the mouse over this column.
Active Command	This column is displayed if one or more Media Servers are currently in transition from their current state to a new user-requested state.

Table continues...

Column	Description
	For each transitional Media Server, this column displays the requested, or final, state. For any other Media Servers in the system, this field displays None .
Config	The configuration state of the Auxiliary EPM/MPP. The options are: • Need certificates: The Primary EPM certificate must be downloaded to the Auxiliary EPM/MPP by running the <code>setup_vpms.php</code> script on the Auxiliary EPM/MPP. • Need ports: The MPP has been configured and is waiting for ports to be assigned. • None: The MPP has never been configured. • OK: The Auxiliary EPM/MPP is currently operating using the last downloaded configuration. • Restart needed: The MPP must be restarted to enable the downloaded configuration. • Reboot needed: The MPP must be rebooted to enable the downloaded configuration. • Upgrade needed: The Auxiliary EPM must be upgraded to the same version of the software as on the Primary EPM. • Unknown: The MPP is either not responding or is in the Offline mode.
Call Capacity	This field displays: • Current: The number of calls that can be currently handled by the system. • Licensed: The number of licenses allocated to this system. • Maximum: The maximum number of simultaneous calls that the MPPs in this system can handle. This value is obtained by adding together the maximum number of calls set for each of the MPPs in the system.  Note: This value can be larger than the number of licenses allocated to the system, but it should never be smaller. If it is smaller, then some of your licenses will never be used.
Active Calls	This field displays: • In: The number of active incoming calls in the system. • Out: The number of active outgoing calls in the system. Clicking the number displayed under the Active Calls In column displays all the active incoming calls for the media servers. Clicking the number displayed under the Active Calls Out column displays all the active outgoing calls for the media servers.
Calls Today	The number of calls handled during the current day.
Alarms	The alarm status indicators for the EPM, each MPP, and the overall Experience Portal system.

Table continues...

Column	Description
	The options are: • Green: There are no active major or critical alarms • Yellow: There are one or more active minor alarms • Red: There are one or more active major or critical alarms  Tip: You can click any red or yellow alarm indicator to view the Alarm report for that system.
Summary	The total number of calls based on Contact Summary and Active Calls. On the Summary line, clicking the number displayed under the Active Calls In column displays all the active incoming calls for the media servers. On the Summary line, clicking the number displayed under the Active Calls Out column displays all the active outgoing calls for the media servers.

Email, HTML and SMS processors section

Column	Description
Zone	The zone where the Email and SMS processors are configured. The summary reports within a zone are: • Email Summary: Summary of the incoming and outgoing email messages in the last 24 hours. • SMS Summary: Summary of the incoming and outgoing SMS messages in the last 24 hours. • HTML Summary: Summary of the incoming HTML messages in the last 24 hours.
Server Name	The name of the EPM on which the Email, SMS and HTML processors are configured.
Type	The options are: • Email processor • HTML processor • SMS processor
State	The operational state of the email/SMS/HTML processors. The options are: • Not Running: The server is either stopped or not started yet. • Starting: The server start request is initiated, and is in the process of initialization. • Running: The server is up and functional. • Stopping: The server shutdown is requested. • Need Configuration: The server does not find configuration. • Need Connections: The server has configuration but does not have any connections assigned or configured.

Table continues...

Column	Description
	• Degraded: The server has configuration and connections. However, some or all connections are not working. • Error: The server data returned has been deemed "stale" (no new data retrieved after a period of 3 minutes), or 2) unexpected return code retrieved from a poll to server. • Stopped: The server is stopped.
Usage (Today)	Displays the number of messages processed during the current day. The Summary row also shows the maximum number of messages allowed per day.
Messages (Last 24 hours)	The options are: • Incoming: The number of incoming messages processed in the last 24 hours. • Outgoing: The number of outgoing messages processed in the last 24 hours.  Note: Clicking on the Last 24 hours text, lets the user to change the number of messages displayed for the following time frames: • Last hour • Last 3 hours • Last 6 hours • Last 12 hours • Last 24 hours
Timeline Graph 	Displays a graph icon. Clicking this graph icon displays the number of messages processed in a graphical form.

Related links

[Viewing Avaya Aura Experience Portal system status](#) on page 425

Events and alarms

Events and alarms

The Experience Portal Manager (EPM) or Media Processing Platform (MPP) software generates an *event* when it encounters a:

- Minor problem
- Change to the system
- Change to system resources

If a specific event is repeated several times in succession, or if the EPM or an MPP encounters a serious problem, the system raises an *alarm*. All alarms have an associated event, but not all events have an associated alarm.

Events and alarms:

- Are divided into categories based on the component that generated them
- Are assigned a severity so that you can quickly find the critical issues

In addition, alarms have a status that you can change to indicated that the issue described in the alarm message has been dealt with.

You cannot control the events and alarms generated by the EPM or an MPP, but you can control:

- When Experience Portal notifies you about high CPU, RAM, and disk space usage
- How long the system stores event and retired alarm records

Related links

[Event and alarm categories](#) on page 433

[Event severities](#) on page 435

[Alarm severities](#) on page 435

Event and alarm categories

Every event and alarm falls into one, and only one, of the following categories:

Column	Description
EP Administration	Messages related to administration activities on the Experience Portal Manager (EPM).
EP Administration	Messages related to administration activities on the Experience Portal Manager (EPM).
EP Application Interface WS	Messages related to the Application Interface web service. This web service runs on the EPM server and allows customer applications to initiate outbound calls.
EP Application Interface WS 2.0	Messages related to the Application Interface web service 2.0. This version is functionally equivalent to the previous one. While there is a single username or password for the former, the new version provides the added facility of allowing multiple users to access the web service.
EP Application Logger	Messages related to the Experience Portal application logger. The application logger is a web service running on Experience Portal which allows Orchestration Designer applications to log messages to the EPM.
EP ASR	Messages related to Automatic Speech Recognition (ASR).
EP Backup	Messages related to the EP Backup subsystem, which provides the means to perform on-demand or scheduled backup operation.

Table continues...

EP CCXML Browser	Messages related to the Call Control eXtensible Markup Language (CCXML) browser, which controls all call handling for all Voice eXtensible Markup Language (VoiceXML) applications.
EP Event Manager	Messages related to the Event Manager, which collects events from other Media Processing Platform (MPP) processes and sends them to the network log web service on the EPM.
EP Licensing	Messages related to port licensing.
EP Listener	Messages related to the Alarm Codes Destinations types (Listeners) where the alarm notification is delivered.
EP Management WS	Messages related to the Experience Portal Management web service. This web service runs on the EPM server and allows you to configure and manage a EPM.
EP Media Manager	Messages related to audio and video Real-time Transport Protocol (RTP) connections.
EP MMS	Messages related to the MPP Management Service (MMS), which stores configuration information and controls the initialization and operation of an MPP.
EP Media Server Manager	Messages related to the MPP management subsystem, which provides the means to start and stop call processing.
EP MPP System Manager	Messages related to the MPP System Manager process, which manages and monitors MPP processes, configuration, licensing, and system resources.
EP MRCP	Messages related to Media Resource Control Protocol (MRCP), which is an open standard for speech interfaces.
EP Reporting	Messages related to the collection of report data and the generation of reports.
EP Session Manager	Messages related to the MPP Session Manager, which coordinates the low-level interactions between the ASR, TTS, and telephony components and the VoiceXML and CCXML browsers.
EP SNMP Agent	Messages related to the SNMP agent, which collects and stores management information and makes this information available to SNMP managers.
EP Telephony	Messages related to the H.323 connections and Voice over IP (VoIP) telephony interfaces.
EP Trace	Messages related to the EP trace reports. It provides the means to collect trace data from EPM or specific MPP.
EP TTS	Messages related to Text-to-Speech (TTS).
EP Upgrade Manager	Messages related to software upgrades for MPPs running on the EPM.
EP Email Processor	Messages related to the EP Email Processor.
EP SMS Processor	Messages related to the EP SMS Processor.
EP Text Browser	Messages related to the EP Text Processor.

*** Note:**

Additional categories may be available if you have installed managed application on Experience Portal. For more information on managed application based categories, see the documentation delivered with the managed application.

Related links

[Events and alarms](#) on page 432

Event severities

Event Severity	Description
Info	Informational message about the system or its resources.
Warning	Indicates that no immediate action is necessary, but the system condition needs to be monitored.
Error	Indicates a potentially serious problem that needs to be fixed soon.
Fatal	Indicates a problem that is interrupting service. Immediate action is needed.

Related links

[Events and alarms](#) on page 432

Alarm severities

Alarm Severity	Description
Minor	Indicates that no immediate action is necessary, but the system condition needs to be monitored.
Major	Indicates a potentially serious problem that needs to be fixed soon.
Critical	Indicates a problem that is interrupting service. Immediate action is needed.

Related links

[Events and alarms](#) on page 432

Alarm statuses

Status	Description
Unacknowledged	When an event or alarm is issued, Experience Portal sets the alarm status to Unacknowledged to indicate that the alarm is new. Experience Portal deletes Unacknowledged alarms from the database depending on the alarm retention period that you specify in the Alarm/Log Options page.
Acknowledged	You can set the event or alarm status to Acknowledged to indicate that you have seen the information but want to refer back to the event or alarm at a later point. Experience Portal deletes Acknowledged alarms from the database depending on the alarm retention period that you specify in the Alarm/Log Options page.
Retired	You can set the event or alarm status to Retired to indicate that you no longer need to refer to the alarm. Experience Portal deletes Retired alarms from the database

Table continues...

Status	Description
	depending on the alarm retention period that you specify in the Alarm/Log Options page.

Resource thresholds for events and alarms

When the use of system resources exceeds certain levels, the performance of the system as a whole can be impaired. Therefore, you want the system to issue an alarm when these levels are exceeded so that you can take appropriate action before the situation becomes critical.

For Experience Portal, you can specify a high water and low water setting for CPU, memory, and disk usage. When a resource exceeds its:

- **High Water** setting for the first time, the system generates an alarm. Experience Portal will not generate another alarm for this resource until the resource usage goes back down below the low water setting and then rises back above the high water setting.

You can view high water alarms by generating an alarm report.

- **Low Water** setting at any time, the system generates an informational event with a severity of **Info**.

If your system is configured to send informational events to the EPM, you can view low water events by generating an event report. Otherwise, you need to look in the System Manager process log, which is accessible from the Log Directories page on the Media Server Service Menu.

For information on setting:

- The level of events that are sent to the EPM, see [Setting the resource thresholds for events and alarms](#) on page 436.
- Which events are available in an event report, see [Setting the global grace period and trace level parameters](#) on page 256.

Related links

[Setting the resource thresholds for events and alarms](#) on page 436

Setting the resource thresholds for events and alarms

Procedure

1. Log on to the EPM Web interface using an account with the Administration user role.
2. From the EPM main menu, select **System Configuration > MPP Servers**.
3. On the MPP Servers page, click the **MPP Settings** button.
4. On the MPP Settings page, go to the **Resource Alerting Thresholds** group at the top of the page.
5. In the **CPU: High Water** field, enter the percentage of the CPU that the system must exceed before an alarm is generated.

The system generates one alarm each time the CPU percentage goes from being below the low water threshold to being above the high water threshold. In other words, once a high water alarm has been generated, another alarm will not occur until the CPU percentage falls back down below the low water setting and then rises above the high water setting again. The default is 70.

6. In the **CPU: Low Water** field, enter the percentage of the CPU that the system must fall below before an event is generated.

The system generates one event each time the CPU percentage goes from being above the low water threshold to being below it. In other words, once a low water event has been generated, another event will not occur until the CPU percentage rises above the low water setting and then falls below it again. The default is 60.

7. In the **Memory: High Water** field, enter the percentage of the available RAM that the system must exceed before an alarm is generated.

The system generates one alarm each time the percentage of the available RAM goes from being below the high water threshold to being above it. The default is 50.

8. In the **Memory: Low Water** field, enter the percentage of the available RAM that the system must fall below before an event is generated.

The system generates one event each time the percentage of the available RAM goes from being above the low water threshold to being below it. The default is 40.

9. In the **Disk: High Water** field, enter the percentage of disk space that the system must exceed before an alarm is generated.

The system generates one alarm each time the percentage of disk space being used goes from being below the high water threshold to being above it. The default is 80.

10. In the **Disk: Low Water** field, enter the percentage of disk space that the system must fall below before an event is generated.

The system generates one event each time the percentage of disk space being used goes from being above the low water threshold to being below it. The default is 60.

Related links

[Resource thresholds for events and alarms](#) on page 436

Setting log data retention periods

About this task

The Experience Portal viewer setting parameters determine whether event, Retired alarm, and audit log records are automatically deleted from the database when the specified retention period expires.

Note:

Experience Portal only purges Retired alarms. Unacknowledged and Acknowledged alarms are never automatically removed from the database.

Procedure

1. Log on to the EPM Web interface using an account with the Administration user role.
2. From the EPM main menu, select **System Configuration > EPM Servers > Alarm/Log Options**.
3. On the Alarm/Log Options page, enter the appropriate information and click **Save**.

Creating an event report

About this task

The Event report is affected by some fields on the Alarm/Log Options page.

- The **Logs** group fields determine whether old events are automatically deleted from the database, and, if so, how long those events remain in the database.
- The **Maximum Report Pages** field in the **Alarms/Logs/Audit Logs Report Size** group affects the length of time that elapses before Experience Portal displays the report, because it sets how many pages Experience Portal generates before it displays the first page.

Procedure

1. Log on to the EPM Web interface using an account with the Administration, Operations, or Maintenance user role.
2. From the EPM main menu, select **System Maintenance > Log Viewer**.
3. On the Log Viewer page, enter the filter criteria that you want to use and click **OK**.

The EPM displays the Log Report page. Because generating this report can take a long time if the Experience Portal database contains a large number of event records, the Log Report only displays the first 10,000 entries that match the specified criteria.

Next steps

You can view any available exception information for an event by clicking the **More** link in the **Event Message** field. [Log Report page field descriptions](#) on page 457

Creating an alarm report

About this task

The amount of data available for this report depends on the **Retention Period** setting in the **Alarms** group on the Alarm/Log Options page.

For example, if this value is set to 14, you can enter a start date that is two weeks prior to the current date. If the value is set to 7, you can only check for the previous week.

Procedure

1. Log on to the EPM Web interface using an account with the Administration, Operations, or Maintenance user role.

2. From the EPM main menu, select **System Maintenance > Alarm Manager**.
3. On the Alarm Manager page, enter the filter criteria that you want to use and click **OK**.
The EPM displays the Alarm Report page.
4. To view the associated event details for an alarm, click the link in the **Event Code** column.
The EPM displays the Log Report for Event page.

Viewing alarms by alarm category

Procedure

1. Log on to the EPM Web interface using an account with the Administration, Operations, or Maintenance user role.
2. From the EPM main menu, select **Real-Time Monitoring > System Monitor**.
3. Go to the <System name> Details tab on the System Monitor page.
The **Alarms** column displays one of the following alarm status indicators for the EPM, each MPP, and the overall Experience Portal system:
 - Green: There are no active major or critical alarms
 - Yellow: There are one or more active minor alarms
 - Red: There are one or more active major or critical alarms
4. To view the alarms in each alarm category for a particular server or the overall Experience Portal system, click any red or yellow alarm indicator at the end of the appropriate row.
5. On the Alarm Monitor page, to view an alarm report for a given category, click any red or yellow alarm indicator in the **Status** column.
The EPM displays the Alarm Report page showing all alarms in the selected category.
6. To view the associated event details for an alarm, click the link in the **Event Code** column.
The EPM displays the Log Report for Event page.

Changing the status of an alarm

Procedure

1. Log on to the EPM Web interface using an account with the Administration or Operations user role.
2. From the EPM main menu, select **System Maintenance > Alarm Manager**.
3. On the Alarm Manager page, enter the filter criteria that you want to use and click **OK**.
4. On the Alarm Report page, if you want to change the status of specific alarms, select them using the check boxes at the beginning of the appropriate alarm rows.

5. In the **Change Alarm Status** group at the bottom of the page, select:
 - **Selected alarms on this page** to change the status of only the alarms you selected.
 - **All alarms on this report** to change the status of all alarms in this report regardless of which alarms are selected.
6. Select the status you want to assign to the alarms from the **New Status** drop-down list. You can select:
 - **ACK** to set the alarm status to Acknowledged
 - **RETIRED** to set the alarm status to Retired
7. Click **Submit**.

Viewing the status changes made to an alarm

Procedure

1. Log on to the EPM Web interface using an account with the Administration or Operations user role.
2. From the EPM main menu, select **System Maintenance > Alarm Manager**.
3. On the Alarm Manager page, enter the filter criteria that you want to use and click **OK**.
4. On the Alarm Report page, click **ACK** or **RETIRED** in the **Alarm Status** column.

The EPM displays the Alarm History window.

Alarm Manager page field descriptions

Use this page to select filtering options and alarm categories and severities when creating an alarm report.

This page contains the:

- [General section](#) on page 440
- [Date and Time group](#) on page 442
- [Categories and Severities group](#) on page 443

General section

Field	Description
Zones	Select the name of the zone from the drop-down box. You can filter the records based on the zone that you select.

Table continues...

Field	Description
	 Note: The Zones drop-down box appears only when you create new zones. If you do not create any new zones, you do not see the drop-down box.
 Zones filter icon	To filter zones, click this icon located at the right side of the page. The system opens the Zone filter window for selecting one or more zones.  Note: The Zones filter icon only appears when you create new zones. If you do not create any new zones, you do not see the icon
Server Names	The name of the system for which you want to view alarms. The options are: • All systems • The EPM • A specific MPP • A combination of systems by selecting the first system and then using Shift+Click to select a range of systems or Ctrl+Click to select individual systems. The default is All systems.
Search Keywords	The text to search for in the alarm records. The search is case insensitive and based on a substring match, not a whole string match. For example, “Acknowledged” matches “acknowledged”, “ACKNOWLEDGED”, and “unacknowledged”. The search uses a logical OR when combining keywords. You can separate multiple entries with a comma, and use the tilde character (~) to indicate NOT. For example, if you enter <code>login, logoff, ~user=admin</code>, the report displays any records that contain the string “login” or “logoff” for all users <i>except</i> those user accounts that start with the string “admin”. If you enter <code>login, logoff, ~ADMIN</code>, the report displays any records that contain the string “login” or “logoff” but that do <i>not</i> contain the string “admin” anywhere within the record.
Status	The options are: • Unacknowledged • Acknowledged • Retired • All The default is Unacknowledged.
Alarm Codes	One or more alarm codes to search for. Separate multiple alarm codes with a comma or a space.

Table continues...

Field	Description
	For example, to search for alarm codes QADMN00001 and QADMN00002, enter QADMN00001,QADMN00002 or QADMN00001 QADMN00002.
Sort By	This can be: • Time: newest first • Time: oldest first • Severity: highest first • Severity: lowest first • Server Name • Status The default is Time: newest first.

Date and Time group

Button	Description
Predefined Values	The options are: • All Dates and Times • Today • Yesterday
Last	Limits the report to a given number of days or hours. Enter that number of days or hours in the associated text field, then select Days or Hours from the associated drop-down list. You can enter a whole number from 1 to 99. The number of days is calculated from midnight to 11:59 p.m. For example, if the current time is 3:00 p.m. on Wednesday and you enter a 3 in this field and select Days from the drop-down, the report will include all activity starting on Monday at midnight through the end of the current day.
Between	Limits the report to a specified range of dates. The default range covers a seven day time span that ends with the current date and time. If you want a different range of dates: • In the beginning of the Start Date/Time field, enter the start date using the format <code>mmm-dd-yyyy</code> or click the calendar icon to select the date from a pop-up calendar. After the start date, enter the start time using a 24-hour format and the same timezone as the EPM. For example, you could enter <code>Mar-03-2007 16:26:10</code>. • The default for this field is one week prior to the current date at time 00:00:00. • In the beginning of the End Date/Time field, enter the end date using the format <code>mmm-dd-yyyy</code> or click the calendar icon to select the date from a pop-up calendar. After the end date, enter the end time using a 24-hour format and the

Table continues...

Button	Description
	same timezone as the EPM. For example, you could enter <code>Mar-10-2007 16:26:10</code>. The default for this field is the day prior to the current date at time 23:59:59.

*** Note:**

The amount of data available for this report depends on the **Retention Period** setting in the **Alarms** group on the Alarm/Log Options page.

For example, if this value is set to 14, you can enter a start date that is two weeks prior to the current date. If the value is set to 7, you can only check for the previous week.

Categories and Severities group

This group lists all the alarm categories and severities available in the report. Use the check boxes to show or hide the alarms for a given category or with a given severity.

*** Note:**

If these fields are not displayed, click the group heading to expand the group.

Column	Description
All Categories	The check box in this column indicates which alarm categories to include in the alarm report. For more information, see Event and alarm categories on page 433.
Critical	Critical alarms describe problems that are interrupting service and require immediate action.
Major	Major alarms describe serious problems that need to be fixed as soon as possible.
Minor	Minor alarms describe problems that do not require immediate action but need monitoring.
EP Administration	Messages related to administration activities on the Experience Portal Manager (EPM).
EP Application Interface WS	Messages related to the Application Interface web service. This web service runs on the EPM server and allows customer applications to initiate outbound calls.
EP Application Interface WS 2.0	Messages related to the Application Interface web service 2.0. This version is functionally equivalent to the previous one. While there is a single username or password for the former, the new version provides the added facility of allowing multiple users to access the web service.
EP Application Logger	Messages related to the Experience Portal application logger. The application logger is a web service running on Experience Portal which allows Orchestration Designer applications to log messages to the EPM.
EP ASR	Messages related to Automatic Speech Recognition (ASR).
EP Backup	Messages related to the EP Backup subsystem, which provides the means to perform on-demand or scheduled backup operation.

Table continues...

EP CCXML Browser	Messages related to the Call Control eXtensible Markup Language (CCXML) browser, which controls all call handling for all Voice eXtensible Markup Language (VoiceXML) applications.
EP Event Manager	Messages related to the Event Manager, which collects events from other Media Processing Platform (MPP) processes and sends them to the network log web service on the EPM.
EP Licensing	Messages related to port licensing.
EP Listener	Messages related to the Alarm Codes Destinations types (Listeners) where the alarm notification is delivered.
EP Management WS	Messages related to the Experience Portal Management web service. This web service runs on the EPM server and allows you to configure and manage a EPM.
EP Media Manager	Messages related to audio and video Real-time Transport Protocol (RTP) connections.
EP MMS	Messages related to the MPP Management Service (MMS), which stores configuration information and controls the initialization and operation of an MPP.
EP Media Server Manager	Messages related to the MPP management subsystem, which provides the means to start and stop call processing.
EP MPP System Manager	Messages related to the MPP System Manager process, which manages and monitors MPP processes, configuration, licensing, and system resources.
EP MRCP	Messages related to Media Resource Control Protocol (MRCP), which is an open standard for speech interfaces.
EP Reporting	Messages related to the collection of report data and the generation of reports.
EP Session Manager	Messages related to the MPP Session Manager, which coordinates the low-level interactions between the ASR, TTS, and telephony components and the VoiceXML and CCXML browsers.
EP SNMP Agent	Messages related to the SNMP agent, which collects and stores management information and makes this information available to SNMP managers.
EP Telephony	Messages related to the H.323 connections and Voice over IP (VoIP) telephony interfaces.
EP Trace	Messages related to the EP trace reports. It provides the means to collect trace data from EPM or specific MPP.
EP TTS	Messages related to Text-to-Speech (TTS).
EP Upgrade Manager	Messages related to software upgrades for MPPs running on the EPM.
EP Email Processor	Messages related to the EP Email Processor.
EP SMS Processor	Messages related to the EP SMS Processor.
EP Text Browser	Messages related to the EP Text Processor.

*** Note:**

Additional categories may be available if you have installed managed application on Experience Portal. For more information on managed application based categories, see the documentation delivered with the managed application.

Alarm Report page field descriptions

Use this page to view, print, or export an alarm report, or to view the history of alarm state changes and information about associated event codes.

This page contains the:

- [Alarm report table](#) on page 445
- [Change Alarm Status group](#) on page 445

Alarm report table

Field	Description
Selection check box	Use this check box to select the alarms whose status you want to change.  Note: This check box is only available if you are logged in with the Administration or Operations System Manager user role
Timestamp	The date and time that the alarm message was generated.
Alarm Status	The options are: • UNACK: The alarm is active and has not been acknowledged. • ACK: The alarm is active and was acknowledged. • RETIRED: The alarm is retired. If the alarm status is ACK or Retired , click the status to view the Alarm History window that details the changes to the alarm's status.
Server Name	The options are: • The name of the primary or auxiliary EPM server • The name of the Media Server that generated the event
Category	Indicates which Experience Portal component generated the alarm.
Alarm Severity	Indicates how severe the problems surrounding the alarm were.
Alarm Code	The unique identification code associated with the alarm.
Event Code	The unique identification code associated with the event. Click this event code to view the Log Report for Event page.
Alarm Message	A brief explanation of the problem or error that caused the alarm.

Change Alarm Status group

 Note:

This group is only available if there are Unacknowledged or Acknowledged alarms in the report and you are logged in with the Administration or Operations System Manager user role.

Field or Button	Description
Alarm selection radio buttons	The options are: • Selected alarms on this page: Changes the status of the selected alarms only. • All alarms on this report: Changes the status of all alarms. regardless of the current selection.
New Status	The options are: • ACK: Change the status to Acknowledged. • RETIRED: Change the status to Retired. Experience Portal may be configured to automatically delete retired alarms after a specified length of time, based on the Purge Enabled setting in the Alarms group on the Alarm/Log Options page.
Submit	Changes the status of the selected alarms.

Trace Viewer

The Trace Viewer enables you to view and generate trace reports more effectively using the EPM interface. Using the trace viewer, you can generate trace reports for the traces that are retrieved from MPPs or the primary EPM, more effectively and securely. With similar interface as the log viewer and alarm manager for filtering and reports, trace viewer provides better debugging capabilities on the Experience Portal system.

Trace Viewer feature has the following enhancements:

- Separate tab to configure the filters and retrieve trace records for MPP traces.
- Separate tab to configure the filters and retrieve trace records for EPM traces.
- Ready to use details of trace information of specific components or processes that occurred in a selected MPP or EPM server.
- Enhanced debugging capabilities through well formatted outputs on the trace report. You can easily analyze the process activities and efficiently identify the root cause if any unexpected issue occurs.

You can use the Trace Viewer feature by clicking **Trace viewer** link under the **System Maintenance** on the left pane.

Important:

You must have the same version of EPM and MPP installed to use the trace viewer feature.

If any of the incompatible MPPs are connected to EPM, the trace client detects the incorrect version and reports an error on the log report. This distinguishes the MPP connection failures due to incompatibility and failure due to Trace WS.

MPP Traces tab on Trace Viewer page field descriptions

Use this page to configure the filters and retrieve trace records for MPP traces.

This page contains the:

- [General section](#) on page 447
- [Select Trace File section](#) on page 448
- [Date and Time section](#) on page 450

General section

Field	Description
Zone	Select the name of the zone from the drop-down box. You can filter the records based on the zone that you select.  Note: The Zone drop-down box appears only when you create new zones. If you do not create any new zones, you do not see the drop-down box.
	To filter zones, click this icon located at the right side of the page. The system opens the Zone filter window for selecting one or more zones.  Note: The Zones filter icon only appears when you create new zones. If you do not create any new zones, you do not see the icon
Servers	Select the name of the MPP server for which you want to view the trace details. For a single box system, the MPP name is displayed. If there are no MPPs configured, a message <code>No MPPs configured</code> is displayed.
Search Keywords	Enter text to search for in the trace records. You can specify multiple search keywords separated by commas. The search is case insensitive and based on a substring match, not a whole string match. For example, “Acknowledged” matches “acknowledged”, “ACKNOWLEDGED”, and “unacknowledged”. The search uses a logical OR when combining keywords. You can separate multiple entries with a comma, and use the tilde character (~) to indicate NOT. For example, if you enter <code>login, logoff, ~user=admin</code>, the report displays any records that contain the string “login” or “logoff” for all users <i>except</i> those user accounts that start with the string “admin”. If you enter <code>login, logoff, ~ADMIN</code>, the report displays any records that contain the string “login” or “logoff” but that do <i>not</i> contain the string “admin” anywhere within the record.
Components	Select the process components for which you want to view the trace details. The options are: • Administration • Call Data Handler WS • CCXML Browser • Event Manager

Table continues...

Field	Description
	• Media Manager • MMS • Outcall WS • Session Manager • SIP • System Manager • Transcript WS • Voice Browser The default is Administration. For details about the components, see Event and alarm categories on page 433.
Trace Level	Select one or multiple levels on traces report. The options are: • All Levels • FATAL • ERROR • WARN • INFO • FINE • FINER • FINEST The default is All Levels.  Note: You can select multiple trace levels by using <i>Shift+Click</i> to select a range of systems or <i>Ctrl+Click</i> to select individual systems.

 Note:

The amount of data available for this report depends on the **Retention Period** setting in the **Logs** group on the Viewer Settings page.

For example, if this value is set to 14, you can enter a start date that is two weeks prior to the current date. If the value is set to 7, you can only check for the previous week.

Select Trace File section

 Note:

This section is available only if you select one of the following **Components**:

- **CCXML Browser**
- **Media Manager**

- **Session Manager**
- **Voice Browser**

The fields in this section vary with the component selection.

Select Trace File fields for Media Manager	
Field	Description
EndPointMgr	Select this option to access the EndPointMgr.log file produced by the MediaManager process. This log file contains the traces regarding media end point management (RTP) and end point control messages exchanged between the MediaManager process and the SessionManager.
Media Manager	Select this option to access the MediaManager.log file produced by the MediaManager process. This log file contains the log traces associated with basic management of the MediaManager process including the start up, configuration, and shutdown messages.
VideoMgr	Select this option to access the VideoMgr.log file produced by the MediaManager process. This log file contains the traces regarding video rendering and video control messages exchanged between the MediaManager process and the SessionManager.
Session Slot	Select the session slot number. The session slot number is used by Avaya Aura[®] Experience Portal to uniquely identify the session. This slot number is included in the name of the associated logs on the MPP. The session slots are numeric values in the range 1 to 999.

Select Trace File fields for Session Manager	
Field	Description
Session Manager	Select this option to access the log files produced by the Session Manager. The session manager contains the following log files: • SessionManager.log– Contains data related to events that are not specifically associated with a single session • SessionSlot-###.log– Where ### represents a unique log identifier. Contains data related to Session Manager operations for individual sessions.  Tip: You can use ### to find related CCXML interpreter and Avaya Voice Browser logs.  Note: The Session Manager component can be parsed with Categories. If you select All Categories, the system displays the records for all existing categories.
Session Slot	Select the session slot number. The session slot number is used by Avaya Aura[®] Experience Portal to uniquely identify the session. This slot number is included in the name of the associated logs on the MPP. The session slots are numeric values in the range 1 to 999.

Select Trace File fields for SIP	
Field	Description
Session ID	Select this option to enter the unique identifier for the SIP call sessions.
Contact ID	Select this option to enter the unique identifier for a single call.
SIP Call-ID From Tag	Select this option to specify values so that the system displays messages that have the matching values in both the SIP Call-ID header and the tag parameter of the From header.

Select Trace File fields for CCXML Browser and Voice Browser	
Field	Description
GlobalProcess	Select the global process ID from the drop down box. The global process ID is a numeric value in the range 0 to 9.
Session Slot	Select the session slot number. The session slot number is used by Avaya Aura [®] Experience Portal to uniquely identify the session. This slot number is included in the name of the associated logs on the MPP. The session slots are numeric values in the range 1 to 999.

Date and Time section

Button	Description
Predefined Values	The options are: • All Dates and Times • Today • Yesterday • This Week • Last Week • This Month • Last Month
Last	Limits the report to a given number of days or hours. Enter that number of days or hours in the associated text field, then select Days or Hours from the associated drop-down list. You can enter a whole number from 1 to 99. The number of days is calculated from midnight to 11:59 p.m. For example, if the current time is 3:00 p.m. on Wednesday and you enter a 3 in this field and select Days from the drop-down, the report will include all activity starting on Monday at midnight through the end of the current day.
Between	Limits the report to a specified range of dates. The default range covers a seven day time span that ends with the current date and time. If you want a different range of dates: • In the beginning of the Start Date/Time field, enter the start date using the format <code>mmmm-dd-yyyy</code> or click the calendar icon to select the date from a pop-up calendar. After the

Table continues...

Button	Description
	start date, enter the start time using a 24-hour format and the same timezone as the EPM. For example, you could enter <code>Mar-03-2007 16:26:10</code>. The default for this field is one week prior to the current date at time 00:00:00. In the beginning of the End Date/Time field, enter the end date using the format <code>mmm-dd-yyyy</code> or click the calendar icon to select the date from a pop-up calendar. After the end date, enter the end time using a 24-hour format and the same timezone as the EPM. For example, you could enter <code>Mar-10-2007 16:26:10</code>. The default for this field is the day prior to the current date at time 23:59:59.

MPP Trace Report page field descriptions

Use this page to view, print, or export the formatted trace reports for the traces that are retrieved from MPPs, or to view the information about associated event codes.

Field	Description
Timestamp	The date and time that the log record was generated.
Server Name	The name of the MPP from which the traces are retrieved.
Category	Indicates which Experience Portal component generated the log record.
Trace Level	Indicates the severity of the log record.
Event Code	The event code associated with the event. Click the event code to view detailed information about the event.
Trace Message	A brief explanation of the trace. If trace information is available for the trace, you can click the Detail link in this column to display the detailed trace information of system server on the Experience Portal system.

EPM Traces tab on Trace Viewer page field descriptions

Use this page to configure the filters and retrieve trace records for primary EPM traces.

General section

Field	Description
Zone	The name of the default zone.  Note: The Zone field appears only if zones are defined on EPM.
	To filter zones, click this icon located at the right side of the page. The system opens the Zone filter window for selecting one or more zones.

Table continues...

Field	Description
Zones filter icon	 Note: The Zones filter icon only appears when you create new zones. If you do not create any new zones, you do not see the icon.
Server Names	The primary EPM.
Search Keywords	Enter text to search for in the trace records. You can specify multiple search keywords separated by commas. The search is case insensitive and based on a substring match, not a whole string match. For example, "Acknowledged" matches "acknowledged", "ACKNOWLEDGED", and "unacknowledged". The search uses a logical OR when combining keywords. You can separate multiple entries with a comma, and use the tilde character (~) to indicate NOT. For example, if you enter <code>login, logoff, ~user=admin</code>, the report displays any records that contain the string "login" or "logoff" for all users <i>except</i> those user accounts that start with the string "admin". If you enter <code>login, logoff, ~ADMIN</code>, the report displays any records that contain the string "login" or "logoff" but that do <i>not</i> contain the string "admin" anywhere within the record.
Components	Select the process components for which you want to view the trace details. The options are: • Application Interface WS • Application Interface WS 2.0 • Application Logger • Email • EP Backup • EP Management WS • EPM • Listener • SMS • SNMP Agent • SUM Upgrade WS • Text The default is Application Interface WS. For details about the components, see Event and alarm categories on page 433.
Trace Level	Select one or multiple levels on traces report.

Table continues...

Field	Description
	The options are: • All Levels • FATAL • ERROR • WARN • INFO • FINE • FINER • FINEST The default is All Levels.  Note: You can select multiple trace levels by using <i>Shift+Click</i> to select a range of systems or <i>Ctrl+Click</i> to select individual systems.

 Note:

The amount of data available for this report depends on the **Retention Period** setting in the **Logs** group on the Alarm/Log Options page.

For example, if this value is set to 14, you can enter a start date that is two weeks prior to the current date. If the value is set to 7, you can only check for the previous week.

Date and Time section

Button	Description
Predefined Values	The options are: • All Dates and Times • Today • Yesterday
Last	Limits the report to a given number of days or hours. Enter that number of days or hours in the associated text field, then select Days or Hours from the associated drop-down list. You can enter a whole number from 1 to 99. The number of days is calculated from midnight to 11:59 p.m. For example, if the current time is 3:00 p.m. on Wednesday and you enter a 3 in this field and select Days from the drop-down, the report will include all activity starting on Monday at midnight through the end of the current day.
Between	Limits the report to a specified range of dates. The default range covers a seven day time span that ends with the current date and time.

Table continues...

Button	Description
	If you want a different range of dates: - In the beginning of the Start Date/Time field, enter the start date using the format <code>mmm-dd-yyyy</code> or click the calendar icon to select the date from a pop-up calendar. After the start date, enter the start time using a 24-hour format and the same timezone as the EPM. For example, you could enter <code>Mar-03-2007 16:26:10</code>. The default for this field is one week prior to the current date at time 00:00:00. - In the beginning of the End Date/Time field, enter the end date using the format <code>mmm-dd-yyyy</code> or click the calendar icon to select the date from a pop-up calendar. After the end date, enter the end time using a 24-hour format and the same timezone as the EPM. For example, you could enter <code>Mar-10-2007 16:26:10</code>. The default for this field is the day prior to the current date at time 23:59:59.

EPM Trace Report page field descriptions

Use this page to view, print, or export the formatted trace reports for the traces that are retrieved from the primary EPM, or to view the information about associated event codes.

Field	Description
Timestamp	The date and time that the log record was generated.
Server Name	The EPM from which the traces are retrieved.
Category	Indicates which Experience Portal component generated the log record.
Trace Level	Indicates the severity of the log record.
Event Code	The event code associated with the event. Click the event code to view detailed information about the event.
Trace Message	A brief explanation of the trace. If trace information is available for the trace, you can click the Detail link in this column to display the detailed trace information of system server on the Experience Portal system.

Log Viewer page field descriptions

Use this page to create an event report.

This page contains the:

- [General information section](#) on page 455
- [Date and Time group](#) on page 456
- [Categories and Severities group](#) on page 457

General information section

Field	Description
Zones	Select the name of the zone from the drop-down box. You can filter the records based on the zone that you select.  Note: The Zones drop-down box appears only when you create new zones. If you do not create any new zones, you do not see the drop-down box.
 Zones filter icon	To filter zones, click this icon located at the right side of the page. The system opens the Zone filter window for selecting one or more zones.  Note: The Zones filter icon appears only when you create new zones. If you do not create any new zones, you do not see the icon.
Server Names	Select the name of the system for which you want to view events. The options are: • All systems • EPM • MPP The default is All systems.  Note: The MPP option is available in EPM only if the media server is MPP.
Search Keywords	Enter text to search for in the event records. The search is case insensitive and based on a substring match, not a whole string match. For example, "Acknowledged" matches "acknowledged", "ACKNOWLEDGED", and "unacknowledged". The search uses a logical OR when combining keywords. You can separate multiple entries with a comma, and use the tilde character (~) to indicate NOT. For example, if you enter <code>login, logoff, ~user=admin</code>, the report displays any records that contain the string "login" or "logoff" for all users <i>except</i> those user accounts that start with the string "admin". If you enter <code>login, logoff, ~ADMIN</code>, the report displays any records that contain the string "login" or "logoff" but that do <i>not</i> contain the string "admin" anywhere within the record.
Sort By	Select one of the following options: • Time: newest first • Time: oldest first • Severity: highest first • Severity: lowest first

Table continues...

Field	Description
	• Server Name The default is Time: newest first.
Event Codes	Enter one or more event codes to search for in the log records. Separate event codes with a comma or a space. For example, to search for event codes PADMN00001 and PADMN00002, enter PADMN00001, PADMN00002 or PADMN00001 PADMN00002

Date and Time group

Button	Description
Predefined Values	The options are: • All Dates and Times • Today • Yesterday
Last	Limits the report to a given number of days or hours. Enter that number of days or hours in the associated text field, then select Days or Hours from the associated drop-down list. You can enter a whole number from 1 to 99. The number of days is calculated from midnight to 11:59 p.m. For example, if the current time is 3:00 p.m. on Wednesday and you enter a 3 in this field and select Days from the drop-down, the report will include all activity starting on Monday at midnight through the end of the current day.
Between	Limits the report to a specified range of dates. The default range covers a seven day time span that ends with the current date and time. If you want a different range of dates: • In the beginning of the Start Date/Time field, enter the start date using the format <code>mmm-dd-yyyy</code> or click the calendar icon to select the date from a pop-up calendar. After the start date, enter the start time using a 24-hour format and the same timezone as the EPM. For example, you could enter <code>Mar-03-2007 16:26:10</code>. The default for this field is one week prior to the current date at time 00:00:00. • In the beginning of the End Date/Time field, enter the end date using the format <code>mmm-dd-yyyy</code> or click the calendar icon to select the date from a pop-up calendar. After the end date, enter the end time using a 24-hour format and the same timezone as the EPM. For example, you could enter <code>Mar-10-2007 16:26:10</code>. The default for this field is the day prior to the current date at time 23:59:59.

Note:

The amount of data available for this report depends on the **Retention Period** setting in the **Logs** group on the Alarm/Log Options page.

For example, if this value is set to 14, you can enter a start date that is two weeks prior to the current date. If the value is set to 7, you can only check for the previous week.

Categories and Severities group

This group lists all the event categories and severities available in the report.

Use the check boxes to show or hide the alarms for a given category or with a given severity. Use the **Check all** or **Uncheck all** links to the right of the group header to select or clear all category and severity check boxes.

 Note:

If these fields are not displayed, click the group heading to expand the group.

Column	Description
All Categories	The check box in this column indicates which event categories to include in the report. For details about the categories, see Event and alarm categories on page 433.
Fatal	Fatal events describe problems that are interrupting service and require immediate action.
Error	Error events describe serious problems that need to be fixed as soon as possible.
Warning	Warning events describe problems that are not currently interrupting service but which should be monitored.
Info	Info events are informational messages about the system or system resources.

Log Report page field descriptions

Use this page to view, print, or export a log report, or to view exception information for an event.

Field	Description
Timestamp	The date and time that the event message was generated.
Server Name	The options are: • EPM. • The name of the media server that generated the event.  Note: If you sort the report by this field, the EPM actually sorts by the name of the server in the Experience Portal database, not the name displayed in this field. Therefore the sort results may be different than what you expect.
Category	Indicates which Experience Portal component generated the event. For more information, see Event and alarm categories on page 433.
Event Severity	Indicates how severe the problems surrounding the event were. For more information, see Event severities on page 435.
Event Code	The event code associated with the event. Click the event code to view detailed information about the event.
Event Message	A brief explanation of the event or condition. If exception information is available for the event, a link labeled More appears in this column that you can click to display the exception information.

<System name> Details tab on the System Monitor page field descriptions

Use this tab for a detailed view of the health and status of the EPM and each MPP in the Experience Portal system named in <System Name>. The information on this page refreshes automatically if you leave the browser window open.

*** Note:**

If the EPM server needs to be restarted, Experience Portal displays the message "EPM needs to be restarted." in red text just above the system status table.

Column	Description
 Zones filter icon	To filter zones, click this icon located at the right side of the page. The system opens the Zone filter window for selecting one or more zones. * Note: The Zones filter icon only appears when you create new zones. If you do not create any new zones, you do not see the icon.
Zone	The zone where the EPM and the MPP servers are configured.
Server Name	The options are: • The name of the EPM server. Click this name to view the <EPM Name> Details page. • The name of an MPP running on the system. Click this name to view the <MPP name> Details page. • <EPM Name>/<MPP Name>, if an MPP resides on the same server as the EPM. Click this name to view the <MPP name> Details page.
Type	The options are: • EPM: The Experience Portal Manager • MPP: A Media Processing Platform + Tip: To verify whether the associated server is a primary or auxiliary EPM server, hover the mouse over the EPM field.
Mode	The operational mode of the Media Server. The options are: • Online: The Media Server is available. • Offline: The Media Server is unavailable and is not being polled by the EPM server. • Test: (MPP only) The Media Server is available to handle calls made to one of the defined H.323 maintenance stations.

Table continues...

Column	Description
	 Tip: To view the date and time that this mode was first reached, hover the mouse over this column.
State	The operational state of the Media Server. The options are: • Booting: The Media Server is in the process of restarting and is not yet ready to take new calls. • Degraded: The Media Server is running but it is not functioning at full capacity. • Error: The Media Server has encountered a severe problem and cannot recover. • Halted: The Media Server is no longer responding to heartbeats because it received a Halt command. • Halting: The Media Server is responding to heartbeats but is not taking new calls. • Need Configuration: An Email or SMS processor residing on the Media Server has not yet been configured. • Need Connections: No connections (SMPP or HTTP) have been configured or assigned to an Email/SMS processor residing on the Media Server. • Never Used: The Media Server has never successfully responded to a heartbeat request. • Not Installed: The Media Server is missing files required for heartbeat requests to occur. • Not Responding: The Media Server is not responding to heartbeat requests and it has not received a Restart or Halt command. • Partially Running: (EPM only) The Media Server is in the process of starting up, and not all individual components of the service, for example: Tomcat, SL, ActiveMQ, have come up yet. • Rebooting: The Media Server is responding to heartbeats but is not taking new calls. • Recovering: The Media Server has encountered a problem and is attempting to recover. • Restart Needed: This state is most often reached when the Media Server has encountered a problem that it cannot recover from and it requires a manual restart. However, it can also appear for an MPP when the EPM software has been upgraded and the MPP software has not. In that case, the state should update automatically when you upgrade the MPP software. • Running: The Media Server is responding to heartbeat requests and is accepting new calls. • Starting: The Media Server is responding to heartbeats but not taking new calls because it is transitioning from the Stopped state to the Running state.

Table continues...

Column	Description
	• Stopped: The Media Server is responding to heartbeats but is not taking new calls. The Media Server enters this state while it initializes after it restarts or when a stop command is received. • Stopping: The Media Server is responding to heartbeats but is not taking new calls. • Unknown: The Media Server is in the Offline mode.  Tip: To view the date and time that this state was first reached, hover the mouse over this column.
Active Command	This column is displayed if one or more Media Servers are currently in transition from their current state to a new user-requested state. For each transitional Media Server, this column displays the requested, or final, state. For any other Media Servers in the system, this field displays None.
Config	The configuration state of the Auxiliary EPM/MPP. The options are: • Need certificates: The Primary EPM certificate must be downloaded to the Auxiliary EPM/MPP by running the <code>setup_vpms.php</code> script on the Auxiliary EPM/MPP. • Need ports: The MPP has been configured and is waiting for ports to be assigned. • None: The MPP has never been configured. • OK: The Auxiliary EPM/MPP is currently operating using the last downloaded configuration. • Restart needed: The MPP must be restarted to enable the downloaded configuration. • Reboot needed: The MPP must be rebooted to enable the downloaded configuration. • Upgrade needed: The Auxiliary EPM must be upgraded to the same version of the software as on the Primary EPM. • Unknown: The MPP is either not responding or is in the Offline mode.
Call Capacity	This field displays: • Current: The number of calls that can be currently handled by the system. • Licensed: The number of licenses allocated to this system. • Maximum: The maximum number of simultaneous calls that the MPPs in this system can handle. This value is obtained by adding together the maximum number of calls set for each of the MPPs in the system.  Note: This value can be larger than the number of licenses allocated to the system, but it should never be smaller. If it is smaller, then some of your licenses will never be used.

Table continues...

Column	Description
Active Calls	This field displays: • In: The number of active incoming calls in the system. • Out: The number of active outgoing calls in the system. Clicking the number displayed under the Active Calls In column displays all the active incoming calls for the media servers. Clicking the number displayed under the Active Calls Out column displays all the active outgoing calls for the media servers.
Calls Today	The number of calls handled during the current day.
Alarms	The alarm status indicators for the EPM, each MPP, and the overall Experience Portal system. The options are: • Green: There are no active major or critical alarms • Yellow: There are one or more active minor alarms • Red: There are one or more active major or critical alarms  Tip: You can click any red or yellow alarm indicator to view the Alarm report for that system.
Summary	The total number of calls based on Contact Summary and Active Calls. On the Summary line, clicking the number displayed under the Active Calls In column displays all the active incoming calls for the media servers. On the Summary line, clicking the number displayed under the Active Calls Out column displays all the active outgoing calls for the media servers.

Email, HTML and SMS processors section

Column	Description
Zone	The zone where the Email and SMS processors are configured. The summary reports within a zone are: • Email Summary: Summary of the incoming and outgoing email messages in the last 24 hours. • SMS Summary: Summary of the incoming and outgoing SMS messages in the last 24 hours. • HTML Summary: Summary of the incoming HTML messages in the last 24 hours.
Server Name	The name of the EPM on which the Email, SMS and HTML processors are configured.
Type	The options are: • Email processor • HTML processor

Table continues...

Column	Description
	• SMS processor
State	The operational state of the email/SMS/HTML processors. The options are: • Not Running: The server is either stopped or not started yet. • Starting: The server start request is initiated, and is in the process of initialization. • Running: The server is up and functional. • Stopping: The server shutdown is requested. • Need Configuration: The server does not find configuration. • Need Connections: The server has configuration but does not have any connections assigned or configured. • Degraded: The server has configuration and connections. However, some or all connections are not working. • Error: The server data returned has been deemed "stale" (no new data retrieved after a period of 3 minutes), or 2) unexpected return code retrieved from a poll to server. • Stopped: The server is stopped.
Usage (Today)	Displays the number of messages processed during the current day. The Summary row also shows the maximum number of messages allowed per day.
Messages (Last 24 hours)	The options are: • Incoming: The number of incoming messages processed in the last 24 hours. • Outgoing: The number of outgoing messages processed in the last 24 hours.  Note: Clicking on the Last 24 hours text, lets the user to change the number of messages displayed for the following time frames: • Last hour • Last 3 hours • Last 6 hours • Last 12 hours • Last 24 hours
Timeline Graph 	Displays a graph icon. Clicking this graph icon displays the number of messages processed in a graphical form.

Related links

[Viewing Avaya Aura Experience Portal system status](#) on page 425

Alarm/Log Options page field descriptions

Use this page to view or change the retention period for alarm and log records as well as the maximum number of report pages Experience Portal generates before it displays the first page of the report to the user.

This page contains the:

- [Alarms group](#) on page 463
- [Logs group](#) on page 463
- [Audit Logs group](#) on page 464
- [Alarms/Logs/Audit Logs/Traces Report Size group](#) on page 464

*** Note:**

For purging the alarms, logs, and audit logs, the purge start time is 00:00 hours (midnight) by default. This implies that the purge period is not triggered until midnight regardless the time that you specify in the retention period.

For example, if you set the purge period to 1 day at 10:00 hours today, the purge does not occur until the third day morning at 00:01 hours.

Alarms group

*** Note:**

You can only change the values in this group if your user account has the Administration user role.

Field	Description
Purge Enabled	The options are: • Yes: Experience Portal deletes Retired alarms once the retention period is exceeded. • No: Experience Portal leaves the Retired alarms in the database indefinitely. The default is Yes. * Note: Experience Portal never automatically purges Acknowledged or Unacknowledged alarms.
Retention Period	The number of days that alarm records are retained if Purge Enabled is set to Yes. Enter an integer between 1 and 365. The default is 30.

Logs group

*** Note:**

You can only change the values in this group if your user account has the Administration user role.

Field	Description
Purge Enabled	The options are: • Yes: Experience Portal deletes event log records once the retention period is exceeded. • No: Experience Portal leaves the event log records in the database indefinitely. The default is Yes .
Retention Period	The number of days that log records are retained if Purge Enabled is set to Yes . Enter an integer between 1 and 365. The default is 15.

Audit Logs group

*** Note:**

You can only change the values in this group if your user account has the Auditor user role.

Field	Description
Purge Enabled	The options are: • Yes: Experience Portal deletes event log records once the retention period is exceeded. • No: Experience Portal leaves the event log records in the database indefinitely. The default is Yes .
Retention Period	The number of days that audit log records are retained if Purge Enabled is set to Yes . Enter an integer between 1 and 365. The default is 180.

Alarms/Logs/Audit Logs/Traces Report Size group

*** Note:**

You can only change the values in this group if your user account has the Administration user role.

Field	Description
Maximum Report Pages	The number of report pages Experience Portal generates before it displays the first page of the report to the user. Enter an integer between 1 and 100. The default is 10. For example, if this field is set to 20, Experience Portal retrieves enough data to fill the first 20 pages of the report before it displays the first page of the report. When the user reaches the end of page 20 and clicks Next , Experience Portal does not display page 21 until it has retrieved the data for pages 21-40.

Alarm History window field descriptions

Use this window to view the history of alarm state changes for Acknowledged or Retired alarms.

This window contains the:

- [Alarm information section](#) on page 465

- [Alarm status change table](#) on page 465

Alarm information section

Field	Description
Alarm Code	The unique identification code associated with the alarm.
Timestamp	The date and time that the alarm message was generated.
Server Name	The options are: • The name of the primary or auxiliary EPM server • The name of the Media Server that generated the event
Alarm Severity	Indicates how severe the problems surrounding the alarm were.
Alarm Message	A brief explanation of the problem or error that caused the alarm.

Alarm status change table

Field	Description
Timestamp	The date and time that the alarm status was changed.
Status Changed To	The status that the alarm was changed to. This can be: • ACK: The alarm status is now Acknowledged. • RETIRED: The alarm status is now Retired.
By	The user name of the user who changed the alarm status.

Creating an Audit Log report

About this task

The Audit Log report shows all action performed by all users logged into the EPM. It does *not* show any system configuration or backup activities performed by running Experience Portal scripts or making other changes outside the EPM Web interface.

Note:

The length of time that events remain in the database depends on the retention period set in the **Audit Logs** group on the Alarm/Log Options page.

Procedure

1. Log on to the EPM Web interface using an account with the Auditor user role.
2. From the EPM main menu, select **System Maintenance > Audit Log Viewer**.
3. On the Audit Log Viewer page, enter the filter criteria that you want to use and click **OK**.

The EPM displays the Audit Log Report page.

Related links

[Audit Log Viewer page field descriptions](#) on page 466

[Audit Log Report page field descriptions](#) on page 468

Audit Log Viewer page field descriptions

Use this page to create an Audit Log report, which provides details on the administration activity that has occurred on this system.

This page contains the:

- [General section](#) on page 466
- [Date and Time group](#) on page 467

General section

Field	Description
Zones	Select the name of the zone from the drop-down box. You can filter the records based on the zone that you select.  Note: The Zones drop-down box appears only when you create new zones. If you do not create any new zones, you do not see the drop-down box.
 Zones filter icon	To filter zones, click this icon located at the right side of the page. The system opens the Zone filter window for selecting one or more zones.  Note: The Zones filter icon only appears when you create new zones. If you do not create any new zones, you do not see the icon.
Categories	The categories used to filter the audit log report.
Search Keywords	The text to search for in the audit log records. The search is case insensitive and based on a substring match, not a whole string match. For example, "Acknowledged" matches "acknowledged", "ACKNOWLEDGED", and "unacknowledged". The search uses a logical OR when combining keywords. You can separate multiple entries with a comma, and use the tilde character (~) to indicate NOT. For example, if you enter <code>login, logoff, ~user=admin</code>, the report displays any records that contain the string "login" or "logoff" for all users <i>except</i> those user accounts that start with the string "admin". If you enter <code>login, logoff, ~ADMIN</code>, the report displays any records that contain the string "login" or "logoff" but that do <i>not</i> contain the string "admin" anywhere within the record.
Sort By	The options are: • Time: newest first

Table continues...

Field	Description
	• Time: oldest first • Category
Actions	The actions to be included in the audit log report.

Date and Time group

Button	Description
Predefined Values	The options are: • All Dates and Times • Today • Yesterday
Last	Limits the report to a given number of days or hours. Enter that number of days or hours in the associated text field, then select Days or Hours from the associated drop-down list. You can enter a whole number from 1 to 99. The number of days is calculated from midnight to 11:59 p.m. For example, if the current time is 3:00 p.m. on Wednesday and you enter a 3 in this field and select Days from the drop-down, the report will include all activity starting on Monday at midnight through the end of the current day.
Between	Limits the report to a specified range of dates. The default range covers a seven day time span that ends with the current date and time. If you want a different range of dates: • In the beginning of the Start Date/Time field, enter the start date using the format <code>mmm-dd-yyyy</code> or click the calendar icon to select the date from a pop-up calendar. After the start date, enter the start time using a 24-hour format and the same timezone as the EPM. For example, you could enter <code>Mar-03-2007 16:26:10</code>. • In the beginning of the End Date/Time field, enter the end date using the format <code>mmm-dd-yyyy</code> or click the calendar icon to select the date from a pop-up calendar. After the end date, enter the end time using a 24-hour format and the same timezone as the EPM. For example, you could enter <code>Mar-10-2007 16:26:10</code>. The default for this field is one week prior to the current date at time 00:00:00. The default for this field is the day prior to the current date at time 23:59:59.

Note:

The amount of data available for this report depends on the setting in the **Retention Period** field in the **Audit Logs** group on the Alarm/Log Options page.

For example, if this value is set to 14, you can enter a start date that is two weeks prior to the current date. If the value is set to 7, you can only check for the previous week.

Related links

[Creating an Audit Log report](#) on page 465

Audit Log Report page field descriptions

Use this page to view, print, or export an Audit Log report.

Column	Description
Timestamp	The date and time the log entry was made.
User	The user name that was logged in to the EPM when the change was made.
Category	EPM audit log category that is used for filtering the audit log.
Action	The action related to the user or category in the audit log report.
Zone	The zone where the audit log is located.
Component	The affected component, if any.
Property	The property that was affected.
From	If applicable, what the value was before the change was made.
To	If applicable, the value after the change was made.

Related links

[Creating an Audit Log report](#) on page 465

Chapter 20: Reports

Configuring report data settings

Procedure

1. Log on to the EPM Web interface using an account with the Administration user role.
2. From the EPM main menu, select **System Configuration > MPP Servers**.
3. On the MPP Servers page, click **MPP Settings**.
4. On the MPP Settings page, fill in the desired retention period in the **Transcription** group.
5. In the **Record Handling on MPP** group:
 - a. For each type of data you want each MPP to collect, verify that the **Enable** check box next to the field for that data type is selected.
 - b. Enter the number of days the data should be kept on the MPP in the associated **Retention Period** field.

The data types are:

- **Session Data:** Avaya Aura® Experience Portal uses this data to create the Session Detail and Session Summary reports.
 - **Contact Data Record:** Experience Portal uses this data to create the Contact Detail and Contact Summary reports.
 - **VoiceXML/CCXML Log Tags:** If desired, Experience Portal can download the Log tag data and display it in the Application Detail report and Application Summary report.
6. When you have set these options, click **Save**.
 7. From the EPM main menu, select **System Configuration > EPM Servers > Report Data**.
 8. On the Report Data Configuration page, enter the appropriate information and click **Save**.
 9. To create application reports for any speech applications running on the Experience Portal system, set the reporting options for each application:
 - a. From the EPM main menu, select **System Configuration > Applications**.
 - b. On the Applications page, click on the name of the application for which you want to create reports.
 - c. On the Change Application page, go to the **Reporting Parameters** group and enter the appropriate information.
 - d. Click **Save**.

- e. Repeat this step for each application for which you want to create reports.

Printing reports

Procedure

1. To print the report, click the **Print** icon at the top of the report page.
2. As you follow the prompts, make sure that:
 - The page orientation is Landscape and not Portrait, or some columns of the report may not print
 - If you want the printout to contain the same shading in the columns and rows as the online report, the browser option to print background colors is selected

Exporting reports

Procedure


To export the data from the report, click the **Export** icon at the top of the report page, select the export option, and follow the prompts. Experience Portal has two export options:

- Export as XLS format
- Export as PDF format

Experience Portal creates a spreadsheet (XLS) or a PDF containing the details shown in the report along with any additional report information available for up to 10,000 data records.

Report generation flow diagram

The following figure shows how the EPM generates reports.



Application activity reports

The application activity reports show:

- Activity relating to and messages generated by the Orchestration Designer applications added to the Experience Portal system
- Voice eXtensible Markup Language (VoiceXML) and Call Control eXtensible Markup Language (CCXML) Log Tag messages from all speech applications added to the Experience Portal system, if the Log Tag messages are stored on, and downloaded from, the MPP

The available activity reports are the Application Summary report and the Application Detail report. The amount of data available for these reports depend on:

- The length of time since the application finished processing. The EPM downloads Application Detail Records (ADRs) within five minutes after an application finishes. If a particular application is not included in your report, make sure the application has finished processing and try running the report again.

- The **Retention Period** setting for the **Application Retention Period** field on the Report Data Configuration page.
For example, if this value is set to 14, you can enter a start date that is two weeks prior to the current date. If the value is set to 7, you can only check for the previous week.
- The settings for the report parameters specified for each individual application in the **Reporting Parameters** group on the Change Application page.

Related links

[Creating an Application Summary report](#) on page 472

[Creating an Application Detail report](#) on page 472

Creating an Application Summary report

Procedure

1. Log on to the EPM Web interface using an account with the Administration, Operations, or Maintenance user role.
2. From the EPM main menu, select **Reports > Standard**.
3. On the Standard Reports page, click **Application Summary** link under the **Report Name** column.
4. Optionally, click  next to Application Summary link to generate the report with the default selections of filters.
5. On the Application Summary page, enter the filter criteria that you want to use.

Tip:

Click the **more >>** link to display the rest of the optional filters.

6. Click **OK**.

The EPM displays the Application Summary Report page.

Related links

[Application activity reports](#) on page 471

Creating an Application Detail report

Procedure

1. Log on to the EPM Web interface using an account with the Administration, Operations, or Maintenance user role.
2. From the EPM main menu, select **Reports > Standard**.
3. On the Standard Reports page, click **Application Detail** link under the **Report Name** column.

4. Optionally, click  next to **Application Detail** link to generate the report with the default selections of filters.
5. On the Application Details page, enter the filter criteria that you want to use.

+ Tip:

Click the **more >>** link to display the rest of the optional filters.

6. Click **OK**.

The EPM displays the Application Detail Report page.

+ Tip:

If the width of the activity type exceeds the width of the **Type** column, then the activity type appears as Hover the mouse over the ... to view a tool tip with the complete type name.

Related links

[Application activity reports](#) on page 471

Call activity reports

Contact activity reports

The following reports track call activity in the Experience Portal system:

Contact Summary report : Provides summary information about all calls handled by the specified MPPs and applications for the specified time period.

Contact Detail report : Provides detailed information about all calls handled by the specified MPPs and applications for the specified time period.

Session Summary report : Provides summary information about call-handling sessions for the specified MPPs and applications for the specified time period.

Session Detail report: Provides detailed information about all call-handling sessions for the specified MPPs and applications for the specified time period. This report also provides access to any transcription information saved for the applications.

The amount of data available for these reports depends on the **Retention Period** setting for the **Contact Data Record** and **Session Data** fields on the MPP Settings page.

For example, if this value is set to 14, you can enter a start date that is two weeks prior to the current date. If the value is set to 7, you can only check for the previous week.

Creating a Contact Detail report

About this task

The Contact Detail report provides detailed information about all calls handled by the specified MPPs and applications for the specified time period.

Procedure

1. Log on to the EPM Web interface using an account with the Administration, Operations, or Maintenance user role.
2. From the EPM main menu, select **Reports > Standard**.
3. On the Standard Reports page, click **Contact Detail** link under the **Report Name** column.
4. Optionally, click  next to **Contact Detail** link to generate the report with the default selections of filters.
5. On the Contact Detail Report page, enter the filter criteria that you want to use.

 Tip:

Click the **more >>** link to display the rest of the optional filters.

6. Click **OK**.
7. On the Contact Detail Report page, if you want to:
 - View the messages generated by one of the Orchestration Designer applications listed in the table, click the appropriate name in the **Application** column. The EPM displays the Application Detail Report page detailing the messages generated during the associated call session.
 - Get more information about how a call ended, hover the mouse over a value in the **End Type** column. Information about how a call ended is displayed in a pop-up window.
 - View details about the session that handled the call, click the **View Session Details** icon  in the appropriate row. The EPM displays the Session Details page.

Creating a Contact Summary report

About this task

The Contact Summary report provides summary information about all calls based on the specified filtering options.

Procedure

1. Log on to the EPM Web interface using an account with the Administration, Operations, or Maintenance user role.
2. From the EPM main menu, select **Reports > Standard**.

3. On the Standard Reports page, click **Contact Summary** link under the **Report Name** column.

*** Note:**

You can also click  next to **Contact Summary** link to generate the report using the default selections of filters.

4. Optionally, click next to **Contact Summary** link to generate the report with the default selections filters.
5. On the Contact Summary page, enter the filter criteria that you want to use.

+ Tip:

Click the **more >>** link to display the rest of the optional filters.

6. Click **OK**.

The EPM displays the Contact Summary Report page.

Creating a Session Detail report

About this task

The Session Detail report provides detailed information about the call-handling sessions for the specified Media Processing Platform (MPP) servers and applications for the specified time period. A session starts with the initial inbound or outbound call and ends with the termination of the CCXML page that resulted from the call.

Procedure

1. Log on to the EPM Web interface using an account with the Administration, Operations, or Maintenance user role.
2. From the EPM main menu, select **Reports > Standard**.
3. On the Standard Reports page, click **Session Detail** link under the **Report Name** column.
4. Optionally, click  next to **Session Detail** link to generate the report using the default selections of filters.
5. On the Session Detail (Filters) page, enter the filter criteria that you want to use.

+ Tip:

Click the **more >>** link to display the rest of the optional filters.

6. Click **OK**.

The EPM displays the Session Detail Report page.

7. If you want to view more information about a particular session, click the **View Session**

Details icon  in the appropriate row.

Experience Portal displays the Session Details page.

Creating a Session Summary report

About this task

The Session Summary report provides summary information about call handling sessions for the specified Media Processing Platform (MPP) servers and applications for the specified time period. A session starts with the initial inbound or outbound call and ends with the termination of the CCXML or VoiceXML page that resulted from the call.

Procedure

1. Log on to the EPM Web interface using an account with the Administration, Operations, or Maintenance user role.
2. From the EPM main menu, select **Reports > Standard**.
3. Optionally, click  next to **Session Summary** link to generate the report with the default selections of filters.
4. On the Standard Reports page, click **Session Summary** link under the **Report Name** column.
5. On the Session Summary (Filters) page, enter the filter criteria that you want to use.

 Tip:

Click the **more >>** link to display the rest of the optional filters.

6. Click **OK**.

The EPM displays the Session Summary Report page.

Viewing application transcription data

Procedure

1. Log on to the EPM Web interface using an account with the Administration, Operations, or Maintenance user role.
2. From the EPM main menu, select **Reports > Standard > Session Detail**.
3. On the Session Detail page, the **more >>** link to display the rest of the optional filters.
4. Enter the criteria you want to use for the report.

+ Tip:

If you want to limit the report to those sessions that have transcription information, select **Yes** in the **Session Transcription** field.

- When you are finished, click **OK**.

The EPM displays the Session Detail Report page.

- Locate the particular session for which you want to view the transcription data and click the **View Session Details** icon at the end of the appropriate row.

Experience Portal displays the Session Details page, which shows both the session and transcription data grouped by information category.

Show/Hide the Extended Exit Info #3 to Info #10 filters/columns in reports

By default, the Extended Exit Info #3 to Info #10 filters and columns are not shown in the Session Summary and Session Detail reports. To show/hide these filters and columns in EPM, you must run the `enableExtendedExitFields` command on the Experience Portal server.

Related links

[Showing the Extended Exit Info #3 to Info #10 filters/columns in the Session Summary and Session Details reports](#) on page 477

[Hiding the Extended Exit Info #3 to Info #10 filters/columns in the Session Summary and Session Details reports](#) on page 478

Showing the Extended Exit Info #3 to Info #10 filters/columns in the Session Summary and Session Details reports

About this task

*** Note:**

By default, the `EnableExtendedExitFields` feature is disabled.

Procedure

- Log on to Linux on the Primary or Auxiliary EPM server.

If you are an Avaya Services representative and are using Avaya Enterprise Linux, or if the Avaya Service accounts are installed on this server:

- Log on to the local Linux console as `sroot`.
- Or log on remotely as a non-root user and enter the `su - sroot` command to change the user to `sroot`.

Otherwise, log on to Linux locally as `root`, or log in remotely as a non-root user and enter the `su -` command to change the user to `root`.

2. Navigate to the `Support/VP-Tools` directory under the Experience Portal installation directory.

Enter the `cd $AVAYA_HOME/Support/VP-Tools` command. `$AVAYA_HOME` is an environmental variable pointing to the name of the installation directory specified during the Experience Portal software installation.

The default value is `/opt/Avaya/ExperiencePortal`.

3. Type `Y` and press `Enter` when prompted to restart the `vpms` service.

Related links

[Show/Hide the Extended Exit Info #3 to Info #10 filters/columns in reports](#) on page 477

Hiding the Extended Exit Info #3 to Info #10 filters/columns in the Session Summary and Session Details reports

Procedure

1. Log on to Linux on the Primary or Auxiliary EPM server.

If you are an Avaya Services representative and are using Avaya Enterprise Linux, or if the Avaya Service accounts are installed on this server:

- Log on to the local Linux console as `sroot`.
- Or log on remotely as a non-root user and enter the `su - sroot` command to change the user to `sroot`.

Otherwise, log on to Linux locally as `root`, or log in remotely as a non-root user and enter the `su -` command to change the user to `root`.

2. Navigate to the `Support/VP-Tools` directory under the Experience Portal installation directory.

Enter the `cd $AVAYA_HOME/Support/VP-Tools` command. `$AVAYA_HOME` is an environmental variable pointing to the name of the installation directory specified during the Experience Portal software installation.

The default value is `/opt/Avaya/ExperiencePortal`.

3. To run the script:

Enter the `./EnableExtendedExitFields --disable` command to hide the extended exit fields in the Session Summary and Session Details reports.

4. Type `Y` and press `Enter` when prompted to restart the `vpms` service.

Related links

[Show/Hide the Extended Exit Info #3 to Info #10 filters/columns in reports](#) on page 477

Creating a Performance report

About this task

The Performance report provides information about resource utilization on the specified Media Processing Platform (MPP) servers for the specified time period.

The amount of data available for this report depends on the **Performance Retention Period** field on the Report Data Configuration page.

For example, if this value is set to 14, you can enter a start date that is two weeks prior to the current date. If the value is set to 7, you can only check for the previous week.

Procedure

1. Log on to the EPM Web interface using an account with the Administration, Operations, or Maintenance user role.
2. From the EPM main menu, select **Reports > Standard**.
3. On the Standard Reports page, click **Performance** link under the **Report Name** column.
4. Optionally, click  next to **Performance** link to generate the report with the default selections of filters
5. On the Performance (Filters) page, enter the filter criteria that you want to use.
6. Click **OK**.
7. In the Performance Report page, if you want to:
 - View additional performance data in graphical format, click **View Summary Graph** above the last column in the table. All graphs show one bar for each MPP. The bars are color-coded to show average and peak usage for each category.
 - View port utilization information, click the magnifying glass icon in the **Port Utilization %** column. The EPM displays the Port Utilization Details page.
 - View resource utilization over time combined with the call volume over time, click the icon in the **Timeline Graph** column.

Advanced reporting in Experience Portal

The Experience Portal solution offers a variety of reports which enable you to analyze call volumes, trends, and effectiveness of your VoiceXML and CCXML applications.

The major new features added to the existing reporting feature are:

- [Custom Reports](#) on page 480
- [Scheduled Reports](#) on page 480
- [Data Export reports](#) on page 480

Custom Reports

With the custom reporting feature you can use any standard Experience Portal report as a base for generating a custom report. A custom report uses the filter settings defined in the selected base report. However, you can change the filter settings to create a different set of filters and configure the columns that you want to use for generating the report. You can also save this configuration for later reference.

Scheduled Reports

You can schedule the generation of the standard or the custom reports to occur on a periodic basis. You can receive the report output as an e-mail attachment, or access it through the secure links in the e-mail notification, RSS feeds or by logging into the Experience Portal Manager (EPM). You can optionally set Record Threshold restriction value when scheduling a report. Setting this restriction generates a notification only when the total record count reaches the specified minimum value.

Data Export reports

You can use the Data Export report to export the data from the Experience Portal reporting database, including the detailed call flow information stored on the MPP server. The call flow information includes the session transcription files containing user experience, performance data, and optionally the caller's utterances stored in wave files.

Data Export report

Data Export reports

You can use the Data Export Report to request a bulk download of the raw report data for application tuning analysis. The raw data includes the session transcription XML files with or without the performance traces block of tags, utterance wave files, SDR, CDR, or ADR records.

Note:

- The Data Export Report does not include the session transcriptions and utterance wave files that reside on MPPs managed by a different EPM, that is, the MPPs that are in another Experience Portal system.
- The Data Export Report does not include transcriptions and/or utterances from MPPs that are in an Offline state.

Only one Data Export report request can be processed at a time.

The filters used in the Data Export report are based on the Session Detail report. However, the **Session Transcription** filter in the **Optional Filters** section is by default set to **All values**. If you are exporting Session Transcriptions and want to skip sessions that do not have transcriptions

enabled, then select **Yes** in the **Session Transcription** filter. This ensures that only the sessions with transcriptions are considered for generating the report.

Creating a Data Export report

Procedure

1. Log into the EPM web interface using an account with the Administration, Operations, or Maintenance user role.
2. From the EPM main menu, select **Reports > Standard**.
3. On the **Standard Reports** page, click **Data Export** link under the **Report Name** column.
4. Optionally, click  next to Data Export link to generate the report with the default selections of filters.
5. On the **Data Export (Filter)** page, enter the filter criteria that you want to use.

+ Tip:

Click the **more>>** link to display the rest of the optional filters

6. Click **OK**.

The EPM displays the Data Export Report page.

Generating Custom reports using third-party software

Generating Custom reports using third-party software

You can use third party reporting tools to create reports using some of the raw application, call, and session data collected by the Experience Portal system and stored in the reporting database. Most of the data is protected by the system for security reasons, but you can use the database report user account created during EPM installation to access the information in the:

- Application Detail Records (ADRs) stored in the `vpapplog` table. For more information, see [Custom application activity reports](#) on page 482.
- Contact Detail Records (CDRs) stored in the `cdr` table. For more information, see [Custom Contact Detail report](#) on page 484.
- Session Detail Records (SDRs) stored in the `sdr` table. For more information, see [Custom Session Detail report](#) on page 488.

*** Note:**

All data that you can access to create customized reports is Read-Only data.

Custom application activity reports

You can create custom application reports using the data stored in the `vpapplog` table of the PostgreSQL `VoicePortal` database. Experience Portal applications are designed to write log entries during their execution, much as other software applications do. Those log entries are composed of standard fields, some of which allow free-form string expressions. The occurrence and content of log entries is therefore subject to the design of the application. For each log entry, there is one row in the table. The columns of each row correspond to the standard fields. Rows are created after the controlling session completes and the data is pushed from the application server to a database updating web service on the EPM. Rows are deleted according to an administrable data retention limit.

Table 1: Primary Key column

This comprises of a collection of 5 columns:

Name
VPID
SessionID
MsgTimestamp
SessionIndex
Logtype

Table 2: Columns

Column	Data Type	Description
ActivityDuration	INTEGER	The number of seconds that have elapsed since the start of the activity. The start time for an activity is the time at which a record with <code>ActivityName <name></code> and <code>LogType Start</code> is logged.
ActivityName	VARCHAR (1024)	Application generated value used to group report or log entries. For example, "Buy Ticket" or "Rent Car".
ApplicationID	VARCHAR (512)	<code><Application Name></code> where entry was logged.
AppServerAddress	VARCHAR (512)	Host name or IP address of the application server where the application was initially invoked.
LogLevel	VARCHAR (512)	Application specified level of log entry "Info", "Warning", "Error", "Fatal".

Table continues...

Column	Data Type	Description
LogTimestamp	TIMESTAMP (62)	Date and time the log entry was generated in the time zone of the EPM.
LogType	VARCHAR (512)	Type of log (generated by application). The possible values are: • <code>Start</code>: Beginning of an activity. • <code>End</code>: End of an activity. • <code>In Progress</code>: General log entry. • <code>Cancel</code>: Canceling of an activity. • <code>Cancel All</code>: Cancel all started activities in session. • <code>Node Entry</code>: Generated automatically by the DD framework if the collection of 'Call Flow Data' is enabled when the application is configured on the EPM. The node that is being entered (destination node) is listed in the <code>ModuleIDNodeID</code> field. The previous node (Exit node or Source node) is listed in the <code>Message</code> field. • <code>Module Exit</code>: Generated automatically by the DD framework if the collection of 'Call Flow Data' is enabled when the application is configured on the EPM. The module name that is exiting is listed in the <code>ModuleIDNodeID</code> field. • <code>Application Exit</code>: Generated automatically by the DD framework if the collection of 'Call Flow Data' is enabled when the application is configured on the EPM.
Message	VARCHAR (1024)	Application-defined, free-format text.
ModuleIDNodeID	VARCHAR	The node name that is being entered when LogType is Node Entry. The module and node identifiers in the format <code>[Module Id]:Node Id</code> , where <code>Module Id</code> is only specified if it is <i>not</i> the same as the application name. For example, if the application name is <code>CollectTicketInfo</code> and it contains the <code>CollectTicketInfo</code> module with the node <code>StartTicket</code> and the <code>GetPayment</code> module with the node <code>StartPay</code> , you would specify them as <code>:StartTicket</code> and <code>GetPayment:StartPay</code> .
MsgTimestamp	TIMESTAMP	Date and time the log entry was generated in GMT time zone.
NoInputCount	INTEGER	The number of times that no input was received prior to entering this node. This field is only populated for LogType of Node Entry and only when the previous node was a menu.
NoMatchCount	INTEGER	The number of times that no match events occurred prior to entering this node. This field is only populated for LogType of Node Entry and only when the previous node was a menu.

Table continues...

Column	Data Type	Description
RecConf	INTEGER	The confidence reported by the speech recognition engine. This field is only populated for LogType of Node Entry and only when the previous node was a menu. Values will range from 0 to 99.
SessionID	VARCHAR (512)	Session ID generated by the media server.
SessionIndex	INTEGER	This log entry's position within the session, where 1 indicated the first log entry, 2 indicates the second log entry, and so on.
SessionLabel	VARCHAR (1024)	A unique identifier set by the application designer.  Note: An application designer can change the session label at any point while processing a single call. This field shows the label that was in effect when the log entry was made.
VarName	VARCHAR (1024)	A user-defined Dialog Designer application variable associated with this log entry by the application designer.
VarValue	VARCHAR (1024)	Value of variable defined in the column VarName when the log entry was made.
VPID	INTEGER	Identifies the EP system within a cluster of multiple EP systems that merge their data into the same external database. If there is only one EP system at your installation, this field will always be 1.

Custom Contact Detail report

You can create a custom Contact Detail report using the data stored in the `cdr` table of the PostgreSQL `VoicePortal` database. Experience Portal applications respond to incoming calls and can place outgoing calls. The details of each such call are recorded in this table. Call records are numbered sequentially by the database across each MPP and the Experience Portal system. Each call is further identified by a distinct universal identifier (UCID) received from the switch for communicating with other call handling systems. SessionID can be used to link a CDR record with its corresponding SDR and vpapplog records. This table has one row for each call handled by the Experience Portal cluster. Rows are created after the controlling session completes and the scheduled data download has occurred. Rows are deleted according to an administrable data retention limit.

Table 3: Primary Key Column

Name
InsertID

Table 4: Columns

Column	Data Type	Description
ApplicationName	VARCHAR (255)	Application name as configured in EPM.
AreaCode	INTEGER	The area code as extracted from the OriginatingNumber field based on rules defined in areacode.properties.
AudioCodec	VARCHAR (32)	Audio codec used in the call.
CallID	VARCHAR (255)	Unique call identifier assigned by the MPP. Value is unique within the Experience Portal cluster.
CallStartDate	INTEGER	Date the call started in YYYYMMDD format for the GMT timezone.
CallStartTime	INTEGER	Time in the day that the call started in HHMMSS format for the GMT timezone.
CallTimestamp	TIMESTAMP	Time in the day that the call started stored in a single Timestamp column. Based on GMT timezone.
CallType	INTEGER	Type of call: • 0: Inbound call. • 1: Outbound call.
ConnectLatency	INTEGER	The number of milliseconds until the call was connected.
DestinationNumber	VARCHAR (255)	DNIS - Pilot number of the application.
EMLEntryId	BIGINT, NUMBER(20,0)	Stores the primary key of the CDR record from the operational database for the email processor component. Contains 0 when CDR is from another source.
Duration	INTEGER	Call length in seconds.
EndDetails	VARCHAR (255)	Extra information as to why the call ended. For example: • SIT: Special Information tone (disconnected number). • Complete: SessionTerminated.
EndType	INTEGER	How the call completed: • 1: The call completed successfully; Near End Disconnect • 2: Transfer • 3: Far End Disconnect • 4: Interrupted • 5: Not Routed • 6: No Resource • 7: Session Manager Error • 8: Redirected • 9: Rejected

Table continues...

Column	Data Type	Description
		• 10: Merged • 11: TimeOut
FirstPromptLatency	INTEGER	The amount of time after the call connected and before the first prompt was played, in milliseconds.
InsertID	BIGSERIAL, NUMBER(20,0) BIGINT_ IDENTITY, BIGINT UNSIGNED	Unique sequence number which is automatically incremented by the database for each row that is inserted into the table. This field exists to permit easy access by extract, transform, and load (ETL) processes that are used by other Avaya products such as, Avaya IQ.
MediaType	INTEGER	Voice=0 (default), Video=1, SMSDelivery=2, SMS=3 EmailDSN=4, Email=5, HTML=6
MPP	VARCHAR (255)	The name of the MPP name that handled this session. This name is configured in the EPM.
OriginatingNumber	VARCHAR (255)	ANI - The caller's number.
PortID	INTEGER	The switch station for H.323.
ProviderName	VARCHAR(65)	The name of the Email or SMS provider that handled the message. The name is configured on the Connections tab for Email and Sms Processors in the EPM. For HTML contacts: It contains the browser-reported operating system and vendor information. For example, "Windows Desktop;Firefox;44.0" or "iPhone;Safari;8.0". The user's web browser determines the content and format.
ProviderMessage	VARCHAR(160)	For SMS, this is the SMS message. For Email, this is either the subject or body of the email as specified under Reporting Parameters when the application is configured on the EPM.  Note: • Only the first n characters are shown, as controlled by the Privacy section under Reporting Parameters when the application is configured on the EPM. The default is 0 characters. • The latter section can only be configured by an administrator who has the Privacy Manager role.
ProviderStatus	INTEGER	The status of the message from the provider. For SMPP, this column will store the 'command_status' from the submit_sm response. A value of 0 indicates Success. A value of -1 indicates that a status was not received within the configured timeout period.

Table continues...

Column	Data Type	Description
		The following are the Status values for emails with a MediaType of EmailDSN(4): • 0: Indicates that the message was successfully delivered to the recipient address specified by the sender, which includes "delivery" to a mailing list exploder. It does not indicate that the message has been read. This is a terminal state and no further DSN for this recipient should be expected. • 1: Indicates that the message could not be delivered to the recipient. The Reporting MTA has abandoned any attempts to deliver the message to this recipient. No further notifications should be expected. • 2: Indicates that the message has been relayed or gatewayed into an environment that does not accept responsibility for generating DSNs upon successful delivery. • 3: Indicates that the Reporting MTA has so far been unable to deliver or relay the message, but it will continue to attempt to do so. Additional notification messages may be issued as the message is further delayed or successfully delivered, or if delivery attempts are later abandoned. • 4: Some other unknown error occurred. The details might be in the DSN message
ReasonCode	VARCHAR (255)	Reason code from a transferred call.
ReceiptRequested	INTEGER	0 = contact was not sent with a delivery receipt request. 1 = contact was sent with a delivery receipt request.
RecordDate	INTEGER	The date on which the record was written on the MPP. The format is YYYYMMDD and is always in GMT.
RecordID	INTEGER	CDR entry count by day.
RedirectedNumber	VARCHAR (255)	The number of the extension that the call is transferred from when calls are transferred to Experience Portal.
RtpRcvJitter	INTEGER	An estimate of the statistical variance of the RTP data packet inter-arrival time, measured in timestamp units and expressed as an unsigned integer.
RtpRcvLost	INTEGER	The total number of RTP data packets from source that have been lost since the beginning of reception. This is the number of packets expected minus the number of packets actually received, where the number of packets received includes any which are late or duplicates.
RTPRcvPackets	INTEGER	The total number of RTP data packets received from the source.

Table continues...

Column	Data Type	Description
RTPRoundTripTime	INTEGER	The delay, expressed in units of 1/65536 seconds, between receiving the last SR packet from source SSRC_ <i>n</i> and sending this reception report block. If no SR packet has been received yet from SSRC_ <i>n</i> , the DLSR field is set to zero.
RTPSendJitter	INTEGER	The Jitter reported from the far end of the RTP stream.
RTPSendLost	INTEGER	The total RTP data packets lost as reported by the far end of the RTP stream.
RTPSendPackets	INTEGER	The total number of RTP data packets transmitted by the sender.
SessionID	VARCHAR (255)	Dialog ID generated by MPP .
SMSEntryId	BIGINT, NUMBER(20,0)	Stores the primary key of the CDR record from the operational database for the SMS processor component. Contains 0 when CDR is from another source.
SwitchOrProxy	VARCHAR (255)	Name of the Switch as configured by the EPM.
TelMediaEncryption	VARCHAR(255)	The media encryption used during the call, if any.
TelProtocol	VARCHAR (255)	Telephony protocol use. This can be: • H.323 • SIP • SIPS
UCID	VARCHAR (255)	The Universal Call ID.
VideoBitRate	VARCHAR (32)	Video bit rate used in the call.
VideoCodec	VARCHAR (32)	Video codec used in the call.
VideoFrameRate	INTEGER	Video frame rate used in the call in Frame Per Second (FPS).
VideoScreenSize	VARCHAR(32)	Video screen resolution delivered on the call.
VPID	INTEGER	The ID number of the EP system that handled the call. If there is only one EP system at your installation, the value of this field will always be 1.
ZoneID	INTEGER	Identifies the Zone of the component creating this record. This value can be used as a key into the vpZones table.

Custom Session Detail report

You can create a custom Session Detail report using the data stored in the `sdr` table of the PostgreSQL `VoicePortal` database. Experience Portal supports both simple VoiceXML applications, which have exactly one dialog per session, and general CCXML applications, which can have zero to many dialogs per session. This table describes details of each session and of each dialog. For simple VoiceXML applications there is one row describing both the session and its single dialog. For general CCXML applications, there is a separate row describing the overall session plus one additional row for each dialog that was invoked during that session. These three types of records are distinguished by the `RecordType` field. Records in this table are uniquely identified

across MPP and Experience Portal systems by a sequential number created by the database. SessionID can be used to link a SDR record with its corresponding CDR and vpapplog records. This table has one or more rows for each session handled by the Experience Portal cluster, as described above. Rows are created after the controlling session completes and the scheduled data download has occurred. Rows are deleted according to an administrable data retention limit.

Table 5: Primary Key Column

Name
InsertID

Table 6: Columns

Column	Data Type	Description
ApplicationName	VARCHAR(255)	Application name as configured in EPM.
AppServer	VARCHAR(255)	Initial URL as configured in EPM that triggered the application.
ASRPercent	INTEGER	Speech recognition percentage for the page with the lowest recognition. This value is computed using the values for: - The number of recognized utterances on the page with the worst recognition, as shown in the UttCntRecWPage column. - The number of total utterances received on the page, as shown in the UttCntWPage column. The formula is: $(\text{UttCntRecWPage} / \text{UttCntWPage}) * 100$
ASRServer	VARCHAR(255)	IP address of the ASR server used by the session.
AverageASRpercent	INTEGER	The average ASR percentage for the session, based on the total number of utterances and the total number of recognized utterances.
AverageLatency	INTEGER	The average time, in milliseconds, after the caller issued a speech command before the subsequent prompt began playing.
AverageRecConf	INTEGER	The average confidence level across all recognized utterances in this session.
DialogID	VARCHAR(255)	The unique ID that describes a specific VXML dialog associated with a particular session.
Duration	INTEGER	The total length of the session, in seconds.
EMLEntryId	BIGINT, NUMBER(20,0)	Stores the primary key of the SDR record from the operational database for the email processor component. Contains 0 when SDR is from another source.

Table continues...

Column	Data Type	Description
ExitCustomerID	VARCHAR(65)	Optional Information set by the application (through session.exitCustomerID variable in DD or manually through the Exit tag)
ExitPreferredPath	INTEGER	This field is determined by the DD framework: • 0 - if a node that has been flagged by the application developer as “unpreferred” was executed in this session. • 1 – if no “unpreferred” nodes were executed in this session.
ExitTopic	VARCHAR(65)	Optional Information set by the application (through session.exitTopic variable in DD or manually through the Exit tag)
HasPerformanceTrace	INTEGER	This can be: • 0: No performance data was captured for this session. • 1: The performance data was captured for this session.
HasTranscription	INTEGER	This can be: • 0: No transcription data was captured for this session. • 1: Transcription data was captured for this session.  Note: By default, the DD nodes are “Preferred”.
InsertRecordID	INTEGER	An uniquely sequential number that resets to 1 when the InsertDate changes.
LatAnswer	INTEGER	The time after which the call was connected and before the first prompt was played, in milliseconds.
LatencyHistogram1	INTEGER	The number of speech application pages that took less than one second to load.
LatencyHistogram2	INTEGER	The number of speech application pages that took between one and two seconds to load.
LatencyHistogram3	INTEGER	The number of speech application pages that took between two and three seconds to load.
LatencyHistogram4	INTEGER	The number of speech application pages that took between three and four seconds to load.
LatencyHistogram5	INTEGER	The number of speech application pages that took more than four seconds to load.
LatWPPage	INTEGER	Longest length of time that it took for any page to load, in milliseconds.
LatWPPageName	VARCHAR (512)	URL of the page that took the longest time to load.
MaxConsecutiveRecErrors	INTEGER	The maximum number of times in a row that an utterance was not recognized during a session.

Table continues...

Column	Data Type	Description
		This value tracks the maximum consecutive number of recognition errors, not the total number of recognition errors for a given utterance. For example, if the caller had to repeat the word "brokerage": • Twice on the first menu • Three times on the second menu This field would display 3.
MPP	VARCHAR(255)	The name of the MPP name that handled this session. This name is configured in the EPM.
MRCPSessionIDASR	VARCHAR(255)	MRCP Session ID for ASR.
MRCPSessionIDTTS	VARCHAR(255)	MRCP Session ID for TTS.
PageReqCacheHits	INTEGER	Number of VXML page cache hits.
PageReqTotal	INTEGER	Number of VXML page requests.
ParentID	VARCHAR(255)	Session ID of parent session, "root".
RecordDate	INTEGER	The date on which the record is written on the MPP. The format is YYYYMMDD and is always in GMT.
RecordID	INTEGER	SDR entry count by day.
RecordType	INTEGER	This can be: • 0: maintains statistics for an entire session and all dialogs within the session • 1: maintains statistics for a single dialog when multiple dialogs exist within a session • 2: maintains statistics for a session containing only a single dialog.
SessionID	VARCHAR(255)	Session ID generated by the media server .
SessionTimestamp	TIMESTAMP	Date and Time of the start of the session stored in a single Timestamp column. Based on GMT time zone.
Slot	INTEGER	MPP slot number that handled the call. This is related to the MPP session log generation.
SMSEntryId	BIGINT, NUMBER(20,0)	Stores the primary key of the SDR record from the operational database for the SMS processor component. Contains 0 when SDR is from another source.
Source	VARCHAR(255)	Cause of the session startup This can be: • Inbound: specifies session was generated from inbound call or an outbound call. • LaunchCCXML: specifies that the session was generated as an outbound call from LaunchVXML.

Table continues...

Column	Data Type	Description
		• LaunchVoiceXML: specifies that the session was generated as an outbound call from LaunchCCXML. • SMSInbound: The session was generated by an incoming SMS. • SMSReceipt: The session was initiated by a SMS delivery receipt. • EmailInbound: The session was generated by an incoming Email. • EmailReceipt: The session was initiated by an Email DSN. • LaunchSMS: The session was initiated through the LaunchSMS method on the outcall webservice. That is, through the SMS application. • LaunchEmail: The session was initiated through the LaunchEmail method on the outcall webservice. That is, through the Email application. LaunchHTML: The session was initiated through the LaunchHTML method on the outcall webservice. For example, called by the HTML Redirector app in response to a request from a mobile web browser.
StartDate	INTEGER	Date the session started in YYYYMMDD format. Based on GMT timezone.
StartPageName	VARCHAR(512)	URL of initial page loaded when call started.
StartTime	INTEGER	Time of day that the call started in HHMMSS format for GMT timezone.
TerminationInfo1	VARCHAR(64)	Optional Information set by the application (through the Exit tag or the session.exitInfo1 variable in DD).
TerminationInfo2	VARCHAR(64)	Optional Information set by the application (through the Exit tag or the session.exitInfo2 variable in DD)
TerminationInfo3	VARCHAR(64)	Optional Information set by the application (through the Exit tag*)
TerminationInfo4	VARCHAR(64)	Optional Information set by the application (through the Exit tag*)
TerminationInfo5	VARCHAR(64)	Optional Information set by the application (through the Exit tag*)
TerminationInfo6	INTEGER	Optional Information set by the application (through the Exit tag*)
TerminationInfo7	INTEGER	Optional Information set by the application (through the Exit tag*)
TerminationInfo8	INTEGER	Optional Information set by the application (through the Exit tag*)

Table continues...

Column	Data Type	Description
TerminationInfo9	INTEGER	Optional Information set by the application (through the Exit tag*)
TerminationInfo10	INTEGER	Optional Information set by the application (through the Exit tag*)
TerminationPageName	VARCHAR(512)	The VoiceXML or CCXML page where the disconnect event occurred.
TerminationPageNameShort	VARCHAR(255)	The VoiceXML or CCXML page where the disconnect event occurred. Similar to terminationpagename column except contains only the page name and the file extension, rather than the full URL.
TerminationReason	VARCHAR(64)	Reason call terminated as set by the application (through the Exit tag). If an application does not set a value, the system defines the default value as Application exited.
TTSServer	VARCHAR(255)	IP address of the TTS server used by the session.
UttCntRecWPage	INTEGER	Number of recognized utterances received on the page with the worst recognition
UttCntTot	INTEGER	Total number of utterances in session.
UttCntTotRec	INTEGER	Total number of recognized utterances in session.
UttCntRecWPage	INTEGER	Number of recognized utterances made on the page with the lowest percentage of correctly recognized utterances.
UttCntWPage	INTEGER	Total number of utterances made on the page with the lowest percentage of correctly recognized utterances.
VPID	INTEGER	Identifies the EP system within a cluster of multiple EP systems that merge the data into the same external database. If there is only one EP system at an installation, this field is always 1.
ZoneID	INTEGER	Identifies the Zone of the component creating this record. This value can be used as a key into the vpZones table. Added in EP 7.0

VPApplication table

Experience Portal is a platform on which customer defined web applications control call flow based on your information provided through voice dialogs. Applications are identified by name on each Experience Portal system in a cluster. The system invokes an application through its URL in order to handle a call. There is one row in this table for each application in a cluster.

Table 7: Primary key columns

Name
VPID
AppName

Table 8: Columns

Column	Data Type	Description
VPID	INTEGER	Identifies the EP system within a cluster of multiple EP systems that merge the data into the same external database. If there is only one EP system at an installation, this field is always 1.
AppName	VARCHAR2(256)	A text string identifying the application within a particular Experience Portal system.
AppURL	VARCHAR2(2048)	The invocation URL of the application.
DeleteDate	VARCHAR2(64)	Currently unused.

Custom VPPerformance Reports

The vpperformance report contains performance statistics for each MPP in the Experience Portal system. This information is obtained from the MPP heartbeat request and is aggregated over a configured period (5 minutes by default). Statistics are identified by the ResourceID and apply to a specific time interval and a specific MPP server in the cluster. This table has one row for each statistic, for each MPP in a cluster, for each time interval in which an MPP heartbeat response was received. Rows are created upon completion of each aggregation period. Rows are deleted according to an administrable data retention limit.

Table 9: Primary key columns

Name
VPID
MPP
Time
ResourceID
ComponentID

Table 10: Columns

Column	Data Type	Description
VPID	INTEGER	Identifies the EP system , within a cluster of multiple EP systems that merge the data into the same external database. If there is only one EP system at an installation, this field will always be 1.
MPP	VARCHAR2(256)	The unique name assigned to this MPP through the EPM.
Time	VARCHAR2(64)	Timestamp of the aggregated statistic.

Table continues...

Column	Data Type	Description
ResourceID	VARCHAR2(256)	Name of the statistic to which this row applies: • CPU - Percentage of CPU utilization • Disk - Percentage of disk utilization • Memory - Percentage of memory in use • Port - Percentage of licensed telephony resources currently in use • Inbound Calls - Total active inbound calls • Outbound Calls - Total active outbound calls
Duration	INTEGER	Time period that the data represents in milliseconds.
Sum	INTEGER	Sum of all the statistics taken in the aggregation period.
Count	INTEGER	Number of statistics taken in the aggregation period (number of heartbeats).
Peak	INTEGER	Largest statistic taken in the aggregation period.
Minimum	INTEGER	Smallest statistic taken in the aggregation period.
CurrentResource	INTEGER	Last value received from the heartbeat in aggregate period.
SourceType	INTEGER	Type of system resource is from: • 0 = MPP • 1 = EPM Primary • 2 = EPM Secondary • 3 = Overall Experience Portal • 4 = OM Stat
ComponentID	INTEGER	The component ID from AMS for OM statistic. The value in this column is populated when the value of SourceType is equal to 4. This column was added in Experience Portal 6.0.

VPMpps table

Each Experience Portal system in a cluster is supported by one or more media servers; the number being configured to support the anticipated system load. When a media server receives a call from a PBX, it invokes a VoiceXML application on an application server and communicates with ASR and TTS servers to process the call. Media servers are identified by name on each Experience Portal system in a cluster. There is one row in this table for each media server in the Experience Portal cluster.

Table 11: Primary key columns

Name

Table continues...

VPID
MPPName

Table 12: Columns

Column	Data Type	Description
VPID	INTEGER	Identifies the Experience Portal system within a cluster of multiple Experience Portal systems that merge the data into the same external database. If there is only one Experience Portal system at an installation, this field is always 1.
MPPName	VARCHAR2(256)	The unique name assigned to the media server through the EPM.
DeleteDate	VARCHAR2(64)	Currently unused.

VPSystems table

Multiple Experience Portal systems store their reporting data in the same external database even though those systems are autonomous in all respects. Together these multiple Experience Portal systems are said to form the Experience Portal cluster. To ensure that the data from separate systems can be distinguished, each system is assigned a unique numeric identifier (the VPID) in addition to having a unique system name (the VPName).

This table has one row for each Experience Portal system in the Experience Portal cluster.

*** Note:**

This data model differs slightly from the actual implementation. The model lists VPID as the primary key to illustrate the logical relationships between tables. In the actual implementation the primary key is VPName with VPID as an attribute.

Table 13: Primary key columns

Name
VPID

Column	Data Type	Description
VPID	INTEGER	Identifies the EP system , within a cluster of multiple EP systems that merge the data into the same external database. If there is only one EP system at an installation, this field is always 1.
VPName	VARCHAR2(512)	The administered name of this Experience Portal system.
TimeZoneDrift	INTEGER	Offset in milliseconds of the Experience Portal system from GMT.
AdminURL	VARCHAR2(2048)	IP address of the Experience Portal system.

Table continues...

Column	Data Type	Description
CreateDate	VARCHAR2(64)	Timestamp of the time the Experience Portal system was first added to the cluster.
LastUpdate	VARCHAR2(64)	Timestamp of the time that configuration data changed in the table.
LicensedTelephony	INTEGER	Total telephony licenses purchased for the Experience Portalsystems.
LicensedASR	INTEGER	Nonzero if ASR is licensed for the Experience Portal system.
LicensedTTS	INTEGER	Nonzero if TTS is licensed for the Experience Portal system.
CallCapacity	INTEGER	Total Telephony resources concurrently configured to take calls across all media servers for this EP system. The number can be less than the sum of the individual media server maximum port configuration represented by TotalCapacity column.
LicensesAllocated	INTEGER	Telephony resources assigned to MPPs.
TotalCapacity	INTEGER	Total of the maximum call capacity of all the MPPs in an EP system.
DatabaseFail	TIMESTAMP	Currently unused.
IncomingCalls	INTEGER	Number of currently active inbound calls.
OutgoingCalls	INTEGER	Number of currently active outbound calls made from Experience Portal system.
AlarmStatus	INTEGER	Current alarm status of the Experience Portal system: • 0 = none • 1 = Minor • 2 = Major • 3 = Critical Corresponds to EPM Status Monitor Alarm icons : • 0 - green • 1 - yellow • 2 - red
StatusUpdate	VARCHAR2(64)	Timestamp of when the last status update occurred (Licensing and call info).
SystemType	INTEGER	Primary or secondary
RecordStatus	VARCHAR2(32)	Set to 'Active' if the Experience Portal system participates in the cluster. Set to 'Inactive' if the Experience Portal system left the cluster.
Version	VARCHAR(32)	The version of the software that is currently running on the system.

VPUCIDMap table

This report maps each MPP within a cluster to a unique numeric identifier, MPPID, which is included in UCID strings identifying calls originated by that media server. This table is just an extension of the VPMPPs table. There is one row in this table for each MPP server in an EP cluster.

The primary keys are:

- VPID
- MPPName

Column	Data Type	Description
VPID	INTEGER	Identifies the EP system , within a cluster of multiple EP systems that merge the data into the same external database.
MPPName	VARCHAR2(256)	The unique name assigned to the MPP through the EPM.
MPPID	INTEGER	Internally generated ID assigned to each MPP which is unique across the cluster. The ID is used to generate UCID.

Generating Custom reports using Experience Portal Manager

Custom Reports using EPM

You can use the Custom Reports feature to generate reports for your specific requirements. You must select a standard report or an existing custom report format as a base for generating the custom report. The custom report uses the standard set of filters defined by the Experience Portal system for the selected base report. You can then change the selection of filters to suite your requirements.

You can run the Custom Report on-demand by clicking the View Report icon. Prior to generating a report, you can also click the Report Name link on the Custom Reports page to view and edit the saved filter and column values.

 Note:

You cannot change the source report and the name of the report while editing the custom report filters.

Generating a Custom report using EPM

About this task

The custom report provides summary information about all the filtering options specified in the source report that you used for generating the report.

Procedure

1. Log on to the EPM Web interface using an account with the Administration, Operations, or Maintenance user role.
2. From the EPM main menu, select **Reports > Custom**.
3. On the Custom Reports page, click **Add**.
4. Optionally, click  next to the existing custom report name link to generate the report.

+ Tip:

Placing the mouse pointer over the existing custom report name displays a tooltip that lists the user ID of the user who created the custom report.

5. On the Add Custom Report (Filters) page, select a source report from the **Standard Reports** or the **Custom Reports** lists. On selecting a source report, the filters get refreshed to correspond to the selected source report.
6. To create a custom report with organization level access, select an organization from the **Organizations** list. If you do not select an organization, this indicates that the user does not belong to any organization.

*** Note:**

This field is displayed only if organization level access is enabled in the Avaya Aura[®] Experience Portal system and you have logged in as a user not assigned to any organization. For more information on organization level access, see [Organization level access in Avaya Aura Experience Portal](#) on page 126.

If you select an organization for a custom report, the option to select an application is enabled. Only those applications are listed which belong to the organization.

7. Specify a name for the report.

*** Note:**

If you have selected an organization in the field above, the selected organization and forward slash character are automatically prefixed to the report name.

8. Enter the filter criteria that you want to use.

+ Tip:

Click the **more >>** link to display the rest of the optional filters.

9. Click **OK**.

The EPM displays the report.

10. Optionally, click **Save** to save the filter settings without generating the report.

Trending By report

Use the Contact Summary Report to produce a trending report to compare different categories of information over a period of time. You can define custom reports that display activities of your interest and use the trending report feature in Contact Summary Report to see how the activity levels varied from day to day. You can compare five such items in a single report.

The report displays the output in both tabular and graph format. The tabular format displays the daily summary and contains a row for every day in the specified time range. The graph displays hourly data and starts with the first hour that contains data and ends with the last hour that contains data.

Each metric displayed in the Contact Trending table and graph is represented by an Experience Portal custom report. Each custom report must contain the filter values that produce a single metric when that report is run. The Trending By option in the Contact Summary filter page provides all eligible custom reports. You can select multiple custom reports to generate the output. Experience Portal uses the name of the custom report as the metric name in the Trending By output table and graph.

The following custom reports are not supported and not displayed for selection:

- Custom reports based on Performance Reports
- Custom reports that contain Trending By reports

Note:

Application reports that contain vxml or ccxml log tags are not currently supported. However, reports populated by the Orchestration Designer call flow data or Orchestration Designer report nodes are supported.

Scenario

A car rental business wants to track and compare certain types of car size rentals over a period of time.

Method

- Set the car size in either an SDR exit variable or log it through the Report Node to the vpAppLog table through the Orchestration Designer application.
- Create two custom reports:
 - One with the filter values to restrict the output of that report to only sessions where small cars were rented. For example, a Session Summary report with **ExitInfo1** set to `small`.
 - Another with sessions where midsize cars were rented. For example, a Session Summary report with **ExitInfo1** set to `midsize`.
- Select both custom reports in the **Trending By** field.

Analysis

The report displays how many contacts each day were associated with the sessions in each of the custom reports. Click the View Graph link to display a timeline graph of hourly contacts that met the criteria in the custom report. The Contact Trending report might show that during the past 90 days rentals of midsize cars trended 20% higher as compared to a relatively flat number of rentals for small cars.

Scheduled reports

Scheduled Reports

You can schedule the generation of the standard or the custom reports to occur on a periodic or one time basis. You can receive the report output as an e-mail attachment, or access it through the secure links in the e-mail notification, RSS feeds or by logging into the Experience Portal Manager (EPM). You can optionally set **Record Threshold** restriction value when scheduling a report. Setting this restriction generates a notification only when the total record count reaches the specified minimum value.

Using the Scheduled Reports page, you can add, edit, or delete a scheduled report. You can also view and export the report output for a specified report or all the reports.

The Scheduled Reports page is distributed in two tabs:

- Schedules
- Outputs

Use the **Schedules** tab to view, add, edit, or delete a scheduled report. You can also view and export the details regarding the output and history for a specific scheduled reports by clicking the **Output** folder icon on this tabbed page. You can also subscribe for change notifications by clicking the  icon under **Notification Method** column.

Use the **Outputs** tab to view the details regarding the output and history for all the scheduled reports. You can export the report outputs by clicking the **Export** icon on this tabbed page.

Scheduling a Report

Procedure

1. Log on to the EPM Web interface using an account with the Administration, Operations, or Maintenance user role.
2. From the EPM main menu, select **Reports > Scheduled**.
3. On the Scheduled Reports page, click **Add**.

4. On the Add Scheduled Report page, select a source report that you want to schedule, from the **Standard Reports** or the **Custom Reports** lists.
5. Enter the filter criteria that you want to use.
6. Specify the date and time for the scheduling, notification method that you want to use, and the record threshold restriction value.
7. Specify the **Output Type** for the scheduled report. You can select one of the **xls**, **pdf**, and **csv** options.
8. Click **Save**.

The EPM displays the scheduled report entry on the Scheduled Reports page.

SQL queries for the EPM reports

When the EPM generates a report, it sends one or more SQL queries to the Experience Portal database and displays the result as a EPM page. This topic shows the:

- [Application Detail report query](#) on page 502
- [Application Summary report queries](#) on page 502
- [Contact Detail report query](#) on page 503
- [Contact Summary report queries](#) on page 503
- [Performance report queries](#) on page 503
- [Session Detail report query](#) on page 503
- [Session Summary report queries](#) on page 504

Note:

For all reports, user-entered dates and times are converted from the local EPM server timezone to the GMT timezone prior to performing the SQL query.

Application Detail report query

```
SELECT * FROM vpapplog
WHERE (LogTimestamp >= 'yyyy-mm-dd hh:mm:ss.0' AND LogTimestamp <= 'yyyy-mm-dd hh:mm:ss.0')
ORDER BY logtimestamp DESC, sessionindex DESC LIMIT 10000;
```

Application Summary report queries

```
SELECT {SummarizeByField}, count(*) as TotalCount FROM vpapplog
WHERE (LogTimestamp >= 'yyyy-mm-dd hh:mm:ss.0' AND LogTimestamp <= 'yyyy-mm-dd hh:mm:ss.0')
GROUP BY {SummarizeByField} ORDER BY TotalCount DESC;
CREATE TEMP TABLE tmpADR AS
SELECT DISTINCT sessionid, {SummarizeByField} FROM vpapplog
WHERE (LogTimestamp >= 'yyyy-mm-dd hh:mm:ss.0' AND LogTimestamp <= 'yyyy-mm-dd hh:mm:ss.0')
GROUP BY sessionid, {SummarizeByField};
+
SELECT {SummarizeByField}, count(*) as CallCount FROM tmpADR
GROUP BY {SummarizeByField} ORDER BY CallCount desc;
```


Where *{SummarizeByField}* can be any of the following:

- loglevel
- message
- activityname
- logtype
- varname & varvalue

Contact Detail report query

```
SELECT * FROM CDR
WHERE ( (CALLSTARTDATE > yyyyymmdd OR (CALLSTARTDATE = yyyyymmdd AND CALLSTARTTIME >=
hhmmss )) AND
( CALLSTARTDATE < yyyyymmdd OR (CALLSTARTDATE = yyyyymmdd AND CALLSTARTTIME <= hhmmss)) )
ORDER BY CALLSTARTDATE ASC, CALLSTARTTIME ASC, RECORDID ASC LIMIT 10000;
```

Contact Summary report queries

```
SELECT Count(DURATION) as totalcalls, Sum(DURATION) as totalsum, ENDTYPE as etype FROM CDR
WHERE ( (CALLSTARTDATE > yyyyymmdd OR (CALLSTARTDATE = yyyyymmdd AND CALLSTARTTIME >=
hhmmss )) AND
( CALLSTARTDATE < yyyyymmdd OR (CALLSTARTDATE = yyyyymmdd AND CALLSTARTTIME <= hhmmss)) )
GROUP BY ENDTYPE;
SELECT Count(DURATION) as totalcalls, Sum(DURATION) as totalsum, applicationname FROM CDR
WHERE ( (CALLSTARTDATE > yyyyymmdd OR (CALLSTARTDATE = yyyyymmdd AND CALLSTARTTIME >=
hhmmss )) AND
( CALLSTARTDATE < yyyyymmdd OR (CALLSTARTDATE = yyyyymmdd AND CALLSTARTTIME <= hhmmss)) )
GROUP BY applicationname ORDER BY Count(DURATION) desc;
SELECT Count(*) as totalcalls, Sum(DURATION) as totalsum, MPP as mppcolumn FROM CDR
WHERE ( (CALLSTARTDATE > yyyyymmdd OR (CALLSTARTDATE = yyyyymmdd AND CALLSTARTTIME >=
hhmmss )) AND
( CALLSTARTDATE < yyyyymmdd OR (CALLSTARTDATE = yyyyymmdd AND CALLSTARTTIME <= hhmmss)) )
GROUP BY MPP ORDER BY COUNT(MPP) DESC;
SELECT Count(MPP) as totalcalls, Sum(DURATION) as totalsum, MPP as mppcolumn, PORTID as
portidcolumn FROM CDR
WHERE ( (CALLSTARTDATE > yyyyymmdd OR (CALLSTARTDATE = yyyyymmdd AND CALLSTARTTIME >=
hhmmss )) AND
( CALLSTARTDATE < yyyyymmdd OR (CALLSTARTDATE = yyyyymmdd AND CALLSTARTTIME <= hhmmss)) )
GROUP BY MPP, PORTID ORDER BY COUNT(MPP) DESC;
SELECT callstartdate, callstarttime, recordid FROM CDR
WHERE ( (CALLSTARTDATE > yyyyymmdd OR (CALLSTARTDATE = yyyyymmdd AND CALLSTARTTIME >=
hhmmss )) AND
( CALLSTARTDATE < yyyyymmdd OR (CALLSTARTDATE = yyyyymmdd AND CALLSTARTTIME <= hhmmss)) )
ORDER BY CALLSTARTDATE ASC, CALLSTARTTIME ASC, RECORDID ASC;
SELECT duration/60 AS BUCKET, count(duration) AS BUCKETCOUNT FROM CDR
WHERE ( (CALLSTARTDATE > yyyyymmdd OR (CALLSTARTDATE = yyyyymmdd AND CALLSTARTTIME >=
hhmmss )) AND
( CALLSTARTDATE < yyyyymmdd OR (CALLSTARTDATE = yyyyymmdd AND CALLSTARTTIME <= hhmmss)) )
GROUP BY duration/60 ORDER BY BUCKET DESC;
```

Performance report queries

```
SELECT Max(Peak) as peak, sum(sum) as sum, sum(count) as count, mpp, resourceid FROM
vppformance
WHERE (time >='yyyy-mm-dd hh:mm:ss.0' AND time < 'yyyy-mm-dd hh:mm:ss.0')
GROUP BY mpp, resourceid ORDER BY mpp;
SELECT peak/10 as util_buckets, sum(duration) as duration FROM vppformance
where time >='yyyy-mm-dd hh:mm:ss.0' AND time < 'yyyy-mm-dd hh:mm:ss.0' AND resourceid =
'PORT'
GROUP BY util_buckets ORDER BY util_buckets;
```

Session Detail report query

```
SELECT * FROM SDR
WHERE ( (STARTDATE > yyyyymmdd OR (STARTDATE = yyyyymmdd AND STARTTIME >= hhmmss )) AND
```

```
( STARTDATE < yyyyymmdd OR (STARTDATE = yyyyymmdd AND STARTTIME <= hhmmss)) )
ORDER BY STARTDATE ASC, STARTTIME ASC, RECORDID ASC LIMIT 10000;
```

Session Summary report queries

```
SELECT count(recordid) as totalcalls, avg(timetillanswer) as timetillanswer,
avg(latanswer) as latanswer,
avg(duration) as duration, avg(uttcnttot) as uttcnttot, avg(uttcnttotrec) as
uttcnttotrec, avg(pagereqcachehits) as pagereqcachehits,
avg(pagereqtotal) as pagereqtotal FROM SDR
WHERE ( (STARTDATE > yyyyymmdd OR (STARTDATE = yyyyymmdd AND STARTTIME >= hhmmss )) AND
( STARTDATE < yyyyymmdd OR (STARTDATE = yyyyymmdd AND STARTTIME <= hhmmss)) );
SELECT latwpage as latwpage, latwpagename as latwpagename, mpp as mpp FROM SDR
WHERE ( (STARTDATE > yyyyymmdd OR (STARTDATE = yyyyymmdd AND STARTTIME >= hhmmss )) AND
( STARTDATE < yyyyymmdd OR (STARTDATE = yyyyymmdd AND STARTTIME <= hhmmss)) )
ORDER BY latwpage desc;
SELECT uttcntwpage as uttcntwpage, uttcntrecwpage as uttcntrecwpage, uttwpagename, mpp as
mpp, asrpercent FROM SDR
WHERE ( (STARTDATE > yyyyymmdd OR (STARTDATE = yyyyymmdd AND STARTTIME >= hhmmss )) AND
( STARTDATE < yyyyymmdd OR (STARTDATE = yyyyymmdd AND STARTTIME <= hhmmss)) )
ORDER BY asrpercent asc;
SELECT Count(*) as totalsessions, vpid, applicationname, terminationpagenameshort
FROM SDR WHERE ( (STARTDATE > yyyyymmdd OR (STARTDATE = yyyyymmdd AND STARTTIME >=
hhmmss )) AND
( STARTDATE < yyyyymmdd OR (STARTDATE = yyyyymmdd AND STARTTIME <= hhmmss)) )
GROUP BY vpid, applicationname, terminationpagenameshort order by vpid, applicationname,
totalsessions desc
```

Chapter 21: Security

Enabling password protection for Single User Mode on Avaya Enterprise Linux

About this task

Booting the Avaya Enterprise Linux system in a Single User Mode without password protection is a security risk. Use this procedure to enable password protection for a Single User Mode login to the Avaya Enterprise Linux system for security reasons.

Note:

By default, the system does not ask for a password of a root user trying to log on in a Single User Mode in the Avaya Enterprise Linux system.

Procedure

1. To enable password requirement in the `/etc/sysconfig/init` file:
 - a. Log on using a secure shell session (SSH) to the Avaya Enterprise Linux system as a user with root privileges.
 - b. Open the `/etc/sysconfig/init` file and replace `SINGLE=/sbin/subshell` with `SINGLE=/sbin/sulogin`.
2. To set password for the root user to enable password protection for the Single User Mode:

By default, the `root` user is disabled from logging into the Avaya Enterprise Linux for security reasons.

 - a. Using a secure shell session (SSH), log on to the Avaya Enterprise Linux system as a user with root privileges.
 - b. On the command prompt, enter `passwd root`.
 - c. In New password, type the new password and press **Enter**.
 - d. In Retype new password, reenter the new password and press **Enter**.
3. To boot the Avaya Enterprise Linux system in a Single User Mode:
 - a. Log on to the Avaya Enterprise Linux system using a secure shell session (SSH) .
 - b. On the command line, enter `init 1` to boot the system in a Single User Mode.
 - c. Enter the root password when the system asks for a **root password**.

Disabling MPP core files

About this task

The core dump files on the MPP server can contain sensitive data. You can disable the generation of core files to prevent logging of sensitive data. However, if you disable the core files, you cannot troubleshoot MPP failures when processes terminate unexpectedly.

Procedure

1. Log on to Linux on the Experience Portal MPP server.
2. Navigate to the `MPP config` directory by entering the `cd $AVAYA_MPP_HOME/config` command.

`AVAYA_MPP_HOME` is the environment variable pointing to the name of the MPP installation directory specified during the Experience Portal software installation.

3. Edit the `mpp` file and make the following changes:

Change `ULIMIT_COREFILE="unlimited"` to `ULIMIT_COREFILE="0"`

4. Repeat this procedure on each MPP server.

Chapter 22: Experience Portal Manager main menu customizations

EPM main menu customizations

Avaya Aura® Experience Portal offers those users who need additional functionality in the Experience Portal Manager (EPM) main menu the ability to modify and customize the EPM main menu by changing the associated configuration files.

The EPM main menu consists of menu groups and menu items associated with each group.

Examples of the menu groups in the EPM include the **User Management** and **System Maintenance** groups.

Examples of menu items under the **System Maintenance** group include **Trace Viewer**, **Log Viewer**, and **Alarm Manager**.

You can add menu items to existing menu groups, or add entire menu groups with their own menu items to the EPM main menu.

Related links

[Add a new menu group and items](#) on page 508

[Add menu items to an existing menu group](#) on page 515

The EPM main menu configuration files

Note:

You must define the groups and items in all four `configuration` files before they will display properly in the EPM main menu.

configuration menu.xml file

This file defines the groups and items that can appear in the main menu. It is located in the `TomcatHome/lib/config` directory, where `TomcatHome` is the directory in which the Tomcat servlet engine software is installed. The default is `/opt/Tomcat/tomcat`.

display.menu.properties file

This file defines the text that the EPM displays for the groups and items defined in the configuration `menu.xml` file. The `display.menu.properties` file is located in the `TomcatHome/lib/messages` directory, where `TomcatHome` is the directory in which the Tomcat servlet engine software is installed. The default is `/opt/Tomcat/tomcat`.

features.xml file

This file defines which user roles can see the menu groups and items defined in the configuration `menu.xml` file. The `features.xml` file is located in the `TomcatHome/lib/config` directory, where `TomcatHome` is the directory in which the Tomcat servlet engine software is installed. The default is `/opt/Tomcat/tomcat`.

features.properties file

This file defines the text that the EPM displays on the Roles web pages for the features defined in the configuration `features.xml` file. The `features.properties` file is located in the `TomcatHome/lib/messages` directory, where `TomcatHome` is the directory in which the Tomcat servlet engine software is installed. The default is `/opt/Tomcat/tomcat`.

Related links

[Add a new menu group and items](#) on page 508

[Add menu items to an existing menu group](#) on page 515

Add a new menu group and items

To add a new menu group, complete the following procedures:

Step	Task	✓
1	Define a unique extensions directory as described in Defining a unique extensions directory on page 520.	
2	Define the new menu group and its items in the configuration <code>menu.xml</code> file as described in Defining a new menu group and its items on page 509.	
3	Define the labels that will be displayed for the menu group and its items in the <code>display.menu.properties</code> file as described in Defining labels for the new menu group and its items on page 511.	
4	Set the access permissions by defining the user roles that can see the menu group and each of its items in the <code>features.xml</code> file as described in Setting user access permissions for the new menu group and its items on page 511.	
5	Define the labels that will be displayed for the features in the <code>display.feature.properties</code> file as described in Defining labels for the features in the new menu group and its items on page 513.	

Related links

[EPM main menu customizations](#) on page 507

[The EPM main menu configuration files](#) on page 507

Defining a new menu group and its items

About this task

The configuration `menu.xml` file specifies the location of and properties for your new menu group and the menu items.

Procedure

1. In an ASCII text editor, create a configuration `menu.xml` file in the `TomcatHome/lib/extensions/UniqueDirectoryName/config` directory, where `TomcatHome` is the directory in which the Tomcat servlet engine software is installed and `UniqueDirectoryName` is the directory defined as described in [Defining a unique extensions directory](#) on page 520. The default is `/opt/Tomcat/tomcat`.

2. Create the basic template for the `menu.xml` by adding the following tags:

```
<?xml version="1.0" encoding="UTF-8"?>
<navigationmenu
  xmlns:xsi="http://www.w3.org/2001/XMLSchema-instance"
  xsi:noNamespaceSchemaLocation="menu.xsd">
</navigationmenu>
```

3. For each menu group to be defined, add the `<menu>` and `</menu>` tags just before the `</navigationmenu>` tag.

* Note:

A menu group is defined by a `<menu>` tag followed by one or more `<item>` tags. The `<menu>` tag must end with a `</menu>` tag.

4. For each menu tag you add for defining a group, specify the following menu attributes:

Attributes	Example	Description
<code>type="group"</code> , where <code>type</code> defines the type of the menu.	To specify the type of the menu as <code>group</code> , specify <code>type="group"</code>	This attribute defines the type of the menu tag.
<code>render=[true false]</code> , where <code>render</code> is either <code>true</code> or <code>false</code> .	To instruct the EPM to display the menu group, specify <code>render=true</code>	If you set this property to <code>false</code> , the EPM does not display the menu group.
<code>tag="groupTag"</code> , where <code>groupTag</code> is the identifier the system uses to identify the group.	To assign the name specify, <code>tag="newMenuGroupId"</code>	The identifier of the menu group. This identifier must be unique across all menu groups and menu items in the configuration <code>menu.xml</code> file.

5. For each menu item you want to add, specify the `<item>` tag after the `<menu>` tag but before the corresponding `</menu>` tag and specify the following attributes:

*** Note:**

A menu item within a menu group is defined by an `<item>` tag.

Attributes	Example	Description
<code>type="item"</code> , where <i>type</i> defines the type of the item.	To specify the type of the menu item as <i>item</i> , specify <code>type="item"</code> .	This attribute defines the type of the item tag.
<code>render=[true false]</code> , where <i>render</i> is either <i>true</i> or <i>false</i> .	To instruct the EPM to display the item in the menu group, specify <code>render=true</code>	If you set this property to <i>false</i> , the EPM does not display the menu group.
<code>tag=itemTag</code> , where <i>itemTag</i> is the identifier the system uses to identify the item.	Specify <code>tag="newMenuItemIdentifier"</code>	The identifier of the menu item. This identifier must be unique across all menu groups and menu items in the configuration <code>menu.xml</code> file.
<code>action=displayURL</code> , where <i>displayURL</i> is the URL that you want the system to display when a user clicks this item.	To instruct the EPM to open <code>admin.ops.page.html</code> when the user clicks on the second item of the fifth menu group, specify <code>action="http://my.site.com/custom_pages/admin.ops.page.html"</code>	Determines what page Experience Portal displays when the user selects the menu item. ! Important: Experience Portal does not validate this URL
<code>newWindow="[true false]"</code> , where <i>newWindow</i> is either <i>true</i> or <i>false</i> .	To instruct the EPM to open a new page when the user clicks on the menu item of the menu group, specify <code>newWindow=true</code>	If this option is set to <i>true</i> , Experience Portal opens the specified URL in a new browser window. If you do not specify this property, it defaults to <i>false</i> .

6. For each new `<item>` tag, specify a `</item>` tag to end the menu item definition.

7. Save and close the file.

Example

For example, if you have a group called `myMenuGroup` with menu items `myUsersItem`, `myAdminItem`, and `myUserMgrItem`, the entire section could look like this:

```
<?xml version="1.0" encoding="UTF-8"?>
<navigationmenu
  xmlns:xsi="http://www.w3.org/2001/XMLSchema-instance"
  xsi:noNamespaceSchemaLocation="menu.xsd">
  <menu type="group" render="true" tag="myMenuGroup">
    <item type="item" render="true" tag="myUsersItem"
      action="http://my.site.com/custom/users.page.html" newWindow="true">
    </item>
    <item type="item" render="true" tag="myAdminItem"
      action="http://my.site.com/custom/admin.page.html" newWindow="true">
    </item>
    <item type="item" render="true" tag="myUserMgrItem"
```



```

        action="http://my.site.com/custom/usermgr.page.html" newWindow="true">
    </item>
</menu>
</navigationmenu>

```

Defining labels for the new menu group and its items

About this task

The display `menu.properties` file specifies the labels that the EPM displays to the end user.

Procedure

1. In an ASCII text editor, open the `display menu.properties` file in the `TomcatHome/lib/extensions/UniqueDirectoryName/messages` directory, where `TomcatHome` is the directory in which the Tomcat servlet engine software is installed and `UniqueDirectoryName` is the directory as described in [Defining a unique extensions directory](#) on page 520. The default is `/opt/Tomcat/tomcat`.
2. Add a section for each menu group that you added to the configuration `menu.xml` file as shown below:

```

myMenuGroup=groupDisplayText
myMenuItem=itemDisplayText

```

where:

- `myMenuGroup` is the menu group identifier specified in the `menu.xml` configuration file.
- `myMenuItem` is the menu item identifier specified in the `menu.xml` configuration file.
- `groupDisplayText` is the group label that Experience Portal displays in the EPM main menu.
- `itemDisplayText` is the item label that Experience Portal displays in the EPM main menu.

3. Save and close the file.

Example

For example:

```

myMenuGroup=My Menu Group
myUsersItem=Users
myAdminItem=Administrator
myUserMgrItem=User Manager

```

Setting user access permissions for the new menu group and its items

About this task

The `features.xml` file specifies which user roles have access to a menu group and each item in the group.

Procedure

1. In an ASCII text editor, create a configuration `features.xml` file in the `TomcatHome/lib/extensions/UniqueDirectoryName/config` directory, where `TomcatHome` is the directory in which the Tomcat servlet engine software is installed and `UniqueDirectoryName` is the directory as described in [Defining a unique extensions directory](#) on page 520. The default is `/opt/Tomcat/tomcat`.
2. Create the basic template for `features.xml` by adding the following tags:

```
<?xml version="1.0" encoding="UTF-8"?>
<features
  xmlns:xsi="http://www.w3.org/2001/XMLSchema-instance"
  xsi:noNamespaceSchemaLocation="features.xsd">
</features>
```

3. For each menu group to be defined in configuration `menu.xml`, add the `<category>` and `</category>` tags just before the `</features>` tag.

*** Note:**

For each new menu group defined in the `menu.xml` configuration file, you need to define the `<category>` and `</category>` tags in the `features.xml` file.

4. For each `<category>` tag added, specify the following attributes:

Attributes	Example	Description
<code>name="groupTag"</code> , where <code>groupTag</code> is the identifier defined for the menu group in the <code>menu.xml</code> configuration file.	Specify <code>name="newMenuGroupId fier"</code>	The identifier of the menu group defined in the configuration <code>menu.xml</code> file.

5. Specify a `<feature>` tag for each new menu item after the `<category>` and before the corresponding `</category>` tags.

*** Note:**

For each new menu item defined in the `menu.xml` configuration file, you need to define a `<feature>` tag within the corresponding `<category>` tag in the `features.xml` file.

6. For each `<feature>` tag added, specify the following attributes:

Attributes	Example	Description
<code>name="itemTag"</code> , where <code>itemTag</code> is the identifier defined for the menu item in the <code>menu.xml</code> configuration file.	Specify <code>name="newMenuItemIdentifier"</code> .	The identifier of the menu item defined in the configuration <code>menu.xml</code> file.
<code>allow="roles"</code> , where <code>roles</code> is a combination of any	To define that this menu group is accessible only to the administrator and user manager roles, specify	This attribute defines the roles that have permission to view this menu group.

Table continues...

Attributes	Example	Description
of the following roles separated by commas: • administration • maintenance • operations • usermanager • auditor	allow= "administration, usermanager".	

*** Note:**

Make sure that any user role specified for a menu item is also specified for the entire group.

7. Make sure each of the new <feature> tags have a corresponding </feature> tag.
8. Save and close the file.

Example

For example, if you have a group called `myMenuGroup` with menu items `myUsersItem`, `myAdminItem`, and `myUserMgrItem`, and you want to specify that:

- Users with any user role can see the `myMenuGroup` and `myUsersItem` groups.
- Only the users with the Administration user role can see the `myAdminItem` group.
- Users with the User Manager user role can see the `myUserMgrItem` group.

You would specify:

```
<?xml version="1.0" encoding="UTF-8"?>
<features
  xmlns:xsi="http://www.w3.org/2001/XMLSchema-instance"
  xsi:noNamespaceSchemaLocation="feature.xsd">
  <category name="myMenuGroup"
    <feature name="myUsersItem"
      allow="administration,operations,maintenance,auditor,usermanager">
    </feature>
    <feature name="myAdminItem" allow="administration"/>
    </feature>
    <feature name="myUserMgrItem" allow="administrator, usermanager"/>
    </feature>
  </category>
</features>
```

Defining labels for the features in the new menu group and its items

About this task

The display `feature.properties` file specifies the labels that the EPM displays to the end user on the Roles page.

Procedure

1. In an ASCII text editor, open the `display feature.properties` file in the `TomcatHome/lib/extensions/UniqueDirectoryName/messages` directory, where `TomcatHome` is the directory in which the Tomcat servlet engine software is installed and `UniqueDirectoryName` is the directory defined as described in [Defining a unique extensions directory](#) on page 520. The default is `/opt/Tomcat/tomcat`.

2. Create the basic template for the `features.properties` by adding the following tags:

```
#{{START:FEATURES:EXTENSIONS:UniqueDirectoryName
#}}END:FEATURES:EXTENSIONS:UniqueDirectoryName
```

3. Add a section for each menu group that you added to the configuration `menu.xml` file as shown below:

```
myMenuGroup=groupDisplayText
myMenuItem=itemDisplayText
```

where:

- `myMenuGroup` is the menu group identifier specified in the `menu.xml` configuration file.
- `myMenuItem` is the menu item identifier specified in the `menu.xml` configuration file.
- `groupDisplayText` is the group label that Experience Portal displays in the EPM main menu.
- `itemDisplayText` is the item label that Experience Portal displays in the EPM main menu.

* Note:

Ensure that display text specified for the menu group and menu items in `feature.properties` match the display text specified for the same in `menu.properties` file.

4. Save and close the file.
5. Insert the contents of this file within the `#{{START:FEATURES:EXTENSIONS` and `#}}END:FEATURES:EXTENSIONS` tags, into the `display features.properties` file under the `TomcatHome/lib/messages` directory, where `TomcatHome` is the directory in which the Tomcat servlet engine software is installed. The default is `/opt/Tomcat/tomcat`.

Example

For example:

```
#{{START:FEATURES:EXTENSIONS
#{{START:FEATURES:EXTENSIONS:UniqueDirectoryName
myMenuGroup=My Menu Group
myUserItem=Users
myAdminItem=Administrators
myUserMgrItem=User Manager
#}}END:FEATURES:EXTENSIONS:UniqueDirectoryName
#}}END:FEATURES:EXTENSIONS
```

Add menu items to an existing menu group

To add a menu item to an existing menu group, complete the following procedures:

Step	Task	✓
1	Define a unique extensions directory as described in Defining a unique extensions directory on page 520.	
2	Define the new menu items in the configuration <code>menu.xml</code> file as described in Defining new menu items under an existing group on page 515.	
3	Define the labels that will be displayed for the menu items in the display <code>menu.properties</code> file as described in Defining a label for the new menu item on page 517.	
4	Set the access permissions by defining the user roles that can see the menu items in the <code>features.xml</code> file as described in Setting user access permissions for the new menu items on page 518.	
5	Define the labels that will be displayed on the role details web page for the features in the display <code>features.properties</code> file as described in Defining labels for features in the new menu item on page 519.	

Related links

[EPM main menu customizations](#) on page 507

[The EPM main menu configuration files](#) on page 507

Defining new menu items under an existing group

About this task

The configuration `menu.xml` file specifies the location of and properties for your new menu items.

Procedure

1. In an ASCII text editor, open the configuration `menu.xml` file in the `TomcatHome/lib/extensions/UniqueDirectoryName/config` directory, where `TomcatHome` is the directory in which the Tomcat servlet engine software is installed and `UniqueDirectoryName` is the directory defined as described in [Defining a unique extensions directory](#) on page 520. The default is `/opt/Tomcat/tomcat`.

2. Create the basic template for `menu.xml` by adding the following tags:

```
<?xml version="1.0" encoding="UTF-8"?>
<navigationmenu
  xmlns:xsi="http://www.w3.org/2001/XMLSchema-instance"
  xsi:noNamespaceSchemaLocation="menu.xsd">
</navigationmenu>
```

3. For each existing menu group for which a new menu item will be defined, add the `<menu>` and `</menu>` tags just before the `</navigationmenu>` tag.

4. Specify the following menu attributes:

Attributes	Example	Description
<code>type="group"</code> , where <i>type</i> defines the type of the menu.	To specify the type of the menu as <i>group</i> , specify <code>type="group"</code>	This attribute defines the type of the menu tag.
<code>tag="groupTag"</code> , where <i>groupTag</i> is the identifier the system uses to identify the group.	To assign the name specify, <code>tag="existingMenuGroupIdentifier"</code>	The identifier of the menu group. This identifier must be unique across all menu groups and menu items in the configuration <code>menu.xml</code> file.

For Menu Group...	Set tag to...
User Management	<code>tag=menuGroupUserManagement</code>
Real-Time Monitoring	<code>tag=menuGroupRealTimeMonitoring</code>
System Maintenance	<code>tag=menuGroupSystemMaintenance</code>
System Management	<code>tag=menuGroupSystemManagement</code>
System Configuration	<code>tag=menuGroupSystemConfiguration</code>
Security	<code>tag=menuGroupSecurity</code>
Reports	<code>tag=menuGroupReports</code>

5. For each menu item you want to add, specify the `<item>` tag after the `<menu>` tag but before the corresponding `</menu>` tag and specify the following attributes:

Property	Example	Description
<code>type="item"</code> , where <i>type</i> defines the type of the item.	To specify the type of the menu item as <i>item</i> , specify <code>type="item"</code>	This attribute defines the type of the item tag.
<code>render=[true false]</code> , where <i>render</i> is either <i>true</i> or <i>false</i> .	To instruct the EPM to display the item in the menu group, specify <code>render=true</code>	If you set this property to <i>false</i> , the EPM does not display the menu group.
<code>tag=itemTag</code> , where <i>itemTag</i> is the identifier the system uses to identify the item.	Specify <code>tag="newMenuItemIdentifier"</code>	The identifier of the menu item. This identifier must be unique across all menu groups and menu items in the configuration <code>menu.xml</code> file.
<code>action=displayURL</code> , where <i>displayURL</i> is the URL that you want the system to display when a user clicks this item.	To instruct the EPM to open <code>admin.ops.page.html</code> when the user clicks on the second item of the fifth menu group, specify <code>action="http://my.site.com/custom_pages/admin.ops.page.html"</code>	Determines what page Experience Portal displays when the user selects the menu item. Important: Experience Portal does not validate this URL

Table continues...

Property	Example	Description
<code>newWindow="[true false]"</code> , where <code>newWindow</code> is either <code>true</code> or <code>false</code> .	To instruct the EPM to open a new page when the user clicks on the menu item of the menu group, specify <code>newWindow=true</code>	If this option is set to <code>true</code> , Experience Portal opens the specified URL in a new browser window. If you do not specify this property, it defaults to <code>false</code> .

6. For each new `<item>` tag, specify a `</item>` tag to end the menu item definition.

7. Save and close the file.

Example

The Report menu group with the `menuItemMyCustomReport` item added could look like this:

```
<?xml version="1.0" encoding="UTF-8"?>
<navigationmenu
  xmlns:xsi="http://www.w3.org/2001/XMLSchema-instance"
  xsi:noNamespaceSchemaLocation="menu.xsd">
  <menu type="group" render="true" tag="menuGroupReports">
    <item type="item" render="true" tag="menuItemStandardReports"
      action="reports/standardReports.jsf?initializeBean=true">
    </item>
    <item type="item" render="true" tag="menuItemCustomReports"
      action="reports/customReports.jsf?initializeBean=true">
    </item>
    <item type="item" render="true" tag="menuItemScheduledReports"
      action="reports/scheduledReports.jsf?initializeBean=true">
    </item>
    <item type="item" render="true" tag="menuItemMyCustomReport"
      action="http://my.site.com/custom/custom.report.page.html" newWindow="true">
    </item>
  </menu>
</navigationmenu>
```

Defining a label for the new menu item

About this task

To specify the labels that Experience Portal will display to the end user, edit the `display.menu.properties` file.

Procedure

1. In an ASCII text editor, open the `display.menu.properties` file in the `TomcatHome/lib/extensions/UniqueDirectoryName/messages` directory, where `TomcatHome` is the directory in which the Tomcat servlet engine software is installed and `UniqueDirectoryName` is the directory defined as described in [Defining a unique extensions directory](#) on page 520. The default is `/opt/Tomcat/tomcat`.
2. Add a line entry for each menu item you added to the configuration `menu.properties` file, as shown below:

```
myMenuItem=itemDisplayText
```

where:

- `myMenuItem` is the menu item identifier specified in the `menu.xml` configuration file.
- `itemDisplayText` is the text that the EPM displays in the main menu.

3. Save and close the file.

Example

For example, if you added menu items `menuItemMyStandardReport` and `menuItemMyCustomReport` to the Reports menu group in the configuration `menu.xml` file, you would specify:

```
menuItemMyStandardReport=My Standard Report
menuItemMyCustomReport=My Custom Report
```

Setting user access permissions for the new menu items

About this task

The `features.xml` file specifies which user roles have access to the new menu items.

Procedure

1. In an ASCII text editor, open the configuration `features.xml` file in the `TomcatHome/lib/extensions/UniqueDirectoryName/config` directory, where `TomcatHome` is the directory in which the Tomcat servlet engine software is installed and `UniqueDirectoryName` is the directory defined as described in [Defining a unique extensions directory](#) on page 520. The default is `/opt/Tomcat/tomcat`.

2. Create the basic template for the `features.xml` by adding the following tags:

```
<?xml version="1.0" encoding="UTF-8"?>
<features
  xmlns:xsi="http://www.w3.org/2001/XMLSchema-instance"
  xsi:noNamespaceSchemaLocation="features.xsd">
</features>
```

3. For each menu group to be defined in configuration `menu.xml`, add the `<category>` and `</category>` tags just before the `</features>` tag.

* Note:

For each new menu group defined in the `menu.xml` configuration file, you need to define the `<category>` and `</category>` tags in the `features.xml` file.

4. Specify a `</feature>` tag for each new menu item after the `<category>` and before the corresponding `</category>` tag.

* Note:

For each new menu item defined in the `menu.xml` configuration file, you need to define a `<feature>` tag within the corresponding `<category>` tag in the `features.xml` file.

5. For each `<feature>` tag added, specify the following attributes:

Attributes	Example	Description
<code>name="itemTag"</code> , where <i>itemTag</i> is the identifier defined for the menu item in the <code>menu.xml</code> configuration file.	Specify <code>name="newMenuItemIdentifier"</code>	The identifier of the menu item defined in the configuration <code>menu.xml</code> file.
<code>allow="roles"</code> , where <i>roles</i> is a combination of any of the following roles separated by commas: • administration • maintenance • operations • usermanager • auditor	To define that this menu group is accessible only to administrator and user manager, specify <code>allow="administration, usermanager"</code>	This attribute defines the roles that have permission to view this menu group.

*** Note:**

Make sure that any user role specified for a menu item is also specified for the entire group.

6. Make sure each of the new `<feature>` tags have a corresponding `</feature>` tag.
7. Save and close the file.

Example

For example, to specify that users with the Administration, Operations, and Reporting user roles can view the menu item `menuItemMyCustomReport` for the Reports menu group, add the following lines within the category which defines the `menuGroupReports`:

```
<?xml version="1.0" encoding="UTF-8"?>
<features
  xmlns:xsi="http://www.w3.org/2001/XMLSchema-instance"
  xsi:noNamespaceSchemaLocation="features.xsd">
  <category name="menuGroupReports">
    <feature name="menuItemMyCustomReport"
      allow="administration,operations,maintenance,reporting">
    </feature>
  </category>
</features>
```

Defining labels for features in the new menu item

About this task

The display `feature.properties` file specifies the labels that the EPM displays to the end user on the Roles page.

Procedure

1. In an ASCII text editor, open the `display feature.properties` file in the `TomcatHome/lib/extensions/UniqueDirectoryName/messages` directory, where `TomcatHome` is the directory in which the Tomcat servlet engine software is installed and `UniqueDirectoryName` is the directory defined as described in [Defining a unique extensions directory](#) on page 520. The default is `/opt/Tomcat/tomcat`.
2. Create the basic template for the `menu.xml` by adding the following tags:

```
#{{START:FEATURES:EXTENSIONS:UniqueDirectoryName
#}}END:FEATURES:EXTENSIONS:UniqueDirectoryName
```

3. Add a section for each menu item that you added to the configuration `menu.xml` file, as shown below:

```
myMenuItem=itemDisplayText
```

where:

- `myMenuItem` is the menu item identifier specified in the `menu.xml` configuration file.
- `itemDisplayText` is the item label that Avaya Aura® Experience Portal displays in the EPM main menu.

* Note:

Ensure that the display text specified for the menu group and menu items in `feature.properties` file match the display text specified for the same in `menu.properties` file.

4. Save and close the file.
5. Insert the contents of this file within the `#{{START:FEATURES:EXTENSIONS` and `#}}END:FEATURES:EXTENSIONS` tags, in the `display features.properties` file under `TomcatHome/lib/messages` directory, where `TomcatHome` is the directory in which the Tomcat servlet engine software is installed. The default is `/opt/Tomcat/tomcat`.

Example

For example:

```
#{{START:FEATURES:EXTENSIONS
#{{START:FEATURES:EXTENSIONS:UniqueDirectoryName
menuItemMyStandardReport=My Standard Report
menuItemMyCustomReport=My Custom Report
#}}END:FEATURES:EXTENSIONS:UniqueDirectoryName
#}}END:FEATURES:EXTENSIONS
```

Defining a unique extensions directory

About this task

Defining a unique extensions directory allows one to separate the menu and feature customizations from other menu and feature customizations.

Procedure

1. Create a unique extensions directory to identify the extension, in the `TomcatHome/lib/extensions` directory, where `TomcatHome` is the directory in which the Tomcat servlet engine software is installed. The default is `/opt/Tomcat/tomcat`.

 Note:

The unique id must be in upper case and three characters long.

The unique ids already in use are EPE, POM, and ICR.

2. Create directories called `config` and `messages` under `TomcatHome/lib/extensions/UniqueDirectoryName` where `UniqueDirectoryName` is the folder created in the previous step.

Chapter 23: The Application Logging web service

The Application Logging web service for third-party speech applications

Avaya Aura® Experience Portal includes an Application Logging web service that lets you save application and call flow data information from third-party speech applications into the `vpappLog` table of the Experience Portal database. Experience Portal can then include information from these third-party applications when it generates the Application Detail report and Application Summary report.

The Application Logging web service conforms to all W3C standards and can be accessed through any web service client using the Avaya-provided Web Services Description Language (WSDL) file.

Best practices

Experience Portal supports Axis 2.0 Application Logging web service.


When using the Application Logging web service, keep in mind that:

- The Axis 2.0 Application Logging web service use Basic Authentication to authenticate web service client requests and only support HTTPS protocol.
- When the HTTPS protocol is used in the Web Service client, the Web Service client needs to handle to accept the certificate from the EPM server. No certificate needs to be installed on the Application Server. It is one-way SSL authentication.
- When calling the Axis 2.0 Application Logging web services, ensure to turn HTTP Chunking off.
- When you submit a request to the web service, you need to specify the user name and password which are specified in the Application Reporting section of the Web Service Authentication group on the EPM Settings page. If you need to change this user name or password, you must do it through the EPM. For details, see [Configuring the Application Logging web service](#) on page 524. For Axis 2.0 Application Logging web service requests, you can also use the Experience Portal web user name and password. The web user has to have the Web Services role with Application Reporting feature enabled.

- You must send all of the log entries for one or more session blocks at the same time. Do not send each log entry as it occurs or you may adversely affect Experience Portal system performance.
- You must use the `logApplicationEventAlarm` web service method with utmost caution. You should implement a throttling mechanism on the client side to limit flooding the EPM with the application events and alarms.
- You should have a proper queuing mechanism or sampling rate control method in place if you are sending a large number of log entries to the database. Otherwise this may adversely affect Experience Portal system performance.
- You should save all log entries in case the EPM is unavailable when the Application Logging web service is called. That way you can resend the log entries when the EPM becomes available.
- If your Experience Portal EPM software runs on a dedicated server machine, you should configure a auxiliary EPM server to handle Application Logging web service requests if the primary EPM server is unavailable.
- The Avaya Aura® Experience Portal Application Detail report and Application Summary report expect the report data to be in a particular format. For details about what Application Detail Records (ADRs) are stored in the `vpappllog` table, see *Generating custom reports using third-party software in Administering Avaya Aura® Experience Portal*.

Application Logging web service flow diagram

The following figure shows how speech applications interact with the Application Logging web service to add application messages to the Experience Portal database.



Configuring the Application Logging web service

About this task

To configure the Application Logging web service, you need to download the Avaya-provided WSDL file and build a custom web service client based on that file.

Procedure

1. Log on to the EPM Web interface using an account with the Administration user role.
2. From the EPM main menu, select **System Configuration > EPM Server**.
3. On the EPM Servers page, click **EPM Settings**.
4. On the EPM Settings page, go to the **Application Reporting** section in the **Web Service Authentication** group.
5. Enter the user name and password that must be included with all Application Logging web service requests for Digest Authentication.

This is the same user name and password that you should use when accessing the web service through the WSDL file.

6. Click **OK**.
7. For Axis 2.0 Application Logging web services: open the `http://EPM-server/axis2/services/VPAppLogService?wsdl` page in a web browser.

Where *EPM-server* is the domain name or IP address of the system on which the primary EPM software is installed.

8. When prompted, enter the user name and password specified in the **Application Reporting** section of the EPM Settings page.
9. Save the WSDL file and use it to build the web service client that accesses the Application Logging web service. This web service conforms to all current W3C standards.

Application Logging web service methods

The Application Logging web service includes the following methods:

- [reportBatch method for application logging](#) on page 526
- [reportBatch method for call flow data](#) on page 528
- [logFailed method](#) on page 525
- [logApplicationEventAlarm method for application Logging / Alarming](#) on page 529

logFailed method

The Application Logging web service `logFailed` method adds the event `PALOG00017` to the Experience Portal database.

Parameters

Parameter	Type	Description
lastVPMSDown	Long integer	The timestamp of the last time the EPM was down.

Return values

There are no return values from this method.

reportBatch method for application logging

The `reportBatch` method can be used to create application or call flow data log entries in the Experience Portal report database. In either case, the list of input parameters is the same. The only difference is the information you specify for each input parameter.

This topic discusses the information you should specify to create an application log entry. For information about creating a call flow data log entry, see [reportBatch method for call flow data](#) on page 528.

Parameters

Parameter	Type	Description
appServerAddress	string	The hostname or IP address of the application server.
applicationID	string	The name of the application. For example: <code>CollectTicketInfo</code>
level	string	The logging level. The options are: • <code>Fatal</code> • <code>Error</code> • <code>Warning</code> • <code>Info</code>
reason	string	The reason this log entry was made. For example: <code>Application ended successfully</code> . The reason for the first log entry in a session block should always be "-" (dash).
sessionID	string	The session ID for the session. This is a user-defined identifier that should be unique across sessions.
timestamp	string	The current system time in milliseconds since January 1, 1970 00:00:00 UTC. The value of this parameter should contain a long number.
transactionName	string	The transaction name that this log entry is a part of. For example: <code>Hung Up</code> ! Important: Every transaction should start with a log entry setting the transaction name along with the activity type of <code>Start</code> . Once you start a transaction, all log entries should use the same transaction name up to and including the final log entry for that transaction.
type	string	The activity type for this log.

Table continues...

Parameter	Type	Description
		The options are: • Start • In Progress • End • Cancel
userLog	string	The session label.
varName	string	A variable name, if one should be included with this log entry.
varValue	string	The value of the variable named in varName.
activityDuration	integer	The duration in seconds between the timestamp of the first log entry with the same transaction name and the activity type of <code>Start</code> and this log entry in a single session block.  Note: This calculation should be based on one block of log entries that belong in one session.
moduleIdNodeId	string	The module ID and node ID in the format: <code>[Module Id]:Node Id</code>, where <code>Module Id</code> is only specified if it is <i>not</i> the same as the application name. For example, if the application name is <code>CollectTicketInfo</code> and it contains the <code>CollectTicketInfo</code> module with the node <code>StartTicket</code> and the <code>GetPayment</code> module with the node <code>StartPay</code>, you would specify them as: • <code>:StartTicket</code> • <code>GetPayment:StartPay</code>

Return values

The `reportBatch` method returns one of the following values:

- success
- decryption failed - error occurred decrypting the password
- Password incorrect
- Request is out of date
- Error storing data in database
- Error initializing database
- Error getting the EPID

If the method fails, you can use the `logFailed` method to enter an event into the Experience Portal event log.

reportBatch method for call flow data

The `reportBatch` method can be used to create application or call flow data log entries in the Experience Portal report database. In either case, the list of input parameters is the same. The only difference is the information you specify for each input parameter.

This topic details the information you should specify to create a call flow data log entry. For information about creating an application log entry, see [reportBatch method for application logging](#) on page 526.

Parameters

Parameter	Type	Description
appServerAddress	string	The hostname or IP address of the application server.
applicationID	string	The name of the application. For example: <code>CollectTicketInfo</code>
level	string	This should always be: <code>Info</code>
reason	string	The reason this log entry was made. When entering data in this field, you should keep in mind that: • The reason for the first log entry in a session block should always be "-" (dash). • If the activity type is <code>Node Entry</code> or <code>Application Exit</code>, this field must contain the <code>moduleId</code> of the previous log entry of type <code>Node Entry</code>. This allows Experience Portal to track the source of the breadcrumb. • If the activity type is <code>Module Exit</code>, this field can contain whatever reason code you want to use.
sessionID	string	The session ID for the session. This is a user-defined identifier that should be unique across sessions.
Timestamp	string	The current system time in milliseconds since January 1, 1970 00:00:00 UTC. The value of this parameter should contain a long number.
transactionName	string	This should always be: <code>Framework</code>
type	string	The options are: • <code>Node Entry</code> • <code>Module Exit</code> • <code>Application Exit</code>
userLog	string	The session label.
varName	string	A variable name, if one should be included with this log entry.
varValue	string	The value of the variable named in <code>varName</code> .

Table continues...

Parameter	Type	Description
activityDuration	integer	The duration in seconds between the timestamp of the first log entry with the activity type of <code>Node Entry</code> or <code>Application Exit</code> and this log entry in a single session block.  Note: This calculation should be based on one block of log entries that belong in one session.
moduleIdNodeId	string	The module and node identifiers. If the type of the last log entry in the session block is <code>Application Exit</code>, than this field should be "--" (dash dash). Otherwise, it should contain the module ID and node ID in the format: <code>[Module Id]:Node Id</code>, where <code>Module Id</code> is only specified if it is <i>not</i> the same as the application name. For example, if the application name is <code>CollectTicketInfo</code> and it contains the <code>CollectTicketInfo</code> module with the node <code>StartTicket</code> and the <code>GetPayment</code> module with the node <code>StartPay</code>, you would specify them as: • <code>:StartTicket</code> • <code>GetPayment:StartPay</code>

Return values

The `reportBatch` method returns one of the following values:

- `success`
- `decryption failed` - error occurred decrypting the password
- `Password incorrect`
- `Request is out of date`
- `Error storing data in database`
- `Error initializing database`
- `Error getting the VPID`

If the method fails, you can use the `logFailed` method to enter an event into the Experience Portal event log.

logApplicationEventAlarm method for application Logging / Alarming

The `logApplicationEventAlarm` method can be used to issue the application events / alarms from the application to the EPM. The alarm events are sent via SNMP traps to the configured network management station but not through INADS.

This topic discusses the information you need to specify to create an application event entry.

Parameters

Parameter	Type	Description
appServerAddress	string	The hostname or IP address of the application server.
applicationID	string	The name of the application. For example: <code>CollectTicketInfo</code>
level	string	The logging level. The options are: • Fatal • Error • Warning
reason	string	The generated message defined by the application. Internationalization must be provided by the application. The maximum length is 100 characters. If the length is over the maximum, it will be truncated.
sessionID	string	The session ID for the session.
timestamp	string	The current system time in milliseconds since January 1, 1970 00:00:00 UTC. The value of this parameter should contain a long number.
transactionName	string	Not used.
type	string	Not used.
userLog	string	Not used.
varName	string	A variable name, if one should be included with this event entry. This is optional.
varValue	string	The value of the variable named in <i>varName</i> . This is optional.
activityDuration	integer	Not used.
moduleIDNodeID	string	Not used.

Return values

The `logApplicationEventAlarm` method returns one of the following values:

- success
- decryption failed - error occurred decrypting the password
- Password incorrect
- Request is out of date
- Error storing data in database
- Error initializing database
- Error getting the EPID

The following table displays the log events and the associated messages to Alarm Maps:

Log Message	Message to Alarm Map	Log Level	Alarm Severity	Log Message Alarm Message
PAPP_00001	QAPP_00001	Warning	Minor	Application {0} reported an error from {1} at {2} with message: {3} {4} QAPP_00001: Application generated a Minor alarm
PAPP_00002	QAPP_00002	Error	Major	Application {0} reported an error from {1} at {2} with message: {3} {4} QAPP_00002: Application generated a Major alarm
PAPP_00003	QAPP_00003	Fatal	Critical	Application {0} reported an error from {1} at {2} with message: {3} {4} QAPP_00003: Application generated a Critical alarm

The parameter definitions for the log entries are:

- {0} – Name of the application defined on the application configuration web page (*applicationID*)
- {1} – Application server IP or host name (*appServerAddress*), Session ID: (*sessionID*)
- {2} – Application server time of the log event (*timestamp*)
- {3} – The generated message defined by the application. Internationalization must be provided by the application (*reason*)
- {4} – Variable Name: (*varName*) Variable Value: (*varValue*)

Sample Application Logging web service WSDL file

The following is an example of the Application Logging web service WSDL file. The actual file is installed on the server that is running the EPM software. For details about accessing this file, see [Configuring the Application Logging web service](#) on page 524.

```
<?xml version="1.0" encoding="UTF-8"?>
<wsdl:definitions targetNamespace="urn:com.avaya.vp.report.EPReport4"
xmlns:apachesoap="http://xml.apache.org/xml-soap"
xmlns:impl="urn:com.avaya.vp.report.EPReport4"
xmlns:intf="urn:com.avaya.vp.report.EPReport4"
xmlns:wsdl="http://schemas.xmlsoap.org/wsdl/"
xmlns:wsdlsoap="http://schemas.xmlsoap.org/wsdl/soap/"
xmlns:xsd="http://www.w3.org/2001/XMLSchema">
<!--WSDL created by Apache Axis version: 2.0
Built on Apr 22, 2006 (06:55:48 PDT)-->
<wsdl:types>
<schema elementFormDefault="qualified"
targetNamespace="urn:com.avaya.vp.report.EPReport4"
xmlns="http://www.w3.org/2001/XMLSchema">
```

```

<complexType name="EPReportEntry4">
  <sequence>
    <element name="appServerAddress" nillable="true" type="xsd:string"/>
    <element name="applicationID" nillable="true" type="xsd:string"/>
    <element name="level" nillable="true" type="xsd:string"/>
    <element name="reason" nillable="true" type="xsd:string"/>
    <element name="sessionID" nillable="true" type="xsd:string"/>
    <element name="timestamp" nillable="true" type="xsd:string"/>
    <element name="transactionName" nillable="true" type="xsd:string"/>
    <element name="type" nillable="true" type="xsd:string"/>
    <element name="userLog" nillable="true" type="xsd:string"/>
    <element name="varName" nillable="true" type="xsd:string"/>
    <element name="varValue" nillable="true" type="xsd:string"/>
    <element name="activityDuration" type="xsd:int"/>
    <element name="moduleIdNodeId" nillable="true" type="xsd:string"/>
  </sequence>
</complexType>
<element name="reportBatch">
  <complexType>
    <sequence>
      <element maxOccurs="unbounded" name="entries" type="impl:EPReportEntry4"/>
    </sequence>
  </complexType>
</element>
<element name="reportBatchResponse">
</complexType>
</element>
<element name="reportBatchReturn" type="xsd:string"/>
</sequence>
</complexType>
</element>
<element name="logFailed">
  <complexType>
    <sequence>
      <element name="lastVpmsDown" type="xsd:long"/>
    </sequence>
  </complexType>
</element>
<element name="logFailedResponse">
  </complexType>
</element>
<element name="logApplicationAlarm">
  </complexType>
  <sequence>
    <element maxOccurs="unbounded" name="entries" type="impl:EPReportEntry4"/>
  </sequence>
</complexType>
</element>
<element name="logApplicationAlarmResponse">
  </complexType>
  <sequence>
    <element name="logApplicationEventAlarmReturn" type="xsd:string"/>
  </sequence>
  <complexType/>
</element>
</schema>
</wsdl:types>
<wsdl:message name="reportBatchRequest">
  <wsdl:part element="impl:reportBatch" name="parameters"/>
</wsdl:message>
<wsdl:message name="logFailedRequest">
  <wsdl:part element="impl:logFailed" name="parameters"/>
</wsdl:message>
<wsdl:message name="logApplicationEventAlarmRequest">
  <wsdl:part element="impl:logApplicationEventAlarm" name="parameters"/>

```

```

</wsdl:message>
<wsdl:message name="reportBatchResponse">
  <wsdl:part element="impl:reportBatchResponse" name="parameters"/>
</wsdl:message>
<wsdl:message name="logFailedResponse">
  <wsdl:part element="impl:logFailedResponse" name="parameters"/>
</wsdl:message>
<wsdl:message name="logApplicationEventAlarmResponse">
<wsdl:part element="impl:logApplicationEventAlarmResponse" name="parameters"/>
</wsdl:message>
<wsdl:portType name="EPReport4">
  <wsdl:operation name="reportBatch">
    <wsdl:input message="impl:reportBatchRequest" name="reportBatchRequest"/>
    <wsdl:output message="impl:reportBatchResponse" name="reportBatchResponse"/>
  </wsdl:operation>
  <wsdl:operation name="logFailed">
    <wsdl:input message="impl:logFailedRequest" name="logFailedRequest"/>
    <wsdl:output message="impl:logFailedResponse" name="logFailedResponse"/>
  </wsdl:operation>
  <wsdl:operation name="logApplicationEventAlarm">
    <wsdl:input message="impl:logApplicationEventAlarmRequest"
name="logApplicationEventAlarmRequest"/>
    <wsdl:output message="impl:logApplicationEventAlarmResponse"
name="logApplicationEventAlarmResponse"/>
  </wsdl:operation>
</wsdl:portType>
<wsdl:binding name="EPReport4SoapBinding" type="impl:EPReport4">
  <wsdlsoap:binding style="document"
    transport="http://schemas.xmlsoap.org/soap/http"/>
  <wsdl:operation name="reportBatch">
    <wsdlsoap:operation soapAction=""/>
    <wsdl:input name="reportBatchRequest">
      <wsdlsoap:body use="literal"/>
    </wsdl:input>
    <wsdl:output name="reportBatchResponse">
      <wsdlsoap:body use="literal"/>
    </wsdl:output>
  </wsdl:operation>
  <wsdl:operation name="logFailed">
    <wsdlsoap:operation soapAction=""/>
    <wsdl:input name="logFailedRequest">
      <wsdlsoap:body use="literal"/>
    </wsdl:input>
    <wsdl:output name="logFailedResponse">
      <wsdlsoap:body use="literal"/>
    </wsdl:output>
  </wsdl:operation>
  <wsdl:operation name="logApplicationEventAlarm">
    <wsdlsoap:operation soapAction=""/>
    <wsdl:input name="logApplicationEventAlarmRequest">
      <wsdlsoap:body use="literal"/>
    </wsdl:input>
    <wsdl:output name="logApplicationEventAlarmResponse">
      <wsdlsoap:body use="literal"/>
    </wsdl:output>
  </wsdl:operation>
</wsdl:binding>
<wsdl:service name="EPReport4Service">
  <wsdl:port binding="impl:EPReport4SoapBinding" name="EPReport4">
    <wsdlsoap:address location="http://localhost:80/EPReport4"/>
  </wsdl:port>
</wsdl:service>
</wsdl:definitions>

```

Chapter 24: The Application Interface web service

The Application Interface web service

Developers can use the Application Interface web service to:

- Start a CCXML or VoiceXML application that has been added to Avaya Aura® Experience Portal using the Add Application page.

The web service automatically examines each MPP in the Experience Portal system and starts the session on the first available MPP that has the required outbound resources available.

- Send an event to a specific application session running on an MPP.
- Query the system for the total number of:
 - Used and unused outbound resources available
 - Unused SIP outbound resources
 - Unused H.323 outbound resources
- Send an SMS message or email message using one of the Avaya Aura® Experience Portal configured SMS or Email connections.
- Start an SMS or email application that has been added to Avaya Aura® Experience Portal using the Add Application page.

The Application Interface web service conforms to all W3C standards and can be accessed through any web service client using the Avaya-provided Web Services Description Language (WSDL) file.

Tip:

Sample files showing how you can communicate with the Application Interface web service using such methods as Java, JavaScript, and php are located in the `Support/Examples/Application Interface Web Service` directory on the Experience Portal installation DVD.

You can use the Application Interface test client to validate the Application Interface web service and the Experience Portal outcall, SMS, and Email functionality. Avaya supplies an installation script that automatically installs the Application Interface test client when Experience Portal is installed. For more information, see the *Configure and run the Application Interface test client* section in the *Implementing Avaya Aura® Experience Portal on a single server* guide or the *Implementing Avaya Aura® Experience Portal on multiple servers* guide.

Best practices

When using the Application Interface web service, keep in mind that:

- The Axis 2.0 Application Interface web service uses Basic Authentication to authenticate web service client requests. When you submit a request to the web service, you need to include the user name and password that is configured as one of the Experience Portal users and that user must have the Web Services role checked.
- If non-ASCII characters are sent in the URL request to the web service they should be encoded as UTF-8 prior to sending the request.

For example, an application name of 'aña' is encoded and sent as 'a%C3%B1a'. Note that the non-ASCII character 'ñ' is sent as the UTF-8 value of '%C3%B1'.

- A non zero timeout value should be specified when using the `LaunchVXML` method. If no timeout value is passed, or if the value is 0, then a default value of 120 seconds will be used.
- For the methods `LaunchCCXML`, `LaunchVXML`, `LaunchSMS`, `LaunchEmail`, `SendSMS`, and `SendEmail`, parameters must be passed as name value pairs. For example, `parameter1=value`.

Each name value pair is separated by semicolon. If a value of the specific parameter has multiple values, those values should be separated by comma (.). If the value contains a semicolon (;), you must escape it by using \;

- If you plan to use a single CCXML application to launch multiple outgoing calls simultaneously, keep in mind that each application is handled by a single MPP, which means that each application is limited to the number of ports available on the MPP to which it is assigned. While the Application Interface web service tries to select the best MPP to handle the call, the application must have a way to verify the number of available ports so that it does not exceed the resources available on the MPP.

If you want to make additional calls, you can either:

- Launch one additional instance of the CCXML call blast application for each additional MPP in the system.
- Use the `QueryResources` method to check the available resources and launch another instance of the CCXML call blast application as soon as enough resources are available.
- If your Experience Portal EPM software runs on a dedicated server machine, you should configure a auxiliary EPM server to handle Application Interface web service requests if the primary EPM server is unavailable.

Application Interface web service flow diagram

The following figure shows how an external application interacts with the Application Interface web service and how the Application Interface web service interacts with the rest of the Experience Portal system.




Figure 1: Application Interface Web service flow diagram

Configuring the Application Interface web service Procedure

1. Log on to the EPM Web interface using an account with the Administration user role.
2. From the EPM main menu, select **User Management > Users**.
3. Select a user that will be used when sending requests to the Web Service.

4. On the Change User page, click the **Web Services** role to enable the user to use web service.
5. Click **Save**.
6. Open the following page in a Web browser: `http://EPM-server/axis2/services/VPAppIntfService?wsdl`

Where *EPM-server* is the domain name or IP address of the system where the primary EPM software is installed.

7. When prompted, enter the user name and password for the Experience Portal with the web services role checked.
8. Save the WSDL file and use it to build the web service client that accesses the Application Interface web service (axis 2.0). This web service conforms to all current W3C standards.

Application Interface web service methods

The Application Interface web service includes the following methods:

- [GetStatus method](#) on page 537
- [GetStatusEx method](#) on page 538
- [LaunchCCXML method](#) on page 540
- [LaunchEmail method](#) on page 545
- [LaunchSMS method](#) on page 546
- [LaunchHTML method](#) on page 548
- [LaunchVXML method](#) on page 549
- [QueryResources method](#) on page 555
- [SendCCXMLEvent method](#) on page 555
- [SendEmail method](#) on page 556
- [SendSMS method](#) on page 557

All methods can be called from any application that is running on the same network as theAvaya Aura® Experience Portal EPM server.

GetStatus method

This method returns the:

- Number of SIP requests processed since the Application Interface web service last started
- Number of telephony requests processed since the Application Interface web service last started

- Number of VoiceXML requests since the Application Interface web service last started
- Number of CCXML event requests since the Application Interface web service last started
- Number of Send CCXML requests sent since the Application Interface web service last started
- Maximum, minimum, and average number of MPP servers examined before a suitable MPP was found to run the requested application
- Date and time that the Application Interface web service was started
- Date and time on which the last request was made
- The version of the EPM software on the server running the Application Interface web service

! Important:

The return values are described [Return values](#) on page 560.

Data Returned

Parameter	Type	Description
iSIPRequestsProcessed_returned	Integer	Total number of SIP requests processed since the Application Interface web service was started.
iTELRequestsProcessed_returned	Integer	Total number of H.323 or SIP telephony requests processed since the web service was started.
iVXMLRequestsProcessed_returned	Integer	Total number of VoiceXML requests processed since the web service was started.
iCCXMLRequestsProcessed_returned	Integer	Total number of CCXML requests processed since the web service was started.
iCCXMLEventsSent_returned	Integer	Total number of CCXML events sent since the web service was started.
maxMPPHops_returned	Integer	Maximum number of MPPs that were examined before the web service found an MPP on which to run the requested application.
minMPPHops_returned	Integer	Minimum number of MPPs that were examined before the web service found an MPP on which to run the requested application.
avgMPPHops_returned	Integer	Average number of MPPs that were examined before the web service found an MPP on which to run the requested application.
lastRequestDateTime_returned	Date	Date and time on which the last request was made.
serviceStartedDateTime_returned	Date	Date and time on which the web service was last started.
vpmsSoftwareVersion_returned	String	The version of the EPM software running on the server.

GetStatusEx method

This method returns the:

- Number of SIP requests processed since the Application Interface web service last started

- Number of telephony requests processed since the Application Interface web service last started
- Number of VoiceXML requests since the Application Interface web service last started
- Number of CCXML requests since the Application Interface web service last started
- Number of Send CCXML event requests sent since the Application Interface web service last started
- Maximum, minimum, and average number of MPP servers examined before a suitable MPP was found to run the requested application
- Date and time that the Application Interface web service was started
- Date and time on which the last request was made
- The version of the EPM software on the server running the Application Interface web service
- Number of `LaunchEmail` requests since the Application Interface web service last started
- Number of `LaunchSMS` requests since the Application Interface web service last started
- Number of `SendEmail` requests since the Application Interface web service last started
- Number of `SendSMS` requests since the Application Interface web service last started

! Important:

The return values are described [Return values](#) on page 560.

Data returned

Parameter	Type	Description
iSIPRequestsProcessed_returned	Integer	Total number of SIP requests processed since the Application Interface web service was started.
iTELRequestsProcessed_returned	Integer	Total number of H.323 or SIP telephony requests processed since the web service was started.
iVXMLRequestsProcessed_returned	Integer	Total number of VoiceXML requests processed since the web service was started.
iCCXMLRequestsProcessed_returned	Integer	Total number of CCXML requests processed since the web service was started.
iCCXMLEventsSent_returned	Integer	Total number of CCXML events sent since the web service was started.
maxMPPHops_returned	Integer	Maximum number of MPPs that were examined before the web service found an MPP on which to run the requested application.
minMPPHops_returned	Integer	Minimum number of MPPs that were examined before the web service found an MPP on which to run the requested application.
avgMPPHops_returned	Integer	Average number of MPPs that were examined before the web service found an MPP on which to run the requested application.
lastRequestDateTime_returned	Date	Date and time on which the last request was made.

Table continues...

Parameter	Type	Description
serviceStartedDateTime_returned	Date	Date and time on which the web service was last started.
vpmsSoftwareVersion_returned	String	The version of the EPM software running on the server.
iLaunchAppRequestsProcessed_returned	Integer	Total number of <code>LaunchApp</code> requests processed since the Application Interface web service was started.
iLaunchEmailRequestsProcessed_returned	Integer	Total number of <code>LaunchEmail</code> requests processed since the Application Interface web service was started.
iLaunchSmsRequestsProcessed_returned	Integer	Total number of <code>LaunchSMS</code> requests processed since the Application Interface web service was started.
iSendAppRequestsProcessed_returned	Integer	Total number of <code>SendApp</code> requests processed since the Application Interface web service was started.
iSendEmailRequestsProcessed_returned	Integer	Total number of <code>SendEmail</code> requests processed since the Application Interface web service was started.
iSendSmsRequestsProcessed_returned	Integer	Total number of <code>SendSMS</code> requests processed since the Application Interface web service was started.

LaunchCCXML method

This method starts the specified CCXML application, and, if successful, returns the:

- Experience Portal session ID for the new session
- Total number of outbound resources available, both used and unused
- Total number of unused SIP outbound resources
- Total number of unused H.323 outbound resources

! Important:

The CCXML application being launched *must* return the status of that launch using a custom event as described in [Returning the status of a LaunchCCXML request](#) on page 543. For information on return values, see [CCXML application status return values](#) on page 542. The return values are described [Return values](#) on page 560.

* Note:

If a CCXML application launches multiple VoiceXML applications, each of these applications can use a different speech server. Prior to Experience Portal 7.0, multiple applications used only one speech server. This feature comes into play if you have different languages loaded onto different speech servers.

When a CCXML application launches a VoiceXML dialog by name, the configured ASR or TTS is used. If the configured ASR or TTS changes, the current ASR or TTS resources are released and new resources are seized before the dialog starts.

For example, a CCXML application can launch a dialog with English ASR or TTS. The application can determine that the caller prefers Spanish and so, the second dialog is launched with Spanish ASR or TTS.

Parameters

Parameter	Type	Description
toURI	String	Provides a hint to the Application Interface web service about what resources this CCXML application requires. The options are: • Blank (no input): Indicates that there are no requirements. • <code>tel</code>: Use this for an H.323 or SIP connection, or a mix of both. • <code>sip</code>: Use this for a standard SIP connection. • <code>sips</code>: Use this for a secure SIP connection.
applicationName	String	Name of the CCXML application to run once the outbound call has connected.  Important: The applicationName must match the name that was specified when the application was added to Experience Portal through the EPM. You can view all application names on the Applications page.
applicationURL	String	Parameters that should be appended to URL specified for the application in the EPM. This allows you to invoke the application with different arguments as needed.
parameters	String	One or more name-value variable pairs that will be passed to the CCXML application when it is invoked. Each pair should be in the format <code>parametername=value</code>, and multiple pairs should be separated by a ; (semi-colon).  Note: When the web service passes the parameter to the application, it appends the namespace <code>session.values.avaya.ParameterMap</code>. Therefore, the variable should be referenced in your application as <code>session.values.avaya.ParameterMap.parametername</code>. For example, if you specify <code>UserCounter=0</code> in the web service, you would reference <code>session.values.avaya.ParameterMap.UserCounter</code> in your application.

Table continues...

Parameter	Type	Description
uiInfo	String	The Application Interface web service passes any information in this parameter to the platform telephony layer included in the outbound call.
launchTimeout	Integer	The maximum amount of time, in seconds, to wait for the CCXML application to be start before returning an error message.
zone	String	Zone name where request should be directed. This is the zone name. (Optional).

Data returned

Parameter	Type	Description
sessionID_returned	String	If the CCXML application connected successfully, the Application Interface web service sets this return value to the session ID Experience Portal assigned to the new CCXML session.
totalRes_returned	Integer	Total number of outbound resources available, both used and unused.
unusedSIP_returned	Integer	Total number of unused SIP outbound resources.
unusedH323_returned	Integer	Total number of unused H.323 outbound resources.

* Note:

If zones are enabled, the returned resource information is the information for either the zone specified in the request, or for the default zone, if no zone was specified.

CCXML application status return values

Status	App Intf WS rc	Application
"success" `	0	
"networkdisconnect"	0	
"nearenddisconnect"	0	
"farenddisconnect"	0	
"calltransferred"	0	
"parse error"	0x22 (Invalid URL)	
"uri not found"	0x22 (Invalid URL)	
"fetch timeout"	0x13 (Failed)	LaunchCCXML only
"web server error"	0x13 (Failed)	LaunchCCXML only
"fetch error"	0x13 (Failed)	LaunchCCXML only
"unknown error"	0x13 (Failed) v	LaunchCCXML only
"noresource"	0x2 (No Resource)	
"busy"	0x10 (Busy)	
"networkbusy"	0x10 (Busy)	
"noanswer"	0x11 (No Answer)	

Table continues...

Status	App Intf WS rc	Application
"noroute"	0x20 (Invalid URI)	LaunchVXML only
"unknown"	0x12 (Network Refusal)	LaunchVXML only
"internalerror"	0x12 (Network Refusal)	LaunchVXML only
"glare"	0x12 (Network Refusal)v	LaunchVXML only
"invalidstate"	0x12 (Network Refusal)	LaunchVXML only
"fax detected"	0x16 (Fax Detected)	

*** Note:**

All return values generated by the LaunchVXML and LaunchCCXML may not have a mapping to the status that the CCXML application sends.

Related links

[Returning the status of a LaunchCCXML request](#) on page 543

[CCXML session properties](#) on page 544

Returning the status of a LaunchCCXML request

About this task

If you invoke a CCXML application using the Application Interface web service `LaunchCCXML` method, the application being launched *must* return the status of that launch using a custom event. This allows the CCXML application to determine whether the launch was successful instead of relying on the limited information available to the Application Interface web service.

For example, if the CCXML application launches correctly but no one answers the outgoing call, the Application Interface web service still considers the call to be a success because the application launched correctly. The CCXML application, on the other hand, may consider that call a failure because no one answered. In this case, the CCXML application would return a failure code to the Application Interface web service, and the Application Interface web service would return the failure code to Experience Portal.

*** Note:**

For information on the status related return values that the CCXML application sends, see [CCXML application status return values](#) on page 542.

Procedure

1. Create a custom event handler in your application that sends the results back to the Application Interface web service.
2. In the custom event handler, create a variable called `status` that contains the status you want to return to the Application Interface web service.

For example, if the call was not answered, you could assign `status` the value "no answer" using the `<var name="status" expr="no answer"/>` tag.

3. Send the response to the Application Interface web service using a `<send>` tag with the format: `<send name="avaya.launchresponse" targettype="avaya_platform" target="session.id" namelist="status"/>`, where `session.id` is the session identifier assigned to the session by Experience Portal.

Related links

[LaunchCCXML method](#) on page 540

CCXML session properties

session.values namespace properties

At the start of a CCXML session, the Application Interface web service places several properties in the `session.values.avaya` namespace properties.

Property	Description
<code>telephony.native_audio_format</code>	The audio encoding codec the MPP uses as the default for audio recording within the Avaya Voice Browser (AVB) when the speech application does not specify the format for recording caller inputs. The options are: • audio/basic: The AVB uses the mu-Law encoding format, which is used mostly in the United States and Japan. • audio/x-alaw-basic: The AVB uses the A-Law encoding format, which is used in most countries other than the United States and Japan.
<code>fax_detect_enabled</code>	For inbound calls, this property is set to the same value as the Fax Detection Enable parameter set for the application through the EPM Web interface.
<code>fax_detect_redirect_uri</code>	For inbound calls, if fax detection is enabled, this property is set to the same value as the Fax Phone Number parameter set for the application through the EPM Web interface.
<code>ConnectTimeoutSecs</code>	For outbound calls launched by the Application Interface web service, this is the maximum amount of time, in seconds, to wait for the CCXML application to be start before returning an error message.
<code>UUI_Info</code>	For outbound calls launched by the Application Interface web service, this property contains the information passed to the application in the <code>uuiInfo</code> parameter of the <code>LaunchCCXML</code> method.
<code>Parameters</code>	For outbound calls launched by the Application Interface web service, this property contains the name-value pairs passed to the application by the <code>LaunchCCXML</code> method.
<code>ParameterMap</code>	For outbound calls launched by the Application Interface web service, this object contains all of the parameters encoded in the <code>session.values.avaya parameters</code> field.

Additional properties

The CCXML browser also maintains current data in the `connections`, `conferences` and `dialogs` objects available within the `session` namespace. For details about these objects, see the [W3C CCXML Version 1.0, W3C Working Draft dated 19 January 2007](#).

Related links

[LaunchCCXML method](#) on page 540

LaunchEmail method

This method starts the specified email type application and if successful, returns the Experience Portal session ID for the new session.



Note:

The launched applications is responsible for sending the email message using the information passed to the application.



Important:

The return values are described [Return values](#) on page 560.

Parameters

Parameter	Type	Description
to	String	Email address that is configured on the system and can be used by the application being launched.
from	String	Multiple values, using a comma (,) as a delimiter, that can be used by an application. For example: john@abc.com,sam@abc.com,bob@abc.com.
cc	String	Email CC. You can specify multiple values using a comma (,) as a delimiter. For example: john@abc.com,sam@abc.com,bob@abc.com. (Optional)
bcc	String	Email BCC. You can specify multiple values using a comma (,) as a delimiter. For example: john@abc.com,sam@abc.com,bob@abc.com. (Optional)
subject	String	The subject of the message. (Optional)
body	String	Body of the message. (Optional)

Table continues...

Parameter	Type	Description
attachments	String	A list of attachment URLs, separated by a comma (,). (Optional)
headers	String	Contains name value in this format: name=value;name=value with a semicolon (;) as delimiter. Content-Type, Reply-To etc can be specified as headers. (optional)
applicationName	String	Name of the application to be launched. Contains zone info in the format zoneId:appName.
appParameters	String	Parameters to be send to Orchestration Designer App. Contains name value in this format: name=value;name=; with ; as delimiter. (optional)
emailParameters	String	Parameters to be send to Orchestration Designer App. Contains name value in this format: name=value;name=; with ; as delimiter. See table below for parameters. (optional)
ucid	String	Unique customer ID. (Optional)
parentID	String	Caller's session ID. (Optional)
requestTimeout	Integer	Time to wait for the request to finish. (In seconds)

Data returned

Parameter	Type	Description
sessionID_returned	String	If the request completes successfully, this return value contains the session ID string

LaunchSMS method

This method starts the specified SMS type application and if successful, returns the Experience Portal session ID for the new session.

 Note:

The launched applications is responsible for sending the SMS message using the information passed to the application.

! Important:

The return values are described [Return values](#) on page 560.

Parameters

Parameter	Type	Description
to	String	Short code that is configured on the system and can be used by the application being launched.
from	String	Multiple values using a comma (,) as a delimiter, that can be used by an application. For example: 12345,23456,54321. (Mandatory)
message	String	Message to send. (Optional)
applicationName	String	name of the application to be launched. Contains zone information in the format: ZoneId:appName.
appParameters	String	Parameters to be sent to the Orchestration Designer app. Contains name value using semicolon (;) as delimiter, in the following format: name=value;name=;. (Optional)
smsParameters	String	Parameters to be sent to o SMSC. Contains name value using semicolon (;) as delimiter, in the following format: name=value;name=;. (Optional)
ucid	String	Unique caller ID. (Optional)
parentID	String	Caller's session ID. (Optional)
requestTimeout	Integer	Time to wait for the request to finish. (In seconds)

Data returned

Parameter	Type	Description
sessionID_returned	String	If the request completed successfully, this return value contains the session ID string.

LaunchHTML method

This method starts the specified HTML type application and if successful, returns the following:

- Experience Portal session ID for the new session
- The session ID created on the application server
- The application URI which the HTML application was launched

Important:

The return values are described in [Return values](#) on page 560.

Parameters

Parameter	Type	Description
applicationName	String	Name of the application to be launched. Contains zone information in the following format: ZoneId:appName.
appParameters	String	Parameters to be sent to the launched application. Contains name value using semicolon (;) as delimiter, in the following format: name=value;name=;. (Optional) If a value contains a semicolon (";") it needs to be escaped using backslash ("\\").
ucid	String	Unique caller ID. (Optional)
parentID	String	Caller's session ID. (Optional)
requestTimeout	Integer	Time to wait for the request to finish. (In seconds) This value must be in the range 1-60 (inclusive).

Data returned

Parameter	Type	Description
sessionID_httpApp	String	If the request completed successfully, this return value contains the Experience Portal session ID that was created when the application was launched.
sessionID_AppServer	String	If the request completed successfully, this return value contains the Session ID that was created on the application server.
applicationURL	String	If the request completed successfully, this return value contains the application URI against which the HTML application was launched.

LaunchVXML method

This method initiates an outbound call on an available MPP, then starts the specified VoiceXML application. If successful, it returns the:

- Experience Portal session ID for the new session
- Total number of outbound resources available, both used and unused
- Total number of unused SIP outbound resources
- Total number of unused H.323 outbound resources

The actual launch of the VoiceXML application is handled by the default CCXML page, which is also responsible for returning success or failure back to the Application Interface web service.

When the VoiceXML application is invoked, the first VoiceXML page is prepared. If this succeeds, the outbound call is placed by the system. If the call connects and the dialog starts without error, then the VoiceXML application returns a successful launch code. Otherwise, the application returns an appropriate error code.

*** Note:**

If the initial VoiceXML page cannot be prepared for any reason, the Application Interface web service does not place the outbound call. Therefore a customer will never be bothered by an outbound call that cannot possibly start correctly.

For information about the status codes returned by the CCXML page, see [Returning the status of a LaunchCCXML request](#) on page 543.

*** Note:**

If a CCXML application launches multiple VoiceXML applications, each of these applications can use a different speech server. Prior to Experience Portal 7.0, multiple applications used only one speech server. This feature comes into play if you have different languages loaded onto different speech servers.

When a CCXML application launches a VoiceXML dialog by name, the configured ASR or TTS is used. If the configured ASR or TTS changes, the current ASR or TTS resources are released and new resources are seized before the dialog starts.

For example, a CCXML application can launch a dialog with English ASR or TTS. The application can determine that the caller prefers Spanish and so, the second dialog is launched with Spanish ASR or TTS.

! Important:

The return values are described [Return values](#) on page 560.

Parameters

Parameter	Type	Description
toURI	String	The number or destination to be contacted by the outbound application.

Table continues...

Parameter	Type	Description
		This parameter can be prefixed with one of the following strings: • <code>tel:</code> Use this for an H.323 or SIP connection, or a mix of both. • <code>sip:</code> Use this for a standard SIP connection. • <code>sips:</code> Use this for a secure SIP connection.
fromURI	String	Calling address information to pass with the outbound call.
applicationName	String	Name of the VoiceXML application to run once the outbound call has connected. ! Important: The applicationName must match the name that was specified when the application was added to Experience Portal through the EPM. You can view all application names on the Applications page.
applicationURL	String	Parameters that should be appended to URL specified for the application in the EPM. This allows you to invoke the application with different arguments as needed.
parameters	String	One or more name-value variable pairs that will be passed to the VoiceXML application when it is invoked. Each pair should be in the format <code>parametername=value</code>, and multiple pairs should be separated by a <code>;</code> (semi-colon). * Note: When the web service passes the parameter to the application, it appends the namespace <code>session.avaya.telephone</code>. Therefore, the variable should be referenced in your application as <code>session.avaya.telephone.parametername</code>. For example, if you specify <code>UserCounter=0</code> in the web service, you would reference <code>session.avaya.telephone.UserCounter</code> in your application. + Tip: If you want to enable call classification for this call, see Call classification with the LaunchVXML method on page 551.
uiInfo	String	The Application Interface web service passes any information in this parameter to the platform telephony layer included in the outbound call.
connectTimeoutSecs	Integer	The maximum amount of time, in seconds, to wait for the outbound call to be connected. Enter a value between 0 and 59.

Table continues...

Parameter	Type	Description
		If this parameter is set to 0 (zero) or omitted, Experience Portal uses the default value of 120 seconds.
zone	String	This is the zone name where request should be directed. (Optional).

Data returned

Parameter	Type	Description
sessionID_returned	String	If the VoiceXML application connected successfully, the Application Interface web service sets this return value to the session ID Experience Portal assigned to the new CCXML session.
totalRes_returned	Integer	Total number of outbound resources available, both used and unused.
unusedSIP_returned	Integer	Total number of unused SIP outbound resources.
unusedH323_returned	Integer	Total number of unused H.323 outbound resources.

* Note:

If zones are enabled, the resource information returned is the information for the zone specified in the request. If no zone is specified, the resource information returned is the information for the default zone.

Related links

[Call classification with the LaunchVXML method](#) on page 551

[VoiceXML session properties](#) on page 553

At the start of a VoiceXML session, the Application Interface web service places several properties in the `session.connection`, `session.avaya.telephone`, and `session.telephone` namespaces.

Call classification with the LaunchVXML method

Call classification allows the VoiceXML application to return the appropriate status code based on whether a human, an answering machine, or a fax machine answers an outbound call.

Call classification parameters for the LaunchVXML method

The following call classification name-value pairs can be passed as parameters with the `launchVXML` method. For both parameters the default is `false`, which means that you must specify the name-value pair in order to enable the associated functionality.

Name-value pair	Description
<code>enable_call_classification=true</code>	This required parameter enables call classification.
<code>detect_greeting_end=true</code>	This optional parameter instructs the VoiceXML application to identify the end of a recorded greeting if an answering machine answers the outbound call.

Table continues...

Name-value pair	Description
<code>call_classification_recorded_msg_timeout = in mili secs (e.g. 30000 is 30 sec)</code>	This Optional parameter is to set wait timeout for “end of recorded greeting”, if an answering machine answers the outbound call. Default is 30 sec.
<code>call_classification_connectWhen = (OnConnect or OnProgress)</code>	This optional parameter is to start the CPA engine (call classification) on either OnConnect or OnProgress. By default it is set to OnProgress. In case the engine is started before connect, early media will also be captured for call classification.
<code>call_classification_timeout=value</code>	This optional parameter indicates how long the call classification function will run if it is unable to determine the classification. The value specified should be in milliseconds. If the value is not provided, the default timeout is 20 sec.
<code>call_classification_timeout = in mili secs (e.g. 20000 is 20 sec)</code>	Timeout for outbound call classification from engine. Default is 20 sec.

Call classifications

If you enable call classification, the VoiceXML application sends one of the following classifications to the application server using the query arguments on the URL:

Classification	Description
<code>live_voice</code>	If a human being answers the call, the application starts the previously-prepared VoiceXML dialog.  Note: This is the default classification assigned to the VoiceXML session before the call is placed. If a human being does not answer the call, this classification must be changed.
<code>recorded_msg</code>	If the <code>LaunchVXML</code> method was invoked with <code>detect_greeting_end=false</code> or if the <code>detect_greeting_end</code> parameter was not specified and an answering machine answers the call, the application terminates the previously-prepared VoiceXML dialog and starts a new dialog by sending the classification <code>recorded_msg</code> to the application server.
<code>msg_end</code>	If the <code>LaunchVXML</code> method was invoked with <code>detect_greeting_end=true</code> and an answering machine answers the call, the application terminates the previously-prepared VoiceXML dialog and starts a new dialog by sending the classification <code>msg_end</code> to the application server.
<code>fax_answer_tone</code>	If a fax machine answers the call, the application terminates and returns the error code <code>fax detected (8206)</code> to the Application Interface web service.
<code>timeout</code>	If the VoiceXML application does not send a classification change message to the CCXML page within a given period of time, the CCXML applications

Table continues...

Classification	Description
	assumes that a live person has answered the phone and it starts the previously-prepared VoiceXML dialog.
*	All other classifications result in the status code for <code>no answer ()</code> being returned the Application Interface web service.

Related links

[LaunchVXML method](#) on page 549

VoiceXML session properties

At the start of a VoiceXML session, the Application Interface web service places several properties in the `session.connection`, `session.avaya.telephone`, and `session.telephone` namespaces.

session.connection namespace properties

Property	Description
<code>call_tag</code>	The unique identifier for the session assigned by the Media Server.
<code>ccxml.namelist.*</code>	If the CCXML application passes data to the VoiceXML dialog at the beginning of the session, this array variable contains a list of the variable names passed by the CCXML application.
<code>ccxml.values.*</code>	If the CCXML application passes data to the VoiceXML dialog at the beginning of the session, this array variable contains a list of the values for the variable names contained in <code>ccxml.namelist.*</code> .
<code>local.uri</code>	The Dialed Number Identification Service (DNIS) associated with the call that triggered the VoiceXML session.
<code>protocol.name</code>	The telephony protocol name. The options are: • <code>h323</code> • <code>sip</code>
<code>remote.uri</code>	The Automatic Number Identification (ANI) associated with the call that triggered the VoiceXML session.

session.avaya namespace properties

* Note:

For convenience, several of the `session.avaya` namespace properties are the same as the `session.connection` namespace properties.

Property	Description
<code>telephone.ani</code>	The Automatic Number Identification (ANI) associated with the call that triggered the VoiceXML session.

Table continues...

Property	Description
<code>telephone.call_tag</code>	The unique identifier for the session assigned by the Media Server.
<code>telephone.called_extension</code>	For calls using an H.323 connection, this is the telephony port servicing the VoiceXML session.
<code>telephone.callid</code>	The unique identifier for the call assigned by the Media Server.
<code>telephone.channel</code>	This property is reserved for future use.
<code>telephone.dnis</code>	The Dialed Number Identification Service (DNIS) associated with the call that triggered the VoiceXML session.
<code>telephone.startPage</code>	The full URL, including any query string parameters, used to fetch the first page of the VoiceXML session.
<code>uui.mode</code>	The User-to-User Interface (UII) mode under which this application is operating. The options are: • <code>shared</code> • <code>service provider</code>
<code>uui.shared[]</code>	If <code>uui.mode</code> is <code>shared</code> , this property contains an array of the shared UII data pieces in name-value format.

session.telephone namespace properties

*** Note:**

For convenience, most of the `session.telephone` namespace properties are the same as the `session.connection` and `session.avaya` namespace properties.

Property	Description
<code>ani</code>	The Automatic Number Identification (ANI) associated with the call that triggered the VoiceXML session.
<code>dnis</code>	The Dialed Number Identification Service (DNIS) associated with the call that triggered the VoiceXML session.
<code>call_tag</code>	The unique identifier for the session assigned by the Media Server.
<code>called_extension</code>	For calls using an H.323 connection, this is the telephony port servicing the VoiceXML session.
<code>callid</code>	The unique identifier for the call assigned by the Media Server.
<code>channel</code>	This property is reserved for future use.
<code>startPage</code>	The full URL, including any query string parameters, used to fetch the first page of the VoiceXML session.
<code>*</code>	This property contains any parameters passed to the Application Interface web service through the <code>LaunchVXML</code> method.

Related links

[LaunchVXML method](#) on page 549

QueryResources method

This method takes a snapshot of the current outbound usage across all MPPs in the Experience Portal system and returns:

- Total number of outbound resources available, both used and unused
- Total number of unused SIP outbound resources
- Total number of unused H.323 outbound resources

If zones are enabled, the returned resource information is the information for all MPPs with the zone specified in the request, or for the default zone if no zone was specified.

You can use this method to determine the approximate availability of outbound resources before you use the `LaunchCCXML` or `LaunchVXML` method to start a new outbound session.

Keep in mind, however, that system usage is extremely dynamic. The `QueryResources` method only returns a snapshot of the current usage. It does not look for upcoming outbound calls or try to determine whether another `LaunchCCXML` or `LaunchVXML` command has just started and is about to claim one or more outbound resources.

In addition, this method reports the total number of outbound resources available across all MPPs in the Experience Portal system, or all MPPs in the specified zone, if zones are enabled. Each application only has access to the available ports on the MPP to which it is assigned. If your site has multiple MPPs, that means any single application will probably not have access to the total number of resources returned by this method. For more information on using applications that launch multiple outgoing calls, see [Best practices](#) on page 535.

! Important:

The return values are described [Return values](#) on page 560.

Data Returned

Name	Type	Description
totalRes_returned	Integer	Total number of outbound resources available, both used and unused.
unusedSIP_returned	Integer	Total number of unused SIP outbound resources.
unusedH323_returned	Integer	Total number of unused H.323 outbound resources.

* Note:

If zones are enabled, the resource information returned is the information for the zone specified in the request. If no zone is specified, the resource information returned is the information for the default zone.

SendCCXMLEvent method

This method instructs the MPP to dispatch a user-named event with an accompanying parameter string to the specified CCXML session.

! Important:

The return values are described [Return values](#) on page 560.

Parameters

Name	Type	Description
sessionID	String	The session ID of an existing CCXML session. This parameter must match exactly the session ID assigned by Avaya Aura® Experience Portal when the session started.
eventName	String	The user-defined event that the MPP should send to the session.
parameters	String	Any user-defined parameters that the MPP should pass along with the event to the CCXML session.

SendEmail method

This method starts the specified email type application and if successful, returns the Experience Portal session ID for the new session.

! Important:

The return values are described [Return values](#) on page 560.

Parameters

Parameter	Type	Description
from	String	Email address used to send the message
to	String	Target of the message. You can specify multiple values, using a comma (,) as a delimiter. For example: john@abc.com,sam@abc.com,bo b@abc.com.
cc	String	Email CC. You can specify multiple values, using a comma (,) as a delimiter. For example: john@abc.com,sam@abc.com,bo b@abc.com. (Optional)
bcc	String	Email BCC. You can specify multiple values, using a comma (,) as a delimiter. For example: john@abc.com,sam@abc.com,bo b@abc.com. (Optional)
subject	String	The subject of the message. (Optional)

Table continues...

Parameter	Type	Description
body	String	Body of the message. (Optional)
attachments	String	A list of attachment URLs, separated by a comma (,). (Optional)
headers	String	Contains name value in this format: name=value;name=value with a semicolon (;) as delimiter. Content-Type, Reply-To etc can be specified as headers. (optional)
applicationName	String	Name of the application to be launched. Contains zone info in the format zoneId:appName.
emailParameters	String	Parameters to be send to Orchestration Designer App. Contains name value in this format: name=value;name=; with ; as delimiter. See table below for parameters. (optional)
ucid	String	Unique customer ID. (Optional)
sessionID	String	Caller's session ID.
requestTimeout	String	Time to wait for the request to finish. (In seconds)

Data returned

Parameter	Type	Description
messageID_returned	String	If the request completes successfully, this return value contains the session ID string

SendSMS method

This method sends an SMS message, and if successful, returns the Experience Portal message ID for the new session.

Important:

The return values are described [Return values](#) on page 560.

Parameters

Parameter	Type	Description
from	String	Short code used to send the message.
to	String	Target of the message. You can specify multiple values using a comma (,) as a delimiter. For example: 12345,23456,54321.
message	String	Message to send.
applicationName	String	name of the application to be launched. Contains zone information in the format: Zoneld:appName.
smsParameters	String	Parameters to be sent to o SMSC. Contains name value using semicolon (;) as delimiter, in the following format: name=value;name=;. (Optional)
ucid	String	Unique caller ID. (Optional)
sessionID	String	Caller's session ID. (Optional)
requestTimeout	Integer	Time to wait for the request to finish. (In seconds)

Data returned

Parameter	Type	Description
sessionID_returned	String	If the request completed successfully, this return value contains the session ID.

Additional parameters in the LaunchEmail and SendEmail methods

Parameter	Description
CC	The CC email address. You can separate multiple email addresses by comma (,).
BCC	The BCC email address. You can separate multiple email addresses by comma (,).
ReplyTo	The ReplyTo address to be set in the email.

Table continues...

Parameter	Description
Attachment	The attachment list. You can separate multiple attachment files by comma (,).
RegisteredDelivery	Demanding a registered delivery for the request. Value should be one of the SMTP notification value: -1 (Notify Never), 1 (Notify Success), 2 (Notify Failure), 4 (Notify Delay)
Priority	Assigns a priority level, in the range of to ≥ 1 and ≤ 5 , to the message. The "X-Priority" value in the email is set accordingly so that email importance is honored by the SMTP servers. 1 indicates high priority and 5 as low. If none specified, set as 0 – no priority marking for the email.
ContentType	Email content type: text/plain or text/html.
Charset	The charset of the email.
DisplayName	Display name to be used for the email from address.

Additional parameters in the LaunchSMS and SendSMS methods

Parameter	Description
RegisteredDelivery	Demanding a registered delivery for the request. Accepted values: 0 and 1. 1= Requires a receipt; 0 (default) = No delivery receipt.
DataCoding	Defines the encoding scheme of the short message user data. Default is 0 to use the SMSC default Alphabet. Refer to the SMPP specifications for details (Short Message Peer to Peer Protocol Specification v3.4; section: 5.2.19).
Priority	Designates a priority level to the message. 4 priority levels are supported (0 being lowest and 3 being highest). Default to 0. Refer to the SMPP specification document section 5.2.14 for more details.
ValidityPeriod	Sets the validity period for this message, so that SMSC can ignore the message if it can't deliver within this time. Default to 0 for SMSC default validity period. Refer to the SMPP specification document section 5.2.16 & 7.1.1.

Table continues...

Parameter	Description
ScheduleDelivery	Indicates that SMSC need to schedule the message for delivery at the time specified. Default to 0 for immediate delivery.
Encoding	Defines the character encoding scheme of the message user data. Default is to use ASCII. For the list of character encoding, refer: http://docs.oracle.com/javase/1.3/docs/guide/intl/encoding.doc.html
Language	The SMPP language indicator of the short message (CMT-136 standard). Refer to the SMPP specification for details: (Short Message Peer to Peer Protocol Specification v3.4; section: 5.3.2.19).
UserMessageReference	A custom reference id that can be submitted along with the message that could be used by the application to build context and further interpretation. Optional parameter; not all SMSC vendor required to support.

Return Values

The following table describes the return values that the application interface web service receives when the system process the web services request:

Return value		Attributes	Condition	Get Status	Get StatusEx	Launch CCKML	Launch Email	Launch SMS	Launch VXML	Query Resources	Send CCKML Event	Send Email	Send SMS	LaunchHTML
hex														
0x0	0	Success	The web service successfully completed the request.	X	X	X	X	X	X	X	X	X	X	X
0x1	1	Failure	The web service was unable to complete the request. Verify that the EPM and MPP servers are communicating properly and retry the request.	X	X	X	X	X	X	X	X	X	X	
0x2	2	No resource	No resources are available to process the request.			X	X	X	X			X	X	
0x3	3	No User Access	The user is not allowed to access the web service.			X	X	X	X		X	X	X	X
0x4	4	No App Access	The user is not allowed to access the specified application.			X	X	X	X			X	X	X
0x10	16	Busy	The destination named in the toURI parameter is busy and cannot be reached.						X					
0x11	17	No Answer	The destination named in the toURI parameter did not answer within the amount of time specified in the connectTimeoutSecs parameter.						X					
0x12	18	Network Refusal	The outbound call was rejected due to a network error.						X					
0x13	19	Failed	The application was not started due to a problem with the application server.			X								
0x14	20	Timeout	The operation did not get a response within the amount of time specified in the timeout parameter.			X	X	X	X			X	X	
0x15	21	No Response	The session ended and the VoiceXML/CCXML page did not return a response to Experience Portal. This can happen if the VoiceXML/CCXML page is not designed to send a response, or if the page has an error and exits before the code that sends the response executes.			X			X					
0x16	22	Fax Detected	The outbound number is associated with a fax machine.			X			X					
0x20	32	Invalid URI	The toURI parameter contains an invalid URI specification.			X			X					
0x21	33	Unknown Application	The applicationName parameter does not match one of the application names configured through the EPM. You can view all application names on the Applications page.			X	X	X	X			X	X	X
0x22	34	Invalid URL	The applicationURL parameter contains an invalid URL specification.			X			X					

Return value		Attributes	Condition	Get Status	Get StatusEx	Launch CCKML	Launch Email	Launch SMS	Launch VXML	Query Resources	Send CCKML Event	Send Email	Send SMS	LaunchHTML
0x23	35	Invalid Session ID	No current session ID matched the one specified in the sessionID parameter. Make sure that the session ID is correct and that the session is still running on the MPP.								X	X	X	
0x24	36	Invalid Connect Timeout	The Connect timeout in LaunchVXML request (connectTimeoutSecs) is too long. The value specified must be less than the MaxLaunchVXMLConnectTimeout parameter in the voiceportal.properties file on Experience Portal.						X					
0x25	37	Invalid Zone	Invalid Zone specified.			X	X	X	X	X		X	X	X
0x30	48	MPP Down	The MPP service is not running and cannot service the request.								X			
0x31	49	MPP Stopped	The MPP service is running, but the MPP is not currently processing calls.								X			
0x32	50	MPP WS Failure	The required out call web service is not running on any MPP in the system. Therefore the call cannot be connected. Messages from the Application Interface web service appear in the OCWSServer.log file on the MPP, which is accessible from the Media Server Service Menu Log Directories page.			X	X	X	X		X	X	X	
0x43	67	Invalid Timeout	Invalid timeout specified				X	X				X	X	X
0x44	68	Invalid To	Invalid data in the "to" field									X	X	
0x45	69	Invalid From	Invalid data in the "from" field				X						X	
0x46	70	Invalid Message	Invalid data in the message field										X	
0x47	71	Invalid Request Data	Invalid data in the request				X	X				X	X	X
0x57	87	Exception from HTMLLauncher	The HTML Launcher generated an exception											X
0x58	88	HTMLLauncher Failure	The HTML Launcher generated a failure											X
0x59	89	HTMLLauncher returned unknown application	The HTML Launcher could not locate the specified application											X
0x5A	90	HTMLLauncher returned unspecified error	The HTML Launcher returned an error that is unspecified.											X

Return value	Attributes	Condition	Get Status	Get StatusEx	Launch CXML	Launch Email	Launch SMS	Launch VXML	Query Resources	Send CXML Event	Send Email	Send SMS	LaunchHTML
0x5B	91	HTML Launcher returned Not Licensed	The HTML Launcher was unable to launch the application due to licensing.										X
0x102	258	Fatal Error	The web service is in an error state that requires a restart of the EPM service.	X	X	X	X	X	X	X	X	X	
0x103	259	Not Initialized	The web service is not initialized and unable to accept requests.	X	X	X	X	X	X	X	X	X	
0x104	260	Shutting Down	The web service is shutting down and no new requests are being accepted.	X	X	X	X	X	X	X	X	X	
0x201	513	Network Failed before Connection Completed	Represents that the network failed before the connection was completed.			X		X					
0x202	514	Near End Disconnect before Connection Completed	Represents that the caller disconnected the call before the called number was connected.			X		X					
0x203	515	Near End Disconnect before Connection Completed	Far End Disconnected before the connection was completed.			X		X					
0x204	516	Transferred before Connection Completed	Represents that the call is transferred before the connection was completed.			X		X					
0x205	517	Unknown Failure before Connection Completed	Represents that the call cannot be completed due to unknown reason.			X		X					
0x206	518	Call Disconnected before Application Started	Represents that the call is disconnected before the application was started.					X					

Sample Application Interface web service WSDL file

The following is an example of the Application Interface web service WSDL file. The actual file is installed on the server that is running the EPM software. For details about accessing this file, see [Configuring the Application Interface web service](#) on page 536.

```
<?xml version="1.0" encoding="UTF-8"?>
<wsdl:definitions xmlns:wsdl="http://schemas.xmlsoap.org/wsdl/"
xmlns:ns1="http://org.apache.axis2/xsd"
xmlns:ns="http://xml.avaya.com/ws/VPAppIntf/VoicePortal"
xmlns:wsaw="http://www.w3.org/2006/05/addressing/wsdl"
xmlns:ax25="http://services.vp.avaya.com/xsd"
xmlns:http="http://schemas.xmlsoap.org/wsdl/http/" xmlns:ax21="http://rmi.java/xsd"
xmlns:ax22="http://io.java/xsd" xmlns:xs="http://www.w3.org/2001/XMLSchema"
xmlns:mime="http://schemas.xmlsoap.org/wsdl/mime/"
xmlns:soap="http://schemas.xmlsoap.org/wsdl/soap/"
xmlns:soap12="http://schemas.xmlsoap.org/wsdl/soap12/"
targetNamespace="http://xml.avaya.com/ws/VPAppIntf/VoicePortal">
  <wsdl:types>
    <xs:schema xmlns:ax23="http://io.java/xsd" attributeFormDefault="qualified"
elementFormDefault="qualified" targetNamespace="http://rmi.java/xsd">
      <xs:import namespace="http://io.java/xsd"/>
      <xs:complexType name="RemoteException">
        <xs:complexContent>
          <xs:extension base="ax23:IOException">
            <xs:sequence>
              <xs:element minOccurs="0" name="cause" nillable="true"
type="xs:anyType"/>
              <xs:element minOccurs="0" name="message" nillable="true"
type="xs:string"/>
            </xs:sequence>
          </xs:extension>
        </xs:complexContent>
      </xs:complexType>
    </xs:schema>
    <xs:schema attributeFormDefault="qualified" elementFormDefault="qualified"
targetNamespace="http://services.vp.avaya.com/xsd">
```

```

    <xs:complexType name="SendCCXMLEventRequest">
      <xs:sequence>
        <xs:element minOccurs="1" name="eventName" nillable="false"
type="xs:string"/>
        <xs:element minOccurs="0" name="parameters" nillable="true"
type="xs:string"/>
        <xs:element minOccurs="1" name="sessionID" nillable="false"
type="xs:string"/>
      </xs:sequence>
    </xs:complexType>
    <xs:complexType name="SendCCXMLEventResponse">
      <xs:sequence>
        <xs:element minOccurs="1" name="retCode" type="xs:int"/>
      </xs:sequence>
    </xs:complexType>
    <xs:complexType name="QueryResourcesRequest">
      <xs:sequence>
        <xs:element minOccurs="0" name="queryResourcesRequestUnused"
type="xs:int"/>
        <xs:element minOccurs="0" name="zone" nillable="true"
type="xs:string"/>
      </xs:sequence>
    </xs:complexType>
    <xs:complexType name="QueryResourcesResponse">
      <xs:sequence>
        <xs:element minOccurs="1" name="totalRes_returned" type="xs:int"/>
        <xs:element minOccurs="1" name="unusedH323_returned" type="xs:int"/>
        <xs:element minOccurs="1" name="unusedSIP_returned" type="xs:int"/>
      </xs:sequence>
    </xs:complexType>
    <xs:complexType name="LaunchVXMLRequest">
      <xs:sequence>
        <xs:element minOccurs="1" name="applicationName" nillable="false"
type="xs:string"/>
        <xs:element minOccurs="0" name="applicationURL" nillable="true"
type="xs:string"/>
        <xs:element minOccurs="0" name="connectTimeoutSecs" type="xs:int"/>
        <xs:element minOccurs="1" name="fromURI" nillable="false"
type="xs:string"/>
        <xs:element minOccurs="0" name="parameters" nillable="true"
type="xs:string"/>
        <xs:element minOccurs="1" name="toURI" nillable="false"
type="xs:string"/>
        <xs:element minOccurs="0" name="uuiInfo" nillable="true"
type="xs:string"/>
        <xs:element minOccurs="0" name="zone" nillable="true"
type="xs:string"/>
      </xs:sequence>
    </xs:complexType>
    <xs:complexType name="LaunchVXMLResponse">
      <xs:sequence>
        <xs:element minOccurs="1" name="sessionID_returned" nillable="false"
type="xs:string"/>
        <xs:element minOccurs="1" name="totalRes_returned" type="xs:int"/>
        <xs:element minOccurs="1" name="unusedH323_returned" type="xs:int"/>
        <xs:element minOccurs="1" name="unusedSIP_returned" type="xs:int"/>
      </xs:sequence>
    </xs:complexType>
    <xs:complexType name="LaunchCCXMLRequest">
      <xs:sequence>
        <xs:element minOccurs="1" name="applicationName" nillable="false"
type="xs:string"/>
        <xs:element minOccurs="0" name="applicationURL" nillable="true"
type="xs:string"/>
        <xs:element minOccurs="0" name="launchTimeout" type="xs:int"/>

```

```

type="xs:string"/>
type="xs:string"/>
type="xs:string"/>
type="xs:string"/>
</xs:sequence>
</xs:complexType>
<xs:complexType name="LaunchCCXMLResponse">
  <xs:sequence>
    <xs:element minOccurs="1" name="sessionID_returned" nillable="false"
type="xs:string"/>
    <xs:element minOccurs="1" name="totalRes_returned" type="xs:int"/>
    <xs:element minOccurs="1" name="unusedH323_returned" type="xs:int"/>
    <xs:element minOccurs="1" name="unusedSIP_returned" type="xs:int"/>
  </xs:sequence>
</xs:complexType>
<xs:complexType name="LaunchSMSRequest">
  <xs:sequence>
    <xs:element minOccurs="0" name="appParameters" nillable="true"
type="xs:string"/>
    <xs:element minOccurs="1" name="applicationName" nillable="false"
type="xs:string"/>
    <xs:element minOccurs="0" name="from" nillable="true"
type="xs:string"/>
    <xs:element minOccurs="0" name="message" nillable="true"
type="xs:string"/>
    <xs:element minOccurs="0" name="parentID" nillable="true"
type="xs:string"/>
    <xs:element minOccurs="1" name="requestTimeout" type="xs:int"/>
    <xs:element minOccurs="0" name="smsParameters" nillable="true"
type="xs:string"/>
    <xs:element minOccurs="0" name="to" nillable="true" type="xs:string"/>
    <xs:element minOccurs="0" name="ucid" nillable="true"
type="xs:string"/>
  </xs:sequence>
</xs:complexType>
<xs:complexType name="LaunchSMSResponse">
  <xs:sequence>
    <xs:element minOccurs="1" name="sessionID_returned" nillable="false"
type="xs:string"/>
  </xs:sequence>
</xs:complexType>
<xs:complexType name="SendSMSRequest">
  <xs:sequence>
    <xs:element minOccurs="1" name="applicationName" nillable="false"
type="xs:string"/>
    <xs:element minOccurs="1" name="from" nillable="false"
type="xs:string"/>
    <xs:element minOccurs="1" name="message" nillable="false"
type="xs:string"/>
    <xs:element minOccurs="1" name="requestTimeout" type="xs:int"/>
    <xs:element minOccurs="1" name="sessionID" nillable="false"
type="xs:string"/>
    <xs:element minOccurs="0" name="smsParameters" nillable="true"
type="xs:string"/>
    <xs:element minOccurs="1" name="to" nillable="false"
type="xs:string"/>
    <xs:element minOccurs="0" name="ucid" nillable="true"
type="xs:string"/>
  </xs:sequence>
</xs:complexType>
<xs:complexType name="SendSMSResponse">

```

```

        <xs:sequence>
          <xs:element minOccurs="1" name="messageID_returned" nillable="false"
type="xs:string"/>
        </xs:sequence>
      </xs:complexType>
      <xs:complexType name="LaunchEmailRequest">
        <xs:sequence>
          <xs:element minOccurs="0" name="appParameters" nillable="true"
type="xs:string"/>
          <xs:element minOccurs="1" name="applicationName" nillable="false"
type="xs:string"/>
          <xs:element minOccurs="0" name="attachments" nillable="true"
type="xs:string"/>
          <xs:element minOccurs="0" name="bcc" nillable="true"
type="xs:string"/>
          <xs:element minOccurs="0" name="body" nillable="true"
type="xs:string"/>
          <xs:element minOccurs="0" name="cc" nillable="true" type="xs:string"/>
          <xs:element minOccurs="0" name="emailParameters" nillable="true"
type="xs:string"/>
          <xs:element minOccurs="1" name="from" nillable="false"
type="xs:string"/>
          <xs:element minOccurs="0" name="headers" nillable="true"
type="xs:string"/>
          <xs:element minOccurs="0" name="parentID" nillable="true"
type="xs:string"/>
          <xs:element minOccurs="1" name="requestTimeout" type="xs:int"/>
          <xs:element minOccurs="0" name="subject" nillable="true"
type="xs:string"/>
          <xs:element minOccurs="0" name="to" nillable="true" type="xs:string"/>
          <xs:element minOccurs="0" name="ucid" nillable="true"
type="xs:string"/>
        </xs:sequence>
      </xs:complexType>
      <xs:complexType name="LaunchEmailResponse">
        <xs:sequence>
          <xs:element minOccurs="1" name="sessionID_returned" nillable="false"
type="xs:string"/>
        </xs:sequence>
      </xs:complexType>
      <xs:complexType name="SendEmailRequest">
        <xs:sequence>
          <xs:element minOccurs="1" name="applicationName" nillable="false"
type="xs:string"/>
          <xs:element minOccurs="0" name="attachments" nillable="true"
type="xs:string"/>
          <xs:element minOccurs="0" name="bcc" nillable="true"
type="xs:string"/>
          <xs:element minOccurs="0" name="body" nillable="true"
type="xs:string"/>
          <xs:element minOccurs="0" name="cc" nillable="true" type="xs:string"/>
          <xs:element minOccurs="0" name="emailParameters" nillable="true"
type="xs:string"/>
          <xs:element minOccurs="0" name="from" nillable="true"
type="xs:string"/>
          <xs:element minOccurs="0" name="headers" nillable="true"
type="xs:string"/>
          <xs:element minOccurs="1" name="requestTimeout" type="xs:int"/>
          <xs:element minOccurs="1" name="sessionID" nillable="false"
type="xs:string"/>
          <xs:element minOccurs="1" name="subject" nillable="false"
type="xs:string"/>
          <xs:element minOccurs="1" name="to" nillable="false"
type="xs:string"/>
          <xs:element minOccurs="0" name="ucid" nillable="true"

```

```

type="xs:string"/>
    </xs:sequence>
</xs:complexType>
<xs:complexType name="SendEmailResponse">
    <xs:sequence>
        <xs:element minOccurs="1" name="messageID_returned" nillable="false"
type="xs:string"/>
    </xs:sequence>
</xs:complexType>
<xs:complexType name="LaunchHtmlRequest">
    <xs:sequence>
        <xs:element minOccurs="0" name="appParameters" nillable="true"
type="xs:string"/>
        <xs:element minOccurs="1" name="applicationName" nillable="false"
type="xs:string"/>
        <xs:element minOccurs="0" name="parentID" nillable="true"
type="xs:string"/>
        <xs:element minOccurs="0" name="requestTimeout" type="xs:int"/>
        <xs:element minOccurs="0" name="ucid" nillable="true"
type="xs:string"/>
    </xs:sequence>
</xs:complexType>
<xs:complexType name="LaunchHtmlResponse">
    <xs:sequence>
        <xs:element minOccurs="1" name="applicationURL" nillable="false"
type="xs:string"/>
        <xs:element minOccurs="1" name="sessionID_AppServer" nillable="false"
type="xs:string"/>
        <xs:element minOccurs="1" name="sessionID_htmlApp" nillable="false"
type="xs:string"/>
    </xs:sequence>
</xs:complexType>
<xs:complexType name="LaunchAppRequest">
    <xs:sequence>
        <xs:element minOccurs="1" name="applicationName" nillable="false"
type="xs:string"/>
        <xs:element minOccurs="1" name="from" nillable="false"
type="xs:string"/>
        <xs:element minOccurs="1" name="genericAppType" nillable="false"
type="xs:string"/>
        <xs:element minOccurs="0" name="parameters" nillable="true"
type="xs:string"/>
        <xs:element minOccurs="0" name="parentID" nillable="true"
type="xs:string"/>
        <xs:element minOccurs="1" name="requestTimeout" type="xs:int"/>
        <xs:element minOccurs="1" name="to" nillable="false"
type="xs:string"/>
        <xs:element minOccurs="0" name="ucid" nillable="true"
type="xs:string"/>
    </xs:sequence>
</xs:complexType>
<xs:complexType name="LaunchAppResponse">
    <xs:sequence>
        <xs:element minOccurs="1" name="ID_returned" nillable="false"
type="xs:string"/>
        <xs:element minOccurs="1" name="parameters" nillable="false"
type="xs:string"/>
    </xs:sequence>
</xs:complexType>
<xs:complexType name="GetStatusExRequest">
    <xs:sequence>
        <xs:element minOccurs="0" name="getStatusExRequestUnused"
type="xs:int"/>
    </xs:sequence>
</xs:complexType>

```



```

    <xs:complexType name="GetStatusExResponse">
      <xs:sequence>
        <xs:element minOccurs="1" name="avgMPPHops_returned" type="xs:int"/>
        <xs:element minOccurs="1" name="iCCXMLEventsSent_returned"
type="xs:int"/>
        <xs:element minOccurs="1" name="iCCXMLRequestsProcessed_returned"
type="xs:int"/>
        <xs:element minOccurs="1" name="iLaunchAppRequestsProcessed_returned"
type="xs:int"/>
        <xs:element minOccurs="1"
name="iLaunchEmailRequestsProcessed_returned" type="xs:int"/>
        <xs:element minOccurs="1" name="iLaunchSmsRequestsProcessed_returned"
type="xs:int"/>
        <xs:element minOccurs="1" name="iSIPRequestsProcessed_returned"
type="xs:int"/>
        <xs:element minOccurs="1" name="iSendAppRequestsProcessed_returned"
type="xs:int"/>
        <xs:element minOccurs="1" name="iSendEmailRequestsProcessed_returned"
type="xs:int"/>
        <xs:element minOccurs="1" name="iSendSmsRequestsProcessed_returned"
type="xs:int"/>
        <xs:element minOccurs="1" name="iTELRequestsProcessed_returned"
type="xs:int"/>
        <xs:element minOccurs="1" name="iVXMLRequestsProcessed_returned"
type="xs:int"/>
        <xs:element minOccurs="1" name="lastRequestDateTime_returned"
nillable="false" type="xs:dateTime"/>
        <xs:element minOccurs="1" name="maxMPPHops_returned" type="xs:int"/>
        <xs:element minOccurs="1" name="minMPPHops_returned" type="xs:int"/>
        <xs:element minOccurs="1" name="serviceStartedDateTime_returned"
nillable="false" type="xs:dateTime"/>
        <xs:element minOccurs="1" name="vpmsSoftwareVersion_returned"
nillable="false" type="xs:string"/>
      </xs:sequence>
    </xs:complexType>
    <xs:complexType name="SendAppRequest">
      <xs:sequence>
        <xs:element minOccurs="1" name="applicationName" nillable="false"
type="xs:string"/>
        <xs:element minOccurs="1" name="from" nillable="false"
type="xs:string"/>
        <xs:element minOccurs="1" name="genericAppType" nillable="false"
type="xs:string"/>
        <xs:element minOccurs="0" name="parameters" nillable="true"
type="xs:string"/>
        <xs:element minOccurs="1" name="requestTimeout" type="xs:int"/>
        <xs:element minOccurs="0" name="sessionID" nillable="true"
type="xs:string"/>
        <xs:element minOccurs="1" name="to" nillable="false"
type="xs:string"/>
        <xs:element minOccurs="0" name="ucid" nillable="true"
type="xs:string"/>
      </xs:sequence>
    </xs:complexType>
    <xs:complexType name="SendAppResponse">
      <xs:sequence>
        <xs:element minOccurs="1" name="ID_returned" nillable="false"
type="xs:string"/>
        <xs:element minOccurs="1" name="parameters" nillable="false"
type="xs:string"/>
      </xs:sequence>
    </xs:complexType>
    <xs:complexType name="GetStatusRequest">
      <xs:sequence>
        <xs:element minOccurs="0" name="getStatusRequestUnused"

```

```

type="xs:int"/>
    </xs:sequence>
</xs:complexType>
<xs:complexType name="GetStatusResponse">
    <xs:sequence>
        <xs:element minOccurs="1" name="avgMPPHops_returned" type="xs:int"/>
        <xs:element minOccurs="1" name="iCCXMLEventsSent_returned"
type="xs:int"/>
        <xs:element minOccurs="1" name="iCCXMLRequestsProcessed_returned"
type="xs:int"/>
        <xs:element minOccurs="1" name="iSIPRequestsProcessed_returned"
type="xs:int"/>
        <xs:element minOccurs="1" name="iTELRequestsProcessed_returned"
type="xs:int"/>
        <xs:element minOccurs="1" name="iVXMLRequestsProcessed_returned"
type="xs:int"/>
        <xs:element minOccurs="1" name="lastRequestDateTime_returned"
nillable="false" type="xs:dateTime"/>
        <xs:element minOccurs="1" name="maxMPPHops_returned" type="xs:int"/>
        <xs:element minOccurs="1" name="minMPPHops_returned" type="xs:int"/>
        <xs:element minOccurs="1" name="serviceStartedDateTime_returned"
nillable="false" type="xs:dateTime"/>
        <xs:element minOccurs="1" name="vpmsSoftwareVersion_returned"
nillable="false" type="xs:string"/>
    </xs:sequence>
</xs:complexType>
</xs:schema>
<xs:schema attributeFormDefault="qualified" elementFormDefault="qualified"
targetNamespace="http://io.java/xsd">
    <xs:complexType name="IOException">
        <xs:sequence/>
    </xs:complexType>
</xs:schema>
<xs:schema xmlns:ax26="http://services.vp.avaya.com/xsd" xmlns:ax24="http://
rmi.java/xsd" attributeFormDefault="qualified" elementFormDefault="qualified"
targetNamespace="http://xml.avaya.com/ws/VPAppIntf/VoicePortal">
    <xs:import namespace="http://rmi.java/xsd"/>
    <xs:import namespace="http://services.vp.avaya.com/xsd"/>
    <xs:element name="VPAppIntfServiceRemoteException">
        <xs:complexType>
            <xs:sequence>
                <xs:element minOccurs="0" name="RemoteException" nillable="true"
type="ax24:RemoteException"/>
            </xs:sequence>
        </xs:complexType>
    </xs:element>
    <xs:element name="sendCCXMLEvent">
        <xs:complexType>
            <xs:sequence>
                <xs:element minOccurs="0" name="args0" nillable="true"
type="ax25:SendCCXMLEventRequest"/>
            </xs:sequence>
        </xs:complexType>
    </xs:element>
    <xs:element name="sendCCXMLEventResponse">
        <xs:complexType>
            <xs:sequence>
                <xs:element minOccurs="0" name="return" nillable="true"
type="ax25:SendCCXMLEventResponse"/>
            </xs:sequence>
        </xs:complexType>
    </xs:element>
    <xs:element name="queryResources">
        <xs:complexType>
            <xs:sequence>

```

```

        <xs:element minOccurs="0" name="args0" nillable="true"
type="ax25:QueryResourcesRequest"/>
    </xs:sequence>
</xs:complexType>
</xs:element>
<xs:element name="queryResourcesResponse">
    <xs:complexType>
        <xs:sequence>
            <xs:element minOccurs="0" name="return" nillable="true"
type="ax25:QueryResourcesResponse"/>
        </xs:sequence>
    </xs:complexType>
</xs:element>
<xs:element name="launchVXML">
    <xs:complexType>
        <xs:sequence>
            <xs:element minOccurs="0" name="args0" nillable="true"
type="ax25:LaunchVXMLRequest"/>
        </xs:sequence>
    </xs:complexType>
</xs:element>
<xs:element name="launchVXMLResponse">
    <xs:complexType>
        <xs:sequence>
            <xs:element minOccurs="0" name="return" nillable="true"
type="ax25:LaunchVXMLResponse"/>
        </xs:sequence>
    </xs:complexType>
</xs:element>
<xs:element name="launchCCXML">
    <xs:complexType>
        <xs:sequence>
            <xs:element minOccurs="0" name="args0" nillable="true"
type="ax25:LaunchCCXMLRequest"/>
        </xs:sequence>
    </xs:complexType>
</xs:element>
<xs:element name="launchCCXMLResponse">
    <xs:complexType>
        <xs:sequence>
            <xs:element minOccurs="0" name="return" nillable="true"
type="ax25:LaunchCCXMLResponse"/>
        </xs:sequence>
    </xs:complexType>
</xs:element>
<xs:element name="launchSMS">
    <xs:complexType>
        <xs:sequence>
            <xs:element minOccurs="0" name="args0" nillable="true"
type="ax25:LaunchSMSRequest"/>
        </xs:sequence>
    </xs:complexType>
</xs:element>
<xs:element name="launchSMSResponse">
    <xs:complexType>
        <xs:sequence>
            <xs:element minOccurs="0" name="return" nillable="true"
type="ax25:LaunchSMSResponse"/>
        </xs:sequence>
    </xs:complexType>
</xs:element>
<xs:element name="sendSMS">
    <xs:complexType>
        <xs:sequence>
            <xs:element minOccurs="0" name="args0" nillable="true"

```

```

type="ax25:SendSMSRequest"/>
    </xs:sequence>
  </xs:complexType>
</xs:element>
<xs:element name="sendSMSResponse">
  <xs:complexType>
    <xs:sequence>
      <xs:element minOccurs="0" name="return" nillable="true"
type="ax25:SendSMSResponse"/>
    </xs:sequence>
  </xs:complexType>
</xs:element>
<xs:element name="launchEmail">
  <xs:complexType>
    <xs:sequence>
      <xs:element minOccurs="0" name="args0" nillable="true"
type="ax25:LaunchEmailRequest"/>
    </xs:sequence>
  </xs:complexType>
</xs:element>
<xs:element name="launchEmailResponse">
  <xs:complexType>
    <xs:sequence>
      <xs:element minOccurs="0" name="return" nillable="true"
type="ax25:LaunchEmailResponse"/>
    </xs:sequence>
  </xs:complexType>
</xs:element>
<xs:element name="sendEmail">
  <xs:complexType>
    <xs:sequence>
      <xs:element minOccurs="0" name="args0" nillable="true"
type="ax25:SendEmailRequest"/>
    </xs:sequence>
  </xs:complexType>
</xs:element>
<xs:element name="sendEmailResponse">
  <xs:complexType>
    <xs:sequence>
      <xs:element minOccurs="0" name="return" nillable="true"
type="ax25:SendEmailResponse"/>
    </xs:sequence>
  </xs:complexType>
</xs:element>
<xs:element name="launchHtml">
  <xs:complexType>
    <xs:sequence>
      <xs:element minOccurs="0" name="args0" nillable="true"
type="ax25:LaunchHtmlRequest"/>
    </xs:sequence>
  </xs:complexType>
</xs:element>
<xs:element name="launchHtmlResponse">
  <xs:complexType>
    <xs:sequence>
      <xs:element minOccurs="0" name="return" nillable="true"
type="ax25:LaunchHtmlResponse"/>
    </xs:sequence>
  </xs:complexType>
</xs:element>
<xs:element name="launchApp">
  <xs:complexType>
    <xs:sequence>
      <xs:element minOccurs="0" name="args0" nillable="true"
type="ax25:LaunchAppRequest"/>

```

```

        </xs:sequence>
      </xs:complexType>
    </xs:element>
    <xs:element name="launchAppResponse">
      <xs:complexType>
        <xs:sequence>
          <xs:element minOccurs="0" name="return" nillable="true"
type="ax25:LaunchAppResponse"/>
        </xs:sequence>
      </xs:complexType>
    </xs:element>
    <xs:element name="getStatusEx">
      <xs:complexType>
        <xs:sequence>
          <xs:element minOccurs="0" name="args0" nillable="true"
type="ax25:GetStatusExRequest"/>
        </xs:sequence>
      </xs:complexType>
    </xs:element>
    <xs:element name="getStatusExResponse">
      <xs:complexType>
        <xs:sequence>
          <xs:element minOccurs="0" name="return" nillable="true"
type="ax25:GetStatusExResponse"/>
        </xs:sequence>
      </xs:complexType>
    </xs:element>
    <xs:element name="sendApp">
      <xs:complexType>
        <xs:sequence>
          <xs:element minOccurs="0" name="args0" nillable="true"
type="ax25:SendAppRequest"/>
        </xs:sequence>
      </xs:complexType>
    </xs:element>
    <xs:element name="sendAppResponse">
      <xs:complexType>
        <xs:sequence>
          <xs:element minOccurs="0" name="return" nillable="true"
type="ax25:SendAppResponse"/>
        </xs:sequence>
      </xs:complexType>
    </xs:element>
    <xs:element name="getStatus">
      <xs:complexType>
        <xs:sequence>
          <xs:element minOccurs="0" name="args0" nillable="true"
type="ax25:GetStatusRequest"/>
        </xs:sequence>
      </xs:complexType>
    </xs:element>
    <xs:element name="getStatusResponse">
      <xs:complexType>
        <xs:sequence>
          <xs:element minOccurs="0" name="return" nillable="true"
type="ax25:GetStatusResponse"/>
        </xs:sequence>
      </xs:complexType>
    </xs:element>
    <xs:element name="getConversation">
      <xs:complexType>
        <xs:sequence>
          <xs:element minOccurs="1" name="args0" nillable="false"
type="xs:string"/>
        </xs:sequence>

```

```

        </xs:complexType>
      </xs:element>
      <xs:element name="getConversationResponse">
        <xs:complexType>
          <xs:sequence>
            <xs:element minOccurs="1" name="return" nillable="false"
type="xs:string"/>
          </xs:sequence>
        </xs:complexType>
      </xs:element>
      <xs:element name="createConversation">
        <xs:complexType>
          <xs:sequence>
            <xs:element minOccurs="1" name="args0" nillable="false"
type="xs:string"/>
            <xs:element minOccurs="1" name="args1" nillable="false"
type="xs:string"/>
            <xs:element minOccurs="1" name="args2" type="xs:long"/>
          </xs:sequence>
        </xs:complexType>
      </xs:element>
      <xs:element name="deleteConversation">
        <xs:complexType>
          <xs:sequence>
            <xs:element minOccurs="1" name="args0" nillable="false"
type="xs:string"/>
          </xs:sequence>
        </xs:complexType>
      </xs:element>
      <xs:element name="updateConversation">
        <xs:complexType>
          <xs:sequence>
            <xs:element minOccurs="1" name="args0" nillable="false"
type="xs:string"/>
            <xs:element minOccurs="1" name="args1" nillable="false"
type="xs:string"/>
            <xs:element minOccurs="1" name="args2" type="xs:long"/>
          </xs:sequence>
        </xs:complexType>
      </xs:element>
      <xs:element name="getConversationByAlias">
        <xs:complexType>
          <xs:sequence>
            <xs:element minOccurs="1" name="args0" nillable="false"
type="xs:string"/>
          </xs:sequence>
        </xs:complexType>
      </xs:element>
      <xs:element name="getConversationByAliasResponse">
        <xs:complexType>
          <xs:sequence>
            <xs:element minOccurs="1" name="return" nillable="false"
type="xs:string"/>
          </xs:sequence>
        </xs:complexType>
      </xs:element>
      <xs:element name="addConversationAlias">
        <xs:complexType>
          <xs:sequence>
            <xs:element minOccurs="1" name="args0" nillable="false"
type="xs:string"/>
            <xs:element minOccurs="1" name="args1" nillable="false"
type="xs:string" maxOccurs="3"/>
          </xs:sequence>
        </xs:complexType>
      </xs:element>

```

```

        </xs:element>
    </xs:schema>
</wsdl:types>
<wsdl:message name="queryResourcesRequest">
    <wsdl:part name="parameters" element="ns:queryResources"/>
</wsdl:message>
<wsdl:message name="queryResourcesResponse">
    <wsdl:part name="parameters" element="ns:queryResourcesResponse"/>
</wsdl:message>
<wsdl:message name="VAppIntfServiceRemoteException">
    <wsdl:part name="parameters" element="ns:VAppIntfServiceRemoteException"/>
</wsdl:message>
<wsdl:message name="launchCCXMLRequest">
    <wsdl:part name="parameters" element="ns:launchCCXML"/>
</wsdl:message>
<wsdl:message name="launchCCXMLResponse">
    <wsdl:part name="parameters" element="ns:launchCCXMLResponse"/>
</wsdl:message>
<wsdl:message name="launchAppRequest">
    <wsdl:part name="parameters" element="ns:launchApp"/>
</wsdl:message>
<wsdl:message name="launchAppResponse">
    <wsdl:part name="parameters" element="ns:launchAppResponse"/>
</wsdl:message>
<wsdl:message name="launchEmailRequest">
    <wsdl:part name="parameters" element="ns:launchEmail"/>
</wsdl:message>
<wsdl:message name="launchEmailResponse">
    <wsdl:part name="parameters" element="ns:launchEmailResponse"/>
</wsdl:message>
<wsdl:message name="launchHtmlRequest">
    <wsdl:part name="parameters" element="ns:launchHtml"/>
</wsdl:message>
<wsdl:message name="launchHtmlResponse">
    <wsdl:part name="parameters" element="ns:launchHtmlResponse"/>
</wsdl:message>
<wsdl:message name="sendAppRequest">
    <wsdl:part name="parameters" element="ns:sendApp"/>
</wsdl:message>
<wsdl:message name="sendAppResponse">
    <wsdl:part name="parameters" element="ns:sendAppResponse"/>
</wsdl:message>
<wsdl:message name="sendEmailRequest">
    <wsdl:part name="parameters" element="ns:sendEmail"/>
</wsdl:message>
<wsdl:message name="sendEmailResponse">
    <wsdl:part name="parameters" element="ns:sendEmailResponse"/>
</wsdl:message>
<wsdl:message name="getStatusRequest">
    <wsdl:part name="parameters" element="ns:getStatus"/>
</wsdl:message>
<wsdl:message name="getStatusResponse">
    <wsdl:part name="parameters" element="ns:getStatusResponse"/>
</wsdl:message>
<wsdl:message name="sendCCXMLEventRequest">
    <wsdl:part name="parameters" element="ns:sendCCXMLEvent"/>
</wsdl:message>
<wsdl:message name="sendCCXMLEventResponse">
    <wsdl:part name="parameters" element="ns:sendCCXMLEventResponse"/>
</wsdl:message>
<wsdl:message name="getStatusExRequest">
    <wsdl:part name="parameters" element="ns:getStatusEx"/>
</wsdl:message>
<wsdl:message name="getStatusExResponse">
    <wsdl:part name="parameters" element="ns:getStatusExResponse"/>

```

```

</wsdl:message>
<wsdl:message name="launchSMSRequest">
  <wsdl:part name="parameters" element="ns:launchSMS"/>
</wsdl:message>
<wsdl:message name="launchSMSResponse">
  <wsdl:part name="parameters" element="ns:launchSMSResponse"/>
</wsdl:message>
<wsdl:message name="launchVXMLRequest">
  <wsdl:part name="parameters" element="ns:launchVXML"/>
</wsdl:message>
<wsdl:message name="launchVXMLResponse">
  <wsdl:part name="parameters" element="ns:launchVXMLResponse"/>
</wsdl:message>
<wsdl:message name="sendSMSRequest">
  <wsdl:part name="parameters" element="ns:sendSMS"/>
</wsdl:message>
<wsdl:message name="sendSMSResponse">
  <wsdl:part name="parameters" element="ns:sendSMSResponse"/>
</wsdl:message>
<wsdl:message name="getConversationResponse">
  <wsdl:part name="parameters" element="ns:getConversationResponse"/>
</wsdl:message>
<wsdl:message name="createConversationRequest">
  <wsdl:part name="parameters" element="ns:createConversation"/>
</wsdl:message>
<wsdl:message name="getConversationRequest">
  <wsdl:part name="parameters" element="ns:getConversation"/>
</wsdl:message>
<wsdl:message name="deleteConversationRequest">
  <wsdl:part name="parameters" element="ns:deleteConversation"/>
</wsdl:message>
<wsdl:message name="updateConversationRequest">
  <wsdl:part name="parameters" element="ns:updateConversation"/>
</wsdl:message>
<wsdl:message name="getConversationByAliasRequest">
  <wsdl:part name="parameters" element="ns:getConversationByAlias"/>
</wsdl:message>
<wsdl:message name="getConversationByAliasResponse">
  <wsdl:part name="parameters" element="ns:getConversationByAliasResponse"/>
</wsdl:message>
<wsdl:message name="addConversationAliasRequest">
  <wsdl:part name="parameters" element="ns:addConversationAlias"/>
</wsdl:message>
<wsdl:portType name="VPAppIntfServicePortType">
  <wsdl:operation name="queryResources">
    <wsdl:input message="ns:queryResourcesRequest"
wsaw:Action="urn:queryResources"/>
    <wsdl:output message="ns:queryResourcesResponse"
wsaw:Action="urn:queryResourcesResponse"/>
    <wsdl:fault message="ns:VPAppIntfServiceRemoteException"
name="VPAppIntfServiceRemoteException"
wsaw:Action="urn:queryResourcesVPAppIntfServiceRemoteException"/>
  </wsdl:operation>
  <wsdl:operation name="launchCCXML">
    <wsdl:input message="ns:launchCCXMLRequest" wsaw:Action="urn:launchCCXML"/>
    <wsdl:output message="ns:launchCCXMLResponse"
wsaw:Action="urn:launchCCXMLResponse"/>
    <wsdl:fault message="ns:VPAppIntfServiceRemoteException"
name="VPAppIntfServiceRemoteException"
wsaw:Action="urn:launchCCXMLVPAppIntfServiceRemoteException"/>
  </wsdl:operation>
  <wsdl:operation name="launchApp">
    <wsdl:input message="ns:launchAppRequest" wsaw:Action="urn:launchApp"/>
    <wsdl:output message="ns:launchAppResponse"
wsaw:Action="urn:launchAppResponse"/>
  </wsdl:operation>

```



```

        <wsdl:fault message="ns:VAppIntfServiceRemoteException"
name="VAppIntfServiceRemoteException"
wsaw:Action="urn:launchAppVAppIntfServiceRemoteException"/>
    </wsdl:operation>
    <wsdl:operation name="launchEmail">
        <wsdl:input message="ns:launchEmailRequest" wsaw:Action="urn:launchEmail"/>
        <wsdl:output message="ns:launchEmailResponse"
wsaw:Action="urn:launchEmailResponse"/>
        <wsdl:fault message="ns:VAppIntfServiceRemoteException"
name="VAppIntfServiceRemoteException"
wsaw:Action="urn:launchEmailVAppIntfServiceRemoteException"/>
    </wsdl:operation>
    <wsdl:operation name="launchHtml">
        <wsdl:input message="ns:launchHtmlRequest" wsaw:Action="urn:launchHtml"/>
        <wsdl:output message="ns:launchHtmlResponse"
wsaw:Action="urn:launchHtmlResponse"/>
        <wsdl:fault message="ns:VAppIntfServiceRemoteException"
name="VAppIntfServiceRemoteException"
wsaw:Action="urn:launchHtmlVAppIntfServiceRemoteException"/>
    </wsdl:operation>
    <wsdl:operation name="sendApp">
        <wsdl:input message="ns:sendAppRequest" wsaw:Action="urn:sendApp"/>
        <wsdl:output message="ns:sendAppResponse" wsaw:Action="urn:sendAppResponse"/>
        <wsdl:fault message="ns:VAppIntfServiceRemoteException"
name="VAppIntfServiceRemoteException"
wsaw:Action="urn:sendAppVAppIntfServiceRemoteException"/>
    </wsdl:operation>
    <wsdl:operation name="sendEmail">
        <wsdl:input message="ns:sendEmailRequest" wsaw:Action="urn:sendEmail"/>
        <wsdl:output message="ns:sendEmailResponse"
wsaw:Action="urn:sendEmailResponse"/>
        <wsdl:fault message="ns:VAppIntfServiceRemoteException"
name="VAppIntfServiceRemoteException"
wsaw:Action="urn:sendEmailVAppIntfServiceRemoteException"/>
    </wsdl:operation>
    <wsdl:operation name="getStatus">
        <wsdl:input message="ns:getStatusRequest" wsaw:Action="urn:getStatus"/>
        <wsdl:output message="ns:getStatusResponse"
wsaw:Action="urn:getStatusResponse"/>
        <wsdl:fault message="ns:VAppIntfServiceRemoteException"
name="VAppIntfServiceRemoteException"
wsaw:Action="urn:getStatusVAppIntfServiceRemoteException"/>
    </wsdl:operation>
    <wsdl:operation name="sendCCXMLEvent">
        <wsdl:input message="ns:sendCCXMLEventRequest"
wsaw:Action="urn:sendCCXMLEvent"/>
        <wsdl:output message="ns:sendCCXMLEventResponse"
wsaw:Action="urn:sendCCXMLEventResponse"/>
        <wsdl:fault message="ns:VAppIntfServiceRemoteException"
name="VAppIntfServiceRemoteException"
wsaw:Action="urn:sendCCXMLEventVAppIntfServiceRemoteException"/>
    </wsdl:operation>
    <wsdl:operation name="getStatusEx">
        <wsdl:input message="ns:getStatusExRequest" wsaw:Action="urn:getStatusEx"/>
        <wsdl:output message="ns:getStatusExResponse"
wsaw:Action="urn:getStatusExResponse"/>
        <wsdl:fault message="ns:VAppIntfServiceRemoteException"
name="VAppIntfServiceRemoteException"
wsaw:Action="urn:getStatusExVAppIntfServiceRemoteException"/>
    </wsdl:operation>
    <wsdl:operation name="launchSMS">
        <wsdl:input message="ns:launchSMSRequest" wsaw:Action="urn:launchSMS"/>
        <wsdl:output message="ns:launchSMSResponse"
wsaw:Action="urn:launchSMSResponse"/>
        <wsdl:fault message="ns:VAppIntfServiceRemoteException"

```

```

name="VAppIntfServiceRemoteException"
wsaw:Action="urn:launchSMSVAppIntfServiceRemoteException"/>
  </wsdl:operation>
  <wsdl:operation name="launchVXML">
    <wsdl:input message="ns:launchVXMLRequest" wsaw:Action="urn:launchVXML"/>
    <wsdl:output message="ns:launchVXMLResponse"
wsaw:Action="urn:launchVXMLResponse"/>
    <wsdl:fault message="ns:VAppIntfServiceRemoteException"
name="VAppIntfServiceRemoteException"
wsaw:Action="urn:launchVXMLVAppIntfServiceRemoteException"/>
  </wsdl:operation>
  <wsdl:operation name="sendSMS">
    <wsdl:input message="ns:sendSMSRequest" wsaw:Action="urn:sendSMS"/>
    <wsdl:output message="ns:sendSMSResponse" wsaw:Action="urn:sendSMSResponse"/>
    <wsdl:fault message="ns:VAppIntfServiceRemoteException"
name="VAppIntfServiceRemoteException"
wsaw:Action="urn:sendSMSVAppIntfServiceRemoteException"/>
  </wsdl:operation>
  <wsdl:operation name="deleteConversation">
    <wsdl:input message="ns:deleteConversationRequest"
wsaw:Action="urn:deleteConversation"/>
    <wsdl:output message="ns:null" wsaw:Action="urn:deleteConversationResponse"/>
    <wsdl:fault message="ns:VAppIntfServiceRemoteException"
name="VAppIntfServiceRemoteException"
wsaw:Action="urn:deleteConversationVAppIntfServiceRemoteException"/>
  </wsdl:operation>
  <wsdl:operation name="getConversation">
    <wsdl:input message="ns:getConversationRequest"
wsaw:Action="urn:getConversation"/>
    <wsdl:output message="ns:getConversationResponse"
wsaw:Action="urn:getConversationResponse"/>
    <wsdl:fault message="ns:VAppIntfServiceRemoteException"
name="VAppIntfServiceRemoteException"
wsaw:Action="urn:getConversationVAppIntfServiceRemoteException"/>
  </wsdl:operation>
  <wsdl:operation name="updateConversation">
    <wsdl:input message="ns:updateConversationRequest"
wsaw:Action="urn:updateConversation"/>
    <wsdl:output message="ns:null" wsaw:Action="urn:updateConversationResponse"/>
    <wsdl:fault message="ns:VAppIntfServiceRemoteException"
name="VAppIntfServiceRemoteException"
wsaw:Action="urn:updateConversationVAppIntfServiceRemoteException"/>
  </wsdl:operation>
  <wsdl:operation name="createConversation">
    <wsdl:input message="ns:createConversationRequest"
wsaw:Action="urn:createConversation"/>
    <wsdl:output message="ns:null" wsaw:Action="urn:createConversationResponse"/>
    <wsdl:fault message="ns:VAppIntfServiceRemoteException"
name="VAppIntfServiceRemoteException"
wsaw:Action="urn:createConversationVAppIntfServiceRemoteException"/>
  </wsdl:operation>
  <wsdl:operation name="getConversationByAlias">
    <wsdl:input message="ns:getConversationByAliasRequest"
wsaw:Action="urn:getConversationByAlias"/>
    <wsdl:output message="ns:getConversationByAliasResponse"
wsaw:Action="urn:getConversationByAliasResponse"/>
    <wsdl:fault message="ns:VAppIntfServiceRemoteException"
name="VAppIntfServiceRemoteException"
wsaw:Action="urn:getConversationByAliasVAppIntfServiceRemoteException"/>
  </wsdl:operation>
  <wsdl:operation name="addConversationAlias">
    <wsdl:input message="ns:addConversationAliasRequest"
wsaw:Action="urn:addConversationAlias"/>
    <wsdl:output message="ns:null"
wsaw:Action="urn:addConversationAliasResponse"/>

```

```

        <wsdl:fault message="ns:VPAppIntfServiceRemoteException"
name="VPAppIntfServiceRemoteException"
wsaw:Action="urn:addConversationAliasVPAppIntfServiceRemoteException"/>
    </wsdl:operation>
</wsdl:portType>
<wsdl:binding name="VPAppIntfServiceSoap11Binding" type="ns:VPAppIntfServicePortType">
    <soap:binding transport="http://schemas.xmlsoap.org/soap/http" style="document"/>
    <wsdl:operation name="queryResources">
        <soap:operation soapAction="urn:queryResources" style="document"/>
        <wsdl:input>
            <soap:body use="literal"/>
        </wsdl:input>
        <wsdl:output>
            <soap:body use="literal"/>
        </wsdl:output>
        <wsdl:fault name="VPAppIntfServiceRemoteException">
            <soap:fault use="literal" name="VPAppIntfServiceRemoteException"/>
        </wsdl:fault>
    </wsdl:operation>
    <wsdl:operation name="launchCCXML">
        <soap:operation soapAction="urn:launchCCXML" style="document"/>
        <wsdl:input>
            <soap:body use="literal"/>
        </wsdl:input>
        <wsdl:output>
            <soap:body use="literal"/>
        </wsdl:output>
        <wsdl:fault name="VPAppIntfServiceRemoteException">
            <soap:fault use="literal" name="VPAppIntfServiceRemoteException"/>
        </wsdl:fault>
    </wsdl:operation>
    <wsdl:operation name="launchApp">
        <soap:operation soapAction="urn:launchApp" style="document"/>
        <wsdl:input>
            <soap:body use="literal"/>
        </wsdl:input>
        <wsdl:output>
            <soap:body use="literal"/>
        </wsdl:output>
        <wsdl:fault name="VPAppIntfServiceRemoteException">
            <soap:fault use="literal" name="VPAppIntfServiceRemoteException"/>
        </wsdl:fault>
    </wsdl:operation>
    <wsdl:operation name="launchEmail">
        <soap:operation soapAction="urn:launchEmail" style="document"/>
        <wsdl:input>
            <soap:body use="literal"/>
        </wsdl:input>
        <wsdl:output>
            <soap:body use="literal"/>
        </wsdl:output>
        <wsdl:fault name="VPAppIntfServiceRemoteException">
            <soap:fault use="literal" name="VPAppIntfServiceRemoteException"/>
        </wsdl:fault>
    </wsdl:operation>
    <wsdl:operation name="launchHtml">
        <soap:operation soapAction="urn:launchHtml" style="document"/>
        <wsdl:input>
            <soap:body use="literal"/>
        </wsdl:input>
        <wsdl:output>
            <soap:body use="literal"/>
        </wsdl:output>
        <wsdl:fault name="VPAppIntfServiceRemoteException">
            <soap:fault use="literal" name="VPAppIntfServiceRemoteException"/>
        </wsdl:fault>
    </wsdl:operation>

```

```

        </wsdl:fault>
    </wsdl:operation>
    <wsdl:operation name="sendEmail">
        <soap:operation soapAction="urn:sendEmail" style="document"/>
        <wsdl:input>
            <soap:body use="literal"/>
        </wsdl:input>
        <wsdl:output>
            <soap:body use="literal"/>
        </wsdl:output>
        <wsdl:fault name="VPAppIntfServiceRemoteException">
            <soap:fault use="literal" name="VPAppIntfServiceRemoteException"/>
        </wsdl:fault>
    </wsdl:operation>
    <wsdl:operation name="sendApp">
        <soap:operation soapAction="urn:sendApp" style="document"/>
        <wsdl:input>
            <soap:body use="literal"/>
        </wsdl:input>
        <wsdl:output>
            <soap:body use="literal"/>
        </wsdl:output>
        <wsdl:fault name="VPAppIntfServiceRemoteException">
            <soap:fault use="literal" name="VPAppIntfServiceRemoteException"/>
        </wsdl:fault>
    </wsdl:operation>
    <wsdl:operation name="getStatus">
        <soap:operation soapAction="urn:getStatus" style="document"/>
        <wsdl:input>
            <soap:body use="literal"/>
        </wsdl:input>
        <wsdl:output>
            <soap:body use="literal"/>
        </wsdl:output>
        <wsdl:fault name="VPAppIntfServiceRemoteException">
            <soap:fault use="literal" name="VPAppIntfServiceRemoteException"/>
        </wsdl:fault>
    </wsdl:operation>
    <wsdl:operation name="sendCCXMLEvent">
        <soap:operation soapAction="urn:sendCCXMLEvent" style="document"/>
        <wsdl:input>
            <soap:body use="literal"/>
        </wsdl:input>
        <wsdl:output>
            <soap:body use="literal"/>
        </wsdl:output>
        <wsdl:fault name="VPAppIntfServiceRemoteException">
            <soap:fault use="literal" name="VPAppIntfServiceRemoteException"/>
        </wsdl:fault>
    </wsdl:operation>
    <wsdl:operation name="getStatusEx">
        <soap:operation soapAction="urn:getStatusEx" style="document"/>
        <wsdl:input>
            <soap:body use="literal"/>
        </wsdl:input>
        <wsdl:output>
            <soap:body use="literal"/>
        </wsdl:output>
        <wsdl:fault name="VPAppIntfServiceRemoteException">
            <soap:fault use="literal" name="VPAppIntfServiceRemoteException"/>
        </wsdl:fault>
    </wsdl:operation>
    <wsdl:operation name="launchSMS">
        <soap:operation soapAction="urn:launchSMS" style="document"/>
        <wsdl:input>

```

```

        <soap:body use="literal"/>
    </wsdl:input>
    <wsdl:output>
        <soap:body use="literal"/>
    </wsdl:output>
    <wsdl:fault name="VPAppIntfServiceRemoteException">
        <soap:fault use="literal" name="VPAppIntfServiceRemoteException"/>
    </wsdl:fault>
</wsdl:operation>
<wsdl:operation name="launchVXML">
    <soap:operation soapAction="urn:launchVXML" style="document"/>
    <wsdl:input>
        <soap:body use="literal"/>
    </wsdl:input>
    <wsdl:output>
        <soap:body use="literal"/>
    </wsdl:output>
    <wsdl:fault name="VPAppIntfServiceRemoteException">
        <soap:fault use="literal" name="VPAppIntfServiceRemoteException"/>
    </wsdl:fault>
</wsdl:operation>
<wsdl:operation name="sendSMS">
    <soap:operation soapAction="urn:sendSMS" style="document"/>
    <wsdl:input>
        <soap:body use="literal"/>
    </wsdl:input>
    <wsdl:output>
        <soap:body use="literal"/>
    </wsdl:output>
    <wsdl:fault name="VPAppIntfServiceRemoteException">
        <soap:fault use="literal" name="VPAppIntfServiceRemoteException"/>
    </wsdl:fault>
</wsdl:operation>
<wsdl:operation name="deleteConversation">
    <soap:operation soapAction="urn:deleteConversation" style="document"/>
    <wsdl:input>
        <soap:body use="literal"/>
    </wsdl:input>
    <wsdl:output>
        <soap:body use="literal"/>
    </wsdl:output>
    <wsdl:fault name="VPAppIntfServiceRemoteException">
        <soap:fault use="literal" name="VPAppIntfServiceRemoteException"/>
    </wsdl:fault>
</wsdl:operation>
<wsdl:operation name="getConversation">
    <soap:operation soapAction="urn:getConversation" style="document"/>
    <wsdl:input>
        <soap:body use="literal"/>
    </wsdl:input>
    <wsdl:output>
        <soap:body use="literal"/>
    </wsdl:output>
    <wsdl:fault name="VPAppIntfServiceRemoteException">
        <soap:fault use="literal" name="VPAppIntfServiceRemoteException"/>
    </wsdl:fault>
</wsdl:operation>
<wsdl:operation name="updateConversation">
    <soap:operation soapAction="urn:updateConversation" style="document"/>
    <wsdl:input>
        <soap:body use="literal"/>
    </wsdl:input>
    <wsdl:output>
        <soap:body use="literal"/>
    </wsdl:output>

```

```

        <wsdl:fault name="VPAppIntfServiceRemoteException">
            <soap:fault use="literal" name="VPAppIntfServiceRemoteException"/>
        </wsdl:fault>
    </wsdl:operation>
    <wsdl:operation name="createConversation">
        <soap:operation soapAction="urn:createConversation" style="document"/>
        <wsdl:input>
            <soap:body use="literal"/>
        </wsdl:input>
        <wsdl:output>
            <soap:body use="literal"/>
        </wsdl:output>
        <wsdl:fault name="VPAppIntfServiceRemoteException">
            <soap:fault use="literal" name="VPAppIntfServiceRemoteException"/>
        </wsdl:fault>
    </wsdl:operation>
    <wsdl:operation name="getConversationByAlias">
        <soap:operation soapAction="urn:getConversationByAlias" style="document"/>
        <wsdl:input>
            <soap:body use="literal"/>
        </wsdl:input>
        <wsdl:output>
            <soap:body use="literal"/>
        </wsdl:output>
        <wsdl:fault name="VPAppIntfServiceRemoteException">
            <soap:fault use="literal" name="VPAppIntfServiceRemoteException"/>
        </wsdl:fault>
    </wsdl:operation>
    <wsdl:operation name="addConversationAlias">
        <soap:operation soapAction="urn:addConversationAlias" style="document"/>
        <wsdl:input>
            <soap:body use="literal"/>
        </wsdl:input>
        <wsdl:output>
            <soap:body use="literal"/>
        </wsdl:output>
        <wsdl:fault name="VPAppIntfServiceRemoteException">
            <soap:fault use="literal" name="VPAppIntfServiceRemoteException"/>
        </wsdl:fault>
    </wsdl:operation>
</wsdl:binding>
<wsdl:binding name="VPAppIntfServiceSoap12Binding" type="ns:VPAppIntfServicePortType">
    <soap12:binding transport="http://schemas.xmlsoap.org/soap/http"
style="document"/>
    <wsdl:operation name="queryResources">
        <soap12:operation soapAction="urn:queryResources" style="document"/>
        <wsdl:input>
            <soap12:body use="literal"/>
        </wsdl:input>
        <wsdl:output>
            <soap12:body use="literal"/>
        </wsdl:output>
        <wsdl:fault name="VPAppIntfServiceRemoteException">
            <soap12:fault use="literal" name="VPAppIntfServiceRemoteException"/>
        </wsdl:fault>
    </wsdl:operation>
    <wsdl:operation name="launchCCXML">
        <soap12:operation soapAction="urn:launchCCXML" style="document"/>
        <wsdl:input>
            <soap12:body use="literal"/>
        </wsdl:input>
        <wsdl:output>
            <soap12:body use="literal"/>
        </wsdl:output>
        <wsdl:fault name="VPAppIntfServiceRemoteException">

```

```

        <soap12:fault use="literal" name="VPAppIntfServiceRemoteException"/>
    </wsdl:fault>
</wsdl:operation>
<wsdl:operation name="launchApp">
    <soap12:operation soapAction="urn:launchApp" style="document"/>
    <wsdl:input>
        <soap12:body use="literal"/>
    </wsdl:input>
    <wsdl:output>
        <soap12:body use="literal"/>
    </wsdl:output>
    <wsdl:fault name="VPAppIntfServiceRemoteException">
        <soap12:fault use="literal" name="VPAppIntfServiceRemoteException"/>
    </wsdl:fault>
</wsdl:operation>
<wsdl:operation name="launchEmail">
    <soap12:operation soapAction="urn:launchEmail" style="document"/>
    <wsdl:input>
        <soap12:body use="literal"/>
    </wsdl:input>
    <wsdl:output>
        <soap12:body use="literal"/>
    </wsdl:output>
    <wsdl:fault name="VPAppIntfServiceRemoteException">
        <soap12:fault use="literal" name="VPAppIntfServiceRemoteException"/>
    </wsdl:fault>
</wsdl:operation>
<wsdl:operation name="launchHtml">
    <soap12:operation soapAction="urn:launchHtml" style="document"/>
    <wsdl:input>
        <soap12:body use="literal"/>
    </wsdl:input>
    <wsdl:output>
        <soap12:body use="literal"/>
    </wsdl:output>
    <wsdl:fault name="VPAppIntfServiceRemoteException">
        <soap12:fault use="literal" name="VPAppIntfServiceRemoteException"/>
    </wsdl:fault>
</wsdl:operation>
<wsdl:operation name="sendEmail">
    <soap12:operation soapAction="urn:sendEmail" style="document"/>
    <wsdl:input>
        <soap12:body use="literal"/>
    </wsdl:input>
    <wsdl:output>
        <soap12:body use="literal"/>
    </wsdl:output>
    <wsdl:fault name="VPAppIntfServiceRemoteException">
        <soap12:fault use="literal" name="VPAppIntfServiceRemoteException"/>
    </wsdl:fault>
</wsdl:operation>
<wsdl:operation name="sendApp">
    <soap12:operation soapAction="urn:sendApp" style="document"/>
    <wsdl:input>
        <soap12:body use="literal"/>
    </wsdl:input>
    <wsdl:output>
        <soap12:body use="literal"/>
    </wsdl:output>
    <wsdl:fault name="VPAppIntfServiceRemoteException">
        <soap12:fault use="literal" name="VPAppIntfServiceRemoteException"/>
    </wsdl:fault>
</wsdl:operation>
<wsdl:operation name="getStatus">
    <soap12:operation soapAction="urn:getStatus" style="document"/>

```



```

    <wsdl:input>
      <soap12:body use="literal"/>
    </wsdl:input>
    <wsdl:output>
      <soap12:body use="literal"/>
    </wsdl:output>
    <wsdl:fault name="VPAppIntfServiceRemoteException">
      <soap12:fault use="literal" name="VPAppIntfServiceRemoteException"/>
    </wsdl:fault>
  </wsdl:operation>
  <wsdl:operation name="sendCCXMLEvent">
    <soap12:operation soapAction="urn:sendCCXMLEvent" style="document"/>
    <wsdl:input>
      <soap12:body use="literal"/>
    </wsdl:input>
    <wsdl:output>
      <soap12:body use="literal"/>
    </wsdl:output>
    <wsdl:fault name="VPAppIntfServiceRemoteException">
      <soap12:fault use="literal" name="VPAppIntfServiceRemoteException"/>
    </wsdl:fault>
  </wsdl:operation>
  <wsdl:operation name="getStatusEx">
    <soap12:operation soapAction="urn:getStatusEx" style="document"/>
    <wsdl:input>
      <soap12:body use="literal"/>
    </wsdl:input>
    <wsdl:output>
      <soap12:body use="literal"/>
    </wsdl:output>
    <wsdl:fault name="VPAppIntfServiceRemoteException">
      <soap12:fault use="literal" name="VPAppIntfServiceRemoteException"/>
    </wsdl:fault>
  </wsdl:operation>
  <wsdl:operation name="launchSMS">
    <soap12:operation soapAction="urn:launchSMS" style="document"/>
    <wsdl:input>
      <soap12:body use="literal"/>
    </wsdl:input>
    <wsdl:output>
      <soap12:body use="literal"/>
    </wsdl:output>
    <wsdl:fault name="VPAppIntfServiceRemoteException">
      <soap12:fault use="literal" name="VPAppIntfServiceRemoteException"/>
    </wsdl:fault>
  </wsdl:operation>
  <wsdl:operation name="launchVXML">
    <soap12:operation soapAction="urn:launchVXML" style="document"/>
    <wsdl:input>
      <soap12:body use="literal"/>
    </wsdl:input>
    <wsdl:output>
      <soap12:body use="literal"/>
    </wsdl:output>
    <wsdl:fault name="VPAppIntfServiceRemoteException">
      <soap12:fault use="literal" name="VPAppIntfServiceRemoteException"/>
    </wsdl:fault>
  </wsdl:operation>
  <wsdl:operation name="sendSMS">
    <soap12:operation soapAction="urn:sendSMS" style="document"/>
    <wsdl:input>
      <soap12:body use="literal"/>
    </wsdl:input>
    <wsdl:output>
      <soap12:body use="literal"/>
    </wsdl:output>
  </wsdl:operation>

```



```

        </wsdl:output>
        <wsdl:fault name="VPAppIntfServiceRemoteException">
            <soap12:fault use="literal" name="VPAppIntfServiceRemoteException"/>
        </wsdl:fault>
    </wsdl:operation>
    <wsdl:operation name="deleteConversation">
        <soap12:operation soapAction="urn:deleteConversation" style="document"/>
        <wsdl:input>
            <soap12:body use="literal"/>
        </wsdl:input>
        <wsdl:output>
            <soap12:body use="literal"/>
        </wsdl:output>
        <wsdl:fault name="VPAppIntfServiceRemoteException">
            <soap12:fault use="literal" name="VPAppIntfServiceRemoteException"/>
        </wsdl:fault>
    </wsdl:operation>
    <wsdl:operation name="getConversation">
        <soap12:operation soapAction="urn:getConversation" style="document"/>
        <wsdl:input>
            <soap12:body use="literal"/>
        </wsdl:input>
        <wsdl:output>
            <soap12:body use="literal"/>
        </wsdl:output>
        <wsdl:fault name="VPAppIntfServiceRemoteException">
            <soap12:fault use="literal" name="VPAppIntfServiceRemoteException"/>
        </wsdl:fault>
    </wsdl:operation>
    <wsdl:operation name="updateConversation">
        <soap12:operation soapAction="urn:updateConversation" style="document"/>
        <wsdl:input>
            <soap12:body use="literal"/>
        </wsdl:input>
        <wsdl:output>
            <soap12:body use="literal"/>
        </wsdl:output>
        <wsdl:fault name="VPAppIntfServiceRemoteException">
            <soap12:fault use="literal" name="VPAppIntfServiceRemoteException"/>
        </wsdl:fault>
    </wsdl:operation>
    <wsdl:operation name="createConversation">
        <soap12:operation soapAction="urn:createConversation" style="document"/>
        <wsdl:input>
            <soap12:body use="literal"/>
        </wsdl:input>
        <wsdl:output>
            <soap12:body use="literal"/>
        </wsdl:output>
        <wsdl:fault name="VPAppIntfServiceRemoteException">
            <soap12:fault use="literal" name="VPAppIntfServiceRemoteException"/>
        </wsdl:fault>
    </wsdl:operation>
    <wsdl:operation name="getConversationByAlias">
        <soap12:operation soapAction="urn:getConversationByAlias" style="document"/>
        <wsdl:input>
            <soap12:body use="literal"/>
        </wsdl:input>
        <wsdl:output>
            <soap12:body use="literal"/>
        </wsdl:output>
        <wsdl:fault name="VPAppIntfServiceRemoteException">
            <soap12:fault use="literal" name="VPAppIntfServiceRemoteException"/>
        </wsdl:fault>
    </wsdl:operation>

```

```

    <wsdl:operation name="addConversationAlias">
      <soap12:operation soapAction="urn:addConversationAlias" style="document"/>
      <wsdl:input>
        <soap12:body use="literal"/>
      </wsdl:input>
      <wsdl:output>
        <soap12:body use="literal"/>
      </wsdl:output>
      <wsdl:fault name="VPAppIntfServiceRemoteException">
        <soap12:fault use="literal" name="VPAppIntfServiceRemoteException"/>
      </wsdl:fault>
    </wsdl:operation>
  </wsdl:binding>
  <wsdl:binding name="VPAppIntfServiceHttpBinding" type="ns:VPAppIntfServicePortType">
    <http:binding verb="POST"/>
    <wsdl:operation name="queryResources">
      <http:operation location="queryResources"/>
      <wsdl:input>
        <mime:content type="application/xml" part="parameters"/>
      </wsdl:input>
      <wsdl:output>
        <mime:content type="application/xml" part="parameters"/>
      </wsdl:output>
    </wsdl:operation>
    <wsdl:operation name="launchCCXML">
      <http:operation location="launchCCXML"/>
      <wsdl:input>
        <mime:content type="application/xml" part="parameters"/>
      </wsdl:input>
      <wsdl:output>
        <mime:content type="application/xml" part="parameters"/>
      </wsdl:output>
    </wsdl:operation>
    <wsdl:operation name="launchApp">
      <http:operation location="launchApp"/>
      <wsdl:input>
        <mime:content type="application/xml" part="parameters"/>
      </wsdl:input>
      <wsdl:output>
        <mime:content type="application/xml" part="parameters"/>
      </wsdl:output>
    </wsdl:operation>
    <wsdl:operation name="launchEmail">
      <http:operation location="launchEmail"/>
      <wsdl:input>
        <mime:content type="application/xml" part="parameters"/>
      </wsdl:input>
      <wsdl:output>
        <mime:content type="application/xml" part="parameters"/>
      </wsdl:output>
    </wsdl:operation>
    <wsdl:operation name="launchHtml">
      <http:operation location="launchHtml"/>
      <wsdl:input>
        <mime:content type="application/xml" part="parameters"/>
      </wsdl:input>
      <wsdl:output>
        <mime:content type="application/xml" part="parameters"/>
      </wsdl:output>
    </wsdl:operation>
    <wsdl:operation name="sendEmail">
      <http:operation location="sendEmail"/>
      <wsdl:input>
        <mime:content type="application/xml" part="parameters"/>
      </wsdl:input>
    </wsdl:operation>
  </wsdl:binding>

```

```

        <wsdl:output>
            <mime:content type="application/xml" part="parameters"/>
        </wsdl:output>
    </wsdl:operation>
    <wsdl:operation name="sendApp">
        <http:operation location="sendApp"/>
        <wsdl:input>
            <mime:content type="application/xml" part="parameters"/>
        </wsdl:input>
        <wsdl:output>
            <mime:content type="application/xml" part="parameters"/>
        </wsdl:output>
    </wsdl:operation>
    <wsdl:operation name="getStatus">
        <http:operation location="getStatus"/>
        <wsdl:input>
            <mime:content type="application/xml" part="parameters"/>
        </wsdl:input>
        <wsdl:output>
            <mime:content type="application/xml" part="parameters"/>
        </wsdl:output>
    </wsdl:operation>
    <wsdl:operation name="sendCCXMLEvent">
        <http:operation location="sendCCXMLEvent"/>
        <wsdl:input>
            <mime:content type="application/xml" part="parameters"/>
        </wsdl:input>
        <wsdl:output>
            <mime:content type="application/xml" part="parameters"/>
        </wsdl:output>
    </wsdl:operation>
    <wsdl:operation name="getStatusEx">
        <http:operation location="getStatusEx"/>
        <wsdl:input>
            <mime:content type="application/xml" part="parameters"/>
        </wsdl:input>
        <wsdl:output>
            <mime:content type="application/xml" part="parameters"/>
        </wsdl:output>
    </wsdl:operation>
    <wsdl:operation name="launchSMS">
        <http:operation location="launchSMS"/>
        <wsdl:input>
            <mime:content type="application/xml" part="parameters"/>
        </wsdl:input>
        <wsdl:output>
            <mime:content type="application/xml" part="parameters"/>
        </wsdl:output>
    </wsdl:operation>
    <wsdl:operation name="launchVXML">
        <http:operation location="launchVXML"/>
        <wsdl:input>
            <mime:content type="application/xml" part="parameters"/>
        </wsdl:input>
        <wsdl:output>
            <mime:content type="application/xml" part="parameters"/>
        </wsdl:output>
    </wsdl:operation>
    <wsdl:operation name="sendSMS">
        <http:operation location="sendSMS"/>
        <wsdl:input>
            <mime:content type="application/xml" part="parameters"/>
        </wsdl:input>
        <wsdl:output>
            <mime:content type="application/xml" part="parameters"/>
        </wsdl:output>
    </wsdl:operation>

```

```

        </wsdl:output>
    </wsdl:operation>
    <wsdl:operation name="deleteConversation">
        <http:operation location="deleteConversation"/>
        <wsdl:input>
            <mime:content type="application/xml" part="parameters"/>
        </wsdl:input>
        <wsdl:output>
            <mime:content type="application/xml" part="parameters"/>
        </wsdl:output>
    </wsdl:operation>
    <wsdl:operation name="getConversation">
        <http:operation location="getConversation"/>
        <wsdl:input>
            <mime:content type="application/xml" part="parameters"/>
        </wsdl:input>
        <wsdl:output>
            <mime:content type="application/xml" part="parameters"/>
        </wsdl:output>
    </wsdl:operation>
    <wsdl:operation name="updateConversation">
        <http:operation location="updateConversation"/>
        <wsdl:input>
            <mime:content type="application/xml" part="parameters"/>
        </wsdl:input>
        <wsdl:output>
            <mime:content type="application/xml" part="parameters"/>
        </wsdl:output>
    </wsdl:operation>
    <wsdl:operation name="createConversation">
        <http:operation location="createConversation"/>
        <wsdl:input>
            <mime:content type="application/xml" part="parameters"/>
        </wsdl:input>
        <wsdl:output>
            <mime:content type="application/xml" part="parameters"/>
        </wsdl:output>
    </wsdl:operation>
    <wsdl:operation name="getConversationByAlias">
        <http:operation location="getConversationByAlias"/>
        <wsdl:input>
            <mime:content type="application/xml" part="parameters"/>
        </wsdl:input>
        <wsdl:output>
            <mime:content type="application/xml" part="parameters"/>
        </wsdl:output>
    </wsdl:operation>
    <wsdl:operation name="addConversationAlias">
        <http:operation location="addConversationAlias"/>
        <wsdl:input>
            <mime:content type="application/xml" part="parameters"/>
        </wsdl:input>
        <wsdl:output>
            <mime:content type="application/xml" part="parameters"/>
        </wsdl:output>
    </wsdl:operation>
</wsdl:binding>
<wsdl:service name="VPAppIntfService">
    <wsdl:port name="VPAppIntfServiceHttpSoap11Endpoint"
binding="ns:VPAppIntfServiceSoap11Binding">
        <soap:address location="http://localhost:8080/axis2/services/
VPAppIntfService"/>
    </wsdl:port>
    <wsdl:port name="VPAppIntfServiceHttpSoap12Endpoint"
binding="ns:VPAppIntfServiceSoap12Binding">

```

```
        <soap12:address location="http://localhost:8080/axis2/services/  
VPAppIntfService"/>  
    </wsdl:port>  
    <wsdl:port name="VPAppIntfServiceHttpEndpoint"  
binding="ns:VPAppIntfServiceHttpBinding">  
        <http:address location="http://localhost:8080/axis2/services/  
VPAppIntfService"/>  
    </wsdl:port>  
    </wsdl:service>  
</wsdl:definitions>
```

Chapter 25: Managing external messages

External messages overview

Experience Portal supports sending and receiving events from the CCXML application synchronously or asynchronously within a voice application as specified in the VXML 3.0 specification. When an external message arrives, it reflects in the application.

VoiceXML 3.0 interpreters receive events from external sources. In particular, VoiceXML 3.0 receives the life cycle events specified as part of the Multimodal Architecture and Interfaces (MMI) specification. These life cycle events allow the flow component of the Data Flow Presentation architecture to control the presentation layer by starting and stopping the processing of markup. By handling these events, the VoiceXML interpreter acts as a modality component in the multimodal architecture, while the flow component acts as an Interaction manager. As a result, you can extend VoiceXML 3.0 into multimodal applications.

External message are reflected in the application in the *application.lastmessage\$* variable.

Note:

Experience Portal cannot send or receive any other source, except the CCXML application, for processing the external event in the VXML browser.

The variable is an ECMAScript object with the following properties:

application.lastmessage\$ properties	
contenttype	The media type of the external message. Vb currently support "string" only.
event	The event name, if any, or ECMAScript undefined if no event name was included in the external message.
content	The content of the message, if any, or ECMAScript undefined. The interpreter throws "error.badfetch" in one of the following scenarios: • An interpreter receives an external message with a payload in a data format that it does not understand. * The payload is not well formed as defined by the specification of that format. • The payload is not well formed as defined by the specification of that format.

If no external messages have been received, *application.lastmessage\$* is ECMAScript undefined. Only the last received message is available.

Since external messages can arrive at any time, they can be disruptive to a voice application. A voice application developer decides whether these messages are delivered to the application synchronously or asynchronously using the *externalevents.enable* property.

You can set the property to one of the following values:

externalevents.enable values	
true	External messages are delivered asynchronously as VoiceXML events.
false	External messages are delivered synchronously. This is the default.

Receiving an external message asynchronously

To receive an external message asynchronously, an application defines an "externalmessage" event handler. If the payload of an external message includes an event name, the name is appended to the name of the event that is thrown to the application separated by a dot, or example, "externalmessage.ready". This allows applications to handle external messages using different event handlers.

Asynchronous external messages are processed in the same manner that a disconnect event is handled in VXML2.

Events are dispatched to the application serially. Because the interpreter only reflects the data associated with a single external message at a time, the application handles the data associated with each external message after that message is delivered. If multiple events arrive, VB deals with them one at a time, until all events are processed, or when execution goes to an element where `externalevents.enable` turns to false, whichever happens first.

The following example demonstrates asynchronous receipt of an external message. The catch handler copies the reflected external message into an array at the application level.

```
<vxml version="2.1"
  xmlns="http://www.w3.org/2001/vxml">
  <property name="externalevents.enable" value="true"/>
  <var name="myMessages" expr="new Array()"/>

  <catch event="externalmessage">
    <var name="lm" expr="application.lastmessage$"/>
    <if cond="typeof lm.content == 'string'"/>
      <log>received <value expr="lm.content"/></log>
    <else/>
      <log>received unknown external message type
        <value expr="typeof lm.content"/>
      </log>
    </if>
    <script>
      myMessages.push({'content' : lm.content, 'ctype' : lm.contenttype});
    </script>
  </catch>

  <form>
  <field name="num" type="digits">
    <prompt>pick a number any number</prompt>
    <catch event="noinput nomatch">
      sorry. didn't get that.
      <reprompt/>
    </catch>
    <filled>
      you said <value expr="num"/>
      <clear/>
    </filled>
  </field>
  </form>
```

```

</field>
</form>
</vxml>

```

Receiving external message synchronously

When external message is delivered synchronously, an application developer decides whether the message is preserved or discarded by setting the `externalevents.queue` property. The property can be set to one of the following values:

externalevents.queue values	
true	External messages are queued and set to <i>application.lastmessage\$</i> .
false	An external message that is not delivered as a VoiceXML event is discarded. This is the default value.

To receive an external message synchronously, set the `externalevents.enable` property to false and the `externalevents.queue` property to true, and use the `<receive>` element to pull messages off the queue. The `<receive>` element blocks until an external message is received or the timeout specified by the `maxtime` attribute is exceeded.

The `<receive>` element supports the following attributes:

The <receive> properties			
Name	Description	Required	Default
fetchaudio	See Section 6.1 of [VXML2]. This the defaults value to the fetchaudio property described in Section 6.3.5 of [VXML2].	No	N/A
fetchaudioexpr	An ECMAScript expression evaluating to the fetchaudio URI. If evaluation of the expression fails, the interpreter displays "error.semantic".	No	N/A
maxtime	A W3C time specifier indicating the maximum amount of time the interpreter waits to receive an external message. If the timeout is exceeded, the interpreter throws "error.badfetch." A value of "none" indicates the interpreter the blocks indefinitely.	No	0s
maxtimeexpr	An ECMAScript expression evaluating to the maxtime value. If evaluation of the expression fails, the interpreter throws "error.semantic".	No	0s

You can specify any one of `fetchaudio` and `fetchaudioexpr`. Otherwise, the system returns the `error.badfetch` error message.

You can specify any one of `maxtime` and `maxtimeexpr`. Otherwise, the system returns the `error.badfetch` error message.

When present, the attributes `fetchaudioexpr` and `maxtimeexpr` are evaluated when the `<receive>` command is executed.

The following example demonstrates synchronously received external message. In this example, the interpreter blocks for up to 15 seconds waiting for an external message to arrive. If no external message is received during that interval, the interpreter returns the `error.badfetch` error message. If a message is received, the interpreter proceeds by executing the `<log>` element.

```
<vxml version="2.1"
  xmlns="http://www.w3.org/2001/vxml">

  <property name="externalevents.queue" value="true"/>
  <form>
    <catch event="error.badfetch">
      <log>timed out waiting for external message</log>
    </catch>

    <block>
      Hold on ...
      <receive maxtime="15s"
        fetchaudio="http://www.example.com/audio/fetching.wav"/>
      <log>got <value expr="application.lastmessage$.content"/></log>
    </block>
  </form>
</vxml>
```

Sending messages from a voice application

To send a message from a VoiceXML application to a remote endpoint, use the `<send>` element.

The `<send>` element supports the following attributes:

The <code><send></code> attributes			
Name	Description	Required	Default
async	A boolean indicating whether to block what? until the final response to the transaction created by sending the external event is received, or a timeout.	No	true
asynceval	An ECMAScript expression evaluating the value of the async attribute. If evaluation of the expression fails, the interpreter displays "error.semantic".	No	N/A
body	A string representing the data to be sent in the body of the message.	No	N/A
bodyexpr	An ECMAScript expression evaluating the body of the message to be sent. If evaluation of the expression fails, the interpreter displays "error.semantic".	No	N/A
contenttype	A string indicating the media type of the body being sent, if any. The set of content types might be limited by the underlying platform. If	No	text/plain

Table continues...

The <send> attributes			
Name	Description	Required	Default
	an unsupported media type is specified, the interpreter displays "error.badfetch.<protocol>.400." The interpreter is not required to inspect the data specified in the body to validate that it conforms to the specified media type.		
contenttypeexpr	An ECMAScript expression evaluating the media type of the body. If evaluation of the expression fails, the interpreter displays "error.semantic".	No	N/A
event	The name of the event to send. The value is a string which only includes alphanumeric characters and the "." (dot) character. The first character must be a letter. If the value is invalid, then an "error.badfetch" event is displayed.	No	N/A
eventexpr	An ECMAScript expression evaluating the name of the event to be sent. If evaluation of the expression fails, the interpreter displays "error.semantic".	No	N/A
fetchaudio	See Section 6.1 of [VXML2]. This is a default value to the fetchaudio property described in Section 6.3.5 of [VXML2].	No	N/A
fetchaudioexpr	An ECMAScript expression evaluating the fetchaudio URI. If evaluation of the expression fails, the interpreter displays "error.semantic".	No	N/A
namelist	A list of zero or more whitespace-separated variable names to send. By default, no variables are submitted. Values for these variables are evaluated when the <send> element is executed. Only declared variables can be referenced. Otherwise, "error.semantic" is displayed. Variables must be submitted to the server with the same qualification used in the namelist. When an ECMAScript variable is submitted to the server, its value must be converted first into a string before being sent. If the variable is an ECMAScript object, the mechanism by which it is submitted is platform specific. Instead of submitting an ECMAScript object directly, the application developer can explicitly submit the individual properties of	No	N/A

Table continues...

The <send> attributes			
Name	Description	Required	Default
	the object. For example, "date.month date.year".		
target	The attribute that specifies the URI to which the event is sent. If the attribute is not specified, the event is sent to the component which started the VoiceXML session.	No	Invoking component
targetexpr	An ECMAScript expression evaluating the target URI. If evaluation of the expression fails, the interpreter displays "error.semantic".	No	N/A
timeout	See 6.13.2.1 sendtimeout . This defaults to the sendtimeout property.	No	N/A
timeoutexpr	An ECMAScript expression evaluating the timeout interval for a synchronous <send>. If evaluation of the expression fails, the interpreter displays "error.semantic"	No	N/A

You can specify any of the following items. Otherwise, the system returns the `error.badfetch` error message:

- `async` or `asyncexpr`
- `event` or `eventexpr`
- `contenttype` or `contenttypeexpr`
- `fetchaudio` or `fetchaudioexpr`
- `target` or `targetexpr`
- `timeout` or `timeoutexpr`

Additionally, only one of the following attributes must be specified. Otherwise the system returns the `error.badfetch` error message:

`body`, `bodyexpr`, or `namelist`.

For synchronous <send>, if time-out occurs, the interpreter returns the `error.badfetch` error message. If the interpreter encounters an error upon sending the external message, the system returns the `error.badfetch.<protocol>.<status_code>` output.

The following example demonstrates the use of <send> synchronously:

```
<vxml version="2.1"
  xmlns="http://www.w3.org/2001/vxml">

  <form>
    <field name="user_id" type="digits">
      <prompt>please type your five digit i d</prompt>
      <filled>
        <send async="false"
          bodyexpr="'<userinfo><id>' + user_id + '</id></userinfo>'"
          contenttype="text/xml" timeout="5s"/>
        <goto next="mainmenu.vxml"/>
      </filled>
    </field>
  </form>
</vxml>
```

```
</filled>
</field>
</form>
</vxml>
```

Upon executing an asynchronous `<send>`, the interpreter continues execution of the voice application immediately and disregards the disposition of the message that was sent.

The following example demonstrates the use of `<send>` asynchronously:

```
<vxml version="2.1"
  xmlns="http://www.w3.org/2001/vxml">

  <form>
    <var name="tasktarget" expr="'http://www.example.com/taskman.pl'"/>
    <var name="taskname" expr="'cc'"/>
    <var name="taskstate"/>
    <block>
      <assign name="taskstate" expr="'start'"/>
      <send async="true"
        targetexpr="tasktarget"
        namelist="taskname taskstate"/>
    </block>
    <field name="ccnum"/>
    <field name="expdate"/>
    <block>
      <assign name="taskstate" expr="'end'"/>
      <send async="true"
        targetexpr="tasktarget"
        namelist="taskname taskstate"/>
    </block>
  </form>
</vxml>
```

Chapter 26: The Management Interface web service

Overview

Administrators can use the Management Interface web service on the Primary EPM to configure and manage the Experience Portal system. This web service supports the following functionality:

Zones

- Retrieve zone names: For retrieving the names of the configured zones.
- Get zone information: For retrieving the information of an existing zone.

Applications

- Retrieve application names: For retrieving the names of the configured applications.
- Add application: For configuring a new application.
- Delete application: For deleting an existing application.
- Get application information: For retrieving the parameters of an existing application.
- Set application information: For updating the parameters of an existing application.

Configurable Application Variables

- Retrieve configurable application variables: For retrieving the CAVs of an existing application.
- Set configurable application variables: For updating the CAVs of an existing application.

Authentication and Authorization

The Management Interface web service is accessible by an authenticated user. An EPM user name and password is required to be able to invoke any of the web service methods.

The authorization is based on the role and features assigned to the EPM user invoking the web service. In order to be able to invoke a specific web service method, the EPM user account used must have permission to perform the same operation on the web page. As an example, if an EPM user has a role which allows addition of an application over the web page, the user will be able to add an application through the web service. Similarly if an EPM user has a role which does not allow deletion of an application over the web page, the user will not be able to delete the application through the web service as well.

Management web services WSDL

The WSDL of the Management web services is available on the Primary EPM. The URL for the Management Interface web service WSDL is:

```
https://<EPM-server>/axis2/services/VPManagementService?wsdl
```

<EPM-server> is the domain name or IP address of the system where the primary EPM software is installed.

The Management Interface web service conforms to all W3C standards and can be accessed through any web service client using the Avaya-provided Web Services Description Language (WSDL) file.


Best Practices

When using the Management Interface web service, keep in mind that:

- The Management Interface web service is only available on the Primary EPM and only accessible over HTTPS. The web service clients need to accept the SSL certificate from the Primary EPM server.
- The Management Interface web service uses Basic Authentication to authenticate web service client requests. When you submit a request to the web service, you need to include the user name and password that is configured as one of the Experience Portal users and that user must have the role with the appropriate feature enabled. As an example, if the user wants to add an application, then the role must have the feature for adding an application enabled. Similarly, if the user wants to delete an application, then the role must have the feature for deleting an application enabled. If the user wants to update an application, then the role must have the feature for updating an application enabled.
- If non-ASCII characters are sent in the URL request to the web service they should be encoded as UTF-8 prior to sending the request. For example, an application name of 'año' is encoded and sent as 'a%C3%B1a'. Note that the non-ASCII character 'ñ' is sent as the UTF-8 value of '%C3%B1'.
- If zones have been configured on the system, the zone name should be specified. If the zone name is not specified, then the web service operation will be performed against the default zone.
- Field names are case sensitive.

Management Interface web service flow diagram

The following diagram shows how an external application interacts with the Management Interface web service and how the Management Interface web service interacts with the rest of the Experience Portal system.



Configuring Management Interface web service

Procedure

1. Log in to the EPM web interface using an account with the User Manager role.
2. From the EPM main menu, select **User Management > Users**.
3. Click the user name that will be used when sending requests to the web service.
4. On the Change User page, select the roles that have the appropriate features checked to enable the user to use web service methods.

For example, if the user wants to invoke the *addApplicationInfo* web service method to add an application, then the role must have the *addApplication* feature enabled. Similarly, if the user wants to invoke the *deleteApplicationInfo* web service to delete an application, then the role must have the *deleteApplication* feature enabled and if the user wants to invoke the *setApplicationInfo* web service to update an application, then the role must have the *changeApplication* feature enabled.

5. Click **Save**.
6. Open the following page in a web browser:
`https://<EPM-server>/axis2/services/VPManagementService?wsdl`
 <EPM-server> is the domain name or IP address of the system where the primary EPM software is installed.
7. When prompted, enter the user name and password for Experience Portal with the web services role checked.
8. Save the WSDL file and use it to build the web service client that accesses the Application Interface web service (axis 2.0). This web service conforms to all current W3C standards.

Management Interface web service method objects

The Management Interface web service methods use the following objects as parameters or as return values:

- Field
- FieldArray
- Status

Field

This object contains the field name, field type, and field value.

Object members	Notes
name	Name of the field. This entry is case sensitive.
dataType	Data type of the field. The supported data types are: • String • Integer • Boolean • Floatingpoint • Date • Time • Datetime • Password • File

Table continues...

Object members	Notes
	• List • Combo
value	Value of the field.

Field array

This object contains an array of fields. When retrieving the application information, each application parameter is returned as an array of fields where each field contains information for each parameter.

The use of the *Field* and *FieldArray* objects provides compatibility to the web services when new parameters are introduced in future. It also allows the web services to be backward compatible if and when existing parameters need to be dropped or changed.

Status

This object contains information about the status of the method invocation.

Object members	Notes
String statusCode	Success or Error
String statusMessage	Empty if the statusCode is Success Error message if the statusCode is Error

Management Interface web service methods

The Management Interface web service includes the following methods:

- [getZoneNames method](#) on page 600
- [getZoneInfo method](#) on page 600
- [getApplicationNames method](#) on page 600
- [getApplicationInfo method](#) on page 601
- [setApplicationInfo method](#) on page 601
- [addApplicationInfo method](#) on page 602
- [deleteApplicationInfo method](#) on page 602
- [getAppConfigurableVars method](#) on page 603
- [setAppConfigurableVars method](#) on page 603

getZoneNames method

This topic describes the method for retrieving the names of the configured zones.

```
FieldArray getZoneNames()
```

Parameter

None

Data returned

Return Type	Notes
FieldArray	Arrays of fields where each field has the name of the zone.

getZoneInfo method

This section describes the method for retrieving the information of an existing zone.

```
FieldArray getZoneInfo(String name)
```

Parameters

Parameters	Notes	Required?
String name	Name of the zone	Y

Data returned

Return Type	Notes
FieldArray	Array of fields where each field contains the details of the zone.

getApplicationNames method

This section describes the method for retrieving the names of the configured applications.

```
FieldArray getApplicationNames(String zoneName)
```

Parameters

Parameters	Notes	Required?
String zoneName	Name of the zone configured on the system. If the zone name is not specified, then the names of the applications configured in the default zone are returned.	N

Data returned

Return Type	Notes
FieldArray	Arrays of fields where each field has the name of the application.

getApplicationInfo method

This section describes the method for retrieving the parameters of an existing application.

```
FieldArray getApplicationInfo(String name, String zoneName)
```

Parameters

Parameters	Notes	Required?
String name	Name of the application in the format application name for global applications or organization name/application name for organization applications.	Y
String zoneName	Name of the zone from which the application information is retrieved. If the zone name is not specified, then the information retrieved for the application configured in the default zone.	N

Data returned

Return Type	Notes
FieldArray	Array of fields where each field contains the details of the application field.

setApplicationInfo method

This section describes the method for updating the parameters of an existing application.

```
Status setApplicationInfo(String name, FieldArray fieldArray, String zoneName)
```

Parameters

Parameters	Notes	Required?
String name	Name of the application in the format application name for global applications or organization name/application name for organization applications.	Y
FieldArray fieldArray	Array of fields where each field contains the details of the application field.	Y
String zoneName	Name of the zone in which the application is updated. If the zone name is not specified, then the application is updated in default zone.	N

Data returned

Return Type	Notes
Status	Status of the method invocation.

addApplicationInfo method

This section describes the method for configuring a new application.

```
Status addApplicationInfo(String name, FieldArray fieldArray, String zoneName)
```

Parameters

Parameters	Notes	Required?
String name	Name of the application in the format application name for global applications or organization name/application name for organization applications.	Y
FieldArray fieldArray	Array of fields where each field contains the details of the application field.	Y
String zoneName	Name of the zone to which the application is added. If the zone name is not specified, then the application is added to the default zone.	N

Data returned

Return Type	Notes
Status	Status of the method invocation.

deleteApplicationInfo method

This section describes the method for deleting an existing application.

```
void deleteApplicationInfo(String name, String zoneName)
```

Parameters

Parameters	Notes	Required?
String name	Name of the application in the format application name for global applications or organization name/application name for organization applications.	Y
String zoneName	Name of the zone from which the application is deleted. If the zone name is not specified, then the application is deleted from the default zone.	N

Data returned

None

Execution of the web service method without any exception implies that the deletion was successful.

getAppConfigurableVars method

This section describes the method for retrieving the configurable application variables of an existing application.

```
FieldArray getAppConfigurableVars(String name, String zoneName)
```

Parameters

Parameters	Notes	Required?
String name	Name of the application in the format application name for global applications or organization name/application name for organization applications.	Y
String zoneName	Name of the zone from which the application information is retrieved. If the zone name is not specified, then the information retrieved for the application configured in the default zone.	N

Data returned

Return Type	Notes
FieldArray	Array of fields where each field contains the details of the configurable application variable of the application.

setAppConfigurableVars method

This section describes the method for updating the configurable application variables of an existing application.

```
Status setAppConfigurableVars(String name, FieldArray fieldArray, String zoneName)
```

Parameters

Parameters	Notes	Required?
String name	Name of the application in the format application name for global applications or organization name/application name for organization applications.	Y
FieldArray fieldArray	Array of fields where each field contains the details of the configurable application variable of the application.	Y
String zoneName	Name of the zone in which the application is updated. If the zone name is not specified, then the application is updated in default zone.	N

Data returned

Return Type	Notes
Status	Status of the method invocation.

*** Note:**

To update the configurable application variable file using the web service method, you must first upload the file to the server using the FileUpload servlet interface and then use the web service method to update the variable. The value specified for the file variable is the name of the file uploaded using the FileUpload servlet interface.

Exception codes

The Management Interface web service methods throw *RemoteException* error codes for various error conditions and validation failures. The following table lists the exception error codes.

Value	Attributes	Condition
401	Unauthorized	Invalid user name and password.
1005	Required field	Required field is missing.
1010	Not in range	Specified value is not in the acceptable range.
1016	Duplicate name	Duplicate name is specified.
1018	Invalid parameter	Invalid parameter name specified.
1025	Invalid file	Invalid file name specified when updating configurable application variable of type file.
1026	Invalid file contents	File with invalid contents or an empty file was specified.
7001	Resource not found	Invalid application name specified.
7014	Invalid ASR	Invalid ASR name specified.
7015	Invalid TTS	Invalid TTS name specified.
7017	Missing language	No ASR with the specified language is available.
7018	Missing voice	No TTS with the specified voice is available.
7019	Invalid language format	Invalid language format, for example: English(USA) EN-US
7020	Invalid voice format	Invalid voice format, for example: English(USA) EN-US Andrew Male
7022	Invalid DNIS	Invalid DNIS format specified.
7024	URI Expression error	Called URI expression error.
7026	Invalid Prosody	Invalid prosody value specified.
7027	Invalid minimum	Value specified is below the minimum acceptable value.
7028	Invalid DTMF	Invalid DTMF value specified.
7029	Invalid TTS data	Invalid TTS data specified.
7030	Invalid ASR data	Invalid ASR data specified.
7032	Invalid VoiceXML handler	Invalid VoiceXML handler name specified.
7033	Invalid CCXML handler	Invalid CCXML handler name specified.

Table continues...

Value	Attributes	Condition
7034	ASR language required	ASR language must be specified.
7035	TTS voice required	TTS voice must be specified.
7038	Only one default	Only one default application can be configured.
7041	Invalid video screen format	Invalid video screen format specified.
7043	Invalid URL	Invalid URL specified
7044	Invalid prompt data	Invalid prompt data specified.
7045	URL username and or password missing	URL username and password must be specified.
7058	Pattern required	Pattern must be specified for the launch parameters.
7072	Enable Remote DTMF is not allowed.	If ASR is not configured, <i>Support Remote DTMF Processing</i> in Advanced group must be set to No.
7073	Algorithm required	Email Additional Launch Parameters: Algorithm is input required. <Email Additional Launch Parameters entry number>
7074	Launch parameters required	Launch parameters must be specified.
7075	Component required.	Email Additional Launch Parameters: Component is input required. <Email Additional Launch Parameters entry number>
7076	Algorithm not supports Component	Email Additional Launch Parameters: The Algorithm does not support the selected Component. <Email Additional Launch Parameters entry number>
7077	Notification URL required	Notification URL must be specified.
7078	Access not allowed	Access is not allowed. Please check the assigned roles.
7079	Notification URL2 required	Notification URL2 must be specified.
7080	Invalid zone name	Invalid zone name specified.
7081	Organization not in zone	Organization does not exist in the specified zone.
7082	Mime type change is not allowed	Changing of <MIME type> MimeType is not allowed.
7083	Extension and ExtensionAppType are required	Extension and ExtensionAppType are required.
7084	Invalid DNIS range	Stations need to be of same length.

FileUpload Servlet Interface

The FileUpload Servlet Interface provides the ability to upload a file to the server. This interface uses the FileUpload method.

You can call the interface from any application that is running on the same network as the EPM server.

FileUpload Servlet Interface URL

The URL for uploading file is:

`https://<EPM server>/axis2/FileUpload/AppVariable`

<EPM server> is the domain name or IP address of the system where the primary EPM software is installed.

FileUpload method

This section provides the details for uploading a file that can be used for setting the configurable application variable of type file. When you need to update the configurable application variable file from the Configurable Application Variables (CAV) web page, you must browse and select a file that is uploaded to the server and then the CAV is updated. To update the configurable application variable file from the web service, you need to first upload the file to the server using the FileUpload Servlet Interface and then use the web service method to update the file variable.

The FileUpload Servlet accepts a file that is uploaded using the HTTP Post method in which the content type is set to multi-part/form data and the file contents are uploaded as multi-part request entity. This interface saves the uploaded file on the server. Then you can use the `setAppConfigurableVars` method to update the file variable of an application. The name of the file uploaded is the name that you must provide when invoking the `setAppConfigurableVars` method for setting the file variable.

Status returned

This method returns HTTP status code for the invocation of the file upload URL. When the URL is invoked successfully, the method returns the standard HTTP status code 200.

Data returned

Apart from checking the HTTP status code, the client must also check the response string returned by the URL.

Response String	Notes
success	Implies the file upload was successful.
failure, error message	Implies the file upload was not successful. The failure text followed by the error message (delimited by a comma).

Management Interface web service client

A Management Interface web service client (`VPManagementClient`) is located in the `Support/WebServices/VPManagementClient` folder on the Experience Portal installation DVD or in the

\$AVAYA_HOME/Support/WebServices/VPManagementClient folder on the Primary EPM. You can use this client for invoking any of the web services including uploading of the files.

The command `./VPManagementClient.sh` from this folder displays the information on how to use the client and the various web service methods supported. The command `VPManagementClient.sh -help` also includes examples for the various web service methods. The help also provides information on how to pass parameters when updating an application.

Management Interface web service client examples

This section provides some examples of how to invoke the `VPManagementClient.sh` script in the `Support/WebServices/VPManagementClient` folder. The following section provides a list of the examples, with the purposes, commands, and a description of the variables used in the commands.

Purpose and Command

Enter the following command to:

- Retrieve the application names for the default zone:

```
./VPManagementClient.sh <epm address> <username> <password> true
getApplicationNames
```

- Retrieve the application names for a specific zone:

```
./VPManagementClient.sh <epm address> <username> <password> true
getApplicationNames <zone name>
```

- Retrieve the application information for a specific application in the default zone:

```
./VPManagementClient.sh <epm address> <username> <password> true
getApplicationInfo <appname>
```

- Update the Launch Parameters of a VoiceXML application in the default zone:

```
./VPManagementClient.sh <epm address> <username> <password> true
setApplicationInfo <appname>
Name=DnisRanges[0].Range,,Type=String,,Value='1022-1033'
```

- Update the multiple parameters of an application in a specific zone:

```
./VPManagementClient.sh <epm address> <username> <password> true
setApplicationInfo <appname> Name=Url,,Type=String,,Value=http://
myappserver/myapp/Start\;
\;Name=DnisRanges[0].Range,,Type=String,,Value='1022-1033'\;
\;Name=DnisRanges[1].Range,,Type=String,,Value='1044-1055' <zonenumber>
```

- Retrieve the configurable application variables for a specific application in the default zone:

```
./VPManagementClient.sh <epm address> <username> <password> true
getAppConfigurableVars <appname>
```

- Update the configurable application variable of type String for a specific application in the default zone:

```
./VPManagementClient.sh <epm address> <username> <password> true  
setAppConfigurableVars <appname>  
Name=<cavname>,,Type=String,,Value=newValue
```

- Upload a file that can be used for updating configurable application variable of type file:

```
./VPManagementClient.sh <epm address> <username> <password> true  
fileUpload AppVariable <filename with full path>
```

- Update the configurable application variable of type file for a specific application in a specific zone:

```
./VPManagementClient.sh <epm address> <username> <password> true  
setAppConfigurableVars <appname>  
Name=<cavname>,,Type=File,,Value=<filename> <zonename>
```

Variables

- **<epm address>**: The EPM host name or EPM IP address
- **<username>**: The EPM user name
- **<password>**: The password for the specified user name
- **<zone name>**: The name of the zone of the application, or the name of the zone for which the application names are to be retrieved.
- **<appname>**: The name of the application.
- **<cavname>**: The name of the configurable application variable.
- **<filename with full path>**: The filename with the fully qualified path.
- **<filename>**: The name of the file uploaded to the system.

Chapter 27: Resources

Documentation

The following table lists the documents related to Experience Portal. Download the documents from the Avaya Support website at <http://www.avaya.com/support>:

Title	Description	Audience
<i>Avaya Aura® Experience Portal Documentation Roadmap</i>	Lists all the documents related to Experience Portal and describes the organization of content across the documents.	Implementation engineers Avaya Professional Services
<i>Avaya Aura® Experience Portal Overview and Specification</i>	Describes tested product characteristics and capabilities, including product overview and feature descriptions, interoperability, performance specifications, security, and licensing requirements.	Implementation engineers
<i>Implementing Avaya Aura® Experience Portal on multiple servers</i>	Provides procedures to install and configure Avaya Aura® Experience Portal software on two or more dedicated servers.	Implementation engineers
<i>Implementing Avaya Aura® Experience Portal on a single server</i>	Provides procedures to install and configure the Avaya Aura® Experience Portal software on a single server.	Implementation engineers
<i>Upgrading to Avaya Aura® Experience Portal 7.1</i>	Describes how to upgrade your Avaya Aura® Experience Portal 6.0 or 7.0 to Experience Portal 7.1.	Implementation engineers
<i>Deploying Avaya Aura® Experience Portal in an Avaya Customer Experience Virtualized Environment</i>	Provides procedures for deploying the Experience Portal virtual application in the Avaya Customer Experience Virtualized Environment. Also describes the process to upgrade an OVA-based system.	Implementation engineers

Table continues...

Title	Description	Audience
	This document includes installation, configuration, initial administration, troubleshooting, and basic maintenance checklists and procedures.	
<i>Troubleshooting Avaya Aura® Experience Portal</i>	Provides general information about troubleshooting and resolving system problems. This document also provides detailed information and procedures for finding and resolving specific problems.	Implementation engineers
<i>Avaya Aura® Experience Portal Security White Paper</i>	Provides information about the security strategy for Experience Portal 7.1 and provides suggestions that companies can use to improve the security of their Experience Portal systems and applications.	Implementation engineers Avaya Professional Services
<i>Avaya Aura® Experience Portal 7.1 Mobile Web Best Practices White Paper</i>	Provides recommended strategies for deploying Avaya Aura® Orchestration Designer Mobile Web applications with Avaya Aura® Experience Portal 7.1, detailing configuration for security, scalability and high availability.	Implementation engineers Avaya Professional Services

Related links

[Finding documents on the Avaya Support website](#) on page 610

Finding documents on the Avaya Support website

About this task

Use this procedure to find product documentation on the Avaya Support website.

Procedure

1. Use a browser to navigate to the Avaya Support website at <http://support.avaya.com/>.
2. At the top of the screen, enter your username and password and click **Login**.
3. Put your cursor over **Support by Product**.
4. Click **Documents**.
5. In the **Enter your Product Here** search box, type the product name and then select the product from the drop-down list.

6. If there is more than one release, select the appropriate release number from the **Choose Release** drop-down list.
7. Use the **Content Type** filter on the left to select the type of document you are looking for, or click **Select All** to see a list of all available documents.

For example, if you are looking for user guides, select **User Guides** in the **Content Type** filter. Only documents in the selected category will appear in the list of documents.
8. Click **Enter**.

Related links

[Documentation](#) on page 609

Training

The following courses are available on the Avaya Learning website at <http://www.avaya-learning.com>. After logging in to the website, enter the course code or the course title in the **Search** field and press **Enter** or click > to search for the course.

Course code	Course title
5C00020E	Knowledge Access: Avaya Aura Experience Portal Administration

Viewing Avaya Mentor videos

Avaya Mentor videos provide technical content on how to install, configure, and troubleshoot Avaya products.

About this task

Videos are available on the Avaya Support website, listed under the video document type, and on the Avaya-run channel on YouTube.

Procedure

- To find videos on the Avaya Support website, go to <http://support.avaya.com> and perform one of the following actions:
 - In **Search**, type `Avaya Mentor Videos` to see a list of the available videos.
 - In **Search**, type the product name. On the Search Results page, select **Video** in the **Content Type** column on the left.
- To find the Avaya Mentor videos on YouTube, go to www.youtube.com/AvayaMentor and perform one of the following actions:
 - Enter a key word or key words in the **Search Channel** to search for a specific product or topic.

- Scroll down Playlists, and click the name of a topic to see the available list of videos posted on the website.

 Note:

Videos are not available for all products.

Support

Go to the Avaya Support website at <http://support.avaya.com> for the most up-to-date documentation, product notices, and knowledge articles. You can also search for release notes, downloads, and resolutions to issues. Use the online service request system to create a service request. Chat with live agents to get answers to questions, or request an agent to connect you to a support team if an issue requires additional expertise.

Index

A

about		
MPPs	251	
access for users	18	
accounts for users	18	
Acknowledged event and alarm status	435	
addapplicationinfo	602	
Add ASR Server page	383	
Add H.323 Connection page	56	
Add ICR to EPM	421	
adding	36	
applications	149 , 158 , 320	
ASR servers	380	
EPM user accounts	23	
event handlers and prompts	363	
H.323 connections	54	
maintenance stations	55	
MPPs	258	
SIP connections	63	
SNMP traps	238	
TTS servers	394	
Add managed application to EPM	416 , 417	
Add MPP Server pages	283	
Add New Roles		
Roles page	35	
Add New Roles page	35	
Add SIP Connection pages	67	
Add SNMP Trap Configuration page	244	
Add TTS Server page	401	
Add User page	27	
Administration user role	18	
Advanced reporting	479	
AF ID, viewing	236	
afview command	236	
agents for SNMP	237	
configuring	238	
Alarm/Log Options page	463	
Alarm History window	464	
Alarm Manager page	440	
Alarm Report page	445	
alarms		
Alarm History window	464	
Alarm Manager page	440	
categories	433	
changing status of	439 , 440	
high water setting	436	
low water setting	436	
overview	432	
reports		
creating	438	
resource thresholds	436	
retention periods	437	
severities	435	
statuses	435	
viewing specific alarm details	439	
allocations, license allocations	44	
Apache Tomcat, deploying applications on	319	
application activity reports	471	
Application Detail	472	
Application Summary	472	
custom	482 , 493 , 496	
application certificate	377	
Application Detail report		
adding applications to	522	
creating	472	
Application Interface web service	534	
best practices	535	
call classification	350 , 551	
CCXML session properties	544 , 553	
configuring	536	
GetStatusEx method	538	
GetStatus method	537	
LaunchCCXML method	540	
LaunchEmail method	545	
LaunchHTML method	548	
LaunchSMS method	546	
LaunchVXML method	549	
methods for	537	
process flow diagram	535	
QueryResources method	555	
returning status of LaunchCCXML method	543	
sample WSDL file	562	
SendCCXMLEvent method	555	
SendEmail method	556	
SendSMS method	557	
Application Logging web service	522 , 529	
best practices	522	
configuring	524	
logFailed method	525	
methods for	525	
process flow diagram	523	
reportBatch method	526	
reportBatch method for call flow data	528	
sample WSDL file	531	
applications		
activity reports for	471	
adding	149 , 158 , 320	
adding event handlers	363	
associating custom dictionary		
using Experience Portal	397	
associating custom dictionary with		
using lexicon tag	398	
call classification for	346	
call classification results	347	
CCXML applications and MPP grace period	329	

deploying (<i>continued</i>)	
changing	149, 158, 321
changing priority of	322
default event handlers	364
deleting	149, 159, 321
deploying	
Apache Tomcat	319
IBM WebSphere	319
design guidelines	325-328
inbound call classification	348
launching voice applications	534
logging messages	522
outbound call classification	349
overview	317
priority of	322
privacy feature in VoiceXML	330
sound design guidelines	325
specifying inbound default	323
UCID in UUI data	353
UUI data format	352
UUI-related parameters	354
viewing	321
viewing Log tag messages	323
viewing transcription data	324, 476
Application Server	
overview	413
Application Server pages	413
application servers	
Apache Tomcat	319
IBM WebSphere	319
secure connection to	377
Application Summary report	
adding applications to	522
creating	472
AS Manager	413
ASR servers	378
Add ASR Server page	383
adding	380
ASR tab	381
Change ASR Server page	387
changing	380
deleting	381
overview	379
viewing	379
asynchronous	589
Audit Log	
Audit Log Report page	468
Audit Log Viewer page	466
creating	465
Audit Log Report page	468
Audit Log Viewer page	466
Auditor user role	18
authentication, authorization	595
Automated Speech Recognition	378
Auto Restart MPP page	289
auxiliary EPM	
changing	184
changing settings	182
configuring	182
EPM Settings page	230
reconnecting with primary	184
Avaya Aura Experience Portal	
call flow example	317
change servers	187
configure as SNMP agent	238
database	
changing hostname in	199, 200, 202, 205
database restoration	217
licenses	39
moving to new server	190
sharing a database among multiple systems	222
System Monitor Summary tab	314, 425
Avaya Aura Experience Portal logs	
packing MPP server	191, 192
Avaya Aura Experience Portal Management System	18
Avaya Service accounts	
viewing AF ID	236
Avaya Services	
change LDN entries	234
maintaining server IP addresses	233
map file for LDN entries	233
remote MPP login	235
view MPPmap file	234
Avaya Services Security Gateway (SSG)	237
Avaya Voice Browser	365
AVB	
options	365
VoiceXML events	366
B	
backing up	210
backup server, setting up	
Linux	208
Windows	209
backup utility	
configuring	218
best practices	596
bridge transfers in mixed SIP/H.323 environment	80
Browser	
Browser Settings page	367
Browser Settings page	367
C	
cache	376
cache control	372
call classification	
for inbound calls	348
for outbound calls	349
overview	346
results	347
categories for alarms and events	433
ccxml elements and attributes	331

CCXML Log tag	323	ASR servers	380
certificate		backup utility	218
auxiliary	109	MPPs	258
for application server	377	report settings	469
generate MPP certificate	111	SNMP agent	238
generate single server	113	Test operational mode	275
import auxiliary	99	TTS servers	394
import MPP	101	VoIP settings	83
import primary	96 , 106	Configuring Nuance	378
import single server	103	Configuring Organization Level access	
import third party	115	access	128
MPP	101 , 111	contact activity reports	473
MPP third party	120	Contact Detail report	
Certificate page	65	creating	474
certificates		custom	484 , 495 , 498
Root Certificate tab	65	Contact Summary report	
third-party signed	115	creating	474
Certificates page		Conversation Repository	
Root Certificate tab	65	Conversation Repository	
Change ASR Server page	387	configure	186
Change H.323 Connection page	58	corporate directory, linking Avaya Aura Experience Portal	
Change MPP Server page	289	with	24
Change SIP Connection page	73	creating	
Change SNMP Trap Configuration page	246	custom reports	
Change TTS Server page	406	application	482 , 493 , 496
Change User page	29	Contact Detail	484 , 495 , 498
changing		Session Detail	488 , 494
alarm status	439 , 440	reports	
all MPP operational states	263	alarms	438
applications	149 , 158 , 321	Application Detail	472
ASR servers	380	Application Summary	472
Avaya Aura Experience Portal servers	187	Audit Log	465
AVB options	365	Contact Detail	474
H.323 connections	54	Contact Summary	474
MPP operational modes	260	custom	481
MPPs	258	events	438
priority of applications	322	Performance	479
SIP connections	63	Session Detail	475
SNMP traps	239	Session Summary	476
TTS servers	394	custom dictionaries for Vocalizer	396
user accounts	23	sample	398
Changing	37	customize	
Changing role		add menu group to EPM menu	508
changing role	37	add menu item to EPM menu	515
client examples	607	customizing EPM main menu	507
codes	604	custom reports	481
component details	372	application	482 , 493
configuration history for MPPs	274	Contact Detail	484 , 495
Configuration History page	316	Session Detail	488 , 494
configuration menu.properties		Custom reports	
adding items	515	Creating Custom report	499
configuration menu.xml		Custom Reports	480
adding groups	509		
configure management interface	597		
configuring		D	
Application Interface web service	536	database	
Application Logging web service	524	external	222

database (<i>continued</i>)	
purging report data from external	227
purging report data from local	221
requirements	223
restoring	217
database requirement	223
Database Restore utility	217
database schema	493
VPMpps table	495
VPSystems table	496
VPUCIDMap table	498
data collection	170
Data Export Report	481
Data Export Reports	480
default	
event handlers and prompts	364
inbound application	323
deleteapplicationinfo	602
deleting	
applications	149 , 159 , 321
ASR servers	381
H.323 connections	55
MPPs	278
SIP connections	64
SNMP traps	240
TTS servers	395
user accounts	24
Deleting	38
Deleting role	
deleting role	38
deploying applications	319
on Apache Tomcat	319
on IBM WebSphere	319
design guidelines for applications	325 – 328
Diagnostics page	196
Dialog Designer	
applications	317
dialogs, restrictions for attaching	329
directory	
EPM components	91
Disable Organization level access	129
disabling	
SNMP traps	239
display feature.properties	
adding groups	513
display features	513
display features.properties	
adding items	519
display menu.properties	
adding groups	511
adding items	517
distribution of telephony ports	47
do_MntDrv backup utility script	218
do_RestoreData restoration utility script	219
customizing	219
dtmf digits	330

E

EDP	
associate Experience Portal	186
email, email browser, email browser settings	150
email, email connection, adding email connection	145
email, email connection, changing email connection	147 , 148
email, email connections	145
email, email overview	140
email, email processor,	
adding email processor	143
changing email processor	144
deleting email processor	145
email, email processor, email processor states	143
email, email processors	142
email, email settings, system parameters, configuring system parameters	150 , 166
email, inbound email, outbound email, email typical flow	141
email application	149
Email reporting filters, Email	151
Enable Organizational level access	128
EPM	
adding menu groups	508
adding user accounts	23
add menu item	515
changing	184
changing auxiliary hostname in database	203
changing hostname in database	200
changing passwords	21
changing server settings	182
changing user accounts	23
configuring auxiliary	182
connecting to MPP	201
Customizing main menu	507
deleting user accounts	24
EPM Settings page	230
logging in	20
moving to new server	187
reconnect auxiliary	184
reestablish link with MPP	190 , 277
restart needed message	309 , 314 , 425 , 427 , 458
user roles	18
viewing system status	425
EPM components	
directory details	91
EPM Servers page	228
EPM Settings page	230
EPM System Manager Settings page	
configure	173
EPM tab Trace Viewer page	451
EPM Trace Report page	454
error codes	604
ETags	372
event handlers	326 , 362
adding	363
specifying default	364
events	

reports (<i>continued</i>)		GetStatus method	537
categories	433	getzoneinfo	600
high water setting	436	getzonenames	600
Log Report page	457	global settings	
Log Viewer page	454	for logins	22
low water setting	436	reports	469
overview	432	resource thresholds	436
reports		grace period for MPPs	256
creating	438	and CCXML applications	329
resource thresholds	436		
retention periods	437	H	
severities	435	H.323 connections	
statuses	435	Add H.323 Connection page	56
viewing the event associated with an alarm	439	adding	54
VoiceXML	366	Change H.323 Connection page	58
example call flow	317	changing	54
exceptions	604	comparison of features with SIP	80
Experience Portal		defining maintenance stations for	55
System Details tab	309, 427, 458	deleting	55
exporting reports	470	H.323 tab	61
extended exit fields		overview	53
hide	477	viewing	54
show	477	hide extended exit fields	478
external database	222, 223	high water setting for events and alarms	436
connecting Avaya Aura Experience Portal to	225	hostname	
creating schema in	223	changing in database	199, 200, 202, 203, 205
disconnecting Avaya Aura Experience Portal from	226	HTML	
external message		communication flow	169
receiving	589, 590	HTML application	
external messages	588	add	170
		change settings	171
F		delete	171
failover	134	HTML Redirector	
feature.properties		configure	171
displaying groups	513	http, http connection, changing http connection	161
features.properties file	507	HTTP , HTTP connection, changing HTTP connection	160
field	598	http, http connection, connection	159
field array	599		
file upload	605, 606	I	
fileupload serverlet	605	IBM WebSphere, deploying applications on	319
flow diagram		ICR	
management interface	597	Add	421
		Logging and Alarming	423
G		Multi-tenancy	422
gatekeepers for VoIP	53	overview	420
gateways for VoIP	53	reports	423
generate certificate	109	roles	422
generating		ICR licenses	421
certificate	64	ICR Logging and Alarming	423
getAppConfigurableVars	603	ICR Multi-tenancy	422
getapplicationinfo	601	ICR reports	423
getapplicationnames	600	ICR role based access	422
getmpplogs.sh		icr system backup and restore	422
using	192	import	96, 99, 101, 103, 106, 113
GetStatusEx method	538	auxiliary EPM third party	118

inbound applications, specifying default	323	Log tag for applications	323
inet and cache interface	371	Log Viewer page	454
Initialization and Administration System (INADS)	237	low water setting for events and alarms	436
installation history, viewing	92		
Integrated Voice and Video Response	424	M	
intelligent customer routing		maintenance stations, defining	55
database backup and restore	422	Maintenance user role	18
Intelligent Customer Routing	420	Managed application	
licenses	421	Add	417
internal database	223	licenses	417
IVVR	424	Logging and Alarming	418
		Multi-tenancy	418
L		overview	416
LaunchCCXML method	540	reports	419
returning status of	543	roles	418
LaunchEmail method	545	Managed application licenses	417
LaunchEmail parameters	558	Managed application Logging and Alarming	418
LaunchHTML method	548	Managed application Multi-tenancy	418
LaunchSMS method	546	Managed application reports	419
LaunchSMS parameters	559	Managed application role based access	418
LaunchVXML method	549	management interface clients	606 , 607
call classification	350 , 551	management interface flow	597
LDAP, using to access corporate directory	24	management interface web service	595
legal notices		management web service methods	
lexicon tag	397 , 398	addapplicationinfo	602
License Server URL page	45	deleteapplicationinfo	602
License Settings page	46	getAppConfigurableVars	603
licensing		getapplicationinfo	601
Avaya Aura Experience Portal License Settings	46	getapplicationnames	600
Licensing page	41	getzoneinfo	600
Licensing URL	45	getzonenames	600
overview	39	list	599
reallocation of	264	setAppConfigurableVars	603
reconnecting WebLM server	40	setapplicationinfo	601
updating manually	41	management web service objects	598
viewing information	40	management web services WSDL	596
Licensing page	41	manager for SNMP	237
limitation		Media Resource Control Protocol	82
internal database	223	menu.properties	515
limitations		displaying groups	511
Single Sign-on	180	displaying items	517 , 519
Linux backup server, setting up	208	menu.properties file	
locked user account	22	configuration	507
logApplicationEventAlarm	529	display	507
logFailed method	525	menu.xml	
logging in		adding groups	509
EPM	20	menu configuration	
global parameters for	22	configuration menu.properties file	507
Tomcat	415	display menu.properties file	507
to the MPP Service Menu	280	features.properties file	507
unlocking accounts	22	methods	599
Login Options page	30	for Application Interface web service	537
Log Report page	457	for Application Logging web service	525
logs		method upload file	606
packing for MPP server	191 , 192	Mixed Protocol	378
setting MPP trace level	256	move Avaya Aura Experience Portal to a new server	187

MPP	
connecting to different EPM	201
MPP Configuration History page	316
MPP core files	
disable	506
MPP Details page	294
MPPmap file	
definition	233
maintaining server IP addresses	233
viewing or changing LDN entries	234
MPPs	
about	
Avaya Voice Browser	254
CCXML Browser	255
Session Manager	254
speech proxies and adapters	255
system manager	252
telephony component	255
Web services	253
adding	258
Add MPP Server pages	283
alarm reports	438
and applications	317
Auto Restart MPP page	289
Avaya Services map file	233
Change MPP Server page	289
changing hostname in database	202
changing operational modes	260
changing operational state for all	263
checking operational state for all	262
configuration history	274
deleting	278
event reports	438
grace period and CCXML applications	329
grace period and logging level	256
logs	
packing	191 , 192
maximum simultaneous calls	259
moving log files	281
moving to new server	189
MPP Configuration History	316
MPP Details page	294
MPP Servers page	301
MPP Service Menu	278
MPP Settings page	302
operational modes	260
operational states	261
overview	
Avaya Voice Browser	254
CCXML Browser	255
Session Manager	254
speech proxies and adapters	255
system manager	252
telephony component	255
Web services	253
processes	265
reconfiguring	258
reestablishing link with EPM	190 , 277
report data settings	469
restarting	273
Restart MPP Today page	308
Restart Schedule for MPP page	308
restoring packed log files	194
secure connection to application server	377
server capacity	259
setting restart options for	274
Software Upgrade pages	266
starting	273 , 414
starting all	272
Test operational mode	275
upgrading	270 , 271
viewing	257
viewing details for an MPP	257
viewing status	425
MPP Servers page	301
MPP Service Menu	
automatic login problems	280
logging in	280
using	278
MPP Settings page	302
MPP Trace Report page	451
MRCP	82
multi tenancy	128
N	
Network Management System (NMS)	237
new user role	
adding role	36
NFS Server Configuration Tool	208
notices, legal	
Nuance	378
O	
object	
field	598
field array	599
status	599
objects	598
OpenView	237
configuration	240
operational modes for MPPs	260
operational states for MPPs	261
Operations user role	18
Organization	127
Organizational Level	126 , 128
Organization Level	127
Organization Level access	
access	126 , 127
Organizations	126 , 128 , 130
Organizations page	130
OS, OS user settings	
OS user settings page field descriptions	33

OS, OS user settings, view OS user settings, view OS user settings page field descriptions	33
overview	
HTML	169
MPPs	251

P

Pack Files Options page	197
page field descriptions	
System Manager Settings	174
passwords	
administration	20
changing	
for PostgreSQL accounts	93
changing for EPM	21
EPM	20
MPP Service Menu	280
Tomcat	415
Performance report	
creating	479
planning applications	325 – 328
Port Distribution page	48
Port Distribution Report page	49 , 197
Port Information window	51
ports	
licenses for	39
Port Distribution page	48 , 49 , 197
Port Information window	51
telephony	
distribution	47
states	48
postgres PostgreSQL account, configuring	93
PostgreSQL	
configuring user accounts	93
PostgreSQL account, configuring	93
prerequisites	173
printing reports	470
priority, for applications	322
privacy feature in VoiceXML applications	330
processes	
on MPPs	265
prompts	326 , 362
adding	363
specifying default	364
protocols	
used in Avaya Aura Experience Portal	82
proxy server settings for MPP Service Menu	280
purging report data, from a local database	221
purging report data, from an external database	227
purging report data from the database	221

Q

QueryResources method	555

R

reallocation of licenses	264
real-time management	134
Real-time Transport Control Protocol	82
Real-time Transport Protocol	82
Recommended releases	378
reconfigure SSO	179
reconfiguring MPPs	258
reinstalling	
Avaya Aura Experience Portal on new server	190
EPM on new server	187
MPP on new server	189
related documents	609
reportBatch method	526
for call flow data	528
Reporting user role	18
report PostgreSQL account, configuring	93
reports	
Alarm Report page	445
application activity	
adding applications to	522
Application Detail	472
Application Summary	472
audit log	465
Audit Log Report page	468
Audit Log Viewer page	466
configuring global data settings	469
contact activity	473
creating	
alarm report	438
Contact Detail	474
Contact Summary	474
custom	481
Performance	479
Session Detail	475
Session Summary	476
creating custom	
application	482 , 493 , 496
Contact Detail	484 , 495 , 498
Session Detail	488 , 494
event reports	438
exporting	470
generation flow diagram	470
Log Report page	457
Log Viewer page	454
printing	470
specifying MPP report data to store	469
SQL statements for	502
Trace Viewer page	446 , 451
resource thresholds for alarms and events	436
restart	
an MPP	273
options for MPPs	274
Restart MPP Today page	308
Restart Schedule for MPP page	308
Restore data	

Restore data (<i>continued</i>)	
using for data restoration	219
restoring the Avaya Aura Experience Portal database	217
from System Backup	219
restrictions, resources	136
retention periods for alarms and events	437
Retired event and alarm status	435
return Values	560
RFC 3261 SIP headers	359
roles	18
Roles	
Roles page	34
roles, for users	18
roles and permissions	178
Roles page	34
root certificate	
Root Certificate tab	65
RTCP	82
RTP	82

S

sample custom dictionary	398
Scheduled Reports	480 , 501
Scheduling a report	501
Secure Access Link (SAL)	237
secure connection to application server	377
SendCCXMLEvent method	555
SendEmail method	556
SendEmail parameters	558
send message	591
SendSMS method	557
SendSMS parameters	559
serverlet interface	605
Service Menu	18
Session Detail report	
creating	475
custom	488 , 494
Session Initiation Protocol	62
Session Summary report	
creating	476
setAppConfigurableVars	603
setapplicationinfo	601
severities for alarms and events	435
shared database	
connecting the Avaya Aura Experience Portal system to	225
creating for Avaya Aura Experience Portal systems ..	222
disconnecting the Avaya Aura Experience Portal system ..	226
from	226
show extended exit fields	477
Single Sign-on	178
Single User Mode	
password protect	505
SIP	
adding connections	63
certificate for TLS	64 , 67

changing connections	63
comparison of features with H.323	80
custom VoiceXML headers	360
deleting connections	64
header support for VoiceXML	355
RFC 3261 headers in VoiceXML	359
sample UPDATE method	361
sample VoiceXML page setting SIP headers	361
sample VoiceXML SIP header logging page	358
Session Manager	67
SIP UPDATE	361
UCID in headers	353
unknown SIP headers in VoiceXML	359
UPDATE	361
UII application parameters	354
UII support	352
viewing connections	63
SIP connections	
Add SIP Connection pages	67
Change SIP Connection pages	73
overview	62
SIP tab	79
SIP UPDATE/L	
Sample method	361
smpp, smpp connection, adding smpp connection	161
smpp, smpp connection, change smpp connection	162
smpp, smpp connection, deleting smpp connection	164
SMPP connections, testing SMPP connections	163
SMS, inbound SMS, outbound SMS, SMS typical flow	154
SMS, SMS browser	164
SMS, SMS browser, SMS browser settings, configuring SMS ..	165
browser settings	165
SMS, SMS delivery receipt	167
SMS, SMS overview	153
SMS, SMS processor,	
adding SMS processor	156
changing SMS processor	157
deleting SMS processor	158
SMS, SMS processor, SMS processor states	156
SMS, SMS processors	155
SMS, SMS reporting filters	167
SMS, SMS web services	166
SMS application	159
SMSC, SMSC success, SMSC failure	168
SNMP	
adding traps	238
Add SNMP Trap Configuration page	244
Change SNMP Trap Configuration page	246
changing traps	239
components and definitions	237
configuring agent for	238
deleting traps	240
disabling traps	239
SNMP Agent Settings page	242
SNMP page	240
testing traps	239
Tivoli and OpenView	240

SNMP (<i>continued</i>)		
View Device Notification page	248	
viewing traps	238	
SNMP Agent Settings page	242	
SNMP page	240	
speech applications	317	
Speech Server	378	
speech servers	378	
Speech Servers page		
ASR tab	381	
TTS tab	400	
SQL statements for reports	502	
states		
operational states for MPPs	261	
status	599	
statuses, for events and alarms	435	
stopping vpms service	185	
support	612	
synchronous	590	
system backup		
backup	210	
System Manager		
items created	177	
System Manager user		
create	176	
System Monitor page		
Details tab	309 , 427 , 458	
Summary tab	314 , 425	
system status, viewing	425	
T		
TCP	82	
telephony ports		
distribution of	47	
licenses for	39	
states	48	
testing		
SNMP traps	239	
Test operation mode		
configuring	275	
maintenance stations for	55	
using	276	
Text-To-Speech	378	
third party signed		
import single server certificate	123	
Tivoli	237	
configuration	240	
TLS, installing certificate for	64 , 67	
Tomcat	413 , 418 , 423	
logging in	415	
tomcat, tomcat server, multimedia tomcat server	151	
trace levels		
setting globally	256	
Trace Report page	451 , 454	
Trace Viewer	446	
Trace Viewer page	446 , 451	
training	611	
Transmission Control Protocol	82	
traps for SNMP	237	
adding	238	
changing	239	
deleting	240	
disabling	239	
testing	239	
viewing	238	
Trending By report	500	
troubleshooting		
logs		
packing for MPP server	191 , 192	
TTS servers	378	
adding	394	
Add TTS Server page	401	
Change TTS Server page	406	
changing	394	
custom dictionaries	396	
deleting	395	
overview	393	
TTS tab	400	
viewing	394	
U		
UCID in SIP headers	353	
UDP	82	
Unacknowledged event and alarm status	435	
unique extensions directory		
defining	520	
unlocking user accounts	22	
Upgrade MPP Server pages	266	
upgrading		
MPPs		
upgrade options	266	
options	266	
uploading		
certificate	64	
upload method	606	
Upload trusted certificate	65	
user accounts		
password longevity	25	
passwords	20	
Users page	25	
User Datagram Protocol	82	
User Manager user role	18	
user roles	18	
users	22	
access to Avaya Aura Experience Portal	18	
adding EPM accounts	23	
Add User page	27	
Change User page	29	
changing EPM accounts	23	
changing EPM password	21	
deleting EPM accounts	24	
getting from corporate directory	24	

users (<i>continued</i>)		sample VoiceXML SIP header logging page	358
global login parameters	22	SIP header support	355
logging in to EPM	20	unknown SIP headers	359
logging in to MPP Service Menu	280	VoiceXML, voice browser	365
logging in to Tomcat	415	voicexml elements and attributes	337
Login Options page	30	VoiceXML Log tag	323
roles for	18	VoIP	
viewing existing accounts	22	comparison of H.323 and SIP features	80
Users page		configuring settings	83
EPM	25	gatekeepers	53
UUI data		gateways	53
format of	352	overview	82
related application parameters	354	view settings	83
UCID values in	353	VoIP Settings page	83
V		with H.323	53
verifying		with SIP	62
NFS service status	208	VoIP Connections page	
videos	611	H.323 tab	61
viewing		SIP tab	79
AF ID	236	VoIP Settings page	83
alarm details	439	W	
applications	321	WebLM server	39
application transcription data	324 , 476	reconnecting	40
ASR servers	379	web service	
H.323 connections	54	Application Interface	534
installation history	92	Application Logging	522
licenses available	40	web service client example	607
Log tag messages	323	web services client	606
MPP configuration history	274	Windows backup server, setting up	209
MPP details	257	WSDL file	
MPPs	257	for Application Interface web service	562
SIP connections	63	for Application Logging web service	531
SNMP traps	238	Z	
system status	425	zone, add zone	137
TTS servers	394	zone, delete	138
user accounts	22	zone, filter	138
VoIP settings	83	zone, zone details, viewing zone details	139
View SNMP Device Notification Settings page	248	zone filtering	136
Vocalizer		zone licenses	134
custom dictionaries	396	zones, change	138
phonetic expressions allowed	399	zoning topology, overview	132
vocalizer sample dictionary	398		
voice application	591		
voice browser	254		
Voice over IP	53		
Voice Portal			
database			
changing auxiliary hostname in	203		
VoiceXML			
AVB events for	366		
custom SIP headers	360		
multiple interpretations of	329		
privacy feature	330		
RFC 3261 SIP headers	359		
sample page setting SIP headers	361		