

PARTNER[®] Advanced Communications System

PARTNER ACS Hong Kong Release 3.0

Addendum

This addendum supplements the documentation that came with your PARTNER Advanced Communications System and addresses the differences specific to using the system in Hong Kong.

- Page 2 of this addendum describes the **Auto Dial Delay (#120)**, which should only be used in Hong Kong.
- The factory setting for **Automatic Daylight Savings Time (#126)** is Not Active.
- When using **Caller ID** features, the dialed digits will display slightly differently than shown in the illustrations in your documentation.
- For the **Emergency Phone Number List (#406)**, the emergency telephone number is 999 rather than 911. By default, 999 is programmed as list entry 01 in the list.
- The **Hold Disconnect Time (#203)** system programming option is not available.
- For **Outgoing Call Restriction (#401)**, the valid entries are as follows:
 1 = No Restriction
 2 = Inside (intercom) Only—Also allows calls to emergency number 999
 3 = Local (intercom and local) Only—Cannot dial numbers beginning with 17, 001, or 002
- The Remote Administration Software is not available for use in Hong Kong. References in the documentation to this product and using the feature **Remote Administration Password (#730)** should be ignored.
- The **Toll Call Prefix (#402)** system programming option is not available.
- The following specifications apply:

Dialing Capabilities	<ul style="list-style-type: none"> • Rotary: Make/Break: 33/67 Interdigit Pause: 800 ms. • DTMF: Signal duration (autodial): 100 ms. Interdigit pause (autodial): 100 ms. • Other: Disconnect signal to CO: 1.5 seconds
System Identifiers	<ul style="list-style-type: none"> • (Tone pattern) ***** P *** P * (P represents a 1.5 second pause) • (Display using Feature 59) P ACS R3.0.4 C02

Auto Dial Delay (#120)

Description

When the system selects a line before dialing an automatically dialed number, the system waits the time specified by Auto Dial Delay, then dials the number. Automatically dialed numbers include Personal Speed Numbers, System Speed Dial Numbers, and numbers dialed using Auto Dialing, Last Number Redial, and Save Number Redial.

Consideration

If automatically dialed numbers do not reach the desired destination because they are dialed before dial tone is received, increase the Auto Dial Delay setting.

Settings

02—10 (1.0 to 5.0 seconds in .5 second increments)
03 (1.5 seconds) (this is the factory setting) ✓

Programming

1. Press **Feature** **00** **System Program** **System Program**.
2. Press **#** **1** **2** **0**. The display reads:
Autodial Delay
03 1.5 - sec
3. Enter a two-digit Auto Dial Delay setting (02—10). For example, to set the Auto Dial Delay to 4 seconds, press **0** **8**.
4. Select another procedure or press **Feature** **00**.