

# **Avaya J100 Series SIP IP Phones Overview and Specifications**

© 2024-2025, Avaya LLC All Rights Reserved.

#### Notice

While reasonable efforts have been made to ensure that the information in this document is complete and accurate at the time of printing, Avaya assumes no liability for any errors. Avaya reserves the right to make changes and corrections to the information in this document without the obligation to notify any person or organization of such changes.

#### **Documentation disclaimer**

"Documentation" means information published in varying media which may include product information, subscription or service descriptions, operating instructions and performance specifications that are generally made available to users of products. Documentation does not include marketing materials. Avaya shall not be responsible for any modifications, additions, or deletions to the original published version of Documentation unless such modifications, additions, or deletions were performed by or on the express behalf of Avaya. End user agrees to indemnify and hold harmless Avaya, Avaya's agents, servants and employees against all claims, lawsuits, demands and judgments arising out of, or in connection with, subsequent modifications, additions or deletions to this documentation, to the extent made by End user.

#### Link disclaimer

Avaya is not responsible for the contents or reliability of any linked websites referenced within this site or Documentation provided by Avaya. Avaya is not responsible for the accuracy of any information, statement or content provided on these sites and does not necessarily endorse the products, services, or information described or offered within them. Avaya does not guarantee that these links will work all the time and has no control over the availability of the linked pages.

#### Warranty

Avaya provides a limited warranty on Avaya hardware and software. Please refer to your agreement with Avaya to establish the terms of the limited warranty. In addition, Avaya's standard warranty language as well as information regarding support for this product while under warranty is available to Avaya customers and other parties through the Avaya Support website: <a href="https://support.avaya.com/helpcenter/getGenericDetails?detailId=C20091120112456651010">https://support.avaya.com/helpcenter/getGenericDetails?detailId=C20091120112456651010</a> under the link "Warranty & Product Lifecycle" or such successor site as designated by Avaya. Please note that if the product(s) was purchased from an authorized Avaya channel partner outside of the United States and Canada, the warranty is provided by said Avaya Channel Partner and not by Avaya.

"Hosted Service" means an Avaya hosted service subscription that You acquire from either Avaya or an authorized Avaya Channel Partner (as applicable) and which is described further in Hosted SAS or other service description documentation regarding the applicable hosted service. If You purchase a Hosted Service subscription, the foregoing limited warranty may not apply but You may be entitled to support services in connection with the Hosted Service as described further in your service description documents for the applicable Hosted Service. Contact Avaya or Avaya Channel Partner (as applicable) for more information.

#### **Hosted Service**

THE FOLLOWING APPLIES ONLY IF YOU PURCHASE AN AVAYA HOSTED SERVICE SUBSCRIPTION FROM AVAYA OR AN AVAYA CHANNEL PARTNER (AS APPLICABLE), THE TERMS OF USE FOR HOSTED SERVICES ARE AVAILABLE ON THE AVAYA WEBSITE, HTTPS://SUPPORT.AVAYA.COM/LICENSEINFO UNDER THE LINK "Avaya Terms of Use for Hosted Services" OR SUCH SUCCESSOR SITE AS DESIGNATED BY AVAYA, AND ARE APPLICABLE TO ANYONE WHO ACCESSES OR USES THE HOSTED SERVICE. BY ACCESSING OR USING THE HOSTED SERVICE, OR AUTHORIZING OTHERS TO DO SO, YOU, ON BEHALF OF YOURSELF AND THE ENTITY FOR WHOM YOU ARE DOING SO (HEREINAFTER REFERRED TO INTERCHANGEABLY AS "YOU" AND "END USER"), AGREE TO THE TERMS OF USE. IF YOU ARE ACCEPTING THE TERMS OF USE ON BEHALF A COMPANY OR OTHER LEGAL ENTITY, YOU REPRESENT THAT YOU HAVE THE AUTHORITY TO BIND SUCH ENTITY TO THESE

TERMS OF USE. IF YOU DO NOT HAVE SUCH AUTHORITY, OR IF YOU DO NOT WISH TO ACCEPT THESE TERMS OF USE, YOU MUST NOT ACCESS OR USE THE HOSTED SERVICE OR AUTHORIZE ANYONE TO ACCESS OR USE THE HOSTED SERVICE.

#### Licenses

The Global Software License Terms ("Software License Terms") are available on the following website <a href="https://www.avaya.com/en/legal-license-terms/">https://www.avaya.com/en/legal-license-terms/</a> or any successor site as designated by Avaya. These Software License Terms are applicable to anyone who installs, downloads, and/or uses Software and/or Documentation. By installing, downloading or using the Software, or authorizing others to do so, the end user agrees that the Software License Terms create a binding contract between them and Avaya. In case the end user is accepting these Software License Terms on behalf of a company or other legal entity, the end user represents that it has the authority to bind such entity to these Software License Terms.

#### Copyright

Except where expressly stated otherwise, no use should be made of materials on this site, the Documentation, Software, Hosted Service, or hardware provided by Avaya. All content on this site, the documentation, Hosted Service, and the product provided by Avaya including the selection, arrangement and design of the content is owned either by Avaya or its licensors and is protected by copyright and other intellectual property laws including the sui generis rights relating to the protection of databases. You may not modify, copy, reproduce, republish, upload, post, transmit or distribute in any way any content, in whole or in part, including any code and software unless expressly authorized by Avaya. Unauthorized reproduction, transmission, dissemination, storage, or use without the express written consent of Avaya can be a criminal, as well as a civil offense under the applicable law.

#### Virtualization

The following applies if the product is deployed on a virtual machine. Each product has its own ordering code and license types. Unless otherwise stated, each Instance of a product must be separately licensed and ordered. For example, if the end user customer or Avaya Channel Partner would like to install two Instances of the same type of products, then two products of that type must be ordered.

#### **Third Party Components**

The following applies only if the H.264 (AVC) codec is distributed with the product. THIS PRODUCT IS LICENSED UNDER THE AVC PATENT PORTFOLIO LICENSE FOR THE PERSONAL USE OF A CONSUMER OR OTHER USES IN WHICH IT DOES NOT RECEIVE REMUNERATION TO (i) ENCODE VIDEO IN COMPLIANCE WITH THE AVC STANDARD ("AVC VIDEO") AND/OR (ii) DECODE AVC VIDEO THAT WAS ENCODED BY A CONSUMER ENGAGED IN A PERSONAL ACTIVITY AND/OR WAS OBTAINED FROM A VIDEO PROVIDER LICENSED TO PROVIDE AVC VIDEO. NO LICENSE IS GRANTED OR SHALL BE IMPLIED FOR ANY OTHER USE. ADDITIONAL INFORMATION MAY BE OBTAINED FROM MPEG LA, L.L.C. SEE HTTP://WWW.MPEGLA.COM.

### Service Provider

WITH RESPECT TO CODECS, IF THE AVAYA CHANNEL PARTNER IS HOSTING ANY PRODUCTS THAT USE OR EMBED THE H.264 CODEC OR H.265 CODEC, THE AVAYA CHANNEL PARTNER ACKNOWLEDGES AND AGREES THE AVAYA CHANNEL PARTNER IS RESPONSIBLE FOR ANY AND ALL RELATED FEES AND/OR ROYALTIES. THE H.264 (AVC) CODEC IS LICENSED UNDER THE AVC PATENT PORTFOLIO LICENSE FOR THE PERSONAL USE OF A CONSUMER OR OTHER USES IN WHICH IT DOES NOT RECEIVE REMUNERATION TO: (i) ENCODE VIDEO IN COMPLIANCE WITH THE AVC STANDARD ("AVC VIDEO") AND/OR (ii) DECODE AVC VIDEO THAT WAS ENCODED BY A CONSUMER ENGAGED IN A PERSONAL ACTIVITY AND/OR WAS OBTAINED FROM A VIDEO PROVIDER LICENSED TO PROVIDE AVC VIDEO. NO LICENSE IS GRANTED OR SHALL BE IMPLIED FOR ANY OTHER USE. ADDITIONAL INFORMATION FOR H.264 (AVC) AND H.265 (HEVC) CODECS MAY BE OBTAINED FROM MPÈG LÁ, L.L.C. SEE HTTP:// WWW.MPEGLA.COM.

#### Compliance with Laws

You acknowledge and agree that it is Your responsibility to comply with any applicable laws and regulations, including, but not limited to laws and regulations related to call recording, data privacy, intellectual property, trade secret, fraud, and music performance rights, in the country or territory where the Avaya product is used.

### **Preventing Toll Fraud**

"Toll Fraud" is the unauthorized use of your telecommunications system by an unauthorized party (for example, a person who is not a corporate employee, agent, subcontractor, or is not working on your company's behalf). Be aware that there can be a risk of Toll Fraud associated with your system and that, if Toll Fraud occurs, it can result in substantial additional charges for your telecommunications services.

#### Avaya Toll Fraud intervention

If You suspect that You are being victimized by Toll Fraud and You need technical assistance or support, please contact your Avaya Sales Representative.

#### **Security Vulnerabilities**

Information about Avaya's security support policies can be found in the Security Policies and Support section of <a href="https://support.avaya.com/security">https://support.avaya.com/security</a>.

Suspected Avaya product security vulnerabilities are handled per the Avaya Product Security Support Flow (<a href="https://support.avaya.com/css/P8/documents/100161515">https://support.avaya.com/css/P8/documents/100161515</a>).

#### **Downloading Documentation**

For the most current versions of Documentation, see the Avaya Support website: <a href="https://support.avaya.com">https://support.avaya.com</a>, or such successor site as designated by Avaya.

### **Contact Avaya Support**

See the Avaya Support website: <a href="https://support.avaya.com">https://support.avaya.com</a> for Product or Cloud Service notices and articles, or to report a problem with your Avaya Product or Cloud Service. For a list of support telephone numbers and contact addresses, go to the Avaya Support website: <a href="https://support.avaya.com">https://support.avaya.com</a> (or such successor site as designated by Avaya), scroll to the bottom of the page, and select Contact Avaya Support.

#### Note

Using a cell, mobile, or GSM phone, or a two-way radio in close proximity to an Avaya IP telephone might cause interference.

#### **Regulatory Statements**

#### **Australia Statements**

### **Handset Magnets Statement:**



#### Danger:

The handset receiver contains magnetic devices that can attract small metallic objects. Care should be taken to avoid personal injury.

### Industry Canada (IC) Statements

RSS Standards Statement

This device complies with Industry Canada license-exempt RSS standard(s). Operation is subject to the following two conditions:

- 1. This device may not cause interference, and
- This device must accept any interference, including interference that may cause undesired operation of the device.

Le présent appareil est conforme aux CNR d'Industrie Canada applicables aux appareils radio exempts de licence. L'exploitation est autorisée aux deux conditions suivantes:

- 1. L'appareil ne doit pas produire de brouillage, et
- L'utilisateur de l'appareil doit accepter tout brouillage radioélectrique subi, même si le brouillage est susceptible d'en compromettre le fonctionnement.

Radio Transmitter Statement

Under Industry Canada regulations, this radio transmitter may only operate using an antenna of a type and maximum (or lesser) gain approved for the transmitter by Industry Canada. To reduce potential radio interference to other users, the antenna type and its gain should be so chosen that the equivalent isotropically radiated power (EIRP) is not more than that necessary for successful communication.

Conformément à la réglementation d'Industrie Canada, le présent émetteur radio peut fonctionner avec une antenne d'un type et d'un gain maximal (ou inférieur) approuvé pour l'émetteur par Industrie Canada. Dans le but de réduire les risques de brouillage radioélectrique à l'intention des autres utilisateurs, il faut choisir le type d'antenne et son gain de sorte que la puissance isotrope rayonnée équivalente ne dépasse pas l'intensité nécessaire à l'établissement d'une communication satisfaisante.

This Class B digital apparatus complies with Canadian ICES-003.

Cet appareil numérique de la classe B est conforme à la norme NMB-003 du Canada.

#### Radiation Exposure Statement

This equipment complies with FCC & IC RSS102 radiation exposure limits set forth for an uncontrolled environment. This equipment should be installed and operated with minimum distance 20cm between the radiator & your body. This transmitter must not be co-located or operating in conjunction with any other antenna or transmitter.

Cet équipement est conforme aux limites d'exposition aux rayonnements ISEDétablies pour un environnement non contrôlé. Cet équipement doit être installé et utilisé avec un minimum de 20 cm de distance entre la source de rayonnement et votre corps.

This product meets the applicable Innovation, Science and Economic Development Canada technical specifications.

#### Japan Statements

#### Class B Statement

This is a Class B product based on the standard of the VCCI Council. If this is used near a radio or television receiver in a domestic environment, it may cause radio interference. Install and use the equipment according to the instruction manual.

この装置は、クラスB情報技術装置です。この装置は、家庭環境で使用することを目的としていますが、この装置がラジオやテレビジョン受信機に近接して使用されると、受信障害を引き起こすことがあります。

取扱説明書に従って正しい取り扱いをして下さい。

VCCI-B

### Denan Power Cord Statement



#### Danger:

Please be careful of the following while installing the equipment:

- Please only use the connecting cables, power cord, and AC adapters shipped with the equipment or specified by Avaya to be used with the equipment. If you use any other equipment, it may cause failures, malfunctioning, or fire.
- Power cords shipped with this equipment must not be used with any other equipment. In case the above guidelines are not followed, it may lead to death or severe injury.



## 警告

本製品を安全にご使用頂くため、以下のことにご注意ください。

- 接続ケーブル、電源コード、AC アダプタなどの部品は、必ず 製品に同梱されております添付品または指定品をご使用くだ さい。添付品指定品以外の部品をご使用になると故障や動作 不良、火災の原因となることがあります。
- 同梱されております付属の電源コードを他の機器には使用しないでください。上記注意事項を守らないと、死亡や大怪我など人身事故の原因となることがあります。

#### México Statement

The operation of this equipment is subject to the following two conditions:

- 1. It is possible that this equipment or device may not cause harmful interference, and
- This equipment or device must accept any interference, including interference that may cause undesired operation.

La operación de este equipo está sujeta a las siguientes dos condiciones:

- Es posible que este equipo o dispositivo no cause interferencia perjudicial y
- Este equipo o dispositivo debe aceptar cualquier interferencia, incluyendo la que pueda causar su operación no deseada.

#### **Brazil Statement**

Este equipamento não tem direito à proteção contra interferência prejudicial e não pode causar interferência em sistemas devidamente autorizados

#### Power over Ethernet (PoE) Statement

This equipment must be connected to PoE networks without routing to the outside plant.

#### Taiwan Low Power Radio Waves Radiated Devices Statement

取得審驗證明之低功率射頻器材,非經核准,公司、商號或使 用者均不得擅自變更頻率、加大功率或變更原設計之特性及功能。低功率射頻器材之使用不得影響飛航安全及干擾合法通信;經發現有干擾現象時,應 立即停用,並改善至無干擾時方得繼續使用。前述合法通信,指依電信管理 法規定作業之無線電通信。低功率射頻器材須忍受合法通信或工業、科學及 醫療用電波輻射性電機設備之干擾。

#### U.S. Federal Communications Commission (FCC) Statements

#### Compliance Statement

The changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

To comply with the FCC RF exposure compliance requirements, this device and its antenna must not be co-located or operating to conjunction with any other antenna or transmitter.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:

- 1. This device may not cause harmful interference, and
- This device must accept any interference received, including interferences that may cause undesired operation.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designated to provide reasonable protection against harmful interferences in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interferences to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- · Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

### Radiation Exposure Statement

This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment . This equipment should be installed and operated with minimum distance of 8 in or 20 cm between the

radiator and your body. This transmitter must not be co-located or operating in conjunction with any other antenna or transmitter.

#### **ENERGY STAR®** compliance statement



As an ENERGY STAR partner, Avaya LLC has determined that this product meets the ENERGY STAR guidelines for energy efficiency. Information on the ENERGY STAR program can be found at <a href="www.energystar.gov">www.energystar.gov</a>. ENERGY STAR and the ENERGY STAR mark are registered trademarks owned by the U.S. Environmental Protection Agency.

#### **EU Countries**

This device when installed complies with the essential requirements and other relevant provisions of the EMC Directive 2014/30/EU, Safety LV Directive 2014/35/EU, and Radio Equipment Directive 2014/53/EU. A copy of the Declaration may be obtained from <a href="https://support.avaya.com">https://support.avaya.com</a> or Avaya LLC, 350 Mt. Kemble Avenue, Morristown, NJ 07960 USA.

#### WiFi transmitter

- Frequencies for 2412-2472 MHz, transmit power: < 20 dBm
- Frequencies for 5180-5240 MHz, transmit power: < 20 dBm

#### BT transmitter

Frequencies for 2402-2480 MHz, transmit power: < 6.0 dBm</li>

#### **General Safety Warning**

- Use only the Avaya approved Limited Power Source power supplies specified for this product.
- · Ensure that you:
  - Do not operate the device near water.
  - Do not use the device during a lightning storm.
  - Do not report a gas leak while in the vicinity of the leak.
  - For Accessory Power Supply in Avaya J100 Series IP Phones

    – Use Only Limited Power Supply Phihong Technology Co. Ltd. Model: PSAC12R-050, Output: 5VDC, 2.4A.

#### **Trademarks**

The trademarks, logos and service marks ("Marks") displayed in this site, the Documentation, Hosted Service(s), and product(s) provided by Avaya are the registered or unregistered Marks of Avaya, its affiliates, its licensors, its suppliers, or other third parties. Users are not permitted to use such Marks without prior written consent from Avaya or such third party which may own the Mark. Nothing contained in this site, the Documentation, Hosted Service(s) and product(s) should be construed as granting, by implication, estoppel, or otherwise, any license or right in and to the Marks without the express written permission of Avaya or the applicable third party.

Avaya is a registered trademark of Avaya LLC.

All non-Avaya trademarks are the property of their respective owners.

The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by Avaya LLC is under license.

### **Device Usage Consent**

By using the Avaya device, you agree that Avaya, from time to time, may collect network and device data from your device and may use such data in order to validate your eligibility to use the device.

## **Contents**

Ch	apter 1: Introduction	
	Purpose	
	Intended audience	6
Ch	apter 2: J100 Series IP Phone overview	7
	Avaya J100 Series IP Phones overview	. 7
	J100 Series IP Phone models	. 7
	Hardware specifications	8
Ch	apter 3: Feature description	11
	Feature description	11
Ch	apter 4: Performance specifications	12
	Power specifications	12
	Port and switch	13
	Supported codecs	14
Ch	apter 5: Environmental specification	15
	Altitude and air pressure	15
	Temperature and humidity	15
	Regulatory compliance	16
Ch	apter 6: Dial plan	19
	Dial plan	19
	Dialable characters	19
Ch	apter 7: Security	20
	Security overview	20
	SSH	20
	TLS	
	Avaya SBC	
	EAP-TLS	
	SCEP	
	802.1X Supplicant operation	
	Virus malware related attacks	
	JITC certification	
	Port utilization	
Ch	apter 8: Related resources	
	Documentation	
	Finding documents on the Avaya Support website	
	Avaya Documentation Center navigation	
	Support	26

## **Chapter 1: Introduction**

## **Purpose**

This document describes tested product characteristics and capabilities, including feature descriptions, interoperability, performance specifications, security, and licensing requirements.

## Intended audience

This document is intended for people who want to gain a high-level understanding of the product features, functions, capacities, and limitations.

## **Chapter 2: J100 Series IP Phone overview**

## Avaya J100 Series IP Phones overview

Avaya J100 Series IP Phones provide a range of applications and features for unified communications. The phones leverage the enterprise IP network and eliminate the need of a separate voice network. The phones offer superior audio quality with the amplified handsets and customization with low power requirements in a Session Initiation Protocol (SIP) environment.

Avaya J100 Series IP Phones work with environments to provide a flexible architecture where you can:

- Make conference calls more efficiently and enhance customer interactions with high-quality audio.
- Gain access to information quickly through easy-to-read high-resolution displays.
- Create a survivable, scalable infrastructure that delivers reliable performance and flexible growth as business needs change.
- Increase performance by deploying Gigabit Ethernet within your infrastructure.
- Reduce energy costs by using efficient Power-over-Ethernet (PoE) including sleep mode, which lowers energy consumption significantly.
- Enhance audio quality by using amplified handset mode.

## J100 Series IP Phone models

Phone model	Description
J129 IP Phone	A phone with a monochrome display that supports single line call appearance.
J139 IP Phone	A phone with a color display that has four lines/feature/application buttons. The primary display is scrollable that supports up to 96 lines/features/applications.

Phone model	Description
J159 IP Phone	A phone with a Primary color display that has four lines/ features/applications buttons. The Primary display is scrollable that supports up to 96 lines/features/applications. A Secondary color display has 6 lines/features/applications buttons. The Secondary display is pageable that supports up to 24 lines/ features/applications.
J169 IP Phone	A phone with a grayscale display that supports eight lines/ features/applications buttons. The Primary display is scrollable that supports up to 96 lines/features/applications. The phone can also support up to three button modules, each supporting 24 lines/ features/applications buttons.
J179 IP Phone	A phone with a color display that supports eight lines/features/applications buttons. The Primary display is scrollable that supports up to 96 lines/features/applications. The phone can also support up to three button modules, each supporting 24 lines/features/applications buttons.
J189 IP Phone	A phone with a Primary color display that supports 10 lines/ features/applications buttons. The Primary display is scrollable, supporting up to 96 line/feature/applications. A Secondary color display that supports 6 lines/features/applications buttons. The Secondary display is pageable supporting up to 24 lines/features/applications. The phone can also support up to two button modules, each supporting 24 lines/features/applications buttons.

## **Hardware specifications**

Avaya J100 Series IP Phones support the following hardware specifications:

### **Device dimensions**

The dimensions are with phone stand in high position and wall mount.

Model	Phone stand in high position (Wide x Deep x Tall in mm)	Phone dimensions in wall mount (Wide x Deep x Tall in mm)
J129	156 x 170 x 175	156 x 100 x 198
J139	179 x 170 x 177	179 x 100 x 219
J159	185 x 170 x 224	185 x 100 x 225
J169	187 x 175 x 183	187 x 100 x 225
J179	187 x 175 x 183	187 x 100 x 225
J189	227 x 179 x 199	227 x 100 x 244
JBM24	89 x 175 x 183	89 x 100 x 225
JEM24	115 x 175 x 140	115 x 100 x 175

## **Display and Call appearances**

Model	Display (pixels)	Display type	Call appearances
J129	2.3", 128 x 32	Monochrome	1
J139	2.8", 320 x 240	Color	4
J159	2.8", 320 x 240 primary display 2.4", 240 x 320 secondary display	Color	4 on the primary display 24 on the secondary display
J169	3.5", 320 x 240	Grayscale	8
J179	3.5", 320 x 240	Color	8
J189	5", 800 x 480 primary display 2.4", 240 x 320 secondary display	Color	10 on the primary display 24 on the secondary display
JBM24	3.3", 160 x 320	Grayscale	NA
JEM24	4.3", 272 x 480	Grayscale and color	NA

## Ethernet, Wi-Fi, and Bluetooth- specifications

Model	Ethernet switch	Wi-Fi support	Bluetooth support
J129	Dual 10/100	Yes, with an optional module	No
J139	Dual 10/100/1000	No	No
J159	Dual 10/100/1000	Yes, with an optional module	Yes, with an optional module
J169	Dual 10/100/1000	No	No
J179	Dual 10/100/1000	Yes, with an optional module	Yes, with an optional module
J189	Dual 10/100/1000	Yes, with an optional module	Yes, with an optional module
JBM24	NA	NA	NA
JEM24	NA	NA	NA

## **Handset and Headset-specifications**

Model	Wired handset (HAC)	Amplified handset mode	Wired headset	Handset adapter
J129	Yes	Yes, with 20dB of gain	No	Yes
J139	Yes	Yes, with 20dB of gain	Yes	Yes

Model	Wired handset (HAC)	Amplified handset mode	Wired headset	Handset adapter
J159	Yes	Yes, with 20dB of gain	Yes	Yes
J169	Yes	Yes, with 20dB of gain	Yes	Yes
J179	Yes	Yes, with 20dB of gain	Yes	Yes
J189	Yes	Yes, with 20dB of gain	Yes	Yes
JBM24	NA	NA	NA	NA
JEM24	NA	NA	NA	NA

## **Power and USB support**

Model	PoE <sup>1</sup>	Optional DC power	USB port
J129	Yes	Yes <sup>2</sup>	No
J139	Yes	Yes	No
J159	Yes	Yes	Yes
J169	Yes	Yes	No
J179	Yes	Yes	No
J189	Yes	Yes	Yes
JBM24	NA	NA	No
JEM24	NA	NA	No

## Other specifications

Model	Dual color call indicator	Soft keys call control	Expansion module capable
J129	0	3	No
J139	4	4	No
J159	4	4	No
J169	8	4	Yes, 3 modules
J179	8	4	Yes, 3 modules
J189	10	4	Yes, 2 modules
JBM24	0	NA	NA
JEM24	24	NA	NA

<sup>&</sup>lt;sup>1</sup> PoE can be supplied from one of the following:

<sup>·</sup> Data switch

<sup>•</sup> in-line PoE injector

Optional DC power is available in J129D03A and later hardware models. J129D01A and J129D02A do not support optional DC power.

## **Chapter 3: Feature description**

## **Feature description**

Avaya J100 Series IP Phones offers the following features:

- · Easy to use interface
- Easy customization
- Support for Gigabit Ethernet
- Boost employee productivity
- Support for button module

## **Chapter 4: Performance specifications**

## **Power specifications**

You can power Avaya J100 Series IP Phones using Power over Ethernet (PoE) or an Avaya 5V DC power adapter. While using a power adapter, disable PoE on the Ethernet connection. You must purchase the power adapter separately.

Avaya J100 Series IP Phones are ENERGY STAR® compliant.

The following table provides the LLDP power measurement of the phones, adjuncts, and peripherals.

Phone model	Avaya standard power measurements (in Watts)			Energy Star (in Watts)	
	Conservation	Typical	Maximum	Standby	
J129	1.26	1.31	1.64	1.04	
J139	1.40	1.67	2.24	1.55	
J159	1.75	2.32	3.03	2.04	
J169	1.72	1.84	2.34	1.85	
J179	1.74	2.10	2.71	1.85	
J189	2.32	2.91	3.93	1.92	
JBM24	0.19	0.69	1.35	NA	
JEM24	1.70	1.90	2.00	NA	
Wi-Fi/BT module	0.90	0.90	0.90	NA	
USB device (PoE slide switch in L position)	0.5	0.5	0.5	NA	
USB device (PoE slide switch in H position)	1.25	1.25	1.25	NA	

The power requirements of the phone vary depending on the connected peripherals. The following table provides the correlation between the connected peripherals and power requirements.

Phone model PoE Class	
-----------------------	--

J129	IEEE 802.3af PoE Class 1 device.
J139	IEEE 802.3af PoE, Class 1 device.
J159	IEEE 802.3af PoE Class 1, PoE Slide switch in L position, without a wireless module and USB device with parameter USB power value set to either 0, 1 or 3.
	IEEE 802.3af PoE Class 2, PoE Slide switch in H position, with a wireless module, USB device, or a wireless module together with USB device.
J169	IEEE 802.3af PoE Class 1 without a button module.
	IEEE 802.3af PoE Class 2 with a button module.
J179	IEEE 802.3af PoE Class 1 without a wireless module or a button module.
	IEEE 802.3af PoE Class 2 for one or more button modules, a wireless module, or a wireless module together with one or more button modules.
	Note:
	Use Avaya 5V DC power adapter if you simultaneously connect a wireless module along with one or more button modules of any model.
J189	IEEE 802.3af PoE Class 2, PoE slide switch in the L position with a wireless module.
	IEEE 802.3af PoE Class 3, PoE slide switch in the H position, one JEM24 module supported with USB Type A and Type C port shared power limited to 900mA.Two JEM24 with USB Type A and Type C port shared power limited to 500mA.

## Port and switch

Avaya J100 Series IP Phones supports the following ports and switches:

Port and switch	J129	J139	J159	J169	J179	J189
USB	No	No	Yes	No	No	Yes, 1 Type-A and 1 Type-C
PC port	Yes	Yes	Yes	Yes	Yes	Yes
Headset jack	No	Yes	Yes	Yes	Yes	Yes

Port and switch	J129	J139	J159	J169	J179	J189
Button module interface	No	No	No	Yes	Yes	Yes
DC Adapter interface	Yes <sup>3</sup>	Yes	Yes	Yes	Yes	Yes
Wired Ethernet interface	10/100 Mbps	10/100/100 0 Mbps	10/100/100 0 Mbps	10/100/1000 Mbps	10/100/100 0 Mbps	10/100/100 0 Mbps
Secondary wired Ethernet interface	10/100 Mbps	10/100/100 0 Mbps	10/100/100 0 Mbps	10/100/1000 Mbps	10/100/100 0 Mbps	10/100/100 0 Mbps
Wireless Ethernet interface	Optional module	No	Optional module	No	Optional module	Optional module
PoE switch	No	No	Yes	No	No	Yes

## **Supported codecs**

Avaya J100 Series IP Phones supports the following codecs:

Models	J129	J139	J159	J169	J179	J189
Codecs	• G.711a					
	• G.711µ					
	• G.729					
	• G.729a					
	• G.729ab					
	• G.726					
	• G722					
	• OPUS					
						OPUS     Superwideb     and

## Note:

Codecs support packet loss concealment, jitter buffer where applicable. Full duplex acoustic echo cancellation is active on all transducers

<sup>&</sup>lt;sup>3</sup> Available in J129D03A and later hardware models. J129D01A and J129D02A do not support this interface.

## **Chapter 5: Environmental specification**

## Altitude and air pressure

Avaya J100 Series IP Phones function normally at altitudes from sea level to 10,000 feet and can withstand a pressure of 15.2 to 9.4 psia.

## Temperature and humidity

### Storage environment specifications

All Avaya J100 Series IP Phones work in a temperature range from 40 to 120 degrees Fahrenheit or 4 to 49 degrees Celsius.

### **Extreme temperature specifications**

All Avaya J100 Series IP Phones work normally after being soaked for at least 6 hours each in a non-operational state at -40 degree Fahrenheit and any relative humidity, at 90 degree Fahrenheit and 90% relative humidity, and at 150 degrees Fahrenheit and 15% relative humidity. The deskphones can function normally after up to three hours of recovery time at ambient conditions following each stress.

### Temperature and humidity specifications

All Avaya J100 Series IP Phones function normally after a recovery time of up a to three hours at ambient conditions when cycled through the following temperature and non-condensing humidity conditions three times: 30 minutes at 150 degree Fahrenheit and 15 percent relative humidity, followed by 30 minutes at 90 degrees Fahrenheit and 90 percent relative humidity, followed by 30 minutes at -40 degrees F and any convenient humidity.

### Normal operating specification

All Avaya J100 Series IP Phones function normally in the environment where temperatures are between 40 degrees Fahrenheit and relative humidities are between 5 percent and 95 percent, except that above 84 degree Fahrenheit, the maximum relative humidity is limited to that corresponding to a specific (absolute) humidity of 168 grains of water vapor per pound (lbm) of dry air. For example, 34 percent relative humidity at 120 degrees Fahrenheit, assuming an atmospheric pressure of 14.7 psia. The deskphones are allowed up to 30 minutes to stabilize at each temperature tested.

### **Design for Environment Guidelines and specifications**

All Avaya J100 Series IP Phones conform to the Design for Environment Guidelines and Requirements [8.1-5] as clarified below.

DFE Guidelines for Energy Efficient Products (Section 2): All Avaya J100 Series IP Phones do not require a cooling fan.

DFE Guidelines for Products Containing Batteries (Section 3): All Avaya J100 Series IP Phones do not contain batteries.

DFE Guidelines for Designing Plastic Parts (Section 4): All Avaya J100 Series IP Phones plastic parts are not coated (Section 4.4). Note: Section 4.4 of the Design for Environment Guidelines and Requirements specifies that plastic parts are not to be painted. However some deskphones might have been painted.

All Avaya J100 Series IP Phones housing and handset surfaces are textured (Section 4.5).

All Avaya J100 Series IP Phones plastic parts do not use resins containing:

- PVC (Section 4.7.1.2)
- Brominated flame retardants: polybrominated biphenyl, polybrominated biphenyl oxide (PBBO, also called polybrominated biphenyl ether (PBBE), polybrominated diphenyl oxide (PBDO) and polybrominated diphenyl ether (PBDE)), bromomethane and halothane (Sections 4.7.1.3, 4.9.1 and Appendix A)
- Halogenated flame retardants (Section 4.9.2)
- Heavy metal additives: lead, cadmium, chromium and mercury (Sections 4.7.1.4 and 4.9.3).
- All Avaya J100 Series IP Phones plastic parts weighing more than 25 grams are marked with ISO-compliant resin codes (Section 4.8). DFE Guidelines for Designing Printed Wiring Boards (Section 5):
- All Avaya J100 Series IP Phones do not contain lead (Section 5.3). All IP telephones do not use components containing mercury (Section 5.7.2).
- DFE Guideline for Waste Electrical and Electronic Equipment (WEEE) (Section 6.5.1). See also section [8.4-6].

## Regulatory compliance

Country	Regulatory compliance
USA	EMC: FCC Part 15 Class B EMC Report
	Telecom: FCC Part 68 (HAC) hearing-aid compatibility) and Volume Control Report
	RF: FCC Part 15C and SAR
	Safety: UL (UL 60950-1 current edition)

Country	Regulatory compliance
European Union (EU)	• EMC: EN 55032: 2012 Emissions Class B
	• EMC: EN 55024: 2010 Immunity
	• EN 61000-3-2: 2014 Harmonics
	• EN 61000-3-3: 2013 Voltage Fluctuations
	• Safety: IEC / EN 60950-1: 2006+A2 CB Scheme
	• RF EN 300 328 EN 301 893. EN 301 489-17, EN 5066 Human Exposure (SAR)
	Environmental: WEEE and RoHS / lead free compliance
	CE marking
Canada	EMC: ICES-003 Class B
	• RF: RS-247, SAR
	Telecom: CS-03
	• Safety: UL (CSA-C22.2 No. 60950-1-07)
Japan	EMC: VCCI Class B
	Telecom: JATE
	• RF: TELEC
	• Safety: IEC / EN 60950-1: 2006+A1 CB Scheme
	Label: with VCCI and JATE mark
Brazil	Safety: RES. 238
	EMC: RES. 237 and RES. 442 Reports Class B
	RF: applicable RES
	Telecom: RES 529
	ANATEL Listing
Korea	EMC KN22 Emissions Class B
	EMC KN24 Immunity
	• RF: KC
	Safety: MIC
	Telecom: MIC
	KCC Listed
Australia	EMC: EN 55022: 2010 Emissions Class B
	• Safety: IEC / EN 60950-1: 2006+A12 CB Scheme
	Telecom AS/ACIF S004
	• RCM

Country	Regulatory compliance
New Zealand	EMC: EN 55022: 2010 Emissions Class B
	• Safety: IEC / EN 60950-1: 2006+A1 CB Scheme
	Telecom PTC 220 Report
	PTC Listing
China	China Safety GB4943.1-2011
	China EMC GB 9254-2008
	China RoHS and China RoHS labeling     Electronics Industry Standard of the People's Republic of China specification SJ/T11364-2006.
Mexico	• RF: NOM / IEFTEL
	Safety NOM
Russia	• EAC

## **Chapter 6: Dial plan**

## Dial plan

You can create a dial plan for and Avaya J100 Series IP Phones using the following characters.

Character	Description
Digits 0 through 9	Specific dialpad digits.
Asterisk (*)	The dialpad character asterisk (*).
Pound (#)	The dialpad character #, but only if it is the first character in the dialed string.
х	Any dialpad digit from 0 to 9.
Z or z	Present dial tone to the user. For example, for Feature Access Code (FAC) entry.
Brackets ([ ])	Any one character within the brackets is a valid match for a dial plan string.
Minus (-)	Any one digit between the bounds within the brackets, inclusive, is a match.
Plus (+)	The character before plus (+) may be repeated 0 or more additional times, for a valid match.
Pipe ( )	If there are multiple valid dial plan elements, each one is separated from the next by an OR symbol.
(" ")	If the dial plan text string begins or ends with an OR symbol, that symbol is ignored.

## **Dialable characters**

Characters that a user would put in a dial string. These are different from the dial plan elements.

Character	Description
Comma (,)	A comma (,) creates a 1.5-second pause between the digits that are sent. Do not use a comma (,) as the first character in the string.
Pound (#)	Can either be the first dialed element used in a FAC or TAC or the last character which is an end of dial string indication.
Asterisk (*)	Can either be the 1st dialed element used in a FAC or TAC.

## **Chapter 7: Security**

## Security overview

Avaya J100 Series IP Phones support the following security features:

- HTTP authentication for backup and restore operations.
- 256-bit Advanced Encryption Standard (AES-256) media encryption.
- Supports FIPS 140-2 cryptographic algorithms for application, processes, and users.
- Supports control to switch between FIPS and non-FIPS mode.
- Supports Public Key Infrastructure (PKI) for users that use third-party certificates for all Avaya services including database.
- Supports Certificate Revocation List (CRL) and On Line Certificate Status Protocol (OCSP) for public key management.
- Supports SRTP/SRTCP and TLS v1.2.
- Secure call indicator provided by Avaya Aura® Platform 7.0.
- Compliance with IETF RFC 1948 Defending Against Sequence Number Attacks, May 1996, 14 by S. Bellovin .
- Support Transport Layer Security (TLS) to establish a secure connection to an HTTP server on which the upgrade and settings files reside.

## SSH

Avaya Services uses Secure Shell (SSH) protocol to remotely connect to Avaya J100 Series IP Phones to monitor, diagnose, or debug phone performance. The Avaya J100 Series IP Phones support SSHv2 only. SSHv1 is disabled.

## **TLS**

Avaya J100 Series IP Phones supports Transport Layer Security (TLS) to enhance the security of your HTTP environment. The deskphones support HTTP and HTTPS authentication for backup and restore operations.

## **Avaya SBC**

You can use Avaya J100 Series IP Phones SIP with Avaya Session Border Controller for Enterprise (SBCE) to provide support for remote workers. The SBCE gives remotely located SIP users access to the internal enterprise Unified Communications (UC) network by implementing comprehensive UC security features. These features include sophisticated firewall/NAT traversal, encryption, user authentication, and session and endpoint call policy enforcement.

## **EAP-TLS**

Avaya J100 Series IP Phones supports Extensible Authentication Protocol-Transport Layer Security (EAP-TLS) mode of authentication. The call server supports EAP-TLS as specified in RFC 2716 if an identity certificate is present in the deskphone.

## **SCEP**

Avaya J100 Series IP Phones supports Simple Certificate Enrollment Protocol (SCEP) to provide an identity certificate for use with certificate-based VPN authentication methods. The 802.1x EAP-TLS method also uses the identity certificate for authentication. When you use TLS with HTTPS, you can use the identity certificate to:

- Authenticate the deskphone
- · Save the agent greetings
- Perform a backup or restore

Avaya J100 Series IP Phones supports Media Encryption (SRTP) and uses built-in Avaya certificates for trust management. You can apply SCEP to your VPN operations or to standard enterprise network operations.

## 802.1X Supplicant operation

Avaya J100 Series IP Phones supports Supplicant operation and Extensible Authentication Protocol (EAP).

## Virus malware related attacks

Deskphones are delivered free from known viruses, worms, and other malware. Products are built in an environment that is free from known viruses, worms, and other malware. The "gold" version of a product is built on a machine that is known to be clean. For example, built from a known source or the operating system version is taken from the manufacturer's source.

## JITC certification

For products sold into the U.S. and Canadian Government and sector, Joint Interoperability Test Command (JITC) certification is a mandatory requirement. Based on the operating system and the capabilities of the product, each product must adhere to the respective standard specified at http://iase.disa.mil/stigs/checklist/index.html.

Verification of JITC functionality includes execution of the scripts for the respective operating system on the product. The scripts are specified at http://iase.disa.mil/stigs/SRR/index.html.

All Avaya J100 Series IP Phones are JITC certified.

## Port utilization

For the latest and most accurate information about ports and protocols that Avaya J100 Series IP Phones utilizes, see Port Matrix. On the Web page, select the required link under Avaya one-X® Deskphone.

## **Chapter 8: Related resources**

## **Documentation**

See the following related documents at <a href="http://support.avaya.com">http://support.avaya.com</a>:

Title	Use this document to:	Audience
Overview		
Avaya Aura® Session Manager Overview and Specification	See characteristics and capabilities, including feature descriptions, interoperability, performance specifications, security, and licensing requirements of the Avaya Aura <sup>®</sup> Session Manager.	People who want to gain a high-level understanding of the Avaya Aura® Session Manager features, functions, capacities, and limitations.
Avaya Aura® Communication Manager Feature Description and Implementation	See characteristics and capabilities, including feature descriptions, interoperability, performance specifications, security, and licensing requirements of the Avaya Aura® Communication Manager.	People who want to gain a high- level understanding of the Avaya Aura® Communication Manager features, functions, capacities, and limitations.
Avaya IP Office <sup>™</sup> Platform Feature Description	See information about the feature descriptions.	People who perform system administration tasks.
Avaya IP Office <sup>™</sup> Platform Solution Description	See information about how the products and services interoperate with this solution.	People who want to gain a high-level understanding of the IP Office features, functions, capacities, and limitations.
Implementing		
Deploying Avaya Aura <sup>®</sup> Session Manager	See the installation procedures and initial administration information for Avaya Aura® Session Manager.	People who install, configure, and verify Avaya Aura <sup>®</sup> Session Manager on Avaya Aura <sup>®</sup> System Platform.

Title	Use this document to:	Audience
Upgrading Avaya Aura <sup>®</sup> Session Manager	See upgrading checklists and procedures.	People who perform upgrades of Avaya Aura® Session Manager.
Deploying Avaya Aura <sup>®</sup> System Manager on System Platform	See the installation procedures and initial administration information for Avaya Aura® System Manager.	People who install, configure, and verify Avaya Aura <sup>®</sup> System Manager on Avaya Aura <sup>®</sup> System Platform at a customer site.
IP Office SIP Telephone Installation Notes	See the installation procedures and initial administration information for IP Office SIP telephone devices.	People who install, configure and verify SIP telephone devices on IP Office.
Administering		
Administering Avaya Aura® Session Manager	See information about performing Avaya Aura® Session Manager administration tasks, including how to use management tools, how to manage data and security, and how to perform periodic maintenance tasks.	People who perform Avaya Aura® Session Manager system administration tasks.
Administering Avaya Aura® System Manager	See information about performing Avaya Aura® System Manager administration tasks, including how to use management tools, how to manage data and security, and how to perform periodic maintenance tasks.	People who perform Avaya Aura® System Manager administration tasks.
Administering Avaya IP Office™ Platform with Manager	See information about short code configurations for the feature list	People who need to access IP Office features using short codes.
Administering Avaya IP Office™ Platform with Web Manager	See information about IP Office Web Manager administration tasks, including how to use the management tool, how to manage data and security, and how to perform maintenance tasks.	People who perform IP Office Web Manager administration tasks.
Maintaining		
Maintaining Avaya Aura <sup>®</sup> Session Manager	See information about the maintenance tasks for Avaya Aura® Session Manager.	People who maintain Avaya Aura <sup>®</sup> Session Manager.
Troubleshooting Avaya Aura® Session Manager	See information for troubleshooting Avaya Aura® Session Manager, resolving alarms, replacing hardware, alarm codes, and event ID descriptions.	People who troubleshoot Avaya Aura® Session Manager.

Title	Use this document to:	Audience
Using IP Office System Status	See information about the maintenance tasks for System Status Application.	People who maintain System Status Application.
Using IP Office System Monitor	See information about the maintenance tasks for SysMonitor.	People who maintain SysMonitor.

## Finding documents on the Avaya Support website

### **Procedure**

- 1. Go to https://support.avaya.com.
- 2. To log in, click **Sign In** at the top of the screen and then enter your login credentials when prompted.
- 3. Click Product Support > Documents.
- 4. In **Search Product**, start typing the product name and then select the appropriate product from the list displayed.
- 5. In **Select Release**, select the appropriate release number.

This field is not available if there is only one release for the product.

- 6. (Optional) In Enter Keyword, type keywords for your search.
- 7. From the **Select Content Type** list, select one or more content types.

For example, if you only want to see user guides, click **User Guides** in the **Select Content Type** list.

8. Click \( \text{\tint{\text{\tint{\text{\tiliex{\text{\texi}\text{\text{\text{\text{\text{\text{\texi}}\tint{\text{\tiin}\tint{\text{\text{\text{\texi}\tiex{\text{\tiin}}\tint{\text{\t

## **Avaya Documentation Center navigation**

For many programs, the latest customer documentation is available on the Avaya Documentation Center website at <a href="https://documentation.avaya.com">https://documentation.avaya.com</a>. Some functionality is only available when you log in to the Avaya Documentation Center. The available functionality depends on your role.

## Important:

If the documentation you are looking for is not available on the Avaya Documentation Center, you can find it on the <u>Avaya Support website</u>.

While navigating through the Documentation Center, you can click the **Avaya Documentation Center** logo at the top of the screen to return to the home page anytime. On the Avaya Documentation Center, you can do the following:

- Click Avaya Links in the top menu bar to access other Avaya websites, including the Avaya Support website.

- In the **Search Documentation** field, search for keywords and click **Filter** to filter by solution category, product, or user role.
  - You can select multiple items in each filter category. For example, you can select a product and multiple user roles.
- Click **Library** in the top menu bar to access the complete library of documents. Use the filtering options to refine your results.
- After performing a search or accessing the library, you can sort content on the search results page. When you find the item you want to view, click it to open it.
- Use the table of contents in a document for navigation. You can also click < or > next to the document title to navigate to the previous topic or the next topic.
- Click Share (→) to share a topic by email or copy the URL.
- Download a PDF of the current topic in a document, the topic and its subtopics, or the entire document.
- Print the section you are viewing.
- Add content to a collection by clicking **Add to My Topics** ( ). You can add the topic and its subtopics or add the entire publication.
- View the topics in your collections. To access your collections, click your name in the top menu bar and then click **My Topics**.

You can do the following:

- Create, rename, and delete a collection.
- Set a collection as the default or favorite collection.
- Save a PDF of the selected content in a collection and download it to your computer.
- Share content in a collection with others through email.
- Receive collections that others have shared with you.
- Click Watch (
   ) to add a topic to your watchlist so you are notified when the content is updated or removed.
- View and manage your watchlist by clicking Watchlist from the top menu with your name.

You can do the following:

- Enable **Email notifications** to receive email alerts.
- Unwatch the selected content or all topics.
- Send feedback for a topic.

## **Support**

Go to the Avaya Support website at <a href="https://support.avaya.com">https://support.avaya.com</a> for the most up-to-date documentation, product notices, and knowledge articles. You can also search for release notes,

downloads, and resolutions to issues. Use the online service request system to create a service request. Chat with live agents to get answers to questions, or request an agent to connect you to a support team if an issue requires additional expertise.

## Index

Numerics	overview (continued)	
802.1X Supplicant operation22	security	<u>20</u>
ouz. 1A Supplicant operation	_	
Λ	P	
A	Port and switch	13
Altitude and air pressure specification15	port utilization	
Avaya support website26	Power management	
	3	
C	R	
collection	Regulatory compliance	<u>16</u>
delete <u>25</u>	related documentation	<u>23</u>
edit <u>25</u>		
generating PDF	S	
sharing content25	3	
content	searching for content	25
publishing PDF output	Secure Shell	
searching25	security	<u>20</u>
sharing <u>25</u>	802.1X Supplicant operation	22
sort by last updated25	Avaya SBCE	
watching for updates25	JITC certification	
3 1	Simple Certificate Enrollment Protocol	
n	SSH	
D	TLS	
dial plan specification19	Virus malware related attacks	
dialable characters19		
documentation center	security overview	
	securityEAP-TLS	
finding content	sharing content	
navigation	Simple Certificate Enrollment Protocol	
documentation portal	software	
	sort documents	<u>25</u>
E	specifications	4.5
	altitude and air pressure	
EAP-TLS <u>21</u>	dial plan	
Extensible Authentication Protocol-Transport Layer	hardware	
Security	temperature and humidity	
	support	<u>26</u>
F	т	
finding content on documentation center25	•	
minding deficent on desamentation contor	temperature and humidity specification	<u>15</u>
	TLS	
J	Transport Layer Security	
J100 Series IP Phone models7		
Joint Interoperability Test Command certification	V	
0	Virus malware related attacks	<u>22</u>
overview		
Avaya J100 Series IP Phones7		

W	
watchlist	<u>25</u>